

Dahua HDCVI Standalone DVR User's Manual

V1.8.2

Table of Contents

1	FEA	TURES AND SPECIFICATIONS	1
1.1	0	verview	1
1.2	F	eatures	1
1.3	S	pecifications	2
1.	.3.1	HCVR5104C Series	
1.	.3.2	HCVR51XXC-V2 Series	
1.	.3.3	HCVR7104C-V2 Series	
1.	.3.4	HCVR410XC-S2 Series	
1.	.3.5	HCVR510XC-S2 Series	
1.	.3.6	HCVR7104C-S2 Series	
1.	.3.7	HCVR2108C-S2 Series	
1.	.3.8	HCVR410XC-S3 Series	
1.	.3.9	HCVR510XC-S3 Series	
1.	.3.10	HCVR7104C-S3 Series	
1.	.3.11	HCVR51XXH Series	
1.	3.12	HCVR51XXH-V2 Series	
1.	.3.13	HCVR51XXHC Series	
1.	3.14	HCVR51XXHC-V2 Series	
1.	3.15	HCVR51XXHE Series	
1.	3.16	HCVR51HE-V2 Series	
1.	3.17	HCVR71XXH-V2 Series	
1.	3.18	HCVR71XXHC-V2 Series	
1.	.3.19	HCVR71XHE-V2 Series	
1.	.3.20	HCVR41XXHE-S2 Series	
1.	.3.21	HCVR51XXH-S2 Series	
1.	.3.22	HCVR51XXHE-S2 Series	
1.	.3.23	HCVR710XH-S2 Series	
1.	.3.24	HCVR710XHE-S2 Series	
1.	.3.25	HCVR41XXHE-S3 Series	
1.	3.26	HCVR51XXHE-S3 Series	
1.	.3.27	HCVR71XXHE-S3 Series	
1.	3.28	HCVR71XXH-S3 Series	
1.	3.29	HCVR41XXHS-S2 Series	
1.	3.30	HCVR21XXHS-S2 Series	
1.	.3.31	HCVR21XXHS-S3 Series	

1.3.32	HCVR41XXHS-S3 Series	58
1.3.33	HCVR51XXHS-S3 Series	60
1.3.34	HCVR71XXHS-S3 Series	62
1.3.35	HCVR52XXA-V2 Series	64
1.3.36	HCVR72XXA-V2 Series	65
1.3.37	HCVR42XXA-S2/4216AN-S2 Series	66
1.3.38	HCVR4224/4232AN-S2 Series	67
1.3.39	HCVR52XXA-S2/HCVR5216AN-S2 Series	69
1.3.40	HCVR720XA-S2 Series	70
1.3.41	HCVR42XXA-S3 Series	72
1.3.42	HCVR42XXAN-S3 Series	74
1.3.43	HCVR52XXA-S3 Series	76
1.3.44	HCVR52XXAN-S3 Series	78
1.3.45	HCVR72XXA-S3/HCVR7216AN-S3 Series	79
1.3.46	HCVR52XXL-V2 Series	82
1.3.47	HCVR54XXL-V2 Series	83
1.3.48	HCVR4224/32L-S2 Series	85
1.3.49	HCVR44XXL-S2 Series	86
1.3.50	HCVR48XXS-S2 Series	89
1.3.51	HCVR58XXS-V2 Series	92
1.3.52	HCVR71XXH-4M Series	93
1.3.53	HCVR72XXAN-4M Series	95
1.3.54	XVR410XC Series	97
1.3.55	XVR510XC Series	98
1.3.56	XVR7104C Series	100
1.3.57	XVR41XXHE Series	101
1.3.58	XVR51XXH Series	103
1.3.59	XVR51XXHE Series	105
1.3.60	XVR71XXHE Series	107
1.3.61	XVR71XXH Series	109
1.3.62	XVR21XXHS Series	111
1.3.63	XVR41XXHS Series	113
1.3.64	XVR51XXHS Series	114
1.3.65	XVR7104HS Series	116
1.3.66	XVR42XXA Series	118
1.3.67	XVR42XXAN Series	120
1.3.68	XVR52XXA Series	122
1.3.69	XVR52XXAN Series	124
1.3.70	XVR72XXA Series	126
1.3.71	XVR72XXAN Series	128

2	OVERVIEW AND CONTROLS	13′	1
---	-----------------------	-----	---

2.1	l Fi	ront Panel	.131
	2.1.1	HCVR5104C/HCVR51XXC-V2/HCVR71XXC-V2/ HCVR4104/4108C-S2/	
	HCVR5	5104 5108C-S2/ HCVR7104C-S2/ HCVR2108C-S2/	
	HCVR4	10XC-S3/HCVR510XC-S3/7104C-S3/ XVR410XC/XVR510XC/7104C Series	.131
	2.1.2	HCVR51XXH/HCVR51XXHE/ HCVR51XXH-V2 /	
	HCVR5	51XXHE-V2/HCVR71XXH-V2 / HCVR71XXHE-V2 Series	.131
	2.1.3	HCVR51XXHC/ HCVR51XXHC-V2/ HCVR71XXHC-V2 Series	.132
	2.1.4	HCVR41XXHE-S2/ HCVR51XXH-S2/ HCVR51XXHE-S2/ HCVR710XH-S2/	
	HCVR7	710XHE-S2/	
	HCVR4	1XXHE-S3/HCVR51XXHE-S3/HCVR71XXH-S3/HCVR71XXHE-S3	
	/HCVR	41XXHS-S2/HCVR21XXHS-S2/	
	HCVR2	21XXHS-S3/HCVR41XXHS-S3/51XXHS-S3/7104HS-S3/	
	XVR41	XXHE/XVR51H/XVR51XXHE/XVR71XXH/XVR71XXHE /HCVR41XXHS-S2/	
	HCVR2	21XXHS-S2/ XVR21XXHS/XVR41XXHS/51XXHS/7104HS/HCVR71XX-4M Serie	es
		133	
	2.1.5	HCVR52XXA-V2/ HCVR72XXA-V2 Series	.134
	2.1.6	HCVR42XXA-S2/ HCVR42XXAN-S2/ HCVR52XXA-S2/	
	HCVR5	5216AN-S2/HCVR720XA-S2/	
	HCVR4	2XXA-S3/HCVR42XXAN-S3/HCVR52XXA-S3/HCVR52XXAN-S3/HCVR72XXA	-S3
	/HCVR	7216AN-S3/XVR42XXA/XVR42XXAN/XVR52XXA/XVR52XXAN/XVR72XXA/XV	'R7
	216AN	/HCVR 72XXAN-4M Series	.135
	2.1.7	HCVR42XXL-S2/HCVR44XXL-S2 Series	.136
	2.1.8	HCVR52XXL-V2/ HCVR54XXL-V2 Series	.137
	2.1.9	HCVR58XXS-V2 Series	.138
	2.1.10	HCVR48XXS-S2 Series	.141
2.2	2 R	ear Panel	.141
	221	HCVR5104C Series	141
	2.2.2	HCVR5104C-V2/HCVR5108C-V2 Series	
	2.2.3	HCVR7104C-V2 Series	
	2.2.4	HCVR4104/HCVR4108C-S2/HCVR2108C-S2 Series	
	2.2.5	HCVR5104/5108C-S2 Series	
	2.2.6	HCVB7104C-S2 Series	
	2.2.7	HCVR410XC-S3/HCVR510XC-S3/7104C-S3/XVR410XC/XVR510XC/7104C	,
	Series	148	
	2.2.8	HCVR5104H/HCVR5108H Series	.150
	2.2.9	HCVR5104H-V2/HCVR5108H-V2/HCVR5116H-V2 Series	.151
	2.2.10	HCVR5104HC/HCVR5108HC Series	
	2.2.11	HCVR5104HC-V2/HCVR5108HC-V2/HCVR5116HC-V2 Series	
	2.2.12	HCVR5104HE/HCVR5108HE Series	.156
	2.2.13	HCVR5104HE-V2/HCVR5108HE-V2/HCVR5116HE-V2 Series	.157
	2.2.14	HCVR7104H-V2/HCVR7108H-V2 Series	.159
	2.2.15	HCVR7104HC-V2/HCVR7108HC-V2 Series	.161

2.6.1	Virtual Keyboard	210
2.6	Virtual Keyboard & Front Panel	210
2.5	Mouse Control	208
2.4	Remote Control	206
2.3.7	2U Series	
2.3.6		
2.3.5		
2.3.4		
2.3.3		
2.3.2		
2.3.7		
2.3	Connection Sample	
2.2.3	35 HCVR72XXAN-4M Series	199
2.2.3		
2.2.3	B3 HCVR58XXS-V2/HCVR48XXS-S2 Series	195
2.2.3	B2 HCVR42XXL-S2 Series	193
2.2.3	HCVR52XXL-V2/ HCVR54XXL-V2/HCVR44L-S2 Series	190
XA/X	(VR7216AN Series	
72X	HCVR42XXA-S3/HCVR42XXAN-S3/HCVR52XXA-S3/HCVR52XXAN A-S3/HCVR7216AN-S3/XVR42XXA/XVR42XXAN/XVR52XXA/XVR52XXA	
2.2.3	-	
2.2.2	P9 HCVR720XA-S2 Series	186
2.2.2	28 HCVR52XXA-S2/ HCVR5216AN-S2 Series	184
2.2.2	P7 HCVR4224/HCVR4232AN-S2 Series	
2.2.2	26 HCVR42XXA-S2/ HCVR4216AN-S2 Series	
2.2.2	25 HCVR52XXA-V2/ HCVR72XXA-V2 Series	
/XVF	R21XXHS/XVR41XXHS/51XXHS/7104HS Series	178
2.2.2	4 HCVR21XXHS-S3/HCVR41XXHS-S3/51XXHS-S3/7104HS-S3	
2.2.2	HCVR41XXHS-S2/ HCVR2108HS-S2/ HCVR2116HS-S2 Series	176
/XVF	R41XXHE/XVR51XXH/XVR51XXHE/XVR71XXH/XVR71XXHE Series	174
2.2.2	HCVR41XXHE-S3/HCVR51XXHE-S3/HCVR71XXH-S3/HCVR71XXH	E-S3
2.2.2	21 HCVR7104/7108HE-S2 Series	172
2.2.2	20 HCVR7104/7108H-S2 Series	170
2.2.7	9 HCVR5104/5108/5116HE-S2 Series	
2.2.		
2.2.		
2.2.7	6 HCVR7104HE-V2/HCVR7108HE-V2 Series	162

2.6.2	Front Panel	
3 IN	STALLATION AND CONNECTIONS	211
3.1	Check Unpacked DVR	
3.2	About Front Panel and Rear Panel	211
3.3	HDD Installation	211
3.3.1	Smart Box Series	
3.3.2	Smart 1U Series	
3.3.3	Compact 1U and Mini 1U Series	
3.3.4	The 1U Series	
3.3.5	The 1.5U Series	
3.3.6	The 2U Series	
3.3.7	Rack Installation	
3.4	Connecting Power Supply	217
3.5	Connecting Video Input and Output Devices	217
3.5.1	Connecting Video Input	217
3.5.2	Connecting Video Output	
3.6	Connecting Audio Input & Output, Bidirectional Audio	
3.6.1	Audio Input	218
3.6.2	Audio Output	
3.7	Alarm Input and Output Connection	
3.7.1	Alarm Input and Output Details	219
3.7.2	Alarm Input Port	
3.7.3		
3.8	RS485	
3.9	Other Interfaces	

4 O\	VERVIEW OF NAVIGATION AND CONTROLS.	222
4.1	Boot up and Shutdown	
4.1.1	Boot up	
4.1.2		
4.1.3	Auto Resume after Power Failure	
4.1.4	Replace Button Battery	
4.2	Set/Reset Password	
4.2.1	Set Password	
4.2.2		
4.3	Startup Wizard	
4.4	Live Viewing	230
4.5	Right-Click Menu	232
4.5.1	Window Switch	
4.5.2	Previous Screen/Next Screen	
4.5.3	PTZ Control	
4.5.4	Auto Focus	
4.5.5	Color	
4.5.6	Display	
4.5.7		
4.5.8	Search	
4.5.9		
4.5.10		
4.5.1		
4.5.12 4.5.13		
4.5.10		
4.6	Navigation Bar	
4.6.1	Main Menu	
4.6.2		
4.6.3		
4.6.4		
4.6.5		
4.6.6		
4.6.7	PTZ	

4.6.8	Color	
4.6.9	Search	
4.6.10	0 Alarm Status	
4.6.1	1 Channel Info	
4.6.12	2 Remote Device	
4.6.13	3 Network	
4.6.14	4 HDD Manager	
4.6.15	5 USB Manager	
4.7	USB Device Auto Pop-up	
4.8	Main Menu	
4.9	Operation	
4.9.1	Search	
4.9.2	Human Face Search	
4.9.3	Backup	
4.9.4	Shut Down	
4.10	Information	
4.10.7	1 System Info	
4.10.2	2 Event	
4.10.3		
4.10.4	4 Log	
4.11	Setting	
4.11.1	1 Camera	
4.11.2	2 Network	
4.11.3		
4.11.4	5	
4.11.5	5 System	
5 W	EB OPERATION	
5.1	Network Connection	
5.2	Login	

5.3	LAN Mode	
5.4	Real-time Monitor	
5.5	PTZ	
5.6	Image/Relay-out	
5.6.1	1 Image	
5.6.2	2 Relay output	
5.7	WAN Login	
5.8	Setup	
5.8.1	1 Camera	
5.8.2	2 Network	
5.8.3	3 Event	
5.8.4	4 Storage	
5.8.5	5 Setting	
5.9	Information	
5.9.1	1 Version	
5.9.2	2 Log	
5.9.3	3 Online User	
5.9.4	4 HDD	
5.10	Playback	
5.10	0.1 Search Record	
5.10		
5.10	0.3 Playback	
5.10	0.4 Download	
5.10	0.5 Load more	
5.11	Face Search	
5.12	Alarm	

5.13 Log out
5.14 Un-install Web Control458
6 PROFESSIONAL SURVEILLANCE SYSTEM
7 FAQ460
APPENDIX A HDD CAPACITY CALCULATION468
APPENDIX B COMPATIBLE BACKUP DEVICES470
Appendix B-1 Compatible USB list470
Appendix B-2 Compatible SD Card list471
Appendix B-3 Compatible Portable HDD list471
Appendix B-4 Compatible USB DVD List471
Appendix B-5 Compatible SATA DVD List471
Appendix B-6 Compatible SATA HDD List472
APPENDIX C COMPATIBLE CD/DVD BURNER LIST476
APPENDIX D COMPATIBLE DISPLAYER LIST
APPENDIX E COMPATIBLE SWITCHER478

'9
•

APPENDIX G	EARTHING	480

Welcome

Thank you for purchasing our HDCVI DVR!

This user's manual is designed to be a reference tool for the installation and operation of your system.

Here you can find information about this series standalone DVR features and functions, as well as a detailed menu tree.

Before installation and operation please read the following safeguards and warnings carefully!

Important Safeguards and Warnings

1. Electrical safety

All installation and operation here should conform to your local electrical safety codes. The product must be grounded to reduce the risk of electric shock.

We assume no liability or responsibility for all the fires or electrical shock caused by improper handling or installation.

2. Transportation security

Heavy stress, violent vibration or water splash are not allowed during transportation, storage and installation.

3. Installation

Keep upwards. Handle with care. Do not apply power to the DVR before completing installation. Do not place objects on the DVR.

4 . Qualified engineers needed

All the examination and repair work should be done by the qualified service engineers. We are not liable for any problems caused by unauthorized modifications or attempted repair.

5. Environment

The DVR should be installed in a cool, dry place away from direct sunlight, inflammable, explosive substances and etc.

6. Accessories

Be sure to use all the accessories recommended by manufacturer. Before installation, please open the package and check all the components are included. Contact your local retailer ASAP if something is broken in your package.

7. Lithium battery

Improper battery use may result in fire, explosion, or personal injury! When replace the battery, please make sure you are using the same model! **RISK OF EXPLOSION IF BATTERY IS REPLACED BY AN INCORRECT TYPE. DISPOSE OF USED BATTERIES ACCORDING TO THE INSTRUCTIONS.**



FOR YOUR OWN SAFETY, PLEASE CHANGE SYSTEM DEFAULT PASSWORD AFTER YOU FIRST LOGIN!

1 FEATURES AND SPECIFICATIONS

1.1 Overview

The standalone series DVR is an excellent digital monitor product designed for security field.

It adopts embedded Linux OS to maintain reliable operation. Popular H.264 compression algorithm and G.711 audio compression technology realize high quality, low bit stream. Unique frame by frame play function is suitable for detailed analysis. It has various functions such as record, playback, monitor at the same time and can guarantee audio video synchronization. This series product has advanced technology and strong network data transmission function.

This series device adopts embedded design to achieve high security and reliability. It can work in the local end, and at the same time, when connecting it to the professional surveillance software (PSS), it can connect to the security network to realize strong network and remote monitor function.

This series product can be widely used in various areas such as banking, telecommunication, electric power, interrogation, transportation, intelligent resident zone, factory, warehouse, resources, and water conservancy.

1.2 Features

This series product has the following features:

• Real-time surveillance

Support VGA port and HDMI port. Realize the surveillance through displayer. Support HDMI, VGA, and TV output at the same time.

• Storage function

Special data format to guarantee data security and can remove the risk of the vicious data modification. Support digital watermark.

• Compression format

Support multiple-channel audio and video. An independent hardware decodes the audio and video signal from each channel to maintain video and audio synchronization.

Backup function

Support backup operation via USB port (such as U disk, portable HDD, burner) Client-end user can download the file to local HDD to backup via network.

• Record & playback function

Support each channel real-time record independently, and at the same time it can support search, forward play, network monitor, record search, download and etc.

Support various playback modes: slow play, fast play, backward play and frame by frame play.

Support time title overlay so that you can view event accurate occurred time Support customized zoom function during the preview.

• Network operation

Support network remote real-time monitor, remote record search and remote PTZ control.

• Alarm activation function

Several relay alarm outputs to realize alarm activation and on-site light control. The alarm input port and output has the protection circuit to guarantee device safety.

• Communication port

RS485 port can realize alarm input and PTZ control.

RS232 port can connect to keyboard to realize central control, and can also connect to PC COM to upgrade system and realize maintenance, and matrix control.

Standard Ethernet port can realize network access function.

The dual-network port has the multiple-access, fault-tolerance, load-balance setup mode.

• PTZ control

Support PTZ decoder via RS485.

• Intelligent operation

Mouse operation function In the menu, support copy and paste setup function

• UPNP (Universal Plug and Play)

Establish mapping connection between LAN and WAN via UPNP protocol.

Slight function differences may be found due to different series.

1.3 Specifications

1.3.1 HCVR5104C Series

	Parameter	HCVR5104C		
System	Main	High-performance industrial embedded micro controller		
	Processor			
	OS	Embedded LINUX		
	System	Multiplex operations: Multiple-channel record, multiple-channel playback		
	Resources	and network operation simultaneously		
	Interface	User-friendly graphical user interface		

	Input	USB mouse		
	Devices			
	Input	Arabic number, English character, donation and extension Chinese		
	Method	(optional)		
	Shortcut	Copy/paste operation, USB mouse right-key shortcut menu, double click		
	Function	USB mouse to switch screen.		
Compression	Video			
Standard	Compressio	H.264		
	n Audio			
	Audio			
	Compressio	G711A, G711U, PCM		
	n Video Input	4-CH composite video input: (NTSC/PAL) BNC (1.0V _{P-P} .75Ω)		
		1-ch VGA output.		
	Video	1-ch HDMI output.		
	Output	Support VGA/HDMI video output at the same time.		
	Video			
Video monitor	Standard	Support PAL/NTSC.		
	Record	Real-time Mode: PAL 1f/s to 25f/s per channel and NTSC 1f/s to 30f/s per		
	Speed	channel		
	Video	1/4 windows(Optional)		
Partition Monitor Support monitor				
		Support monitor tour functions such as motion detection, and schedule		
	Touring	auto control.		
		PAL/NTSC		
		Real-time monitor:		
		720P 1280*720		
	Resolution	Playback:		
	(PAL/NTSC)	All-ch: 720P 1280*720, 960H 960 ×576/960×480, D1		
		704×576/704×480, HD1 352×576/352×480, 2CIF 704×288/704×240, CIF 352×288/ 352×240 , QCIF 176×144/176×120		
		Support dual streams: extra stream resolution CIF 352×288/ 352×240,		
		QCIF 176×144/176×120.		
	Image	6-level image quality (Adjustable)		
	Quality			
		Support one privacy mask of user-defined size in full screen.		
	mask	Support max 4 zones.		
	Image Information	Channel information, time information and privacy mask zone.		
	TV Adjust	Adjust TV output zone suitable to anamorphic video.		

	Channel Lock	Cover secret channel with black screen though system is encoding normally. Screen-lock function to prevent unauthorized user seeing secret video.		
	Channel Information	Channel name, recording status, screen lock status, video loss status and motion detection status are shown on the bottom left of display screen.		
	Color Configuratio n	Hue, brightness, contrast, saturation and gain setup for each channel.		
Audio	Audio Input	N/A		
	Audio Output	N/A		
	Bidirectional Audio	N/A		
	Hard Disk	1 built-in SATA port. Support 1 HDD.		
Hard disk	One HDD Space	4T		
	Hard Disk	Audio: PCM 28.8MByte/h		
	Occupation	Video: 56-900MByte/h		
Record and	Recording Mode	Manual recording, motion detection recording, schedule recording and alarm recording Priority: Manual recording> alarm recording>motion detection recording>schedule recording.		
playback	Storage Mode	Support channel record quota setup		
	Recording Length	1 to 120 minutes single record duration (Default setup is 60 minutes)		
	Playback Repeat Way	When hard disk is full, system can overwrite previous video file.		
	Record Search	Various search engines such as time, type and channel.		
	Playback Mode	Various fast play, slow play speeds, manual frame by frame playback and reverse play mode.		
	Various File	Can switch to previous or next file or any file in current play list.		
	Switch	Can switch to file on other channel of the same time. (If there is a file)		
	Ways	Support file continuous play, when a file is end system auto plays the next file in the current channel		
	Playback Way	Support mark playback		
	Multi-chann el Playback	There is 1/4-channel playback mode.		
	Window Zoom	Switch between self-adaptive screen/full screen when playback		

	Partial	When in one-window full-screen playback mode, you can select any zone	
	Enlargemen	to activate partial enlargement function.	
	t		
Backup		HDD backup	
function		Support peripheral USB backup device. (Flash disk, portable disk and	
	Backup	etc.)	
	Mode	Support peripheral USB burner.	
		Support network download and save	
		View monitor channel remotely.	
		DVR configuration through client-end and web browser	
		Upgrade via client or browser to realize remote maintenance.	
Network		View alarm information such as motion detection and video loss via client.	
Function		Support network PTZ lens control	
	Network	File download backup and playback	
	control	Multiple devices share information via corresponding software such as	
		professional surveillance software (PSS)	
		Duplex transparent COM	
		Network alarm input and output	
		Zero-channel encoding	
		Bidirectional audio.	
	Motion	Zone setup: support 396((PAL 22×18, NTSC 22×15)) detection zones.	
Motion	Detection	Various sensitivity levels.	
Detection and		Alarm can activate record or external alarm or screen message prompt.	
Alarm	Video Loss	Alarm can activate screen message prompt.	
	External	N/A	
	Alarm		
	Manual	N/A	
	Alarm		
	Control		
	Alarm Input	N/A	
	Alarm	N/A	
	Output		
	Alarm Relay	N/A	
	USB	2 USB 2.0 port.	
Interface	Interface		
	Network	1 RJ45 10M/100M self-adaptable Ethernet port	
	connection		
	RS485	N/A	
	RS232	N/A	
System	Hard Disk	Display HDD current status	
Information	Information		

	Data	Data stream statistics for each channel (in wave mode)	
	Stream		
	Statistics		
	Log	Backup to 1024 log files.	
	statistics	Support various search engines such as time and type.	
		Display version information: channel amount, system version and release	
	Version	date.	
	On-line user	Display current on-line user	
User		Multi-lever user management; various management modes	
Management	User	Integrated management for local user, serial port user and network user.	
	Manageme	Configurable user power.	
	nt	Support user /group and its corresponding rights modification.	
		No limit to the user or group amount.	
		Password modification	
	Password	Administrator can modify other user's password.	
	Authenticati	Account lock strategy	
	on	Five times login failure in thirty minutes may result in account lock.	
Upgrade		Web browser, client-end and update tool.	
		Password login protection to guarantee safety	
		User-friendly interface when login. Provide the following options: Logout	
Login, Logout a	and Shutdown	/shutdown/ restart.	
- 3 , - 3		Right authentication when shut down to make sure only those proper	
		people can turn off DVR	
	Power	DC 12V	
	Power		
General	Consumptio		
Parameter	n	\leq 15W (With adapter, no HDD)	
	Working	-10℃−+55℃	
	Temperatur		
	e		
	Working	10%-90%	
	Humidity		
	Air Pressure	86kpa—106kpa	
	Dimension	SMART 1U case 270(W) x205 (D) x41mm(H)	
	Weight	1.25KG(no HDD)	
	Installation	Desktop installation	
	Mode		
		1	

1.3.2 HCVR51XXC-V2 Series

	Parameters	HCVR5104C-V2	HCVR5108C-V2
System	Main Processor	Industrial embedded micro controller	
	OS	Embedded LINUX	

	Parameters	HCVR5104C-V2	HCVR5108C-V2	
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	720P/D1/HD1/2CIF/CIF/QCIF		
	Resolution			
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s		
	Rate			
	Video Bit Rate	1536Kbps-4096Kbps,		
		For 720P: default setup is 2Mbps, max supports 4Mbps		
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz,16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC port	
	Input			
	Network Video	N/A		
	Input			
	Video Output	1-channel VGA output,		
		1-channel HDMI output (of the same video source),		
		HDMI/ VGA video output at the same time.		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	N/A		
	Audio Output	N/A		
	Bidirectional	N/A		
	Talk Input			
Record	Record Mode	Schedule record/manual record/MD	D record/Alarm record	
	Record	Max 4-channel playback	Max 8-channel playback	
	Playback			
	Backup Mode	HDD, burner, USB device, network backup		
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does not support eSATA port		
One HDD Space 4T		4T		
Communication	Network	1 RJ45 port, 100Mbps Ethernet port		
Port	Communication N/A			
	USB	2 USB ports		
Others	Power	DC12V		
	Power	≤15W (With power adapter, no HD	D)	

	Parameters	HCVR5104C-V2	HCVR5108C-V2	
	Consumption			
	Working	-10°C-+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	DimensionsSMART 1U case, 270mm (W) x205mm (D) x41mmWeight1.25KG (No HDD)InstallationDesk		205mm (D) x41mm (H)	
	Mode			

1.3.3 HCVR7104C-V2 Series

	Parameters	HCVR7104C-V2
System	Main Processor	Industrial embedded micro controller
	OS	Embedded LINUX
Video	Video Encode	H.264
Parameters	Standard	
	Encode	1080P /720P/D1/HD1/2CIF/CIF/QCIF
	Resolution	
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s
	Rate	
	Video Bit Rate	2048Kbps-6144Kbps,
		For 1080P: default setup is 4Mbps, max supports 6Mbps
	Bit Stream Type	Video stream/composite stream
	Dual-Stream	Support
Audio	Encode	G.711A/G.711U/PCM
Parameters	Standard	
	Audio Sampling	8KHz, 16Bit
	Rate	
	Audio Bit Rate	64Kbps
Video Port Analog Video		4-channel, BNC port
	Input	
	Network Video	N/A
	Input	
	Video Output	1-channel VGA output,
		1-channel HDMI output (of the same video source),
		HDMI/ VGA video output at the same time.
	Loop Output	N/A
	Matrix Output	N/A
Audio Port	Audio Input	N/A
	Audio Output	N/A
	Bidirectional	N/A

	Parameters	HCVR7104C-V2		
	Talk Input			
Record	Record Mode	Schedule record/manual record/MD record/Alarm record		
	Record	Max 4-channel playback		
	Playback			
	Backup Mode	HDD, burner, USB device, networ	k backup	
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does not support es	SATA port	
	One HDD Space	4T		
Communication	Network	1 RJ45 port, 100Mbps Ethernet p	ort	
Port	Communication	N/A		
	USB	2 USB ports		
Others	Power	DC12V		
	Power	≤20W(With power adapter, no H	IDD)	
	Consumption			
	Working	-10°C-+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimensions	SMART 1U case, 270mm (W) x205mm (D) x41mm (H)		
	Weight	1.25KG (No HDD)		
	Installation	Desk		
	Mode			
1.3.4 HCVR41	I0XC-S2 Series			
	Parameters	HCVR4104C-S2	HCVR4108C-S2	
System	Main Processor	Industrial embedded micro contro	ller	
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	720P/960H/D1/HD1/	720P(1~15fps)/960H/D1/	
	Resolution	2CIF/CIF/QCIF	HD1/2CIF/CIF/QCIF	
	Video Frame	HDCVI: 1~25f/s(PAL); 1~30f/s	HDCVI: 1 \sim 15f/s (The 1 st	
	Rate	(NTSC)	channel supports 25/30f)	
		CVBS: 1~25f/s (PAL); 1~30f/s	CVBS: 1~25f/s (PAL); 1~30f/s	
		(NTSC)	(NTSC)	
	Video Bit Rate	2048Kbps-4096Kbps,	1024Kbps-4096Kbps,	
		For 720P: default setup is	For 720P: default setup is	

2Mbps, max supports 4Mbps.

1Mbps, max supports 3Mbps.

Video stream/composite stream

Bit Stream Type

For 960H: default setup is

1Mbps, max supports 4Mbps.

1Mbps, max supports 3Mbps.

For 960H: default setup is

	Parameters	HCVR4104C-S2	HCVR4108C-S2	
	Dual-Stream	Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz,16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC port	
	Input			
	Network Video	Max 2-channel IPC connections (8M)	
	Input			
	Video Output	1-channel VGA output,		
		1-channel HDMI output (of the sa	me video source),	
		HDMI/ VGA video output at the sa	ame time.	
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	1-channel RCA port.		
	Audio Output	1-channel RCA port.		
	Bidirectional	Reuse the audio input/output port.		
	Talk Input			
Record	Record Mode	Schedule record/manual record/MD record/Alarm record		
	Record	Max 4-channel playback	Max 8-channel playback	
	Playback			
	Backup Mode	HDD, burner, USB device, network backup		
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does not support es	SATA port	
	One HDD Space	4T		
Communication	Network	1 RJ45 port, 100Mbps Ethernet p	ort	
Port	Communication	N/A		
	USB	2 USB ports		
Others	Power	DC12V		
	Power	≤15W (With power adapter, no HDD)		
	Consumption			
	Working	-10℃−+55℃		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimensions	SMART 1U case, 270mm (W) ×205mm (D) ×41mm (H)		
	Weight	1.25KG (No HDD)		
	Installation	Desk		
	Mode			

1.3.5 HCVR510XC-S2 Series

	Parameters	HCVR5104C-S2	HCVR5108C-S2	
System	Main Processor	Industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	1080P(1~15fps) /720P/960H/D1/HD1/2CIF/CIF/QCIF		
	Resolution			
	Video Frame	HDCVI: 1~25f/s (PAL); 1~30f/s (NTSC)		
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s	(NTSC)	
	Video Bit Rate	2048Kbps-4096Kbps,		
		For 1080P/720P: default setup is		
		For 960H: default setup is 1Mbps	, max supports 3Mbps.	
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC port	
	Input			
	Network Video	Max 2-channel IPC connections (8M)		
	Input			
	Video Output	1-channel VGA output,		
		1-channel HDMI output (of the same video source),		
		HDMI/ VGA video output at the same time.		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	1-channel RCA port.		
	Audio Output	1-channel RCA port.		
	Bidirectional	Reuse the audio input/output port.		
	Talk Input			
Record	Record Mode	Schedule record/manual record/N		
	Record	Max 4-channel playback	Max 8-channel playback	
	Playback			
	Backup Mode	HDD, burner, USB device, network backup		
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does not support eSATA port		
	One HDD Space	4T		

	Parameters	HCVR5104C-S2	HCVR5108C-S2
Communication	Network	1 RJ45 port, 100Mbps Ethernet port	
Port	Communication	N/A	
	USB	2 USB ports	
Others	Power	DC12V	
	Power	≤15W (With power adapter, no H	IDD)
	Consumption		
	Working	-10℃−+55℃	
	Temperature		
	Working	10%~90%	
	Humidity		
Dimensions SM		SMART 1U case, 270mm (W)	×205mm(D)×41mm(H)
	Weight	1.25KG(No HDD)	
	Installation	Desk	
	Mode		

1.3.6 HCVR7104C-S2 Series

	Parameters	HCVR7104C-S2
System	Main Processor	Industrial embedded micro controller
	OS	Embedded LINUX
Video	Video Encode	H.264
Parameters	Standard	
	Encode	1080P/720P/960H/D1/HD1/2CIF/CIF/QCIF
	Resolution	
	Video Frame	HDCVI: 1~25f/s (PAL); 1~30f/s (NTSC)
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s (NTSC)
	Video Bit Rate	2048Kbps-6144Kbps,
		For 1080P: default setup is 4Mbps, max supports 6Mbps.
		For 720P: default setup is 2Mbps, max supports 4Mbps.
	Bit Stream Type	Video stream/composite stream
Dual-Stream		Support
Audio	Encode	G.711A/G.711U/PCM
Parameters	Standard	
	Audio Sampling	8KHz, 16Bit
	Rate	
	Audio Bit Rate	64Kbps
Video Port	Analog Video	4-channel, BNC port
	Input	
	Network Video	Max 2-channel IPC connections (16M)
	Input	
	Video Output	1-channel VGA output,
		1-channel HDMI output (of the same video source),

	Parameters	HCVR7104C-S2	
		HDMI/ VGA video output at the same time.	
	Loop Output	N/A	
	Matrix Output	N/A	
Audio Port	Audio Input	1-channel RCA port.	
	Audio Output	1-channel RCA port.	
	Bidirectional	Reuse the audio input/output port.	
	Talk Input		
Record	Record Mode	Schedule record/manual record/MD record/Alarm record	
	Record	Max 4-channel playback	
	Playback		
	Backup Mode	HDD, burner, USB device, network backup	
Alarm	Alarm Input	N/A	
	Alarm Output	N/A	
HDD	HDD Port	1 SATA port, does not support eSATA port	
	One HDD Space	4T	
Communication	Network	1 RJ45 port, 100Mbps Ethernet port	
Port	Communication	N/A	
	USB	2 USB ports	
Others	Power	DC12V	
	Power	≤15W (With power adapter, no HDD)	
	Consumption		
	Working	-10℃-+55℃	
	Temperature		
	Working	10%~90%	
	Humidity		
	Dimensions	SMART 1U case, 270mm (W) ×205mm (D) ×41mm (H)	
	Weight	1.25KG (No HDD)	
	Installation	Desk	
	Mode		

1.3.7 HCVR2108C-S2 Series

	Devenueteve	LIOV/D01000 00
	Parameters	HCVR2108C-S2
System	Main Processor	Industrial embedded micro controller
	OS	Embedded LINUX
Video	Video Encode	H.264
Parameters	Standard	
	Encode	720P(1~15fps) /960H/D1/HD1/2CIF/CIF/QCIF
	Resolution	
	Video Frame	HDCVI: 1~12f/s
	Rate	CVBS: 1~20f/s (PAL); 1~20f/s (NTSC)
	Video Bit Rate	1024Kbps-4096Kbps,

	Parameters	HCVR2108C-S2
		For 720P: default setup is 1Mbps, max supports 4Mbps.
		For 1080P: default setup is 1Mbps, max supports 2Mbps.
	Bit Stream Type	Video stream/composite stream
	Dual-Stream	Support
Audio	Encode	G.711A/G.711U/PCM
Parameters	Standard	
	Audio Sampling	8KHz, 16Bit
	Rate	
	Audio Bit Rate	64Kbps
Video Port	Analog Video	8-channel, BNC port
	Input	
	Video Output	1-channel VGA output,
		1-channel HDMI output (of the same video source),
		HDMI/ VGA video output at the same time.
	Loop Output	N/A
	Matrix Output	N/A
Audio Port	Audio Input	1-channel RCA port.
	Audio Output	1-channel RCA port.
	Bidirectional	Reuse the audio input/output port.
	Talk Input	
Record	Record Mode	Schedule record/manual record/MD record/Alarm record
	Record	Max 8-channel playback
	Playback	
	Backup Mode	HDD, burner, USB device, network backup
Alarm	Alarm Input	N/A
	Alarm Output	N/A
HDD	HDD Port	1 SATA port, does not support eSATA port
	One HDD Space	4T
Communication	Network	1 RJ45 port, 100Mbps Ethernet port
Port	Communication	N/A
	USB	2 USB ports
Others	Power	DC12V
	Power	≤15W (With power adapter, no HDD)
	Consumption	
	Working	-10℃−+55℃
	Temperature	
	Working	10%~90%
	Humidity	
	Dimensions	SMART 1U case, 270mm (W) x205mm (D) x41mm (H)
	Weight	1.25KG(No HDD)
	U	

Parameters	HCVR2108C-S2
Mode	

1.3.8 HCVR410XC-S3 Series

	Parameters	HCVR4104C-S3	HCVR4108C-S3
System	Main Processor	Industrial embedded micro controlle	r
	OS	Embedded LINUX	
Video Parameters	Video Encode Standard	H.264	
	Encode Resolution	1080N/720P/960H/D1/HD1/2CIF/CI	F 1080N@12f/720P(Non realtime)/960H/D1/HD1/2C IF/CIF
	Video Frame Rate	PAL:1~25f/s; NTSC: 1~30f/s	
	Video Bit Rate	32Kbps-4096Kbps, For 720P: default setup is 1.5Mbps, For 1080P: default setup is 1.5Mbps	
	Bit Stream Type	Video stream/composite stream	
	Dual-Stream	Support	
Audio Parameters	Encode Standard	G.711A/G.711U/PCM	
	Audio Sampling	8KHz, 16Bit	
	Rate		
	Audio Bit Rate	64Kbps	
Video Port	Analog Video Input	4-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)	8-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)
	Network Video Input	 Max add 1 IP channel connection Analog/digital channel switch. Max 5 IP channel connections Connection bandwidth:4Mbps-20Mbps 	 Max add 2 IP channel connections Analog/digital channel switch. Max 10 IP channel connections Connection bandwidth:8Mbps-56Mbp s
	Video Output	1-channel VGA output, 1-channel HDMI output (of the same video source), HDMI/ VGA video output at the same time.	
	Loop Output	N/A	
	Matrix Output	N/A	
Audio Port	Audio Input	1-channel RCA port.	
	Coaxial Audio Input	4-ch	8-ch

	Parameters	HCVR4104C-S3	HCVR4108C-S3
	Audio Output	1-channel RCA port.	
	Bidirectional	Reuse the audio input/output port of the 1 st channel.	
	Talk Input		
Record	Record Mode	Schedule record/manual record/MD	record/Alarm record
	Playback Mode	Instant playback, normal playback, event playback, mark playback, smart playback	
	Backup Mode	HDD, burner, USB device, network I	packup
Alarm	Alarm Input	N/A	
	Alarm Output	N/A	
HDD	HDD Port	1 SATA port, does not support eSA	TA port
	One HDD Space	6T	
Communication	Network	1 RJ45 port, 100Mbps Ethernet port	
Port	Communication	RS485 port	
	USB	2 USB2.0 ports(at the rear panel)	
Others	Power	DC12V	
	Power	≤7W	≤8W
	Consumption		
	(No HDD)		
	Working	-10°C−+55°C	
	Temperature		
	Working	10%~90%	
	Humidity		
	Dimensions	SMART 1U case, 270mm (W) ×20	5mm (D) ×41mm (H)
	Weight (No	≪0.5KG	≤0.55KG
	HDD)		
	Installation	Desk	
	Mode		

1.3.9 HCVR510XC-S3 Series

	Parameters	HCVR5104C-S3	HCVR5108C-S3
System	Main Processor	ocessor Industrial embedded micro controller	
	OS	Embedded LINUX	
Video	Video Encode	H.264	
Parameters	Standard		
	Encode	1080P@15f/1080N/720P/960H/D1/HD	1/2CIF/CIF/
	Resolution		
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s	
	Rate		
	Video Bit Rate	32Kbps-6144Kbps,	
		For 720P: default setup is 2Mbps, max	x supports 4Mbps.
		For 1080P: default setup is 2Mbps, ma	ax supports 6Mbps.

	Parameters	HCVR5104C-S3	HCVR5108C-S3	
	Bit Stream Type	Video stream/composite stream	·	
	Dual-Stream	Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-ch BNC port(HDCVI HD	8-ch BNC port(HDCVI HD	
	Input	video/general standard definition	video/general standard	
		video self-adaptive)	definition video self-adaptive)	
	Network Video	 Max add 1 IP channel 	 Max add 2 IP channel 	
	Input	connection	connections	
		• Analog/digital channel switch.	Analog/digital channel	
		Max 5 IP channel	switch. Max 10 IP channel	
		connections	connections	
		Connection	Connection	
		bandwidth:8Mbps-24Mbps	bandwidth:16Mbps-48Mb	
			ps	
	Video Output	1-channel VGA output,		
		1-channel HDMI output (of the same		
		HDMI/ VGA video output at the same	ie time.	
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	1-channel RCA port.		
	Coaxial Audio	4-ch	8-ch	
	Input			
	Audio Output	1-channel RCA port.		
	Bidirectional	Reuse the audio input/output port o	t the 1st channel.	
	Talk Input			
Record	Record Mode	Schedule record/manual record/MD		
	Playback Mode	Instant playback, normal playback,	event playback, mark playback,	
	De aluva Maria	smart playback		
	Backup Mode			
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does not support eSA	ATA port	
	One HDD Space	6T		
Communication	Network			
Port	Communication	RS485 port		
	USB	2 USB2.0 ports(at the rear panel)		
Others	Power	DC12V		

Parameters	HCVR5104C-S3	HCVR5108C-S3
Power	≤7W	≤8W
Consumption		
(No HDD)		
Working	-10°C−+55°C	
Temperature		
Working	10%~90%	
Humidity		
Dimensions	SMART 1U case, 270mm (W) x205mm (D) x41mm (H)	
Weight (No	≤0.5KG	≤0.55KG
HDD)		
Installation	Desk	
Mode		

1.3.10 HCVR7104C-S3 Series

	Parameters	HCVR7104C-S3
System	Main Processor	Industrial embedded micro controller
	OS	Embedded LINUX
Video	Video Encode	H.264
Parameters	Standard	
	Encode	1080P/720P/960H/D1/HD1/2CIF/CIF
	Resolution	
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s
	Rate	
	Video Bit Rate	32Kbps-6144Kbps,
		For 720P: default setup is 2Mbps, max supports 4Mbps.
		For 1080P: default setup is 4Mbps, max supports 6Mbps.
	Bit Stream Type	Video stream/composite stream
	Dual-Stream	Support
Audio	Encode	G.711A/G.711U/PCM
Parameters	Standard	
	Audio Sampling	8KHz, 16Bit
	Rate	
	Audio Bit Rate	64Kbps
Video Port	Analog Video	4-ch BNC port(HDCVI HD video/general standard definition video
	Input	self-adaptive)
	Network Video	 Max add 2 IP channel connections.
	Input	• Analog/digital channel switch. Max 6 IP channel connections.
		 Connection bandwidth:8Mbps-24Mbps
	Video Output	1-channel VGA output,
		1-channel HDMI output (of the same video source),
		HDMI/ VGA video output at the same time.
	Loop Output	N/A

	Parameters	HCVR7104C-S3	
	Matrix Output	N/A	
Audio Port	Audio Input	1-channel RCA port.	
	Coaxial Audio	4-ch	
	Input		
	Audio Output	1-channel RCA port.	
	Bidirectional	Reuse the audio input/output port of the 1st channel.	
	Talk Input		
Record	Record Mode	Schedule record/manual record/MD record/Alarm record	
	Playback Mode	Instant playback, normal playback, event playback, mark playback,	
		smart playback	
	Backup Mode	HDD, burner, USB device, network backup	
Alarm	Alarm Input	N/A	
	Alarm Output	N/A	
HDD	HDD Port	1 SATA port, does not support eSATA port	
	One HDD Space	6T	
Communication	Network	1 RJ45 port, 100Mbps Ethernet port	
Port	Communication	RS485 port	
	USB	2 USB2.0 ports(at the rear panel)	
Others	Power	DC12V	
	Power	≤8W	
	Consumption		
	(No HDD)		
	Working	-10℃—+55℃	
	Temperature		
	Working	10%~90%	
	Humidity		
	Dimensions	SMART 1U case, 270mm (W) x205mm (D) x41mm (H)	
	Weight (No HDD)	≪0.5KG	
	Installation	Desk	
	Mode		

1.3.11 HCVR51XXH Series

	Parameter	HCVR5104H	HCVR5108H		
System	Main Processor	High-performance industrial embedded micro controller			
	OS				
	System Multiplex operations: Multiple-channel record, multiple-channel				
	Resources	and network operation simultaneously			
Interface User-friendly graphical user interface					

	Input	USB mouse		
	Devices			
	Input Method	Arabic number, English character, donation and extension Chinese (optional)		
	Shortcut	Copy/paste operation, USB mouse right-key shortcut menu, double click		
	Function	USB mouse to switch screen.		
Compression Standard	Video Compressio	H.264		
	n	o G711A, G711U, PCM		
	Audio Compressio n			
	Video Input	4-CH composite video input: (NTSC/PAL) BNC (1.0V _{P-P} ,75Ω)	8-CH composite video input: (NTSC/PAL) BNC (1.0V _{P-P} ,75Ω)	
	Video Output	1-ch VGA output. 1-ch HDMI output. Support VGA/HDMI video output at the same time.		
Video monitor	Video Standard	Support PAL/NTSC.		
	Record Speed	Real-time Mode: PAL 1f/s to 25f/s per channel and NTSC 1f/s to 30f/s per channel		
	Video Partition	1/4 windows(Optional)	1/4/8/9 windows	
	Monitor Touring	Support monitor tour functions such as motion detection, and schedule auto control.		
		PAL/NTSC Real-time monitor: 720P 1280*720		
	Resolution (PAL/NTSC)	Playback: All-ch: 720P 1280*720, 960H 960 ×576/960×480, D1 704×576/704×480, HD1 352×576/352×480, 2CIF 704×288/704×240, CIF 352×288/ 352×240 , QCIF 176×144/176×120		
		Support dual streams: extra stream resolution CIF 352×288/ 352×240, QCIF 176×144/176×120.		
	Image Quality	6-level image quality (Adjustable)		
	Privacy	Support one privacy mask of user-defined size in full screen.		
	mask	Support max 4 zones.		
	Image Information	Channel information, time information and privacy mask zone.		
	TV Adjust	Adjust TV output zone suitable to anamorphic video.		

	Channel Lock	Cover secret channel with black screen though system is encoding normally. Screen-lock function to prevent unauthorized user seeing secret video.		
	Channel Information	Channel name, recording status, screen lock status, video loss status and motion detection status are shown on the bottom left of display screen.		
	Color Configuratio n	Hue, brightness, contrast, saturation and gain setup for each channel.		
Audio	Audio Input	1-ch 200-2000mv 10KΩ(RCA)		
	Audio Output	1-ch audio output 200-3000mv 5KΩ(RCA)		
	Bidirectional Audio	Reuse the audio input/output channel.		
	Hard Disk	1 built-in SATA port. Support 1 HDD.		
Hard disk	One HDD Space	4T		
	Hard Disk	Audio: PCM 28.8MByte/h		
	Occupation	Video: 56-900MByte/h		
Record and	Recording Mode	Manual recording, motion detection recording, schedule recording and alarm recording Priority: Manual recording> alarm recording>motion detection recording>schedule recording.		
playback	Storage Mode	Support channel record quota setup		
	Recording Length	1 to 120 minutes single record duration (Default setup is 60 minutes)		
	Playback Repeat Way	When hard disk is full, system can overwrite previous video file.		
	Record Search	Various search engines such as time, type and channel.		
	Playback Mode	Various fast play, slow play speeds, manual frame by frame playback and reverse play mode.		
	Various File Switch Ways	Can switch to previous or next file or any file in current play list. Can switch to file on other channel of the same time. (If there is a file) Support file continuous play, when a file is end system auto plays the next file in the current channel		
	Playback Way	Support mark playback		
	Multi-chann el Playback	There is 1/4-channel playback mode.		
	Window Zoom	Switch between self-adaptive screen/full screen when playback		

	Partial	When in one-window full-screen playback mode, you can select any zone		
	Enlargemen	to activate partial enlargement function.		
	t			
Backup		HDD backup		
function	Backup	Support peripheral USB backup device. (Flash disk, portable disk and		
	Mode	etc.)		
		Support network download and save		
		View monitor channel remotely.		
		DVR configuration through client-end and web browser		
		Upgrade via client or browser to realize remote maintenance.		
Network		View alarm information such as motion detection and video loss via client.		
Function		Support network PTZ lens control		
	Network	File download backup and playback		
	control	Multiple devices share information via corresponding software such as		
		professional surveillance software (PSS)		
		Duplex transparent COM		
		Network alarm input and output		
		Zero-channel encoding.		
		Bidirectional audio.		
	Motion	Zone setup: support 396((PAL 22×18, NTSC 22×15)) detection zones.		
Motion	Detection	Various sensitivity levels.		
Detection and		Alarm can activate record or external alarm or screen message prompt.		
Alarm	Video Loss	Alarm can activate screen message prompt.		
	External	N/A		
	Alarm			
	Manual	N/A		
	Alarm			
	Control			
	Alarm Input	N/A		
	Alarm	N/A		
	Output			
	Alarm Relay	N/A		
	USB	2 USB 2.0 ports.		
Interface	Interface			
	Network	1 RJ45 10M/100M self-adaptable Ethernet port		
	connection			
	RS485	PTZ control port		
		Support various PTZ control protocols.		
	RS232	N/A		
System	Hard Disk	Display HDD current status		
Information	Information			

	Data	Data stream statistics for each channel (in wave mode)		
	Stream			
	Statistics			
Log		Backup to 1024 log files.		
		Support various search engines such as time and type.		
		Display version information: channel amount, system version and release		
Version		date.		
	On-line user	Display current on-line user		
User		Multi-lever user management; various management modes		
Management	User	Integrated management for local user, serial port user and network user.		
Ŭ	Manageme	Configurable user power.		
	nt	Support user /group and its corresponding rights modification.		
		No limit to the user or group amount.		
		Password modification		
	Password	Administrator can modify other user's password.		
	Authenticati	Account lock strategy		
	on	Five times login failure in thirty minutes may result in account lock.		
Upgrade		Web browser, client-end and update tool.		
		Password login protection to guarantee safety		
		User-friendly interface when login. Provide the following options: Logout		
Login, Logout a	nd Shutdown	/shutdown/ restart.		
		Right authentication when shut down to make sure only those proper		
		people can turn off DVR		
	Power	DC 12V		
	Power			
General	Consumptio	(15)N/ (Nith adapter, evaluate LIDD)		
Parameter	n	\leq 15W (With adapter, exclude HDD)		
	Working	-10°C-+55°C		
	Temperatur			
	е			
	Working	10%—90%		
	Humidity			
	Air Pressure	86kpa—106kpa		
	Dimension	325(W) x245 (D) x45mm(H)		
	Weight	1.25KG(Exclude HDD)		
	Installation	Desktop installation		
	Mode			

1.3.12 HCVR51XXH-V2 Series

	Parameters	HCVR5104H-V2	HCVR5108H-V2	HCVR5116H-V2	
System	Main Processor	Industrial embedded micro controller			
	OS	Embedded LINUX			

	Parameters	HCVR5104H-V2	HCVR5108H-V2	HCVR5116H-V2		
Video	Video Encode	H.264				
Parameters	Standard					
	Encode	720P/D1/HD1/2CIF/CIF/QCIF				
	Resolution					
	Video Frame	PAL:1~25f/s; NTSC:	1~30f/s			
	Rate					
	Video Bit Rate	1536Kbps-4096Kbps,	1536Kbps-4096Kbps,			
		For 720P: default setup is 2Mbps, max supports 4Mbps				
	Bit Stream Type	Video stream/composite stream				
	Dual-Stream	Support				
Audio	Encode	G.711A/G.711U/PCM				
Parameters	Standard					
	Audio Sampling	8KHz,16Bit				
	Rate					
	Audio Bit Rate	64Kbps				
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC port	16-channel , BNC		
	Input			port		
	Network Video	N/A				
	Input					
	Video Output	1-channel VGA output,				
		1-channel HDMI output (of the same video source),				
		HDMI/ VGA video output at the same time.				
	Loop Output	N/A				
	Matrix Output	N/A				
Audio Port	Audio Input	1-channel RCA				
	Audio Output	1-channel RCA				
	Bidirectional	Support (reuse the audio port)				
	Talk Input					
Record	Record Mode	Schedule record/manu	ual record/MD record/A	larm record		
	Record	Max 4-channel	Max 8-channel	Max 16-channel		
	Playback	playback	playback	playback		
	Backup Mode	HDD, burner, USB dev	vice, network backup			
Alarm	Alarm Input	N/A				
	Alarm Output	N/A				
HDD	HDD Port	1 SATA port, does no	ot support eSATA port			
	One HDD Space	4T				
Communication	Network	1 RJ45 port, 100Mbps	Ethernet port			
Port	Communication	RS485 port				
	USB	2 USB ports				
Others	Power	DC12V				
	Power	≤30W (With power ad	dapter, no HDD)			

Parameters	HCVR5104H-V2	HCVR5108H-V2	HCVR5116H-V2
Consumption			
Working	-10℃-+55℃		
Temperature			
Working	10%~90%		
Humidity			
Dimensions	Mini 1U case, 325mn	n (W) x245mm (D)	x45mm (H)
Weight	1.25KG (No HDD)		
Installation	Desk		
Mode			

1.3.13 HCVR51XXHC Series

	Parameter	HCVR5104HC	HCVR5108HC	
	Main	High-performance industrial embedde	ed micro controller	
System	Processor			
	OS	Embedded LINUX		
	System	Multiplex operations: Multiple-channe	el record, multiple-channel playback	
	Resources	and network operation simultaneousl	У	
	Interface	User-friendly graphical user interfac	ce	
	Input	USB mouse		
	Devices			
	Input		, donation and extension Chinese	
	Method	(optional)		
	Shortcut		ight-key shortcut menu, double click	
	Function	USB mouse to switch screen.		
Compression	Video			
Standard	Compressio	H.264		
	n			
	Audio			
	Compressio	N/A		
	n			
	Video Input	4-CH composite video input: (NTSC/PAL) BNC (1.0V _{P-P} ,75Ω)	8-CH composite video input: (NTSC/PAL) BNC (1.0V _{P-P} ,75Ω)	
	Video	1-ch VGA output.		
	Output	1-ch HDMI output.		
		Support VGA/HDMI video output at the	ne same time.	
Video monitor	Video Standard	Support PAL/NTSC.		
	Record	Real-time Mode: PAL 1f/s to 25f/s per channel and NTSC 1f/s to 30f/s per		
	Speed	channel		
	Video	1/4 windows(Optional)	1/4/8/9 windows	
	Partition			

	Monitor	Support monitor tour functions such as motion detection, and schedule
	Touring	auto control.
		PAL/NTSC
		Real-time monitor:
		720P 1280*720
	Deschilter	Playback:
	Resolution	All-ch: 720P 1280*720, 960H 960 ×576/960×480, D1
	(PAL/NTSC)	704×576/704×480, HD1 352×576/352×480, 2CIF 704×288/704×240,
		CIF 352×288/ 352×240 , QCIF 176×144/176×120
		Support dual streams: extra stream resolution CIF 352×288/ 352×240,
		QCIF 176×144/176×120.
	Image	6-level image quality (Adjustable)
	Quality	
	Privacy	Support one privacy mask of user-defined size in full screen.
	mask	Support max 4 zones.
	Image	Channel information, time information and privacy mask zone.
	Information	
	TV Adjust	Adjust TV output zone suitable to anamorphic video.
	Channel	Cover secret channel with black screen though system is encoding
	Lock	normally.
		Screen-lock function to prevent unauthorized user seeing secret video.
	Channel	Channel name, recording status, screen lock status, video loss status and
	Information	motion detection status are shown on the bottom left of display screen.
	Color	Hue, brightness, contrast, saturation and gain setup for each channel.
	Configuratio	
A	n	
Audio	Audio Input	N/A
	Audio	N/A
	Output	
	Bidirectional	N/A
	Audio	
	Hard Disk	1 built-in SATA port. Support 1 HDD.
	One HDD	4T
Hard disk	Space	
	Hard Disk	Audio: PCM 28.8MByte/h
	Occupation	Video: 56-900MByte/h
		Manual recording, motion detection recording, schedule recording and
	Recording	alarm recording
	Mode	Priority: Manual recording> alarm recording>motion detection
Record and		recording>schedule recording.

playback	Storage Mode	Support channel record quota setup
	Recording Length	1 to 120 minutes single record duration (Default setup is 60 minutes)
	Playback Repeat Way	When hard disk is full, system can overwrite previous video file.
	Record Search	Various search engines such as time, type and channel.
	Playback Mode	Various fast play, slow play speeds, manual frame by frame playback and reverse play mode.
	Various File Switch Ways	Can switch to previous or next file or any file in current play list. Can switch to file on other channel of the same time. (If there is a file) Support file continuous play, when a file is end system auto plays the next file in the current channel
	Playback Way	Support mark playback
	Multi-chann el Playback	There is 1/4-channel playback mode.
	Window Zoom	Switch between self-adaptive screen/full screen when playback
	Partial Enlargemen t	When in one-window full-screen playback mode, you can select any zone to activate partial enlargement function.
Backup		HDD backup
function	Backup Mode	Support peripheral USB backup device. (Flash disk, portable disk and etc.)
		Support network download and save
		View monitor channel remotely.
		DVR configuration through client-end and web browser
		Upgrade via client or browser to realize remote maintenance.
Network		View alarm information such as motion detection and video loss via client.
Function		Support network PTZ lens control
	Network	File download backup and playback
	control	Multiple devices share information via corresponding software such as professional surveillance software (PSS)
		Duplex transparent COM
		Network alarm input and output
		Zero-channel encoding.
		Bidirectional audio.
	Motion	Zone setup: support 396((PAL 22×18, NTSC 22×15)) detection zones.
Motion	Detection	Various sensitivity levels.
Detection and		Alarm can activate record or external alarm or screen message prompt.
Alarm	Video Loss	Alarm can activate screen message prompt.

	External	N/A
	Alarm	
	Manual	N/A
	Alarm	
	Control	
	Alarm Input	N/A
	Alarm	N/A
	Output	
	Alarm Relay	N/A
	USB	2 USB 2.0 port.
Interface	Interface	
	Network	1 RJ45 10M/100M self-adaptable Ethernet port
	connection	
	RS485	N/A
	RS232	N/A
System	Hard Disk	Display HDD current status
Information	Information	
	Data	Data stream statistics for each channel (in wave mode)
	Stream	
	Statistics	
	Log	Backup to 1024 log files.
	statistics	Support various search engines such as time and type.
	Version	Display version information: channel amount, system version and release
	Version	date.
	On-line user	Display current on-line user
User		Multi-lever user management; various management modes
Management	User	Integrated management for local user, serial port user and network user.
	Manageme	Configurable user power.
	nt	Support user /group and its corresponding rights modification.
		No limit to the user or group amount.
	Password	Password modification
	Authenticati	Administrator can modify other user's password.
		Account lock strategy
	on	Five times login failure in thirty minutes may result in account lock.
Upgrade		Web browser, client-end and update tool.
		Password login protection to guarantee safety
		User-friendly interface when login. Provide the following options: Logout
Login, Logout and Shutdown		/shutdown/ restart.
		Right authentication when shut down to make sure only those proper
		people can turn off DVR
	Power	DC 12V

	Power	
General	Consumptio	\leqslant 15W (With adapter, exclude HDD)
Parameter	n	
	Working	-10°C-+55°C
	Temperatur	
	е	
	Working	10%-90%
	Humidity	
	Air Pressure	86kpa—106kpa
	Dimension	325(W) x245 (D) x45mm(H)
	Weight	1.25KG(Exclude HDD)
	Installation	Desktop installation
	Mode	

1.3.14 HCVR51XXHC-V2 Series

Parameters	HCVR5104HC-V2	HCVR5108HC-V2	HCVR5116HC-V2
Main Processor	Industrial embedded r	nicro controller	
OS	Embedded LINUX		
Video Encode	H.264		
Standard			
Encode	720P/D1/HD1/2CIF/C	IF/QCIF	
Resolution			
Video Frame	PAL:1~25f/s; NTSC:	1~30f/s	
	1536Kbps-4096Kbps		
VIGEO DIT HATE			orts 4Mbps
Bit Stream Type			
Standard			
Audio Sampling	8KHz, 16Bit		
Rate			
Audio Bit Rate	64Kbps		
Analog Video	4-channel, BNC port	8-channel, BNC port	16-channel, BNC
Input			port
Network Video	N/A		
Input			
Video Output	1-channel VGA output,		
		,	
	HDMI/ VGA video output at the same time.		
Loop Output	N/A		
Matrix Output	N/A		
Audio Input	N/A		
	Main ProcessorOSOSVideo EncodeStandardEncodeResolutionVideo FrameRateVideo Bit RateBit Stream TypeDual-StreamEncodeStandardAudio SamplingRateAudio Bit RateAudio Bit RateAudio OBit RateNetwork VideoInputVideo OutputLoop OutputMatrix Output	Main ProcessorIndustrial embedded rOSEmbedded LINUXVideo EncodeH.264Standard720P/D1/HD1/2CIF/CResolution720P/D1/HD1/2CIF/CResolutionVideo FrameVideo FramePAL:1~25f/s; NTSC:Rate1536Kbps-4096Kbps,Video Bit Rate1536Kbps-4096Kbps,Bit Stream TypeVideo stream/composDual-StreamSupportEncodeG.711A/G.711U/PCMStandardStandardAudio Sampling8KHz, 16BitRate4-channel, BNC portInputN/ANetwork VideoN/AInput1-channel VGA outputLoop OutputN/AMatrix OutputN/A	Main Processor Industrial embedded micro controller OS Embedded LINUX Video Encode Standard H.264 Standard Frame PAL:1~25f/s: NTSC: Video Frame PAL:1~25f/s: NTSC: Video Frame PAL:1~25f/s: NTSC: Video Frame PAL:1~25f/s: NTSC: Video Bit Rate 1536Kbps-4096Kbps, For 720P: default setup is 2Mbps, max supp Bit Stream Type Video stream/composite stream Dual-Stream Support Encode G.711A/G.711U/PCM Standard Audio Sampling Audio Sampling 8KHz, 16Bit Rate Analog Audio Bit Rate 64Kbps Analog Video Network N/A Input 1-channel, BNC port Network N/A Uideo Output 1-channel HDMI output (of the same video sc HDMI/ VGA video output at the same time. Loop Output N/A Matrix Output

	Parameters	HCVR5104HC-V2	HCVR5108HC-V2	HCVR5116HC-V2		
	Bidirectional	N/A				
	Talk Input					
Record	Record Mode	Schedule record/manual record/MD record/Alarm record				
	Record	Max 4-channel	Max 8-channe	el Max 16-channel		
	Playback	playback	playback	playback		
	Backup Mode	HDD, burner, USB device, network backup				
Alarm	Alarm Input	N/A				
	Alarm Output	N/A				
HDD	HDD Port	1 SATA port, does no	ot support eSATA port			
	One HDD Space	4T				
Communication	Network	1 RJ45 port, 100Mbps Ethernet port				
Port	Communication	RS485 port				
	USB	2 USB ports				
Others	Power	DC12V				
	Power	≤30W (With power adapter, no HDD)				
	Consumption					
	Working	-10°C-+55°C				
	Temperature					
	Working	10%~90%				
	Humidity					
	Dimensions	Mini 1U case, 325mm (W) x245mm (D) x45mm (H)				
	Weight	1.25KG (No HDD)				
	Installation	Desk				
	Mode					

1.3.15 HCVR51XXHE Series

	Parameter	HCVR5104HE	HCVR5108HE	
System	Main	High-performance industrial embedde	ed micro controller	
	Processor			
	OS	Embedded LINUX		
	System	Multiplex operations: Multiple-channe	el record, multiple-channel playback	
	Resources	and network operation simultaneously		
	Interface	User-friendly graphical user interfac	ce	
	Input	USB mouse		
	Devices			
	Input	Arabic number, English character	, donation and extension Chinese	
	Method	(optional)		
	Shortcut	Copy/paste operation, USB mouse r	ight-key shortcut menu, double click	
	Function	USB mouse to switch screen.		

Compression	Video			
Standard	Compressio	H.264		
	n			
	Audio			
	Compressio	G711A, G711U, PCM		
	n			
	Video Input	4-CH composite video input:	8-CH composite video input:	
		(NTSC/PAL) BNC (1.0V _{P-P} , 75Ω)	(NTSC/PAL) BNC (1.0V _{P-P} , 75Ω)	
	Video	1-ch VGA output.		
	Output	1-ch HDMI output.	he some time	
Video monitor	Video	Support VGA/HDMI video output at t		
	Standard	Support PAL/NTSC.		
	Record	Real-time Mode: PAL 1f/s to 25f/s pe	r channel and NTSC 1f/s to 30f/s per	
	Speed	channel		
	Video	1/4 windows(Optional)	1/4/8/9 windows	
	Partition			
	Monitor	Support monitor tour functions such	as motion detection, and schedule	
	Touring	auto control.		
		PAL/NTSC		
		Real-time monitor:		
		720P 1280*720		
	Resolution	Playback:		
	(PAL/NTSC)	All-ch: 720P 1280*720, 960H 960 ×576/960×480, D1		
		704×576/704×480, HD1 352×576/352×480, 2CIF 704×288/704×240, CIF 352×288/ 352×240 , QCIF 176×144/176×120		
			resolution CIF 352×288/ 352×240,	
		QCIF 176×144/176×120.		
	Image	6-level image quality (Adjustable)		
	Quality			
	Privacy	Support one privacy mask of user-de	fined size in full screen.	
	mask	Support max 4 zones.		
	Image	Channel information, time information and privacy mask zone.		
	Information	· · · · · · · · · · · · · · · · · · ·		
	TV Adjust	Adjust TV output zone suitable to ana	amorphic video.	
	Channel	Cover secret channel with black s	screen though system is encoding	
	Lock	normally.		
		Screen-lock function to prevent unau	•	
	Channel	Channel name, recording status, screen lock status, video loss status and		
	Information	motion detection status are shown or	i the bottom left of display screen.	

	Color Configuratio n	Hue, brightness, contrast, saturation and gain setup for each channel.
Audio	Audio Input	1-ch 200-2000mv 10KΩ(RCA)
	Audio Output	1-ch audio output 200-3000mv 5KΩ(RCA)
	Bidirectional Audio	Reuse the audio input/output channel.
	Hard Disk	1 built-in SATA port. Support 1 HDD.
Hard disk	One HDD Space	4T
	Hard Disk Occupation	Audio: PCM 28.8MByte/h Video: 56-900MByte/h
Record and playback	Recording Mode	Manual recording, motion detection recording, schedule recording and alarm recording Priority: Manual recording> alarm recording>motion detection recording>schedule recording.
	Storage Mode	Support channel record quota setup
	Recording Length	1 to 120 minutes single record duration (Default setup is 60 minutes)
	Playback Repeat Way	When hard disk is full, system can overwrite previous video file.
	Record Search	Various search engines such as time, type and channel.
	Playback Mode	Various fast play, slow play speeds, manual frame by frame playback and reverse play mode.
	Various File Switch Ways	Can switch to previous or next file or any file in current play list. Can switch to file on other channel of the same time. (If there is a file) Support file continuous play, when a file is end system auto plays the next file in the current channel
	Playback Way	Support mark playback
	Multi-chann el Playback	There is 1/4-channel playback mode.
	Window Zoom	Switch between self-adaptive screen/full screen when playback
	Partial Enlargemen t	When in one-window full-screen playback mode, you can select any zone to activate partial enlargement function.

Backup		HDD backup		
function	Backup Mode	Support peripheral USB backup dev etc.)	vice. (Flash disk, portable disk and	
		Support network download and save		
		View monitor channel remotely.		
		DVR configuration through client-end and web browser		
		Upgrade via client or browser to realize	ze remote maintenance.	
Network		View alarm information such as motic	on detection and video loss via client.	
Function	Nationali	Support network PTZ lens control		
	Network control	File download backup and playback		
	CONTION	Multiple devices share information v		
		professional surveillance software (P	SS)	
		Duplex transparent COM		
		Network alarm input and output		
		Bidirectional audio.		
	Motion	Zone setup: support 396((PAL 22×18	, NTSC 22×15)) detection zones.	
Motion	Detection	Various sensitivity levels.		
Detection and		Alarm can activate record or external		
Alarm	Video Loss	Alarm can activate screen message p	•	
	External	Support record activation function o	r activate external alarm or screen	
	Alarm	message in specified period.		
	Manual	Enable or disable alarm input channe		
	Alarm	Support analog alarm signal to specif	ic alarm output channel.	
	Control	4 ob alarm input (NO/NC)	9 ob clorm input (NO/NC)	
	Alarm Input Alarm	4-ch alarm input (NO/NC) 3-channel relay output.	8-ch alarm input (NO/NC)	
	Output			
	Alarm Relay	30V DC 2A, 125VAC 1A (activa	ation alarm	
	USB	2 USB 2.0 ports.		
Interface	Interface			
	Network	One RJ45 10M/100M self-adaptable	Ethernet port	
	connection			
	RS485	PTZ control port		
	10405	Support various PTZ control protocol	S.	
	RS232	N/A		
System	Hard Disk	Display HDD current status		
Information	Information			
	Data	Data stream statistics for each channel (in wave mode)		
	Stream			
	Statistics			
	Log	Backup to 1024 log files.		
	statistics	Support various search engines such	as time and type.	

	Version	Display version information: channel amount, system version and release	
		date.	
	On-line user	Display current on-line user	
User		Multi-lever user management; various management modes	
Management	User	Integrated management for local user, serial port user and network user.	
	Manageme	Configurable user power.	
	nt	Support user /group and its corresponding rights modification.	
		No limit to the user or group amount.	
	Deceward	Password modification	
	Password	Administrator can modify other user's password.	
	Authenticati	Account lock strategy	
	on	Five times login failure in thirty minutes may result in account lock.	
Upgrade		Web browser, client-end and update tool.	
		Password login protection to guarantee safety	
		User-friendly interface when login. Provide the following options: Logout	
Login, Logout a	and Shutdown	/shutdown/ restart.	
		Right authentication when shut down to make sure only those proper	
		people can turn off DVR	
	Power	DC 12V	
	Power		
General	Consumptio		
Parameter	n	\leq 15W (With adapter, exclude HDD)	
	Working	-10℃−+55℃	
	Temperatur		
	e		
	Working	10%-90%	
	Humidity		
	Air Pressure	86kpa—106kpa	
	Dimension	325(W) x245 (D) x45mm(H)	
	Weight	1.25KG(Exclude HDD)	
	Installation	Desktop installation	
	Mode		
		1	

1.3.16 HCVR51HE-V2 Series

	Parameters	HCVR5104HE-V2	HCVR5108HE-V2	HCVR5116HE-V2
System	Main Processor	Industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard	Standard		
	Encode	720P/D1/HD1/2CIF/C	IF/QCIF	
	Resolution			
	Video Frame	PAL:1~25f/s; NTSC:	1~30f/s	

	Parameters	HCVR5104HE-V2	HCVR5108HE-V2	HCVR5116HE-V2	
	Rate				
	Video Bit Rate	1536Kbps-4096Kbps,			
		For 720P: default setup is 2Mbps, max supports 4Mbps			
	Bit Stream Type	Video stream/composite stream Support			
	Dual-Stream				
Audio	Encode	G.711A/G.711U/PCM			
Parameters	Standard				
	Audio Sampling	8KHz,16Bit			
	Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC port	16-channel, BNC	
	Input			port	
	Network Video	N/A		1	
	Input				
	Video Output	1-channel VGA output	,		
		1-channel HDMI outpu	ut (of the same video so	ource),	
		HDMI/ VGA video output at the same time.			
	Loop Output	N/A			
	Matrix Output	N/A			
Audio Port	Audio Input	4-channel RCA			
	Audio Output	1-channel RCA			
	Bidirectional	Support (reuse the au	dio port)		
	Talk Input				
Record	Record Mode	Schedule record/manu	ual record/MD record/A	larm record	
	Record	Max 4-channel	Max 8-channel	Max 16-channel	
	Playback	playback	playback	playback	
	Backup Mode	HDD, burner, USB dev	vice, network backup		
Alarm	Alarm Input	4-channel alarm	8-channel alarm	16-channel alarm	
		input	input	input	
	Alarm Output	3-channel alarm outpu	ıt		
HDD	HDD Port	1 SATA port, does no	t support eSATA port		
	One HDD Space	4T			
Communication	Network	1 RJ45 port, 100Mbps Ethernet port			
Port	Communication	RS485 port			
	USB	2 USB ports			
Others	Power	DC12V			
	Power	≤30W (With power adapter, no HDD)			
	Consumption				
	Working	-10℃−+55℃			
	Temperature				
	Working	10%~90%			

Parameters	B HCVR5104HE-	V2 HCVR5108H	E-V2 HC	VR5116HE-V2
Humidity				
Dimension	Mini 1U case,	Mini 1U case, 325mm (W) x245mm (D) x45mm (H)		
Weight	1.25KG(No HI) (DC		
Installation	Desk			
Mode				

1.3.17 HCVR71XXH-V2 Series

	Parameters	HCVR7104H-V2	HCVR7108H-V2	
System	Main Processor	Industrial embedded micro contro	ller	
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	1080P /720P/D1/HD1/2CIF/CIF/QCIF		
	Resolution			
	Video Frame Rate	PAL:1~25f/s; NTSC: 1~30f/s		
	Video Bit Rate	2048Kbps-6144Kbps,		
		For 1080P: default setup is 4Mbp	s,max supports 6Mbps	
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz,16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video Input	4-channel, BNC port	8-channel, BNC port	
	Network Video Input	N/A		
	Video Output	1-channel VGA output,		
		1-channel HDMI output (of the same video source),		
		HDMI/ VGA video output at the sa	ame time.	
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	1-channel RCA		
	Audio Output	1-channel RCA		
	Bidirectional	Support (reuse the audio port)		
	Talk Input			
Record	Record Mode	Schedule record/manual record/M	1D record/Alarm record	
	Record	Max 4-channel playback	Max 8-channel playback	
	Playback			

	Parameters	HCVR7104H-V2	HCVR7108H-V2
	Backup Mode	HDD, burner, USB device, network backup	
Alarm	Alarm Input	N/A	
	Alarm Output	N/A	
HDD	HDD Port	1 SATA port, does not support es	SATA port
	One HDD Space	4T	
Communication	Network	1 RJ45 port, 100Mbps Ethernet p	ort
Port	Communication	N/A	
	USB	2 USB ports	
Others	Power	DC12V	
	Power	≤30W (With power adapter, no H	DD)
	Consumption		
	Working	-10 °C−+55°C	
	Temperature		
	Working	10%~90%	
	Humidity		
	Dimensions	Mini 1U case, 325mm (W) ×24	5mm(D)×45mm(H)
	Weight	1.25KG (No HDD)	
	Installation	Desk	
	Mode		

1.3.18 HCVR71XXHC-V2 Series

	Parameters	HCVR7104HC-V2	HCVR7108HC-V2
System	Main Processor	Industrial embedded micro controller	
	OS	Embedded LINUX	
Video	Video Encode	H.264	
Parameters	Standard		
	Encode	1080P/720P/D1/HD1/2CIF/CIF/Q	CIF
	Resolution		
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s	
	Rate		
	Video Bit Rate	2048Kbps-6144Kbps,	
		For 1080P: default setup is 4Mbps, max supports 6Mbps	
	Bit Stream Type	Video stream/composite stream	
	Dual-Stream	Support	
Audio	Encode	G.711A/G.711U/PCM	
Parameters	Standard		
	Audio Sampling	8KHz,16Bit	
	Rate		
	Audio Bit Rate	idio Bit Rate 64Kbps	
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC port
	Input		

	Parameters	HCVR7104HC-V2	HCVR7108HC-V2	
	Network Video	N/A		
	Input			
	Video Output	1-channel VGA output,		
		1-channel HDMI output (of the sa	me video source),	
		HDMI/ VGA video output at the sa	ame time.	
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	N/A		
	Audio Output	N/A		
	Bidirectional	N/A		
	Talk Input			
Record	Record Mode	Schedule record/manual record/M	ID record/Alarm record	
	Record	Max 4-channel playback	Max 8-channel playback	
	Playback			
	Backup Mode	HDD, burner, USB device, networ	k backup	
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does not support es	SATA port	
	One HDD Space	4T		
Communication	Network	1 RJ45 port, 100Mbps Ethernet p	ort	
Port	Communication	RS485 port		
	USB	2 USB ports		
Others	Power	DC12V		
	Power	≤30W (With power adapter, no H	DD)	
	Consumption			
	Working	-10°C−+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimensions	Mini 1U case, 325mm (W) ×24	5mm (D) ×45mm (H)	
	Weight	1.25KG (No HDD)		
	Installation	Desk		
	Mode			

1.3.19 HCVR71XHE-V2 Series

	Parameters	HCVR7104HE-V2	HCVR7108HE-V2
System	Main Processor	Industrial embedded micro controller	
	OS	Embedded LINUX	
Video	Video Encode	H.264	
Parameters	Standard		
	Encode	1080P/720P/D1/HD1/2CIF/CIF/Q	CIF

	Parameters	HCVR7104HE-V2	HCVR7108HE-V2		
	Resolution		•		
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s			
	Rate				
	Video Bit Rate	2048Kbps-6144Kbps,			
		For 1080P: default setup is 4Mbp	s, max supports 6Mbps		
	Bit Stream Type	Video stream/composite stream			
	Dual-Stream	Support			
Audio	Encode	G.711A/G.711U/PCM			
Parameters	Standard				
	Audio Sampling	8KHz,16Bit			
	Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC port		
	Input				
	Network Video	N/A			
	Input				
	Video Output	1-channel VGA output,			
		1-channel HDMI output (of the same video source),			
		HDMI/ VGA video output at the same time.			
	Loop Output	N/A			
	Matrix Output	N/A			
Audio Port	Audio Input	4-channel RCA			
	Audio Output	1-channel RCA			
	Bidirectional	Support (reuse the audio port)			
	Talk Input				
Record	Record Mode	Schedule record/manual record/N	1		
	Record	Max 4-channel playback	Max 8-channel playback		
	Playback				
	Backup Mode	HDD, burner, USB device, netwo			
Alarm	Alarm Input	4-channel alarm input	16-channel alarm input		
	Alarm Output	3-channel alarm output			
HDD	HDD Port	1 SATA port, does not support e	SATA port		
	One HDD Space	4T			
Communication	Network	1 RJ45 port, 100Mbps Ethernet p	ort		
Port	Communication	RS485 port			
	USB	2 USB ports			
Others	Power	DC12V			
	Power	≤30W (With power adapter, no H	IDD)		
	Consumption				
	Working	-10°C−+55°C			
	Temperature				

Parameters	HCVR7104HE-V2	HCVR7108HE-V2	
Working Humidity	10%~90%		
		325mm (W) x245mm (D) x45mm (H)	
Weight 1.25KG (No HDD)			
Installation	Desk		
Mode			

1.3.20 HCVR41XXHE-S2 Series

	Parameters	HCVR4104HE-S2	HCVR4108HE-S2	HCVR4116HE-S2			
System	Main Processor	Industrial embedded mic	ro controller				
	OS	Embedded LINUX					
Video	Video Encode	H.264					
Parameters	Standard						
	Encode	720P/960H/D1/	720P(1~15fps)/960H/				
	Resolution	HD1/2CIF/CIF/QCIF	D1/HD1/2CIF/CIF/QCI	F			
	Video Frame	HDCVI : 1 \sim 25f/s	HDCVI : 1 \sim 15f/s	(The 1 st channel			
	Rate	(PAL) ; 1~30f/s	supports 25/30f)				
		(NTSC)	CVBS: 1~25f/s (PAL)); 1~30f/s (NTSC)			
		CVBS: 1~25f/s (PAL);					
		1~30f/s (NTSC)					
	Video Bit Rate	2048Kbps-4096Kbps,	1024Kbps-4096Kbps,				
		For 720P: default setup	For 720P: default set	up is 1Mbps, max			
		is 2Mbps , max	supports 4Mbps.				
		supports 4Mbps.	For 960H: default set	up is 1Mbps, max			
		For 960H: default	supports 3Mbps.				
		setup is 1Mbps, max supports 3Mbps.					
	Bit Stream Type	Video stream/composite	stream				
	Dual-Stream	Support	Silean				
Audio	Encode	G.711A/G.711U/PCM					
Parameters	Standard						
	Audio Sampling	8KHz,16Bit					
	Rate						
	Audio Bit Rate	64Kbps					
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC port	16-channel,			
	Input			BNC port			
	Network Video						
	Input	x [−] ,					
	Video Output	1-channel VGA output,					
		1-channel HDMI output (of the same video sour	ce),			
		HDMI/ VGA video output at the same time.					
				N/A			

	Parameters	HCVR4104HE-S2	HCVR4108HE-S2	HCVR4116HE-S2	
	Matrix Output	N/A			
Audio Port	Audio Input	4-channel RCA port.			
	Audio Output	1-channel RCA port.			
	Bidirectional	Reuse the audio input/ou	itput port.		
	Talk Input				
Record	Record Mode	Schedule record/manual	record/MD record/Ala	arm record	
	Record	Max 4-channel playback	Max 8-chann	el Max 16-channel	
	Playback		playback	playback	
	Backup Mode	HDD, burner, USB device	e, network backup	·	
Alarm	Alarm Input	4-channel input	8-channel input	16-channel input	
	Alarm Output	3-channel output	•		
HDD	HDD Port	1 SATA port, does not s	upport eSATA port		
	One HDD Space	4T			
Communication	Network	1 RJ45 port, 100Mbps Et	thernet port		
Port	Communication	RS485 port			
	USB	2 USB ports			
Others	Power	DC12V			
	Power	≤15W (With power adapter, no HDD)			
	Consumption				
-	Working	-10°C − + 55°C			
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions	Mini 1U case, 325mm (W) x245mm (D) x45mm (H)			
	Weight	1.25KG(No HDD)			
	Installation	Desk			
	Mode				
1.3.21 HCVR51	XXH-S2 Series				
	Parameters	HCVR5104H-S2 H	CVR5108H-S2	HCVR5116H-S2	
System	Main Processor	Industrial embedded mic	ro controller		
	OS	Embedded LINUX			
Video	Video Encode	H.264			
Parameters	Standard				
	Encode	1080P(1~15fps)/720P/96	0H/D1/HD1/2CIF/CI	F/QCIF	
	Resolution				
	Video Frame	HDCVI: 1~25f/s (PAL); 1~30f/s (NTSC)			
	Rate	CVBS: 1~25f/s (PAL);	1~30f/s (NTSC)		
	Video Bit Rate	2048Kbps-4096Kbps,			
		For 1080P/720P: default			
		For 960H: default setup i		orts 3Mbps.	
	Bit Stream Type	Video stream/composite stream			

	Parameters	HCVR5104H-S2	HCVR5108H-S2	HCVR5116H-S2	
	Dual-Stream	Support		I	
Audio	Encode	G.711A/G.711U/PCM			
Parameters	Standard				
	Audio Sampling	8KHz,16Bit			
	Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC por	t 16-channel,	
	Input			BNC port	
	Network Video	Max 2-channel IPC co	nnections (8M)	•	
	Input				
	Video Output	1-channel VGA output	3		
		1-channel HDMI outpu	t (of the same video so	ource),	
		HDMI/ VGA video outp	out at the same time.		
	Loop Output	N/A			
	Matrix Output	N/A			
Audio Port	Audio Input	1-channel RCA port.			
	Audio Output	1-channel RCA port.			
	Bidirectional	Reuse the audio input/output port.			
	Talk Input				
Record	Record Mode	Schedule record/manual record/MD record/Alarm record			
	Record	Max 4-channel	Max 8-channe	el Max 16-channel	
	Playback	playback	playback	playback	
	Backup Mode	HDD, burner, USB dev	rice, network backup		
Alarm	Alarm Input	N/A			
	Alarm Output	N/A			
HDD	HDD Port	1 SATA port, does no	t support eSATA port		
	One HDD Space	4T			
Communication	Network	1 RJ45 port, 100Mbps	Ethernet port		
Port	Communication	RS485 port			
	USB	2 USB ports			
Others	Power	DC12V			
	Power	≤15W (With power ac	apter, no HDD)		
	Consumption				
	Working	-10℃-+55℃			
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions	Mini 1U case, 325mm	(W) x245mm (D) >	«45mm (H)	
	Weight	1.25KG(No HDD)			
	Installation	Desk			
	Mode				

1.3.22 HCVR51XXHE-S2 Series

	Parameters	HCVR5104HE-S2	HCVR5108HE-S2	HCVR5116HE-S2
System	Main Processor	Industrial embedded m	nicro controller	
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	1080P(1~15fps)/720P/960H/D1/HD1/2CIF/CIF/QCIF		
	Resolution			
	Video Frame	HDCVI: 1~25f/s (PA	L); 1~30f/s (NTSC)	
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s (NTSC)	
	Video Bit Rate	2048Kbps-4096Kbps,		
		For 1080P/720P: defai	ult setup is 2Mbps, max	supports 4Mbps.
		For 960H: default setu	p is 1Mbps, max suppo	rts 3Mbps.
	Bit Stream Type	Video stream/composi	te stream	
	Dual-Stream	Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC port	16-channel,
	Input			BNC port
	Network Video	Max 2-channel IPC connections (8M)		
	Input			
	Video Output	1-channel VGA output		
		1-channel HDMI output (of the same video source),		
		HDMI/ VGA video output at the same time.		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	4-channel RCA port.		
	Audio Output	1-channel RCA port.		
	Bidirectional	Reuse the audio input/	output port.	
	Talk Input			
Record	Record Mode		al record/MD record/Ala	
	Record	Max 4-channel		
	Playback	playback	playback	playback
	Backup Mode	HDD, burner, USB device, network backup		
Alarm	Alarm Input	4-channel input	8-channel input	16-channel input
	Alarm Output	3-channel output		
HDD	HDD Port	1 SATA port, does not support eSATA port bace 4T		
	One HDD Space			
Communication	Network	1 RJ45 port, 100Mbps	Ethernet port	

	Parameters	HCVR5104HE-S2	HCVR5108	HE-S2	HCVR5116HE-S2
Port	Communication	RS485 port			
	USB	2 USB ports			
Others	Power	DC12V			
	Power	≤15W (With power ad	dapter, no HD	D)	
	Consumption	-10°C−+55°C			
	Working				
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions	Mini 1U case, 325mn	n (W) x245r	mm (D) >	«45mm (H)
	Weight	1.25KG (No HDD)			
	Installation	Desk			
	Mode				
1.3.23 HCVR710XH-S2 Series					
	Parameters	HCVR7104H-S2		HCVR71	08H-S2

	Parameters	HCVR7104H-S2	HCVR7108H-S2	
System	Main Processor	Industrial embedded micro controlle	er	
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	1080P/720P/960H/D1/HD1/2CIF/CI	F/QCIF	
	Resolution			
	Video Frame	HDCVI: 1~25f/s (PAL); 1~30f/s	(NTSC)	
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s (NTSC)	
	Video Bit Rate	2048Kbps-6144Kbps,		
		For 1080P: default setup is 4Mbps, max supports 6Mbps.		
		For 720P: default setup is 2Mbps, max supports 4Mbps.		
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	al-Stream Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC port	
	Input			
	Network Video	Max 2-channel IPC connections (16	SM)	
	Input			
	Video Output	1-channel VGA output,		
		1-channel HDMI output (of the same video source),		
		HDMI/ VGA video output at the same	ie time.	
	Loop Output	N/A		

	Parameters	HCVR7104H-S2	HCVR7108H-S2	
	Matrix Output	N/A	L	
Audio Port	Audio Input	1-channel RCA port.		
	Audio Output	1-channel RCA port.		
	Bidirectional	Reuse the audio input/output port.		
	Talk Input			
Record	Record Mode	Schedule record/manual record/ME) record/Alarm record	
	Record	Max 4-channel playback	Max 8-channel playback	
	Playback			
	Backup Mode	HDD, burner, USB device, network	backup	
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does not support eSA	ATA port	
	One HDD Space	4T		
Communication	Network	1 RJ45 port, 100Mbps Ethernet por	t	
Port	Communication	RS485 port		
	USB	2 USB ports		
Others	Power	DC12V		
	Power	≤15W (With power adapter, no HDD)		
-	Consumption			
	Working	-10℃−+55℃		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimensions	Mini 1U case, 325mm (W) x245r	mm (D) ×45mm (H)	
	Weight	1.25KG(No HDD)		
	Installation	Desk		
	Mode			
1.3.24 HCVR71	0XHE-S2 Series			
	Parameters	HCVR7104HE-S2	HCVR7108HE-S2	
System	Main Processor	Industrial embedded micro controlle	er	
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	1080P/720P/960H/D1/HD1/2CIF/C	IF/QCIF	
	Resolution			
	Video Frame	HDCVI: 1~25f/s (PAL); 1~30f/s		
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s (NISC)	
	Video Bit Rate	2048Kbps-6144Kbps,		
		For 1080P: default setup is 4Mbps,		
		For 720P: default setup is 2Mbps,	max supports 4MDpS.	
	Bit Stream Type	Video stream/composite stream		

	Parameters	HCVR7104HE-S2	HCVR7108HE-S2		
	Dual-Stream	Support	1		
Audio	Encode	G.711A/G.711U/PCM			
Parameters	Standard				
	Audio Sampling	8KHz, 16Bit			
	Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-channel, BNC port	8-channel, BNC port		
	Input				
	Network Video	Max 2-channel IPC connection (16	M)		
	Input				
	Video Output	1-channel VGA output,			
		1-channel HDMI output (of the sam	e video source),		
		HDMI/ VGA video output at the same time.			
	Loop Output	N/A			
	Matrix Output	N/A			
Audio Port	Audio Input	4-channel RCA port.			
	Audio Output	1-channel RCA port.			
	Bidirectional	Reuse the audio input/output port.			
	Talk Input				
Record	Record Mode	Schedule record/manual record/MD record/Alarm record			
	Record	Max 4-channel playback	Max 8-channel playback		
	Playback				
	Backup Mode	HDD, burner, USB device, network backup			
Alarm	Alarm Input	8-channel input	16-channel input		
	Alarm Output	3-channel output			
HDD	HDD Port	1 SATA port, does not support eSA	ATA port		
	One HDD Space	4T			
Communication	Network	1 RJ45 port, 100Mbps Ethernet por	t		
Port	Communication	RS485 port			
	USB	2 USB ports			
Others	Power	DC12V			
	Power	≤15W(With power adapter, no HD	D)		
	Consumption				
	Working	-10℃—+55℃			
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions	Mini 1U case, 325mm (W) x245r	mm (D) x45mm (H)		
	Weight	1.25KG(No HDD)			
	Installation	Desk			
	Mode				

1.3.25 HCVR41XXHE-S3 Series

	Parameters	HCVR4104HE-S3	HCVR4108HE-S3	HCVR4116HE-S3
System	Main Processor	Industrial embedded m	nicro controller	
	OS	Embedded LINUX		
Video Parameters	Video Encode Standard	H.264		
	Encode Resolution Video Frame	1080N/720P/960H/ D1/HD1/2CIF/CIF PAL:1~25f/s; NTSC:	1080N@12f/720P@15f. /CIF 1~30f/s	/960H/D1/HD1/2CIF
Rate Video Bit Rate 32Kbps-4096Kbps, For 720P: default setup is 1.5Mbps, max supports For 1080P: default setup is 1.5Mbps, max supports				
	Bit Stream Type Dual-Stream	Video stream/composit	le Sliedin	
Audio Parameters	Encode Standard	Support G.711A/G.711U/PCM		
	Audio Sampling Rate	8KHz, 16Bit		
	Audio Bit Rate	64Kbps	1	1
Video Port	Analog Video Input	4-ch BNC port (HDCVI HD video/general standard definition video self-adaptive)	8-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)	port(HDCVI HD
	Network Video Input	 Max add 1 IP channel Connection. Analog /digital channel switch. Max 5 IP channel connections Connection bandwidth:4Mbp s-20Mbps 	 Max add 2 IP channel connections Analog /digital channel switch. Max 10 IP channel connections Connection bandwidth:8Mbp s-40Mbps 	channel connections • Analog /digital
	Video Output	1-channel VGA output, 1-channel HDMI output (of the same video source), HDMI/ VGA video output at the same time.		

	Parameters	HCVR4104HE-S3	HCVR4108HE-S3	HCVR4116HE-S3	
			NCVN4100NE-33	NCVN4110NE-33	
	Loop Output	N/A			
	Matrix Output	N/A			
Audio Port	Audio Input	4-channel RCA port.	8-channel RCA port.	16-channel RCA	
				port.	
	Coaxial Audio Input	4-ch	8-ch-	16-ch	
	Audio Output	1-channel RCA port.			
	Bidirectional Talk Input	Support (Reuse the a	udio port of the 1st cha	nnel)	
Record	Record Mode	Schedule record/manu	al record/MD record/Ala	arm record	
	Playback Mode	Instant playback, normal playback, event playback, mark playback, smart playback			
	Record	Max 4-channel	Max 8-channe	el Max 16-channel	
	Playback	playback	playback	playback	
	Backup Mode	HDD, burner, USB device, network backup			
Alarm	Alarm Input	8-channel input	8-channel input	16-channel input	
	Alarm Output	3-channel output			
HDD	HDD Port	1 SATA port, does no	t support eSATA port		
	One HDD Space	6T			
Communication	Network	1 RJ45 port, 100Mbps	Ethernet port		
Port	Communication	RS485 port			
	USB	2 USB2.0 ports(One at the front panel and one at the rear panel)			
Others	Power	DC12V			
	Power Consumption	≤7W	≪8W	≤10W	
	Working Temperature	-10°C-+55°C	·	•	
	Working Humidity	10%~90%			
	Dimensions	Mini 1U case, 325mm	n (W) ×245mm (D) ×	45mm (H)	
	Weight	≤1.1KG	≤1.25KG	≤1.45KG	
	Installation	Desk	1		
	Mode				

1.3.26 HCVR51XXHE-S3 Series

	Parameters	HCVR5104HE-S3	HCVR5108HE-S3	HCVR5116HE-S3
System	Main Processor	in Processor Industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	1080P@12f/720P@1	5f/960H/D1/HD1/2CIF/0	CIF

	Parameters	HCVR5104HE-S3	HCVR5108HE-S3	HCVR5116HE-S3	
	Resolution				
	Video Frame Rate	PAL:1~25f/s; NTSC:	1~30f/s		
	Video Bit Rate	32Kbps-6144Kbps,			
			o is 2Mbps,max suppor up is 2Mbps,max suppo	•	
	Bit Stream Type	Video stream/composit	Video stream/composite stream		
	Dual-Stream	Support			
Audio Parameters	Encode Standard	G.711A/G.711U/PCM			
	Audio Sampling Rate	8KHz,16Bit			
	Audio Bit Rate	64Kbps			
Video Port	Analog Video Input	4-ch BNC port (HDCVI HD video/general standard definition video self-adaptive)	8-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)	16-chBNCport(HDCVIHDvideo/generalstandard definitionvideoself-adaptive)	
	Network Video Input	 Max add 2 IP channel Connection. Analog /digital channel switch. Max 6 IP channel connections Connection bandwidth:8Mbp s-24Mbps 	 Max add 4 IP channel connections Analog /digital channel switch. Max 12IP channel connections Connection bandwidth:16Mb ps-48Mbps 	 Max add 8 IP channel connections Analog /digital channel switch. Max 24 IP channel connections Connection bandwidth:32 Mbps-96Mbp s 	
	Video Output	utput 1-channel VGA output, 1-channel HDMI output (of the same video source), HDMI/ VGA video output at the same time.		ce),	
	Loop Output	N/A			
	Matrix Output	N/A	1	1	
Audio Port	Audio Input	4-channel RCA port.	8-channel RCA port.	16-channel RCA port.	
1 1					
	Coaxial Audio Input	4-ch	8-ch-	16-ch	

	Parameters	HCVR5104HE-S3	HCVR5108HE-S3	HCVR5116HE-S3	
	Bidirectional	Support (Reuse the a	udio port of the 1st chan	nel)	
	Talk Input				
Record	Record Mode	Schedule record/manu	al record/MD record/Ala	rm record	
	Playback Mode	Instant playback, norm	al playback, event playl	back, mark playback,	
		smart playback		_	
	Record	Max 4-channel	Max 8-channel	Max 16-channel	
	Playback	playback	playback	playback	
	Backup Mode	HDD, burner, USB device, network backup			
Alarm	Alarm Input	8-channel input	8-channel input	16-channel input	
	Alarm Output	3-channel output			
HDD	HDD Port	1 SATA port, does not support eSATA port			
	One HDD Space	6T			
Communication	Network	1 RJ45 port, 100Mbps	Ethernet port		
Port	Communication	RS485 port			
	USB	2 USB2.0 ports(One at	the front panel and one	at the rear panel)	
Others	Power	DC12V			
	Power	≤7W	≪8W	≤10W	
	Consumption	<td></td> <td><10W</td>		<10W	
	Working	-10°C-+55°C			
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions	Mini 1U case, 325mm	(W) ×245mm (D) ×4	45mm(H)	
	Weight	≤1.1KG	≤1.25KG	≤1.45KG	
	Installation	Desk			
	Mode				

1.3.27 HCVR71XXHE-S3 Series

	Parameters	HCVR7104HE-S3	HCVR7108HE-S3	HCVR7116HE-S3	
System	Main Processor	Industrial embedded micro controller			
	OS	Embedded LINUX			
Video	Video Encode	H.264			
Parameters	Standard				
	Encode	1080P/720P/960H/D1/HD1/2CIF/CIF			
	Resolution				
	Video Frame	PAL:1~25f/s; NTSC:	1~30f/s		
	Rate				
	Video Bit Rate	32Kbps-6144Kbps,			
		For 720P: default setup is 2Mbps, max supports 4Mbps.			
		For 1080P: default setup is 4Mbps, max supports 6Mbps.			
	Bit Stream Type	Video stream/compos	ite stream		

	Parameters	HCVR7104HE-S3	HCVR7108HE-S3	HCVR7116HE-S3
	Dual-Stream	Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz,16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video Input	4-ch BNC port (HDCVI HD video/general standard definition video self-adaptive)	8-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)	port(HDCVI HD
	Network Video Input	 Max add 2 IP channel Connection. Analog /digital channel switch. Max 6 IP channel connections Connection bandwidth:8Mbp s-24Mbps 	 Max add 4 IP channel connections Analog /digital channel switch. Max 12IP channel connections Connection bandwidth:16Mb ps-48Mbps 	channel connections • Analog /digital
	Video Output	1-channel VGA output, 1-channel HDMI output (of the same video source), HDMI/ VGA video output at the same time.		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	4-channel RCA port.	8-channel RCA port.	16-channel RCA port.
	Coaxial Audio Input	4-ch	8-ch-	16-ch
	Audio Output	1-channel RCA port.		
	Bidirectional Talk Input	Support (Reuse the audio port of the 1st channel)		
Record	Record Mode	Schedule record/manu	al record/MD record/Ala	rm record
	Playback Mode	Instant playback, normal playback, event playback, mark playback		
	-	smart playback		
	Record	smart playback Max 4-channel	Max 8-channel	Max 16-channel

	Parameters	HCVR7104HE-S3	HCVR7108HE-S3	HCVR7116HE-S3
	Backup Mode	HDD, burner, USB dev	ice, network backup	
Alarm	Alarm Input	8-channel input	8-channel input	16-channel input
	Alarm Output	3-channel output	· ·	· ·
HDD	HDD Port	1 SATA port, does not	support eSATA port	
	One HDD Space	6T		
Communication	Network	1 RJ45 port, 100Mbps Ethernet port		
Port	Communication	RS485 port		
	USB	2 USB2.0 ports(One	1 USB2.0 port at the	1 USB2.0 port at
		at the front panel and	front panel and one	the front panel
		one at the rear panel)	USB3.0 port at the	and one USB3.0
			rear panel	port at the rear
				panel
Others	Power	DC12V		
	Power Consumption	≪8W	≤10W	≤15W
	Working	-10°C-+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimensions	Mini 1U case, 325mm	(W) x245mm (D) x4	45mm(H)
	Weight	≤1.1KG	≤1.25KG	≤1.45KG
	Installation	Desk		
	Mode			

1.3.28 HCVR71XXH-S3 Series

	Parameters	HCVR7104HS3	HCVR7108H-S3	HCVR7116H-S3	
System	Main Processor	Industrial embedded r	nicro controller	•	
	OS	Embedded LINUX			
Video	Video Encode	H.264	H.264		
Parameters	Standard				
	Encode	1080P/720P/960H/D1	/HD1/2CIF/CIF		
	Resolution				
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s			
	Rate				
	Video Bit Rate	32Kbps-6144Kbps,			
		For 720P: default setu	ıp is 2Mbps,max supp	orts 4Mbps.	
		For 1080P: default set	tup is 4Mbps,max sup	ports 6Mbps.	
	Bit Stream Type	Video stream/compos	ite stream		
	Dual-Stream	Support			
Audio	Encode	G.711A/G.711U/PCM			
Parameters	Standard				

	Parameters	HCVR7104HS3	HCVR7108H-S3	HCVR7116H-S3
	Audio Sampling	8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video Input	4-ch BNC port (HDCVI HD video/general standard definition video self-adaptive)	8-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)	16-chBNCport(HDCVIHDvideo/generalstandard definitionvideoself-adaptive)
	Network Video Input	 Max add 2 IP channel Connection. Analog /digital channel switch. Max 6 IP channel connections Connection bandwidth:8Mbp s-24Mbps 	 Max add 4 IP channel connections Analog /digital channel switch. Max 12IP channel connections Connection bandwidth:16Mb ps-48Mbps 	Max add 8 IP channel connections Analog /digital channel switch. Max 24 IP channel connections Connection bandwidth:32 Mbps-96Mbp s
	Video Output	1-channel VGA output, 1-channel HDMI outpu HDMI/ VGA video outp	t (of the same video sour	rce),
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	4-channel RCA port.	8-channel RCA port.	16-channel RCA port.
	Coaxial Audio Input	4-ch	8-ch-	16-ch
	Audio Output	1-channel RCA port.		
	Bidirectional Talk Input	Support (Reuse the a	udio port of the 1st chanr	nel)
Record	Record Mode	Schedule record/manu	al record/MD record/Alar	m record
	Playback Mode	Instant playback, norm smart playback	al playback, event playb	ack, mark playback,
	Record Playback	Max 4-channel playback	Max 8-channel playback	Max 16-channel playback
	Backup Mode	HDD, burner, USB dev	ice, network backup	
Alarm	Alarm Input	8-channel input	8-channel input	16-channel input
	Alarm Output	3-channel output		

	Parameters	HCVR7104HS3	HCVR7108H-S3	HCVR7116H-S3	
HDD	HDD Port	1 SATA port, does not	support eSATA port		
	One HDD Space	6T			
Communication	Network	1 RJ45 port, 100Mbps	Ethernet port		
Port	Communication	RS485 port			
	USB	2 USB2.0 ports(One 1 USB2.0 port at the 1 USB2.0 p			
		at the front panel and	front panel and one	e the front panel	
		one at the rear panel)	USB3.0 port at the	and one USB3.0	
			rear panel	port at the rear	
				panel	
Others	Power	DC12V			
	Power	≪8W	≤10W	≤15W	
	Consumption	<000		< 1500	
	Working	-10°C-+55°C			
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions	Mini 1U case, 325mm	(W) ×245mm (D) ×4	45mm(H)	
	Weight	≤1.1KG	≤1.25KG	≤1.45KG	
	Installation	Desk			
	Mode				

1.3.29 HCVR41XXHS-S2 Series

	Parameter	rs	HCVR4104HS-S2	HCVR4108HS-S2	HCVR4116HS-S2
System	Main Proc	essor	Industrial embedded i	nicro controller	
	OS		Embedded LINUX		
Video	Video E	Incode	H.264		
Parameters	Standard				
	Encode		720P/960H/D1/HD1/	720P(1-15f/s)/960	H/D1/HD1/
	Resolutior	า	2CIF/CIF/QCIF	2CIF/CIF/QCIF	
	Video	Frame	HDCVI : 1 \sim 25f	/s HDCVI : 1 \sim 15	if/s (The 1 st channel
	Rate		(PAL); 1~30f	/s supports 25/30fps/	()
			(NTSC)	CVBS: 1~25f/s (F	PAL); 1~30f/s (NTSC)
			CVBS: 1~25f/s (PAL));	
			1~30f/s(NTSC)		
	Video Bit I	Rate	2048Kbps-4096Kbps	, 1024Kbps-4096Kb	ops,
			For 720P: default setu	p For 720P: default	setup is 1Mbps, max
			is 2Mbps , ma	ax supports 4Mbps.	
			supports 4Mbps.	For 960H: default	setup is 1Mbps, max
			For 960H: defau	ult supports 3Mbps.	
			setup is 1Mbps, ma	ax	
			supports 3Mbps.		
	Bit Stream	Туре	Video stream/composite stream		

	Parameters	HCVR4104HS-S2	HCVR4108	HS-S2 HC	VR4116HS-S2
	Dual-Stream	Support		-	
Audio	Encode	G.711A/G.711U/PCM			
Parameters	Standard				
	Audio Sampling	8KHz, 16Bit			
	Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-channel, BNC port	8-chann	el, BNC port	16-channel,
	Input				BNC port
	Network Video Input	Max 2-channel IPC co	onnections (8	3M)	
	Video Output	1-channel VGA output	.,		
		1-channel HDMI outpu	ut (of the sar	ne video sourc	ce),
		HDMI/ VGA video out	out at the sa	me time.	
	Loop Output	N/A			
	Matrix Output	N/A			
Audio Port	Audio Input	1-channel RCA port.			
	Audio Output	1-channel RCA port.			
	Bidirectional	Reuse the audio input/output port.			
	Talk Input				
Record	Record Mode	Schedule record/manual record/MD record/Alarm record			
	Record	Max 4-channe	el Max	8-channel	Max 16-channel
	Playback	playback	playbacl	<	playback
	Backup Mode	HDD, burner, USB de	vice, networ	k backup	
Alarm	Alarm Input	N/A			
	Alarm Output	N/A			
HDD	HDD Port	1 SATA port, does no	t support eS	SATA port	
	One HDD Space	4T			
Communication	Network	1 RJ45 port, 100Mbps	Ethernet po	ort	
Port	Communication	RS485 port			
	USB	2 USB ports			
Others	Power	DC12V			
	Power	≤15W (With power ad	dapter, no H	DD)	
	Consumption				
	Working	-10℃−+55℃			
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions	Compact 1U case, 26	0mm (W) :	×220mm (D)	x44mm (H)
	Weight	1.25KG(No HDD)			
	Installation	Desk			
	Mode				

1.3.30 HCVR21XXHS-S2 Series

	Parameters	HCVR2108HS-S2	HCVR2116HS-S2	
System	Main Processor	Industrial embedded micro controlle	er	
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	720P(1-15f/s)/960H/D1/HD1/2CIF/CIF/QCIF		
	Resolution			
	Video Frame	HDCVI: 1~12f/s		
	Rate	CVBS: 1~20f/s (PAL); 1~20f/s (NTSC)	
	Video Bit Rate	1024Kbps-4096Kbps,		
		For 720P: default setup is 1Mbps,		
		For 960H: default setup is 1Mbps,	max supports 3Mbps.	
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	8-channel, BNC port	16-channel, BNC port	
	Input			
	Video Output	1-channel VGA output,		
		1-channel HDMI output (of the same video source),		
		HDMI/ VGA video output at the same	ne time.	
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	1-channel RCA port.		
	Audio Output	1-channel RCA port.		
	Bidirectional	Reuse the audio input/output port.		
	Talk Input			
Record	Record Mode	Schedule record/manual record/MD	record/Alarm record	
	Record	960H: Max 4-channel playback		
	Playback	720P: Max 1-channel playback		
	Backup Mode	HDD, burner, USB device, network	backup	
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does not support eSA	ATA port	
	One HDD Space	4T		
Communication	Network	1 RJ45 port, 100Mbps Ethernet por	t	
Port	Communication	RS485 port		
	USB	2 USB ports		

	Parameters	HCVR2108HS-S2	HCVR2116HS-S2	
Others	Power	DC12V ≤15W (With power adapter, no HDD) -10°C−+55°C		
	Power			
	Consumption			
	Working			
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimensions	Compact 1U case, 260mm (W) x2	220mm (D) x44mm (H)	
	Weight 1.25KG (No HDD)			
	Installation	Desk		
	Mode			

1.3.31 HCVR21XXHS-S3 Series

	Parameters	2104HS-S3	2108HS-S3	2116HS-S3	
System	Main Processor	Industrial embedded m	icro controller		
	OS	Embedded LINUX			
Video	Video Encode	H.264			
Parameters	Standard				
	Encode	1080N@12f/720P@15	f/960H/D1/HD1/2CIF/CI	F	
	Resolution				
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s			
	Rate				
	Video Bit Rate	32Kbps-4096Kbps,			
			o is 1.5Mbps, max supp		
		For 1080N: default setup is 1.5Mbps, max supports 4Mbps.			
	Bit Stream Type	Video stream/composite stream			
	Dual-Stream	Support			
Audio	Encode	G.711A/G.711U/PCM			
Parameters	Standard				
	Audio Sampling	8KHz,16Bit			
	Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-ch BNC port(HDCVI	8-ch BNC port(HDCVI		
	Input	HD video/general	HD video/general		
		standard definition	standard definition	June of general	
		video self-adaptive)	video self-adaptive)	standard definition	
				video	
				self-adaptive)	
	Network Video	5 5			
	Input	Connection bandwidth:			
	Video Output	1-channel VGA output,			
		1-channel HDMI outpu	t (of the same video sou	irce),	

	Parameters	2104HS-S3	2108HS-S3	2116HS-S3	
		HDMI/ VGA video output at the same time.			
	Loop Output				
	Matrix Output	N/A			
Audio Port	Audio Input	1-channel RCA port.			
	Coaxial Audio	4-ch	8-ch	16-ch	
	Input				
	Audio Output	1-channel RCA port.			
	Bidirectional	Reuse the audio input/output port of the 1st channel.			
	Talk Input				
Record	Record Mode	Schedule record/manual record/MD record/Alarm record			
	Playback Mode	Instant playback, normal playback, event playback, mark playback,			
		smart playback			
	Backup Mode	HDD, burner, USB device, network backup			
Alarm	Alarm Input	N/A			
	Alarm Output	N/A			
HDD	HDD Port	1 SATA port, does not support eSATA port			
	One HDD Space	6T			
Communication	Network	1 RJ45 port, 100Mbps Ethernet port			
Port	Communication	RS485 port			
	USB	2 USB2.0 ports(One at the front panel and one at the rear panel)			
Others	Power	DC12V			
	Power	≤10W			
	Consumption				
	(No HDD)				
	Working	-10°C−+55°C			
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions	Compact 1U case, 260mm (W) x220mm (D) x44mm (H)			
	Weight (No	≤1.25KG	≤1.35KG	≤1.45KG	
	HDD)				
	Installation	Desk			
	Mode				

1.3.32 HCVR41XXHS-S3 Series

	Parameters	HCVR4104HS-S3	HCVR4108HS-S3	HCVR4116HS-S3
System	Main Processor	Industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	1080N/720P/960H/D1	1080N@12f/720P@	15f/960H/D1/HD1/2CI

	Parameters	HCVR4104HS-S3	HCVR4108HS-S3 F	ICVR4116HS-S3	
	Resolution	/HD1/2CIF/CIF/	F/CIF/		
	Video Frame Rate	PAL:1~25f/s; NTSC:	1~30f/s		
	Video Bit Rate		720P: default setup is 1.5Mbps, max supports 4Mbps.		
		For 1080P: default setup is 1.5Mbps, max supports 4Mbps.			
	Bit Stream Type		eo stream/composite stream		
A	Dual-Stream	Support			
Audio Parameters	Encode Standard	G.711A/G.711U/PCM			
	Audio Sampling Rate	8KHz,16Bit			
	Audio Bit Rate	64Kbps			
Video Port	Analog Video Input	4-ch BNC port (HDCVI HD video/general standard definition video self-adaptive)	8-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)	16-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)	
Audio Port	Network Video Input	 Max add 1 IP channel connection Analog /digital channel switch. Max 5 IP channel connections Connection bandwidth:4Mbp s-20Mbps 	 Max add 1 IP channel connection Analog /digital channel switch. Max 9 IP channel connections Connection bandwidth:8Mbp s-40Mbps 	 Max add 2 IP channel connections Analog /digital channel switch. Max 18 IP channel connections Connection bandwidth:8 Mbps-56Mbp s 	
	Video Output	1-channel VGA output, 1-channel HDMI output (of the same video source), HDMI/ VGA video output at the same time.			
	Loop Output	N/A			
	Matrix Output	N/A			
	Audio Input Coaxial Audio	1-channel RCA port. 4-ch	8-ch-	16-ch	
	Input				
	Audio Output	1-channel RCA port.			
	Bidirectional	Reuse the audio input/output port.			

	Parameters	HCVR4104HS-S3	HCVR4108HS-S3	HCVR4116HS-S3		
	Talk Input		L			
Record	Record Mode	Schedule record/manu	al record/MD record/Ala	arm record		
	Playback Mode	Instant playback, norm	nal playback, event play	back, mark playback,		
		smart playback				
	Record	Max 4-channel	Max 8-channe	I Max 16-channel		
	Playback	playback	playback	playback		
	Backup Mode	HDD, burner, USB device, network backup				
Alarm	Alarm Input	N/A				
	Alarm Output	N/A				
HDD	HDD Port	1 SATA port, does not support eSATA port				
	One HDD Space	6T				
Communication	Network	1 RJ45 port, 100Mbps Ethernet port				
Port	Communication	RS485 port				
	USB	2 USB2.0 ports(One at the front panel and one at the rear panel)				
Others	Power	DC12V				
	Power					
	Consumption	≪7W	≪8W	≤10W		
	(No HDD)					
	Working	-10°C-+55°C				
	Temperature					
	Working	10%~90%				
	Humidity					
	Dimensions	Compact 1U case, 260	0mm (W) ×220mm (D)×44mm(H)		
	Weight (No	≪0.85KG	≪0.95KG	≤1.05KG		
	HDD)					
	Installation	Desk				
	Mode					

1.3.33 HCVR51XXHS-S3 Series

	Parameters	HCVR5104HS-S3	HCVR5108HS-S3	HCVR5116HS-S3			
System	Main Processor	Industrial embedded r	Industrial embedded micro controller				
	OS	Embedded LINUX	Embedded LINUX				
Video	Video Encode	e H.264	H.264				
Parameters	Standard						
	Encode	1080P@15f/1080N/720P/960H/D1/HD1/2CIF/CIF/1080P@15f/720					
	Resolution	P@15f/960H/D1/HD1	/2CIF/CIF				
	Video Frame	PAL:1~25f/s; NTSC:	1~30f/s				
	Rate						
	Video Bit Rate	32Kbps-6144Kbps,	32Kbps-6144Kbps,				
		For 720P: default setup is 2Mbps, max supports 4Mbps.					
		For 1080P: default se	tup is 2Mbps,max sup	ports 6Mbps.			

	Parameters	HCVR5104HS-S3	HCVR5108HS-S3	HCVR5116HS-S3		
	Bit Stream Type	Video stream/composit	e stream			
	Dual-Stream	Support				
Audio	Encode	G.711A/G.711U/PCM				
Parameters	Standard					
	Audio Sampling	8KHz, 16Bit				
	Rate	,				
	Audio Bit Rate	64Kbps				
Video Port	Analog Video	4-ch BNC port 8-ch BNC port(HDCVI 16-ch BI				
	Input	(HDCVI HD	HD video/general	port(HDCVI HD		
		video/general	standard definition	video/general		
		standard definition	video self-adaptive)	standard definition		
		video self-adaptive)		video		
				self-adaptive)		
	Network Video	• Max add 2 IP	Max add 4 IP	Max add 8 IP		
	Input	channel	channel	channel		
		connections	connection	connections		
		 Analog 	 Analog 	 Analog 		
		/digital channel	/digital channel	/digital		
		switch. Max 6 IP	switch. Max 12 IP			
		channel 	channel	switch. Max		
		connections	connections	24 IP channel		
		Connection	Connection	connections		
		bandwidth:8Mbp s-24Mbps	bandwidth:16Mb ps-48Mbps	 Connection bandwidth:32 		
		5-241010p5	ps-401010ps	Mbps-96Mbp		
				S		
	Video Output	1-channel VGA output,		0		
			t (of the same video sou	rce).		
		HDMI/ VGA video outp		100/1		
	Loop Output	N/A				
	Matrix Output	N/A				
Audio Port	Audio Input	1-channel RCA port.				
	Coaxial Audio	4-ch	8-ch-	16-ch		
	Input					
	Audio Output	1-channel RCA port.		1		
	Bidirectional		output port of the 1 st cha	innel.		
	Talk Input	· ·	· ·			
Record	Record Mode	Schedule record/manu	al record/MD record/Ala	rm record		
	Playback Mode					
	Record	smart playback Max 4-channel Max 8-channel Max 16-chan				
	Playback	playback	playback	playback		
	1 laybaok	praybaok	playbaok	playbaok		

	Parameters	HCVR5104HS-S3	HCVR5108HS-S3	HCVR5116HS-S3			
				NCVN3110N3-33			
	Backup Mode	HDD, burner, USB dev	ice, network backup				
Alarm	Alarm Input	N/A					
	Alarm Output	N/A					
HDD	HDD Port	1 SATA port, does not support eSATA port					
	One HDD Space	6T	6T				
Communication	Network	1 RJ45 port, 100Mbps	1 RJ45 port, 100Mbps Ethernet port				
Port	Communication	RS485 port					
	USB	2 USB2.0 ports(One at the front panel and one at the rear panel)					
Others	Power	DC12V					
	Power						
	Consumption	≤7W	≪8W	≤10W			
	(No HDD)						
	Working	-10°C-+55°C	-				
	Temperature						
	Working	10%~90%					
	Humidity						
	Dimensions	Compact 1U case, 260	0mm (W) x220mm (D) x44mm (H)			
	Weight (No						
	HDD)	≪0.85KG	≪0.95KG	≤1.05KG			
	Installation	Desk					
	Mode						

1.3.34 HCVR71XXHS-S3 Series

	Parameters	HCVR7104HS-S3			
System	Main Processor	Industrial embedded micro controller			
	OS	Embedded LINUX			
Video	Video Encode	H.264			
Parameters	Standard				
	Encode	1080P/720P/960H/D1/HD1/2CIF/CIF			
	Resolution				
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s			
	Rate				
	Video Bit Rate	32Kbps-6144Kbps,			
		For 720P: default setup is 2Mbps, max supports 4Mbps.			
		For 1080P: default setup is 4Mbps, max supports 6Mbps.			
	Bit Stream Type	Video stream/composite stream			
	Dual-Stream	Support			
Audio	Encode	G.711A/G.711U/PCM			
Parameters	Standard				
	Audio Sampling	8KHz, 16Bit			
	Rate				

Parameters	HCVR7104HS-S3		
Audio Bit Rate	64Kbps		
Analog Video Input	4-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)		
Network Video Input	 Max add 2 IP channel connections Analog/digital channel switch. Max 6 IP channel connections Connection bandwidth:8Mbps-24Mbps 		
Video Output	1-channel VGA output, 1-channel HDMI output (of the same video source), HDMI/ VGA video output at the same time.		
Loop Output	N/A		
Matrix Output	N/A		
Audio Input	1-channel RCA port.		
Coaxial Audio	4-ch		
•			
	1-channel RCA port.		
Bidirectional Talk Input	Reuse the audio input/output port of the 1 st channel.		
Record Mode	Schedule record/manual record/MD record/Alarm record		
Playback Mode	Instant playback, normal playback, event playback, mark playback smart playback		
Backup Mode	HDD, burner, USB device, network backup		
Alarm Input	N/A		
Alarm Output	N/A		
HDD Port	1 SATA port, does not support eSATA port		
One HDD Space	6T		
Network	1 RJ45 port, 100Mbps Ethernet port		
Communication	RS485 port		
USB	2 USB2.0 ports(One at the front panel and one at the rear panel)		
Power	DC12V		
Power	≤8W		
Consumption			
(No HDD)			
Working	-10℃−+55℃		
Temperature			
Working	10%~90%		
Humidity			
Dimensions	Compact 1U case, 260mm (W) x220mm (D) x44mm (H)		
Weight (No HDD)	0.85KG		
Installation	Desk		
	Audio Bit FateAnalogVideoInputVideoNetworkVideoInputVideoVideo OutputVideoVideo OutputAudioMatrix OutputAudioAudio InputAudioAudio OutputAudioAudio OutputAudioBidirectionalAudioBidirectionalAudioBidirectionalAudioBidirectionalAudioBidirectionalAudioAudio OutputAudioAudio OutputAudioAudio OutputAudioAlarm OutputAlarmAlarm OutputAlarmAlarm OutputAlarmOne HDD SpaceAlarmNetworkSpaceConsumption(No HDD)VorkingInputHumidityVorkingWorkingKongWeightNoMontputKongMutidityNoMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorkingKongMorking		

1.3.35 HCVR52XXA-V2 Series

1.3.35 HCVR52	Parameters	HCVR5204A-V2	HCVR5208A-V2	HCVR5216A-V2		
System	Main Processor	High-performance i	ndustrial embedded	micro controller		
-	OS	Embedded LINUX				
Video	Video Encode Standard	H.264				
	Encode Resolution	720P/960H/D1/HD1	/2CIF/CIF/QCIF (for	sub-stream only)		
	Video Frame Rate	PAL:1~25f/s; NTS	,			
	Video Bit Rate	1536Kbps-4096Kbp				
		For 720P:default value is 2Mbps, max value is 4Mbps				
	Bit Stream Type	Video stream/comp	•			
	Dual-Stream	Support				
Audio	Encode Standard	G.711A, G.711U, P	СМ			
	Audio Sampling Rate	8KHz,16Bit	-			
	Audio Bit Rate	64Kbps				
Video Port	Analog Video Input	4-ch, BNC port 8-ch, BNC port 16-ch, BNC port				
	Network Video Input					
	Video Output	1-ch VGA output,		•		
		1-ch HDMI output,				
		HDMI/ VGA video o	utput at the same tim	ne (VGA/HDMI of the		
		same video source)				
	Loop Output	N/A				
	Matrix Output	N/A				
Audio Port	Audio Input	4-ch, RCA port, au	dio via coaxial cable			
	Audio Output	1-ch, RCA port				
	Bidirectional Talk Input	Support (Reuse the	e audio port)			
Record	Record Mode	Auto record, manu	al record, motion o	letect record, alarm		
		record				
	Record Playback	Max 4-ch playback	Max 8-ch	Max 16-ch		
			playback	playback		
	Backup Mode	HDD, burner, flash	disk, network backup).		
Alarm	Alarm Input	4-ch alarm input	8-ch alarm input	16-ch alarm input		
	Alarm Output	3-ch alarm output	·	•		
HDD	HDD Port	2 SATA ports. Does	not support eSATA	port		
	Space/HDD	4T				
Communication	Network	1 RJ45 port, 1000M	bps Ethernet port			
Port	Communication	RS485 port				
	USB	2 USB ports				
Other	Power	DC12V				
		≤30W (exclude HDD)				

Model	Parameters	HCVR5204A-V2	HCVR5208A-V2	HCVR5216A-V2			
	Working Temperature	-10°C-+55°C					
	Working Humidity	10%~90%					
	Dimension	1U case, 375mm (W) x280mm (D) x50mm (H)					
	Weight	1.5kg~2.5kg (exclude HDD)					
	Installation Mode	Desk installation					

1.3.36 HCVR72XXA-V2 Series

Model	Parameters	HCVR7204A-V2	HCVR7208A-V2	
System	Main Processor	High-performance industrial emb	edded micro controller	
	OS	Embedded LINUX		
Video	Video Encode	H.264		
	Standard			
	Encode Resolution	1080P /720P/960H/D1/HD1/2CIF	F/CIF/QCIF (for sub-stream	
		only)		
	Video Frame Rate	PAL:1~25f/s; NTSC: 1~30f/s		
	Video Bit Rate	2048Kbps-6144Kbps Kbps-4096	Kbps,	
		For 1080P:default value is 4Mbp	s, max value is 6Mbps	
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	Support		
Audio	Encode Standard	G.711A, G.711U, PCM		
	Audio Sampling Rate	ate 8KHz, 16Bit		
	Audio Bit Rate	64Kbps		
Video Port	Analog Video Input	4-ch, BNC port	8-ch, BNC port	
	Network Video Input	Switch 2 analog channels to the	IP channels (16Mbps)	
	Video Output	1-ch VGA output,		
		1-ch HDMI output,		
		HDMI/ VGA video output at the sa	ame time (VGA/HDMI of the	
		same video source)		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	4-ch, RCA port, audio via coaxia	al cable	
	Audio Output	1-ch, RCA port		
	Bidirectional Talk	Support (Reuse the audio port)		
	Input			
Record	Record Mode	Auto record, manual record, m	otion detect record, alarm	
		record		
	Record Playback	Max 4-ch playback	Max 16-ch playback	
	Backup Mode	HDD, burner, flash disk, network		
Alarm	Alarm Input	4-ch alarm input	16-ch alarm input	
	Alarm Output	3-ch alarm output		
HDD	HDD Port	2 SATA ports. Does not support	eSATA port.	

Model	Parameters	HCVR7204A-V2	HCVR7208A-V2		
	Space/HDD	4T			
Communication	Network	1 RJ45 port, 1000Mbps Ethernet	port		
Port	Communication	RS485 port			
	USB	2 USB ports			
Other	Power	DC12V			
	Power Consumption	≤30W (exclude HDD)			
	Working Temperature	-10°℃−+55°℃			
	Working Humidity	10%~90%			
	Dimension	1U case, 375mm (W) x280mm (D) x50mm (H) 1.5kg~2.5kg (exclude HDD)			
	Weight				
	Installation Mode	Desk installation			

1.3.37 HCVR42XXA-S2/4216AN-S2 Series

Model	Parameters	HCVR4204A-	HCVR4208A-	HCVR4216A-	HCVR4216AN		
		S2	S2	S2	-S2		
System	Main Processor	High-performanc	e industrial embe	edded micro contr	oller		
	OS	Embedded LINU	X				
Video	Video Encode	H.264					
	Standard						
	Encode	720P(1-15fps)/960H/D1/HD1/2CIF/CIF/QCIF (for sub-stream only)					
	Resolution						
	Video Frame	HDCVI: $1 \sim 15$ (The 1 st channel supports 25/30 f/s)					
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s (NTSC)					
	Video Bit Rate	1024Kbps-4096Kbps,					
		For 720P:default value is 1Mbps, max value is 4Mbps					
		For 960H:defaul	t value is 1Mbps,	max value is 3N	lbps		
	Bit Stream	Video stream/co	mposite stream				
	Туре						
	Dual-Stream	Support					
Audio	Encode	G.711A, G.711U	, PCM				
	Standard						
	Audio	8KHz,16Bit					
	Sampling Rate						
	Audio Bit Rate	64Kbps					
Video Port	Analog Video	4-ch, BNC port	8-ch, BNC por	t 16-ch, BNC	16-ch, BNC		
	Input	port port					
	Network Video	Max 2 IPC connections (8Mbps)					
	Input						

Model	Parameters	HCVR4204A-	HCVR4208A-	HCVR4216A-	HCVR4216AN		
		S2	S2	S2	-S2		
	Video Output	1-ch VGA output	-				
		1-ch HDMI output,					
		HDMI/ VGA video output at the same time (VGA/HDMI of the same					
		video source)					
	Loop Output	N/A					
	Matrix Output	N/A			I		
Audio Port	Audio Input	4-ch, RCA port,			1-ch ,		
					RCA		
	Audio Output	1-ch, RCA port					
	Bidirectional	Support (Reuse the audio port)					
	Talk Input						
Record	Record Mode	Auto record, ma	nual record, motio	,			
	Record	Max 4-ch	Max 8-0	ch Max 16-ch p	layback		
	Playback	playback	playback				
	Backup Mode	HDD, burner, fla	sh disk, network l	backup.			
Alarm	Alarm Input	8-ch alarm input	8-ch alarm inp	ut 16-ch alarm	input N/A		
	Alarm Output	3-ch alarm outpu	ıt		N/A		
HDD	HDD Port	2 SATA ports. D	oes not support e	SATA port.			
	Space/HDD	4T					
Communication	Network	1 RJ45 port, 100	Mbps Ethernet p	ort			
Port	Communication	RS485 port					
	USB	2 USB ports					
Other	Power	DC12V/4A					
	Power	≤30W (No HDD)				
	Consumption						
	Working	-10℃-+55℃					
	Temperature						
	Working	10%~90%					
	Humidity						
	Dimension	1U case, 375m	m (W) x280mm	(D) x50mm (H	H)		
	Weight	1.5-2.5kg(no H	DD)				
	Installation	Desk installation					
	Mode						

1.3.38 HCVR4224/4232AN-S2 Series

Model	Parameters	HCVR4224AN-S2	HCVR4232AN-S2
System	Main Processor	High-performance industrial embedded micro controller	
	OS	Embedded LINUX	

Model	Parameters	HCVR4224AN-S2	HCVR4232AN-S2	
Video	Video Encode	H.264		
	Standard			
	Encode	720P(1-15fps)/960H/D1/HD1/2CIF/C	IF/QCIF (for sub-stream only)	
	Resolution			
	Video Frame	HDCVI: $1 \sim 15$ (The 1 st / 2 nd chan	nel supports 25/30f/s)	
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s (N	ITSC)	
	Video Bit Rate	1024Kbps \sim 4096Kbps,		
		For 720P realtime (The first two channels):default value is 2Mbps, max value is 4Mbps.		
		For 720P non-realtime: default val	ue is 1Mbps, max value is	
		2Mbps.		
	Bit Stream	Video stream/composite stream		
	Туре			
	Dual-Stream	Support		
Audio	Encode	G.711A, G.711U, PCM		
	Standard			
	Audio	8KHz,16Bit		
	Sampling Rate			
	Audio Bit Rate	64Kbps		
Video Port			32-ch, BNC port	
	Input			
	Network Video	Max 4 IPC connections (16Mbps)		
	Input			
	Video Output	1-ch VGA output,		
		1-ch HDMI output, HDMI/ VGA video output at the same	time (VCA/UDML of the same	
		video source)		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	1-ch, RCA port, Coaxibale audio	1-ch, RCA port. Coaxibale	
			audio	
	Audio Output	1-ch, RCA port		
	Bidirectional	Support (Reuse the audio port)		
	Talk Input			
Record	Record Mode	Auto record, manual record, motion of	detect record. alarm record	
	Record	Max 16-ch playback	······································	
	Playback			
	Backup Mode	HDD, burner, flash disk, network backup.		
Alarm	Alarm Input	N/A	1	
	Alarm Output	N/A		
HDD	HDD Port	2 SATA ports. Does not support eSA	.TA port.	
	Space/HDD	4T	l	
	opacentur			

Model	Parameters	HCVR4224AN-S2	HCVR4232AN-S2
Communication	Network	1 RJ45 port, 1000Mbps Ethernet port	
Port	Communication	1 RS485 port	
	USB	2 USB ports	
Other	Power	DC12V/5A	
	Power	≤30W (With adapter, no HDD)	
	Consumption		
	Working	-10℃−+55℃	
	Temperature		
	Working	10%~90%	
	Humidity		
	Dimension	1U case, 375mm (W) x280mm (D) x50mm (H)
	Weight	1.5-2.5kg (no HDD)	
	Installation	Desk installation	
	Mode		

1.3.39 HCVR52XXA-S2/HCVR5216AN-S2 Series

Model	Parameters	HCVR5204A-	HCVR5208A-	HCVR5216A-	HCVR5216AN
		S2	S2	S2	-S2
System	Main Processor	High-performanc	e industrial emb	edded micro conti	roller
	OS	Embedded LINUX			
Video	Video Encode	H.264			
	Standard				
	Encode	1080P(1-15fps)	/720P/960H/D1/ŀ	ID1/2CIF/CIF/QC	IF
	Resolution				
	Video Frame	HDCVI: 1~25f/s	; (PAL); 1~30f/	s (NTSC)	
	Rate	CVBS: 1~25f/s	(PAL); 1~30f/s	(NTSC)	
	Video Bit Rate	2048Kbps-4096	Kbps		
		For 1080P/720P:default value is 2Mbps, max value is 4Mbps			
		For 960H:defaul	t value is 1Mbps,	max value is 3M	1bps
	Bit Stream	Video stream/co	mposite stream		
	Туре				
	Dual-Stream	Support			
Audio	Encode	G.711A, G.711U	I, PCM		
	Standard				
	Audio	8KHz,16Bit			
	Sampling Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-ch, BNC port	8-ch, BNC po	ort 16-ch,	BNC 16-ch,
	Input	port BNC			
		port			
	Network Video	Max 2 IPC connections (8Mbps)			
	Input				

Model	Parameters	HCVR5204A- S2	HCVR5208A- S2	HCVF S2	R5216A-	HCVF -S2	R5216AN
	Video Output	1-ch VGA outpu	t,				
		1-ch HDMI outpu					
		HDMI/ VGA vide	o output at the s	ame tim	ie (VGA/H	DMI of	the same
		video source)					
	Loop Output	N/A					
	Matrix Output	N/A					
Audio Port	Audio Input	4-ch, RCA port	, audio via coaxia	al cable			
	Audio Output	1-ch, RCA port					
	Bidirectional	Support (Reuse	the audio port)				
	Talk Input						
Record	Record Mode	Auto record, ma	nual record, moti	on dete	ct record,	alarm r	ecord
	Record	Max 4-ch Max 8-ch Max 16-ch playback			ack		
	Playback	playback	playback				
	Backup Mode	HDD, burner, flash disk, network backup.					
Alarm	Alarm Input	8-ch alarm input 8-ch alarm input 16-ch alarn			alarm	N/A	
					input		
	Alarm Output	3-ch alarm outpu	ut				N/A
HDD	HDD Port	2 SATA ports. D	oes not support e	eSATA	port.		
	Space/HDD	4T					
Communication	Network	1 RJ45 port, 100	Mbps Ethernet p	ort			
Port	Communication	RS485 port					
	USB	2 USB ports					
Other	Power	DC12V/4A					DC12V/ 5A
	Power	≤30W (No HDD))				
	Consumption						
	Working	-10℃-+55℃					
	Temperature						
	Working	10%~90%					
	Humidity						
	Dimension	1U case, 375m	m (W) ×280mm	n (D) >	<50mm(I	H)	
	Weight	1.5-2.5kg (No H	IDD)				
	Installation	Desk installation					
	Mode						

1.3.40 HCVR720XA-S2 Series

Model	Parameters	HCVR7204A-S2	HCVR7208A-S2
System	Main Processor	High-performance industrial embedded micro controller	
	OS	Embedded LINUX	

Model	Parameters	HCVR7204A-S2	HCVR7208A-S2
Video	Video Encode	H.264	
	Standard		
	Encode	1080P /720P/960H/D1/HD1/2CIF/CI	F/QCIF
	Resolution		
	Video Frame	HDCVI: 1~25f/s (PAL); 1~30f/s (NTSC)
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s (N	NTSC)
	Video Bit Rate	2048Kbps-6144Kbps	
		For 1080P:default value is 4Mbps,	max value is 6Mbps
		For 720P:default value is 2Mbps, m	nax value is 4Mbps
	Bit Stream	N Video stream/composite stream	
	Туре		
	Dual-Stream	Support	
Audio	Encode	G.711A, G.711U, PCM	
	Standard		
	Audio	8KHz, 16Bit	
	Sampling Rate		
	Audio Bit Rate	64Kbps	
Video Port	Analog Video	4-ch, BNC port	8-ch, BNC port
	Input		
	Network Video Max 2 IPC connections 16Mbps)		
	Input		
	Video Output	1-ch VGA output,	
		1-ch HDMI output, HDMI/ VGA video output at the same	time (VGA/HDML of the same
		video source)	
	Loop Output	N/A	
	Matrix Output	N/A	
Audio Port	Audio Input	4-ch, RCA port, audio via coaxial ca	ahle
	Audio Output	1-ch, RCA port	
	Bidirectional	Support (Reuse the audio port)	
	Talk Input		
Record	Record Mode	Auto record, manual record, motion	detect record, alarm record
	Record	Max 4-ch playback	Max 8-ch playback
	Playback		, ,
	Backup Mode	HDD, burner, flash disk, network backup.	
Alarm	Alarm Input	8-ch alarm input	16-ch alarm input
	Alarm Output	3-ch alarm output	
HDD	HDD Port	2 SATA ports. Does not support eSA	ATA port.
	Space/HDD	4T	
Communication	Network	1 RJ45 port, 100Mbps Ethernet port	
Port	Communication	RS485 port	

Model	Parameters	HCVR7204A-S2	HCVR7208A-S2
	USB	2 USB ports	
Other	Power	DC12V/4A	DC12V/5A
	Power	≤30W (No HDD)	
	Consumption		
	Working	-10°C-+55°C	
	Temperature		
	Working	10%~90%	
	Humidity		
	Dimension	1U case, 375mm (W) x280mm (D) x50mm (H)
	Weight	1.5-2.5kg (No HDD)	
	Installation	Desk installation	
	Mode		

1.3.41 HCVR42XXA-S3 Series

Model	Parameters	HCVR4204A-S3	HCVR4208A-S3 H	CVR4216A-S3
System	Main Processor	High-performance indus	trial embedded micro cor	troller
	OS	Embedded LINUX		
Video	Video Encode	H.264		
	Standard			
	Encode	1080N/720P/	1080N@12f/720P@15f	/960H/D1/HD1/2
	Resolution	960H/D1/HD1/ CIF/CIF		
		2CIF/CIF/		
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s		
	Rate			
	Video Bit Rate	32Kbps~4096Kbps,		
		For 720P:default value is 1.5Mbps, max value is 4Mbps.		
		For 1080P:default value	is 1.5Mbps, max value i	s 4Mbps.
	Bit Stream Type	Video stream/composite	stream	
	Dual-Stream	Support		
Audio	Encode	G.711A, G.711U, PCM		
	Standard			
	Audio	8KHz,16Bit		
	Sampling Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-ch BNC port (HDCVI	8-ch BNC port(HDCVI	16-ch BNC
	Input	HD video/general	HD video/general	port(HDCVI
		standard definition	standard definition	HD
		video self-adaptive)	video self-adaptive)	video/general
				standard
				definition video
				self-adaptive)

Model	Parameters	HCVR4204A-S3	HCVR4208A-S3	HCVR4216A-S3
	Network Video Input	 Max add 1 IP channel connection Analog /digital channel switch. Max 5 IP channel connections Connection bandwidth:4Mbps-20Mbps 	channel connections • Analog /digital channel	 channel switch. Max 18 IP channel connectio ns Connectio n bandwidth :8Mbps-56
	Video Output	Mbps 1-ch VGA output, 1-ch HDMI output, HDMI/ VGA video output at the same time (VGA/HDMI of the same video source)		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	External Audio Input	4-ch, RCA port,	I	1
	Coaxial Audio Input	4-ch	8-ch	16-ch
	Audio Output	1-ch RCA port		
	Bidirectional Talk Input	Support (Reuse the au	idio port of the 1 st chani	nel)
Record	Record Mode	Auto record, manual re	cord, motion detect reco	ord, alarm record
	Playback Mode	Instant playback, norma smart playback	al playback, event playb	oack, mark playback,
	Record Playback	Max 4-ch playback	Max 8-ch playback	Max 16-ch playback
	Backup Mode	HDD, burner, flash disk	, network backup.	·
Alarm	Alarm Input	8-ch alarm input	8-ch alarm input	16-ch alarm input
	Alarm Output	3-ch alarm output	•	·
HDD	HDD Port	2 SATA ports. Does not support eSATA port.		
	Space/HDD	4T 6T		
Communication	Network	1 RJ45 port, 100Mbps I	Ethernet port	

Model	Parameters	HCVR4204A-S3	HCVR4208A-S3	HCVR4216A-S3
Port	Communication	RS485 port		
	USB	2 USB2.0 ports(One at	t the front panel and on	e at the rear panel)
Other	Power	DC12V		
	Power	≤7W	≤8W	≤10W
	Consumption			
	(No HDD)			
	Working	-10℃-+55℃		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimension	1U case, 375mm (W) x280mm (D) x50m	m (H)
	Weight	≤1.5KG	≤1.65KG	≤1.8KG
	(No HDD)		< 1.00100	
	Installation	Desk installation		
	Mode			

1.3.42 HCVR42XXAN-S3 Series

Model	Parameters	HCVR4216AN-S3	HCVR4232AN-S3	
System	Main Processor	High-performance industrial embedde	ed micro controller	
	OS	Embedded LINUX		
Video	Video Encode	H.264		
	Standard			
	Encode	1080N@12f/720P@15f/960H/D1/HD	1/2CIF/CIF	
	Resolution			
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s		
	Rate			
	Video Bit Rate	32Kbps~4096Kbps,		
		For 720P:default value is 1.5Mbps, r	nax value is 4Mbps.	
		For 1080P:default value is 1.5Mbps,	max value is 4Mbps.	
	Bit Stream	Video stream/composite stream		
	Туре			
	Dual-Stream	Support		
Audio	Encode	G.711A, G.711U, PCM		
	Standard			
	Audio	8KHz,16Bit		
	Sampling Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	16-ch BNC port(HDCVI HD	32-ch BNC port(HDCVI HD	
	Input	video/general standard definition	video/general standard definition	
		video self-adaptive)	video self-adaptive)	

Model	Parameters	HCVR4216AN-S3	HCVR4232AN-S3	
	Network Video Input	 Max add 2 IP channel connections Analog /digital channel switch. Max 18 IP channel connections Connection bandwidth:8Mbps-56Mbps 	 Analog /digital channel switch. Max 16 IP channel connections Connection bandwidth: Max 64Mbps 	
	Video Output	1-ch VGA output, 1-ch HDMI output, HDMI/ VGA video output at the same source)	time (VGA/HDMI of the same video	
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	External Audio Input	1-ch, RCA port		
	Coaxial Audio Input	16-ch	32-ch	
	Audio Output	1-ch RCA port		
	Bidirectional Talk Input	Support (Reuse the audio port of the 1 st channel)		
Record	Record Mode	Auto record, manual record, motion d	etect record, alarm record	
	Playback Mode	Instant playback, normal playback, ev playback	vent playback, mark playback, smart	
	Record Playback	Max 16-ch playback		
	Backup Mode	HDD, burner, flash disk, network back	kup.	
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	2 SATA ports. Does not support eSA	•	
	Space/HDD	6T	8T	
Communication	Network	1 RJ45 port, 100Mbps Ethernet port		
Port	Communication	RS485 port		
Other	USB	2 USB2.0 ports(One at the front pane	and one at the rear panel)	
Other	Power	DC12V	<00.04	
	Power Consumption (No HDD)	≤10	≤20W	
	Working Temperature	-10°C−+55°C		

Model	Parameters	HCVR4216AN-S3	HCVR4232AN-S3
	Working	10%~90%	
	Humidity		
	Dimension	1U case, 375mm (W) x280mm (D) x50mm (H)	
	Weight		
	(No HDD)	≤1.8KG	≤3.3KG
	Installation	Desk installation	
	Mode		

1.3.43 HCVR52XXA-S3 Series

Model	Parameters	HCVR5204A-S3	HCVR5208A-S3	HCVR5216A-S3
System	Main Processor	High-performance indust	rial embedded micro cont	roller
	OS	Embedded LINUX		
Video	Video Encode	H.264		
	Standard			
	Encode	1080P@15f/1080N/720F	P/960H/D1/HD1/2CIF/CIF	
	Resolution			
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s		
	Rate			
	Video Bit Rate	32 Kbps \sim 6144Kbps,		
		For 720P:default value is 2Mbps, max value is 4Mbps		
		For 1080P:default value is 2Mbps, max value is 6Mbps		
	Bit Stream	Video stream/composite stream		
	Туре			
	Dual-Stream	Support		
Audio	Encode	G.711A, G.711U, PCM		
	Standard			
	Audio	8KHz,16Bit		
	Sampling Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-ch BNC port (HDCVI	8-ch BNC port(HDCVI	16-ch BNC
	Input	HD video/general	HD video/general	port(HDCVI HD
		standard definition	standard definition	video/general
		video self-adaptive)	video self-adaptive)	standard definition
				video self-adaptive)

Model	Parameters	HCVR5204A-S3	HCVR5208A-S3	HCVR5216A-S3
	Network Video Input	 Max add 2 IP channel connections Analog /digital channel switch. Max 6 IP channel connections Connection bandwidth:8Mbps- 24Mbps 	 Max add 4 IP channel connections Analog /digital channel switch. Max 12 IP channel connections Connection bandwidth:16Mbp s-48Mbps 	 Max add 8 IP channel connections Analog /digital channel switch. Max 24 IP channel connections Connection bandwidth:32Mb ps-96Mbps
	Video Output	1-ch VGA output, 1-ch HDMI output, HDMI/ VGA video output source)	t at the same time (VGA/H	IDMI of the same video
	Loop Output	N/A		
	Matrix Output	N/A 4-ch, RCA port,		
Audio Port	External Audio Input			
	Coaxial Audio Input	4-ch	8-ch-	16-ch
	Audio Output	1-ch RCA port		
	Bidirectional Talk Input	Support (Reuse the aud	lio port of the 1 st channel)	
Record	Record Mode	Auto record, manual reco	ord, motion detect record,	alarm record
	Playback Mode	Instant playback, normal playback	playback, event playback	k, mark playback, smart
	Record Playback	Max 4-ch playback	Max 8-ch playback	Max 16-ch playback
	Backup Mode	HDD, burner, flash disk,	network backup.	
Alarm	Alarm Input	8-ch alarm input	8-ch alarm input	16-ch alarm input
	Alarm Output	3-ch alarm output		
HDD	HDD Port	2 SATA ports. Does not	support eSATA port.	
	Space/HDD	4T	6T	
Communication	Network	1 RJ45 port, 100Mbps E	thernet port	
Port	Communication	RS485 port		
	USB	2 USB2.0 ports(One at the	he front panel and one at	the rear panel)
Other	Power	DC12V		
	Power Consumption (No HDD)	≤7W	≤8W	≤10W

Model	Parameters	HCVR5204A-S3	HCVR5208A-S	3 HCVR5216A-S3
	Working	-10℃-+55℃		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimension	1U case, 375mm (W)	x280mm (D) x8	50mm (H)
	Weight	≤1.5KG	≤1.65KG	≤1.8KG
	(no HDD)	<1.5KG	<1.05KG	
	Installation	Desk installation		
	Mode			
	VR52XXAN-S3 S	eries		
Model	Parameters	HCVR5216AN-S3	НС	VR5232AN-S3
System	Main Processor	r High-performance industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	e H.264		
	Standard			
	Encode	1080P@15f/1080N/720F	2/960H/D1/HD1/2	2CIF/CIF
	Resolution			
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s		
	Rate			
	Video Bit Rate	32Kbps~6144Kbps,		
		For 720P:default value is	•	•
		For 1080P:default value		alue is 6Mbps
	Bit Stream	Video stream/composite	stream	
	Type Dual-Stream	Cupport		
Audio		Support		
Audio	Encode Standard	G.711A, G.711U, PCM		
	Audio	8KHz,16Bit		
	Sampling Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	16-ch BNC port(HI	DCVI HD 32-	-ch BNC port(HDCVI HD
VIGEO POIL	Input	1 (eo/general standard definition
		video self-adaptive)		eo self-adaptive)
	Network Video	 Max add 8 IP chann 		Analog
	Input	connections		/digital channel
		 Analog 		switch. Max 16 IP channel
		/digital channel		connections
		switch. Max 24 I	P channel •	Connection bandwidth: Max
		connections		64Mbps
		Connection		
		bandwidth:32Mbps-	96Mbps	

Model	Parameters	HCVR5216AN-S3	HCVR5232AN-S3	
	Video Output	1-ch VGA output, 1-ch HDMI output, HDMI/ VGA video output at the same source)	time (VGA/HDMI of the same video	
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Port External 1-ch, RCA port Audio Input			
	Coaxial Audio Input	16-ch	32-ch	
	Audio Output	1-ch RCA port		
	Bidirectional	Support (Reuse the audio port of the	e 1 st channel)	
	Talk Input			
Record	Record Mode	Auto record, manual record, motion d	etect record, alarm record	
	Playback Mode	de Instant playback, normal playback, event playback, mark playback playback		
	Record Max 16-ch playback Playback			
	Backup Mode	HDD, burner, flash disk, network backup.		
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	2 SATA ports. Does not support eSA	TA port.	
	Space/HDD	6T	8T	
Communication	Network	1 RJ45 port, 1000Mbps Ethernet port		
Port	Communication	RS485 port		
	USB	2 USB2.0 ports(One at the front pane	el and one at the rear panel)	
Other	Power	DC12V		
	Power Consumption (No HDD)	≤10W	≤25W	
	Working Temperature	-10°C-+55°C		
	Working Humidity	10%~90%		
	Dimension	1U case, 375mm (W) ×280mm (D	0) x50mm (H)	
	Weight (no HDD)	≤1.8KG		
	Installation Mode	Desk installation		

1.3.45 HCVR72XXA-S3/HCVR7216AN-S3 Series

Model	Parameters	HCVR7204A-S3	HCVR7208A-S3	HCVR7216A-S3	HCVR7216AN- S3
System	Main Processor	High-performance	e industrial embedd	ed micro controller	
	OS	Embedded LINUX	(
Video	Video Encode Standard	H.264	H.264		
	Encode Resolution	1080P@15f/1080N/720P/960H/D1/HD1/2CIF/CIF			
	Video Frame Rate	PAL:1~25f/s; NT	SC: 1~30f/s		
	Video Bit Rate	32Kbps~6144Kbps, For 720P:default value is 2Mbps, max value is 4Mbps For 1080P:default value is 2Mbps, max value is 6Mbps			
	Bit Stream Type	Video stream/composite stream			
	Dual-Stream	Support			
Audio	Encode Standard	G.711A, G.711U,	PCM		
	Audio Sampling Rate	8KHz,16Bit			
	Audio Bit Rate	64Kbps			
Video Port	Analog Video Input	4-ch BNC port (HDCVI HD video/general standard definition video self-adaptive)	8-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)	16-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)	16-ch BNC port(HDCVI HD video/general standard definition video self-adaptive)

Model	Parameters	HCVR7204A-S3	HCVR7208A-S3	HCVR7216A-S3	HCVR7216AN- S3
	Network Video Input	 Max add 2 IP channel connections Analog /digital channel switch. Max 6 IP channel connections Connection bandwidth:8 Mbps-24Mb ps 	 Max add 4 IP channel connection Analog /digital channel switch. Max 12 IP channel connection Connection n bandwidth: 16Mbps-48 Mbps 	 Max add 8 IP channel connections Analog /digital channel switch. Max 24 IP channel connections Connection bandwidth:3 2Mbps-96M bps 	 Max add 8 IP channel connection Analog /digital channel switch. Max 24 IP channel connection s Connection bandwidth: 32Mbps-96 Mbps
	Video Output	1-ch VGA output, 1-ch HDMI output, HDMI/ VGA video output at the same time (VGA/HDMI of the same video source)			of the same video
	Loop Output	N/A			
	Matrix Output	N/A			1
Audio Port	External Audio Input	4-ch, RCA port,			1-ch, RCA port
	Coaxial Audio Input	4-ch	8-ch-	16-ch	16-ch
	Audio Output	1-ch RCA port			
	Bidirectional Talk Input	Support (Reuse t	he audio port of the	e 1 st channel)	
Record	Record Mode	Auto record, manu	ual record, motion o	detect record, alarm	record
	Playback Mode	Instant playback, i playback	normal playback, e	event playback, marl	k playback, smart
	Record Playback	Max 4-ch playback	Max 8-ch playback	Max 16-ch playba	ck
	Backup Mode	HDD, burner, flast	n disk, network bac	kup.	
Alarm	Alarm Input	8-ch alarm input	8-ch alarm input	16-ch alarm input	N/A
	Alarm Output	3-ch alarm output			N/A
HDD	HDD Port	· · · · ·	es not support eSA	TA port.	1
	Space/HDD	4T 6T			
Communication	Network	1 RJ45 port, 100M	Ibps Ethernet port		

Model	Parameters	HCVR7204A-S3	HCVR7208A-S3	HCVR7216A-S3	HCVR7216AN- S3
Port	Communication	RS485 port			
	USB	2 USB2.0 ports(O	ne at the front pane	el and one at the re	ar panel)
Other	Power	DC12V			
	Power	≤8W	≤10W	≤15W	≤15W
	Consumption				
	(No HDD)				
	Working	-10°C-+55°C			
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimension	1U case, 375mm (W) x280mm (D) x50mm (H)			
	Weight (no HDD)	≤1.5KG	≤1.65KG	≤1.8KG	≤1.8KG
	Installation	Desk installation			
	Mode				

1.3.46 HCVR52XXL-V2 Series

Model	Parameters	HCVR5204L-V2	HCVR5208L-V2	HCVR5216L-V2	
System	Main Processor	High-performance industrial e	mbedded micro controller		
	OS	Embedded LINUX			
Video	Video Encode	H.264			
	Standard				
	Encode	720P/960H/D1/HD1/2CIF/CIF/QCIF (for sub-stream only)			
	Resolution				
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/	′S		
	Rate				
	Video Bit Rate	1536Kbps-4096Kbps,	1536Kbps-4096Kbps,		
		For 720P:default value is 2Mbps, max value is 4Mbps			
	Bit Stream	Video stream/composite stream			
	Туре				
	Dual-Stream	Support			
Audio	Encode	G.711A, G.711U, PCM			
	Standard				
	Audio	8KHz,16Bit			
	Sampling Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-ch, BNC port	8-ch, BNC port	16-ch, BNC port	
	Input				
	Network Video	Switch 2 analog channels to the IP channels (8Mbps)			
	Input				

Model	Parameters	HCVR5204L-V2	HCVR5208L-V2	HCVR5216L-V2		
	Video Output	1-ch VGA output,				
		1-ch HDMI output,				
		HDMI/ VGA video output at th	ne same time (VGA/HDM	I of the same video		
		source)				
	Loop Output	N/A				
	Matrix Output	N/A				
Audio Port	Audio Input	4-ch, RCA port, audio via co	axial cable			
	Audio Output	1-ch, RCA port				
	Bidirectional	Support (Reuse the audio port)				
	Talk Input					
Record	Record Mode	Auto record, manual record, motion detect record, alarm record				
	Record	Max 4-ch playback	Max 8-ch playback	Max 16-ch		
	Playback			playback		
	Backup Mode	HDD, burner, flash disk, netw	ork backup.			
Alarm	Alarm Input	ut4-ch alarm input8-ch alarm input16-				
	Alarm Output	3-ch alarm output				
HDD	HDD Port	2 SATA ports. Does not supp	ort eSATA port			
	Space/HDD	4T				
Communication	Network	1 RJ45 port, 1000Mbps Ether	met port			
Port	Communication	RS485 port				
	USB	2 USB ports				
Other	Power	DC12V				
	Power	≤30W (exclude HDD)				
	Consumption					
	Working	-10°℃−+55°℃				
	Temperature					
	Working	10%~90%				
	Humidity					
	Dimension	1.5U case, 440mm (W) ×4	10mm (D) x70mm (H)			
	Weight	3.0kg \sim 3.5kg (exclude HDD))			
	Installation	Desk installation				
	Mode					
1.3.47 HC	VR54XXL-V2 Se	ries				

1.3.47 HCVR54XXL-V2 Series

Model	Parameters	HCVR5404L-V2	HCVR5408L-V2	HCVR5416L-V2
System	Main Processor	High-performance industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	H.264		
	Standard			
	Encode	720P/960H/D1/HD1/2CIF/CIF/QCIF (for sub-stream only)		ly)
	Resolution			

Model	Parameters	HCVR5404L-V2	HCVR5408L-V2	HCVR5416L-V2
	Video Frame	PAL:1~25f/s; NTSC: 1~30	f/s	
	Rate			
	Video Bit Rate	1536Kbps-4096Kbps,		
		For 720P:default value is 2N	Ibps, max value is 4Mbp	s
	Bit Stream	Video stream/composite stre	am	
	Туре			
	Dual-Stream	Support		
Audio	Encode	G.711A, G.711U, PCM		
	Standard			
	Audio	8KHz,16Bit		
	Sampling Rate			
	Audio Bit Rate	64Kbps	1	-1
Video Port	Analog Video	4-ch, BNC port	8-ch, BNC port	16-ch, BNC port
	Input			
	Network Video	Switch 2 analog channels to	the IP channels (8Mbps)
	Input			
	Video Output	1-ch VGA output,		
		1-ch HDMI output,		
		1-ch TV output,	it at the same time ()/C	
		HDMI/ VGA/TV video outpu same video source)	ut at the same time (ve	
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	4-ch, BNC port, audio via c	oaxial cable	
	Audio Output	1-ch, BNC port		
	Bidirectional	Support (Independent bidire	ectional talk port)	
	Talk Input			
Record	Record Mode	Auto record, manual record,	motion detect record, ala	rm record
	Record	Max 4-ch playback	Max 8-ch playback	Max 16-ch
	Playback			playback
	Backup Mode	HDD, burner, flash disk, net	work backup.	-
Alarm	Alarm Input	8-ch alarm input	8-ch alarm input	16-ch alarm input
	Alarm Output	6-ch alarm output	-	-
HDD	HDD Port	4 SATA ports. Does not sup	port eSATA port	
	Space/HDD	4T		
Communication	Network	1 RJ45 port, 1000Mbps Ethe	ernet port	
Port	Communication	1 RS232 port, 1 RS422 port, 1 RS485 port		
	USB	3 USB ports (One at the front panel and two at the rear panel)		ar panel)
Other	Power	AC90~264V 50+2% Hz (4/	8-ch max 75W)	
	Power	≤35W (exclude HDD)		
	Consumption			

Model	Parameters	HCVR5404L-V2	HCVR5408L-V2	HCVR5416L-V2
	Working	-10°C-+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimension	1.5U case, 440mm (W) ×410mm (D) ×70mm (H) 4.5kg~5.5kg (exclude HDD)		
	Weight			
	Installation	Desk/rack installation		
	Mode			

1.3.48 HCVR4224/32L-S2 Series

Model	Parameters	HCVR4224L-S2	HCVR4232L-S2
System	Main Processor	High-performance industrial embedded mid	cro controller
	OS	Embedded LINUX	
Video	Video Encode	H.264	
	Standard		
	Encode	720P(1-15fps)/960H/D1/HD1/2CIF/CIF/QC	CIF (for sub-stream only)
	Resolution		
	Video Frame	HDCVI: 1 \sim 15f/s (The 1 st / 2 nd channel su	pports 25/30f/s)
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s (NTSC)	
	Video Bit Rate	1024Kbps \sim 4096Kbps,	
		For 720P realtime (The first two channels)	:default value is 2Mbps, max
		value is 4Mbps.	
		For 720P non-realtime: default value is 1M	bps, max value is 2Mbps.
	Bit Stream Type	Video stream/composite stream	
	Dual-Stream	Support	
Audio	Encode	G.711A, G.711U, PCM	
	Standard		
	Audio Sampling	8KHz,16Bit	
	Rate		
	Audio Bit Rate	64Kbps	
Video Port	Analog Video	24-ch, BNC port	32-ch, BNC port
	Input		
	Network Video	Max 4 IPC connections (16Mbps)	
	Input		
	Video Output	1-ch VGA output,	
		1-ch HDMI output,	
		HDMI/ VGA video output at the same time (VGA/HDMI of th	
source)		,	
	Loop Output	N/A	
	Matrix Output	N/A	
Audio Port	Audio Input	4-ch, RCA port, Coaxible audio	4-ch, RCA port. Coaxible audio

Model	Parameters	HCVR4224L-S2	HCVR4232L-S2	
	Audio Output	1-ch, RCA port		
	Bidirectional	Support (Reuse the audio port)		
	Talk Input			
Record	Record Mode	Auto record, manual record, motion detect record, alarm record		
	Record	Max 16-ch playback		
	Playback			
	Backup Mode	HDD, burner, flash disk, network backup.		
Alarm	Alarm Input	16-channel alarm input		
	Alarm Output	3-channel alarm output		
HDD	HDD Port	2 SATA ports. Does not support eSATA po	ort.	
	Space/HDD	4T		
Communication	Network	1 RJ45 port, 1000Mbps Ethernet port		
Port	Communication	1 RS232 port, 1 RS485 port		
	USB	2 USB ports		
Other	Power	DC12V/5A		
	Power	≤30W (With adapter, no HDD)		
	Consumption			
	Working	-10°C-+55°C		
	Temperature			
Working 10%~9		10%~90%		
	Humidity			
	Dimension	1.5U case, 440mm (W) x410mm (D) x70mm (H)		
Weight4.5-5.5kg (no HDD)				
	Installation Desk/rack installation			
	Mode			

1.3.49 HCVR44XXL-S2 Series

Model	Parameters	HCVR4404L-S2	HCVR4408L-S2	HCVR4416L-S2
System	Main Processor	High-performance industria	l embedded micro controlle	er
	OS	Embedded LINUX		
Video	Video Encode	H.264		
	Standard			
	Encode	720P/960H/D1/HD1/2CIF/0	CIF/QCIF (for sub-stream o	nly)
	Resolution			
	Video Frame	HDCVI: 1~15f/s (The 1s	t channel supports 25/30f/s	s)
	Rate	CVBS: 1~25f/s (PAL); 1	~30f/s (NTSC)	
	Video Bit Rate	1536Kbps-4096Kbps,		
		For 720P:default value is 2Mbps, max value is 4Mbps		S
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	Support		

Model	Parameters	HCVR4404L-S2	HCVR4408L-S2	HCVR4416L-S2
Audio	Encode	G.711A, G.711U, PCM	•	•
	Standard			
	Audio Sampling	8KHz,16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-ch, BNC port	8-ch, BNC port	16-ch, BNC port
	Input			
	Network Video	Switch 2 analog channels t	to the IP channels (8Mbp	s)
	Input			
	Video Output	1-ch VGA output,		
		1-ch HDMI output,		
		1-ch TV output,		
		HDMI/ VGA/TV video out	put at the same time (V	GA/HDMI/TV of the
		same video source)		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	4-ch, BNC port, audio via	coaxial cable	
	Audio Output	1-ch, BNC port		
	Bidirectional	Support (Independent bidirectional talk port)		
	Talk Input			
Record	Record Mode	Auto record, manual record		
	Record	Max 4-ch playback	Max 8-ch playback	Max 16-ch
	Playback			playback
	Backup Mode	HDD, burner, flash disk, ne		
Alarm	Alarm Input	8-ch alarm input	8-ch alarm input	16-ch alarm input
	Alarm Output	6-ch alarm output		
HDD	HDD Port	4 SATA ports. Does not su	pport eSATA port	
	Space/HDD	6T		
Communication	Network	1 RJ45 port, 1000Mbps Etl	•	
Port	Communication	1 RS232 port, 1 RS422 po	•	
	USB	3 USB ports (One at the fro		ear panel)
Other	Power	AC90~264V 50+2% Hz (4	4/8-ch max 75W)	
	Power	≤35W (exclude HDD)		
	Consumption			
	Working	-10°℃−+55°℃		
	Temperature	109/ 009/		
	Working	10%~90%		
	Humidity	1 511 0000 440mm (M)	v410mm (D)70mm (1	L)
	Dimension	1.5U case, 440mm (W)		ער
	Weight	4.5kg \sim 5.5kg (exclude HE	(ענ	

Model	Parameters	HCVR4404L-S2	HCVR4408L-S2	HCVR4416L-S2
	Installation	Desk/rack installation		
	Mode			

Model	Parameters	HCVR4424L-S2	HCVR4432L-S2	
System	Main Processor	High-performance industrial embedded	d micro controller	
	OS	Embedded LINUX		
Video	Video Encode	H.264		
	Standard			
	Encode	720P/960H/D1/HD1/2CIF/CIF/QCIF (fc	or sub-stream only)	
	Resolution			
	Video Frame	HDCVI: $1 \sim 15$ (The 1 st /2 nd channed)		
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s (NT	SC)	
	Video Bit Rate	1024Kbps-4096Kbps,		
		For 720P realtime (The first two chann	nels):default value is 2Mbps, max	
		value is 4Mbps.		
		For 720P non-realtime: default value is	s 1Mbps, max value is 2Mbps.	
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	Support		
Audio	Encode	G.711A, G.711U, PCM		
	Standard			
	Audio Sampling	g 8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	24-ch, BNC port	32-ch, BNC port	
	Input			
	Network Video	Switch 4 analog channels to the IP cha	annels (16Mbps)	
	Input			
	Video Output	1-ch VGA output,		
		1-ch HDMI output,		
		1-ch TV output,		
		HDMI/ VGA/TV video output at the s	same time (VGA/HDMI/TV of the	
		same video source)		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	4-ch, BNC port, audio via coaxial cab	le	
	Audio Output 1-ch, BNC port			
	Bidirectional	Support (Independent bidirectional talk port)		
	Talk Input			
Record	Record Mode	Auto record, manual record, motion de	tect record, alarm record	
	Record	Max 16-ch playback		
	Playback			
	Backup Mode	HDD, burner, flash disk, network back	up.	

Model	Parameters	HCVR4424L-S2	HCVR4432L-S2
Alarm	Alarm Input	16-ch alarm input	
	Alarm Output	6-ch alarm output	
HDD	HDD Port	4 SATA ports. Does not support eSATA port	
	Space/HDD	6T	
Communication	Network	1 RJ45 port, 1000Mbps Ethernet port	
Port	Communication	1 RS232 port, 1 RS422 port	
	USB	3 USB ports (One at the front panel and two at the rear panel)	
Other	Power	AC110~240V 50+2%HZ (max 220W)	
	Power	≤35W (exclude HDD)	
	Consumption		
	Working	-10 °C−+55°C	
	Temperature		
	Working	10%~90%	
	Humidity		
	Dimension	1.5U case, 440mm (W) ×410mm (E	0) x70mm (H)
	Weight	4.5kg~5.5kg (exclude HDD) ion Desk/rack installation	
	Installation		
	Mode		

1.3.50 HCVR48XXS-S2 Series

Model	Parameters	HCVR4804S-S2	HCVR4808S-S2	HCVR4816S-S2	
System	Main Processor	High-performance industria	High-performance industrial embedded micro controller		
	OS	Embedded LINUX			
Video	Video Encode	H.264			
	Standard				
	Encode	720P/960H/D1/HD1/2CIF/0	CIF/QCIF (for sub-stream of	only)	
	Resolution				
	Video Frame	HDCVI: 1 \sim 15f/s (The 1s	t channel supports 25/30f/s	s)	
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s (NTSC)			
	Video Bit Rate	1536Kbps-4096Kbps,			
		For 720P:default value is 2	Mbps, max value is 4Mbp	S	
	Bit Stream Type	Video stream/composite st	ream		
	Dual-Stream	Support			
Audio	Encode	G.711A, G.711U, PCM			
	Standard				
	Audio Sampling	8KHz,16Bit			
	Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-ch, BNC port	8-ch, BNC port	16-ch, BNC port	
	Input				

Model	Parameters	HCVR4804S-S2	HCVR4808S-S2	HCVR4816S-S2
	Network Video	Switch 2 analog channels t	o the IP channels (8Mb	ps)
	Input			
	Video Output	1-ch VGA output,		
		1-ch HDMI output,		
		1-ch TV output,		
		HDMI/ VGA/TV video outp	HDMI/ VGA/TV video output at the same time (VGA/HDMI/TV of the	
		same video source)		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	4-ch, BNC port, audio via	8-ch , BNC port,	16-ch, BNC port,
		coaxial cable	audio via coaxial	audio via coaxial
			cable	cable
	Audio Output	1-ch, BNC port		
	Bidirectional	Support (Independent bidi	rectional talk port)	
	Talk Input			
Record	Record Mode	Auto record, manual record, motion detect record, alarm record		1
	Record	Max 4-ch playback	Max 8-ch playback	Max 16-ch
	Playback			playback
	Backup Mode	HDD, burner, flash disk, ne		1
Alarm	Alarm Input	8-ch alarm input	8-ch alarm input	16-ch alarm input
	Alarm Output	6-ch alarm output		
HDD	HDD Port	8 SATA ports, does not su	ipport eSATA port	
	Space/HDD	6T		
Communication	Network	1 RJ45 port, 1000Mbps Eth	nernet port	2 RJ45 ports,
Port				1000Mbps
				Ethernet ports
	Communication	1 RS232 port, 1 RS422 por	•	
	USB	4 USB ports (Two at the fro	•	rear panel)
Other	Power	AC90~264V 50+2% Hz (N	viax 220VV)	
	Power	≤35W (exclude HDD)		
	Consumption			
	Working	-10℃−+55℃		
	Temperature			
	Working	10%~90%		
	Humidity Dimension	2U case, 440mm (W) x460mm (D) x89mm (H)		
)
	Weight Installation	7.0kg~8.0kg (exclude HD Desk/rack installation	<i>י</i> שי /	
	Mode	DESK/IACK INStallation		
	MODE			

Model	Parameters	HCVR4824S-S2	HCVR4832S-S2
System	Main Processor	High-performance industrial embeddec	l micro controller
	OS	Embedded LINUX	
Video	Video Encode	H.264	
	Standard		
	Encode	720P/960H/D1/HD1/2CIF/CIF/QCIF (fc	or sub-stream only)
	Resolution		
	Video Frame	HDCVI: 1~15f/s (The 1 st / 2 nd channed	el supports 25/30f/s)
	Rate	CVBS: 1~25f/s (PAL); 1~30f/s (NTSC)	
	Video Bit Rate	1024Kbps-4096Kbps,	
		For 720P realtime (The first two channels):default value is 2M	
		value is 4Mbps.	
		For 720P non-realtime: default value is	1Mbps, max value is 2Mbps.
	Bit Stream Type	Video stream/composite stream	
	Dual-Stream	Support	
Audio	Encode	G.711A, G.711U, PCM	
	Standard		
	Audio Sampling	8KHz,16Bit	
	Rate	Rate	
	Audio Bit Rate	64Kbps	
Video Port	Analog Video	24-ch, BNC port	32-ch, BNC port
	Input		
	Network Video	Switch 4 analog channels to the IP channels (16Mbps)	
	Input		
	Video Output	1-ch VGA output,	
		1-ch HDMI output,	
		1-ch TV output,	
		HDMI/ VGA/TV video output at the s	ame time (VGA/HDMI/TV of the
		same video source) N/A	
	Loop Output	N/A	
Audio Dort	Matrix Output Audio Input		16 ch DNC port oudio via
Audio Port	Audio input	16-ch, BNC port, audio via coaxial cable	16-ch, BNC port, audio via coaxial cable
	Audio Output	1-ch, BNC port	
	Bidirectional	Support (Independent bidirectional tal	k port)
	Talk Input		
Record	Record Mode	Auto record, manual record, motion de	tect record alarm record
	Record	Max 16-ch playback	
	Playback		
	Backup Mode	HDD, burner, flash disk, network backup.	
Alarm	Alarm Input	16-ch alarm input	- La -
	Alarm Output	6-ch alarm output	
HDD	HDD Port	8 SATA ports	
	TIDDFOIL		

Model	Parameters	HCVR4824S-S2	HCVR4832S-S2	
	Space/HDD	6T		
Communication	Network	2 RJ45 ports, 1000Mbps Ethernet ports	3	
Port	Communication	1 RS232 port, 1 RS422 port		
	USB	4 USB ports (Two at the front panel and two at the rear panel)		
Other	Power	AC110~240V 50+2%HZ (Max 220W)		
	Power	≤35W (exclude HDD)		
	Consumption	-10°C-+55°C		
	Working			
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimension	2U case, 440mm (W) ×460mm (D) ×89mm (H)		
	Weight	7.0kg \sim 8.0kg (exclude HDD)		
	Installation	Desk/rack installation		
	Mode			

1.3.51 HCVR58XXS-V2 Series

Model	Parameters	HCVR5804S-V2	HCVR5808S-V2	HCVR5816S-V2
System	Main Processor	High-performance industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	H.264		
	Standard			
	Encode	720P/960H/D1/HD1/2CIF/0	CIF/QCIF (for sub-stream of	only)
	Resolution			
	Video Frame	PAL:1~25f/s; NTSC: 1~3	Of/s	
	Rate	 1536Kbps-4096Kbps, For 720P:default value is 2Mbps, max value is 4Mbps Video stream/composite stream 		
	Video Bit Rate			
	Bit Stream Type			
	Dual-Stream	Support		
Audio	Encode	G.711A, G.711U, PCM		
	Standard			
	Audio Sampling	8KHz,16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-ch, BNC port	8-ch, BNC port	16-ch, BNC port
	Input			
	NetworkVideoSwitch 2 analog channels to the IP channels (8Mbps)			;)
	Input			

Model	Parameters	HCVR5804S-V2	HCVR5808S-V2	HCVR5816S-V2
	Video Output	1-ch VGA output, 1-ch HDMI output,		
		1-ch TV output,		
		HDMI/ VGA/TV video output at the same time (VGA/HDMI/TV of the		
		same video source)		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	4-ch, BNC port, audio via	8-ch , BNC port,	16-ch, BNC port,
		coaxial cable	audio via coaxial	audio via coaxial
			cable	cable
	Audio Output	1-ch, RCA port		
	Bidirectional	Support (Independent bidi	rectional talk port)	
	Talk Input			
Record	Record Mode	Auto record, manual record	, motion detect record,	alarm record
	Record	Max 4-ch playback	Max 8-ch playback	Max 16-ch
	Playback			playback
	Backup Mode	HDD, burner, flash disk, ne	twork backup.	
Alarm	Alarm Input	8-ch alarm input	8-ch alarm input	16-ch alarm input
	Alarm Output	6-ch alarm output		
HDD	HDD Port	8 SATA ports, does not support eSATA port		
	Space/HDD	4T		
Communication	Network	2 RJ45 ports, 1000Mbps E	thernet port	
Port	Communication	1 RS232 port, 1 RS422 por	rt, 1 RS485 port	
	USB	3 USB ports (One at the fro	ont panel and two at the	rear panel)
Other	Power	AC90~264V 50+2% Hz (I	Max 220W)	
	Power	≤35W (exclude HDD)		
	Consumption			
	Working	-10°C-+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimension	2U case, 440mm (W) x460mm (D) x89mm (H)		
Weight 7.0kg~8.0kg (exclude HDD)				
	Installation	Desk/rack installation		
	Mode			
1.3.52 HC	/R71XXH-4M Ser	ies		
Model	Parameters	HCVR7104H-4M	ICVR7108H-4M HC	CVR7116H-4M
System	Main Processor	Industrial embedded mic	ro controller	

System	Main Processor		Industrial embedded micro controller		
	OS		Embedded LINUX		
Video	Video	Encode	H.264+/H.264		
Parameters	Standard				

Model	Parameters	HCVR7104H-4M	HCVR7108H-4M	HCVR7116H-4M	
	Encode	Main stream			
	Resolution	2K(2560*1440)@15f/1080P/720P/960H/D1/HD1/BCIF/CIF/QCIF Sub stream: D1/CIF/QCIF 2K resolution: PAL:1~15f/s; NTSC: 1~15f/s Other resolutions: PAL:1~25f/s; NTSC: 1~30f/s			
	Video Frame Rate				
	Video Bit Rate	32Kbps-6144Kbps,			
		For 720P: default setup is 2Mbps, max supports 4Mbps. For 1080N: default setup is 4Mbps, max supports 6Mbps.			
		For 2K: non realtime d	For 2K: non realtime default setup is 4Mbps, max supports 6Mbps.		
	Bit Stream Type	Video stream/composi	te stream		
	Dual-Stream	Support			
Audio	Encode Standard	G.711A/G.711U/PCM			
Parameters	Audio Sampling	8KHz, 16Bit			
	Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-ch BNC port	8-ch BNC port	16-ch BNC port	
	Input	(HDCVI/CVBS)	(HDCVI/CVBS)	(HDCVI/CVBS)	
	Network Video	• Max add 2 IP	Max add 4 IP	Max add 8 IP	
	Input	channel	channel	channel	
		connection.	connection.	connection.	
		 Analog 	 Analog 	Analog	
		/digital channel	/digital channel	/digital channel	
		switch. Max 6 IP	switch. Max 12	switch. Max 24 IP	
		channel	IP channel	channel	
		connections	connections	connections	
		Connection	 Connection 	Connection	
		bandwidth:8Mbp	bandwidth:16	bandwidth:32Mbps-	
		s-24Mbps	Mbps-48Mbps	96Mbps	
	Video Output	1-channel VGA output	,		
		1-channel HDMI outpu	it, max 4K(3840*2160))@30f	
		HDMI/ VGA video out	out at the same time (of the same video source	
		or different video source	ce).		
	Loop Output	N/A			
	Matrix Output	When the HDMI and	VGA are of differe	ent video output, system	
		supports one matrix ou	utput.		
Audio Port	Audio Input	1-channel RCA port.			
	Coaxial Audio	N/A			
	Input				
	Audio Output	1-channel RCA port.			
	Bidirectional Talk	Reuse the audio input	/output port		
	Input				
	Input				

Model	Parameters	HCVR7104H-4M	HCVR7108H-4M	HCVR7116H-4M	
		record Instant playback, normal playback, event playback, mark playback, smart playback			
	Playback Mode				
	Playback Channel	4-channel	8-channel	16-channel	
	Backup Mode	HDD, burner, USB dev	vice, network backup		
Alarm	Alarm Input	N/A			
	Alarm Output	N/A			
HDD	HDD Port	1 SATA port			
	One HDD Space	8T			
Communication	Network	1 RJ45 port, 1000Mbps Ethernet port			
Port	Communication	1 RS485 port			
	USB	2 USB ports(One USB2.0 port at the front panel and one USB3.0 port			
		at the rear panel)			
Others	Power	DC12V			
	Power	≤12W	≤13W	≤20W	
	Consumption (No				
	HDD)				
	Working	-10°C − +55°C			
	Temperature				
	Working Humidity	10%~90%			
	Dimensions	Mini 1U case, 325mm (W) ×245mm (D) ×45mm (H)			
	Weight (No HDD)	≤1.25KG	≤1.25KG	≤1.40KG	
	Installation Mode	Desk			

1.3.53 HCVR72XXAN-4M Series

Model	Parameters	HCVR7204AN-4M	HCVR7208AN-4M	HCVR7216AN-4M
System	Main Processor	Industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	H.264+/H.264		
Parameters	Standard			
	Encode	Main		stream:
	Resolution	2K(2560*1440)/1080P/720P/960H/D1/HD1/BCIF/CIF/QCIF		
		Sub stream: D1/CIF/QCIF		
	Video Frame Rate	2K resolution: PAL:1~15f/s; NTSC: 1~15f/s		
		Other resolutions: PAL:1~25f/s; NTSC: 1~30f/s		30f/s
	Video Bit Rate	32Kbps-6144Kbps,		
		For 720P: default setu	p is 2Mbps, max sup	ports 4Mbps.
		For 1080N: default setup is 4Mbps, max supports 6Mbps.		pports 6Mbps.
		For 2K: non realtime default setup is 4Mbps, max supports 6Mbps.		
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	Support		

Model	Parameters	HCVR7204AN-4M	HCVR7208AN-4M	HCVR7216AN-4M
Audio	Encode Standard	G.711A/G.711U/PCM		
Parameters	Audio Sampling	8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-ch BNC port	8-ch BNC port	16-ch BNC port
	Input	(HDCVI/CVBS)	(HDCVI/CVBS)	(HDCVI/CVBS)
	Network Video	• Max add 2 IP	• Max add 4 IP	• Max add 8 IP
	Input	 channel connection. Analog /digital channel switch. Max 6 IP channel connections Connection bandwidth:8Mbp s-24Mbps 	channel connection. • Analog /digital channel switch. Max 12 IP channel connections • Connection bandwidth:16 Mbps-48Mbps	 channel connection. Analog /digital channel switch. Max 24 IP channel connections Connection bandwidth:32Mbps- 96Mbps
	Video Output	1-channel VGA output 1-channel HDMI outpu HDMI/ VGA video outp or different video sourc	it, max 4K(3840*2160) but at the same time (@30f of the same video source
	Loop Output	N/A		
	Matrix Output	When the HDMI and	I VGA are outputting	different video, system
		supports one matrix ou	ıtput.	
Audio Port	Audio Input	1-channel RCA port.		
	Coaxial Audio Input	N/A		
	Audio Output	1-channel RCA port.		
	Bidirectional Talk Input	Reuse the audio input	output port	
Record	Record Mode	record		d/Alarm record/intelligent
	Playback Mode	smart playback		blayback, mark playback,
	Playback Channel	4-channel	8-channel	16-channel
	Backup Mode	HDD, burner, USB dev	vice, network backup	
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	2 SATA ports		
	One HDD Space	8T		
Communication	Network	1 RJ45 port, 1000Mbps Ethernet port		
Port	Communication	1 RS485 port		

Model	Parameters	HCVR7204AN-4M	HCVR7208AN-4M	HCVR7216AN-4M	
	USB	2 USB ports(One USB	2 USB ports(One USB2.0 port at the front panel and one USB3.0 port		
		at the rear panel)			
Others	Power	DC12V	DC12V		
	Power	≤12W	≤13W	≤20W	
	Consumption (No				
	HDD)				
	Working	-10℃-+55℃	-10℃−+55℃		
	Temperature				
	Working Humidity	10%~90%			
	Dimensions	1U case, 375mm (W) x280mm (D) x50mm (H)			
	Weight (No HDD)	≤1.60KG	≤1.60KG	≤1.75KG	
	Installation Mode	Desk			

1.3.54 XVR410XC Series

	Parameters	XVR4104C	XVR4108C	
System	Main Processor	Industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode Resolution	1080N/720P/960H/D1/HD1/2CIF/CIF	1080N@12f/720P@15f	
			/960H/D1/HD1/2CIF/CIF	
	Video Frame Rate	PAL:1~25f/s; NTSC: 1~30f/s		
	Video Bit Rate	32Kbps-4096Kbps		
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	Support		
Audio	Encode Standard	G.711A/G.711U/PCM		
Parameters	Audio Sampling	8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video Input	4-ch BNC port(CVBS/CVI/AHD/ other	8-ch BNC port(CVBS/CVI/	
		analog HD video self-adaptive)	AHD/other analog HD video	
			self-adaptive)	
	Network Video Input	• There is no IP channel by default.	• There is no IP channel	
		Max add 1 IP channel	by default.Max add 2 IP	
		connection	channel connections	
		Analog/digital channel switch. Max	Analog/digital channel	
		5 IP channel connectionsConnection	switch. Max 10 IP	
		 Connection bandwidth:0Mbps-20Mbps 	channel connectionsConnection	
		5410WIGHT.0WID45-20WID45	bandwidth:0Mbps-40M	
			bps	
	Video Output	1-channel VGA output,	~~~~	

	Parameters	XVR4104C	XVR4108C	
		1-channel HDMI output (of the same HDMI/ VGA video output at the same	-	
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	1-channel RCA port.		
	Coaxial Audio Input	N/A		
	Audio Output	1-channel RCA port.		
	Bidirectional Talk Input	Reuse the audio input/output port of t	he 1 st channel.	
Record	Record Mode	Schedule record/manual record/MD r	ecord/Alarm record	
	Playback Mode	Instant playback, normal playback, e smart playback	event playback, mark playback,	
	Backup Mode			
Alarm	Alarm Input	HDD, burner, USB device, network ba	ackup	
Alalin	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does not support eSATA	A port	
	One HDD Space	6T	A poir	
Communication	Network	1 RJ45 port, 100Mbps Ethernet port		
Port	Communication	RS485 port		
	USB	2 USB2.0 ports(at the rear panel)		
Others	Power	DC12V		
	Power Consumption	≤7W	≤8W	
	(No HDD)			
	Working	-10℃−+55℃	•	
	Temperature			
	Working Humidity	10%~90%		
	Dimensions	SMART 1U case, 270mm(W)×205	mm (D) x41mm (H)	
	Weight (No HDD)	≤0.5KG	≤0.55KG	
	Installation Mode	Desk		

1.3.55 XVR510XC Series

	Parameters	XVR5104C	XVR5108C		
System	Main Processor Industrial embedded micro controller				
	OS	Embedded LINUX			
Video	Video Encode	H.264			
Parameters	Standard				
	Encode Resolution	1080P@15f/1080N/720P/960H/D1/HD1/2	2CIF/CIF/		
	Video Frame Rate	PAL:1~25f/s; NTSC: 1~30f/s			
	Video Bit Rate	32Kbps-6144Kbps			
	Bit Stream Type	Video stream/composite stream			
	Dual-Stream	Support			

	Parameters	XVR5104C	XVR5108C	
Audio	Encode Standard	G.711A/G.711U/PCM		
Parameters	Audio Sampling	8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video Input	4-ch BNC port(CVBS/CVI/AHD	8-ch BNC	
		/other analog HD video	port(CVBS/CVI/AHD/other	
		self-adaptive)	analog HD video self-adaptive)	
	Network Video Input	 There is no IP channel by default. Max add 2 IP channel connections Analog/digital channel switch. Max 6 IP channel connections Connection bandwidth:0Mbps-24Mbps 	default. Max add 4 IP channel connections	
			S	
	Video Output	1-channel VGA output,		
		1-channel HDMI output (of the same video source),		
		HDMI/ VGA video output at the same time.		
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	1-channel RCA port.		
	Coaxial Audio Input	N/A		
	Audio Output	1-channel RCA port.		
	Bidirectional Talk	Reuse the audio input/output port of the 1st channel.		
	Input			
Record	Record Mode	Schedule record/manual record/MD re		
	Playback Mode	nstant playback, normal playback, event playback, mark playback,		
		smart playback		
	Backup Mode	HDD, burner, USB device, network ba	ackup	
Alarm	Alarm Input	N/A		
	Alarm Output	N/A	-	
HDD	HDD Port	1 SATA port, does not support eSATA	A port	
	One HDD Space	6T		
Communication	Network	1 RJ45 port, 100Mbps Ethernet port		
Port	Communication	RS485 port		
0.1	USB	2 USB2.0 ports(at the rear panel)		
Others	Power	DC12V		
	Power Consumption (No HDD)	≤7W	≤8W	
	Working	-10℃−+55℃		

Parameters	XVR5104C	XVR5108C
Temperature	10%~90% SMART 1U case, 270mm (W) x205mm (D) x41mm (H)	
Working Humidity		
Dimensions		
Weight (No HDD)	≤0.5KG	≪0.55KG
Installation Mode	Desk	

1.3.56 XVR7104C Series

	Parameters	XVR7104C		
System	Main Processor	Industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	1080P/720P/960H/D1/HD1/2CIF/CIF		
	Resolution			
	Video Frame Rate	PAL:1~25f/s; NTSC: 1~30f/s		
	Video Bit Rate	32Kbps-6144Kbps		
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-ch BNC port(CVBS/CVI/AHD/other analog HD video		
	Input	self-adaptive)		
	Network Video	• There is no IP channel by default. Max add 2 IP channel		
	Input	connections		
		Analog/digital channel switch. Max 6 IP channel connections		
		Connection bandwidth:0Mbps-24Mbps		
	Video Output	1-channel VGA output,		
		1-channel HDMI output (of the same video source),		
		HDMI/ VGA video output at the same time.		
	Loop Output Matrix Output	N/A		
Audio Port	Audio Input	1-channel RCA port.		
	Coaxial Audio	N/A		
	Input			
	Audio Output	1-channel RCA port.		
1		· · ··································		
	Bidirectional	Reuse the audio input/output port of the 1st channel.		

	Parameters	XVR7104C
Record	Record Mode	Schedule record/manual record/MD record/Alarm record
	Playback Mode	Instant playback, normal playback, event playback, mark playback,
		smart playback
	Backup Mode	HDD, burner, USB device, network backup
Alarm	Alarm Input	N/A
	Alarm Output	N/A
HDD	HDD Port	1 SATA port, does not support eSATA port
	One HDD Space	6Т
Communication	Network	1 RJ45 port, 100Mbps Ethernet port
Port	Communication	RS485 port
	USB	2 USB2.0 ports(at the rear panel)
Others	Power	DC12V
	Power	≤8W
	Consumption	
	(No HDD)	
	Working	-10℃−+55℃
	Temperature	
	Working	10%~90%
	Humidity	
	Dimensions	SMART 1U case, 270mm (W) x205mm (D) x41mm (H)
	Weight (No	≤0.5KG
	HDD)	
	Installation	Desk
	Mode	

1.3.57 XVR41XXHE Series

	Parameters	XVR4104HE	XVR4108HE	XVR4116HE
System	Main Processor	Industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	1080N/720P/960H/	1080N@12f/720P@1	5f/960H/D1/HD1/2CIF
	Resolution	D1/HD1/2CIF/CIF	/CIF	
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s		
	Rate			
	Video Bit Rate	32Kbps-4096Kbps		
	Bit Stream Type	Video stream/compos	ite stream	
	Dual-Stream	Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz,16Bit		

	Parameters	XVR4104HE	XVR4108HE	XVR4116HE
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video Input	4-ch BNC port (CVBS/CVI/AHD /other analog HD video self-adaptive)	8-ch BNC port(CVBS/CVI/AHD /other analog HD video self-adaptive)	port(CVBS/CVI/A
	Network Video Input	 There is no IP channel by default. Max add 1 IP channel connection. Analog /digital channel switch. Max 5 IP channel connections Connection bandwidth:0Mbp s-20Mbps 	 There is no IP channel by default. Max add 2 IP channel connections Analog /digital channel switch. Max 10 IP channel connections Connection bandwidth:0Mbp s-40Mbps 	 channel by default. Max add 2 IP channel connections Analog
	Video Output	1-channel VGA output, 1-channel HDMI outpu HDMI/ VGA video outp	t (of the same video sou	rce),
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	Audio Input	4-channel RCA port.	8-channel RCA port.	16-channel RCA port.
	Coaxial Audio Input	N/A		
	Audio Output	1-channel RCA port.		
	Bidirectional Talk Input	Support (Reuse the a	udio port of the 1st chan	nel)
Record	Record Mode	Schedule record/manu	al record/MD record/Ala	rm record
	Playback Mode Instant playback, normal playback, event playback smart playback		back, mark playback,	
	Record Playback	Max 4-channel playback	Max 8-channel playback	Max 16-channel playback
	Backup Mode	HDD, burner, USB dev	ice, network backup	

	Parameters	XVR4104HE	XVR4108HE	XVR4116HE
Alarm	Alarm Input	8-channel input	8-channel input	16-channel input
	Alarm Output	3-channel output		
HDD	HDD Port	1 SATA port, does not	support eSATA port	
	One HDD Space	6T		
Communication	Network	1 RJ45 port, 100Mbps	Ethernet port	
Port	Communication	RS485 port		
	USB	2 USB2.0 ports(One at	the front panel and one	e at the rear panel)
Others	Power	DC12V		
	Power	≤7W	≪8W	≤10W
	Consumption		<000	<1000
	Working	-10°C-+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimensions	Mini 1U case, 325mm	(W) ×245mm (D) ×	45mm(H)
	Weight	≤1.1KG	≤1.25KG	≤1.45KG
	Installation	Desk		
	Mode			

1.3.58 XVR51XXH Series

	Parameters	XVR5104H	XVR5108H	XVR5116H	
System	Main Processor	Industrial embedded n	nicro controller		
	OS	Embedded LINUX			
Video	Video Encode	H.264			
Parameters	Standard				
	Encode	1080P@15fps/1080N/	720P/960H/D1/HD1/2CIF/	/CIF	
	Resolution				
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s			
	Rate				
	Video Bit Rate	32Kbps-6144Kbps			
	Bit Stream Type	Video stream/composi	te stream		
	Dual-Stream	Support			
Audio	Encode	G.711A/G.711U/PCM			
Parameters	Standard				
	Audio Sampling	8KHz, 16Bit			
	Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-ch BNC port	8-ch BNC	16-ch BNC	
	Input	(CVBS/CVI/AHD	port(CVBS/CVI/AHD	port(CVBS/CVI/A	
		/other analog HD	/other analog HD	HD /other analog	
		video self-adaptive)	video self-adaptive)	HD video	

	Parameters	XVR5104H	XVR5108H	XVR5116H
				self-adaptive)
	Network Video Input	 There is no IP channel by default. Max add 2 IP channel connections Analog /digital channel switch. Max 6 IP channel connections Connection bandwidth:0Mbp s-24Mbps 	 There is no IP channel by default. Max add 4 IP channel connections Analog /digital channel switch. Max 12 IP channel connections Connection bandwidth:0Mbp s-48Mbps 	 There is no IP channel by default. Max add 8 IP channel connections Analog /digital channel switch. Max 24 IP channel connections Connection bandwidth:0 Mbps-96Mbp s
	Video Output	1-channel VGA output, 1-channel HDMI output (of the same video source), HDMI/ VGA video output at the same time.		
	Loop Output	N/A		
	Matrix Output	N/A		VGA/HDMI optional
Audio Port	Audio Input	1-channel RCA port.		
	Coaxial Audio Input	N/A		
	Audio Output	1-channel RCA port.		
	Bidirectional Talk Input	Support (Reuse the a	udio port of the 1st chann	el)
Record	Record Mode	Schedule record/manu	al record/MD record/Alarr	n record
	Playback Mode	Instant playback, norm smart playback	al playback, event playba	ack, mark playback,
	Record	Max 4-channel	Max 8-channel	Max 16-channel
	Playback	playback	playback	playback
	Backup Mode	HDD, burner, USB dev	ice, network backup	
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does not support eSATA port		
	One HDD Space	ə 6T		
Communication Port	Network	1 RJ45 port, 100Mbps	Ethernet port	1 RJ45 port, 1000Mbps Ethernet port

	Parameters	XVR5104H	XVR5108H	XVR5116H	
	Communication	RS485 port			
	USB	2 USB2.0 ports(One a	2 USB2.0 ports(One at the front panel and one		
		at the rear panel)		and 1 USB3.0	
				port (One	
				USB2.0 port at	
				the front panel	
				and one USB3.0	
				port at the rear	
		panel)			
Others	Power	DC12V	1		
	Power	≤7W	≪8W	≤10W	
	Consumption				
	Working	-10°C-+55°C			
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions	Mini 1U case, 325mm	n (W) ×245mm (D) ×45	mm(H)	
	Weight	≤1.1KG	≤1.25KG	≤1.45KG	
	Installation	Desk			
	Mode				

1.3.59 XVR51XXHE Series

	Parameters	XVR5104HE XVR5108HE XVR5116HE		
System	Main Processor	Industrial embedded micro controller		
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	1080P@15f/720P/960H/D1/HD1/2CIF/CIF		
	Resolution			
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s		
	Rate			
	Video Bit Rate	32Kbps-6144Kbps		
	Bit Stream Type	Video stream/composite stream		
	Dual-Stream	Support		
Audio	Encode	G.711A/G.711U/PCM		
Parameters	Standard			
	Audio Sampling	8KHz, 16Bit		
	Rate			
	Audio Bit Rate	64Kbps		
Video Port	Analog Video	4-ch BNC port 8-ch BNC 16-ch BNC		
	Input	(CVBS/CVI/AHD port(CVBS/CVI/AHD port(CVBS/CVI/A		
		/other analog HD /other analog HD HD /other analog		

	Parameters	XVR5104HE	XVR5108HE	XVR5116HE
	Network Video	video self-adaptive) There is no IP 		HD video self-adaptive) • There is no IP
	Input	channel by default. Max add 2 IP channel connections • Analog /digital channel switch. Max 6 IP channel connections • Connection bandwidth:0Mbp s-24Mbps	 default. Max add 4 IP channel connections Analog /digital channel 	channel by default. Max add 8 IP channel connections • Analog /digital channel switch. Max 24 IP channel connections • Connection bandwidth:0 Mbps-96Mbp s
	Video Output	1-channel VGA output,1-channel HDMI output (of the same video source),HDMI/ VGA video output at the same time.		
	Loop Output Matrix Output	N/A N/A		VGA/HDMI optional
Audio Port	Audio Input	4-channel RCA port.	8-channel RCA port.	16-channel RCA port.
	Coaxial Audio Input	N/A	1	•
	Audio Output	1-channel RCA port.		
	Bidirectional Talk Input	Support (Reuse the a	udio port of the 1st chann	el)
Record	Record Mode Playback Mode		ial record/MD record/Alarr nal playback, event playba	
	Record Playback	Max 4-channel playback	playback	Max 16-channel playback
	Backup Mode	HDD, burner, USB dev		
Alarm	Alarm Input	8-channel input	8-channel input	16-channel input
HDD	Alarm Output HDD Port	3-channel output 1 SATA port, does no	t support eSATA port	
	One HDD Space	6T		

	Parameters	XVR5104HE	XVR5108HE	XVR5116HE
Communication Port	Network	1 RJ45 port, 100Mbps Ethernet port		1 RJ45 port, 1000Mbps Ethernet port
	Communication	RS485 port		
	USB	2 USB2.0 ports(One at the front panel and one at the rear panel)		1 USB2.0 port and 1 USB3.0 port (One USB2.0 port at the front panel and one USB3.0 port at the rear panel)
Others	Power	DC12V		
	Power Consumption	≤7W	≪8W	≤10W
	Working Temperature	-10°C-+55°C		
	Working Humidity	10%~90%		
	Dimensions	Mini 1U case, 325mm	ı (W) ×245mm (D) ×45	mm (H)
	Weight	≤1.1KG	≤1.25KG	≤1.45KG
	Installation Mode	Desk		

1.3.60 XVR71XXHE Series

	Parameters	XVR7104HE	XVR7108HE	XVR7116HE	
System	Main Processor	Industrial embedded micro controller			
	OS	Embedded LINUX			
Video	Video Encode	H.264			
Parameters	Standard				
	Encode	1080P/720P/960H/D1	/HD1/2CIF/CIF		
	Resolution				
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s			
	Rate				
	Video Bit Rate	32Kbps-6144Kbps			
	Bit Stream Type	Video stream/compos	site stream		
	Dual-Stream	Support			
Audio	Encode	G.711A/G.711U/PCM			
Parameters	Standard				
	Audio Sampling	8KHz, 16Bit			
	Rate				
	Audio Bit Rate	64Kbps			

	Parameters	XVR7104HE	XVR7108HE X	(VR7116HE
Video Port	Analog Video Input	4-ch BNC port (CVBS/CVI/AHD /other analog HD video self-adaptive)	port(CVBS/CVI/AHD /other analog HD video self-adaptive)	port(CVBS/CVI/A HD /other analog HD video self-adaptive)
	Network Video Input	 There is no IP channel by default. Max add 2 IP channel connection Analog /digital channel switch. Max 6 IP channel connections Connection bandwidth:0Mbp s-24Mbps 	 channel by default. Max add 4 IP channel connections Analog /digital channel 	 channel by default. Max add 8 IP channel connections Analog
	Video Output	HDMI/ VGA video outp	el VGA output, el HDMI output (of the same video source), GA video output at the same time.	
	Loop Output	N/A		
Audio Port	Matrix Output Audio Input	N/A 4-channel RCA port.	VGA/HDMI optional 8-channel RCA port.	16-channel RCA port.
	Coaxial Audio Input	N/A	•	
	Audio Output	1-channel RCA port.		
	Bidirectional Talk Input	Support (Reuse the a	udio port of the 1st chan	nel)
Record	Record Mode	Schedule record/manu	al record/MD record/Ala	rm record
	Playback Mode	Instant playback, norm smart playback	nal playback, event playb	back, mark playback,
	Record Playback	Max 4-channel playback	Max 8-channel playback	Max 16-channel playback
	Backup Mode	HDD, burner, USB dev	vice, network backup	
Alarm	Alarm Input	8-channel input	8-channel input	16-channel input
	Alarm Output	3-channel output		
HDD	HDD Port	1 SATA port, does no	t support eSATA port	

	Parameters	XVR7104HE	XVR7108HE	XVR7116HE	
	One HDD Space	6T			
Communication	Network	1 RJ45 port,	port, 1 RJ45 port, 1000Mbps Ethernet port		
Port		100Mbps Ethernet			
		port			
	Communication	RS485 port			
	USB	2 USB2.0 ports(One	1 USB2.0 port and	d 1 USB3.0 port (One	
		at the front panel and	USB2.0 port at the front panel and on		
		one at the rear panel)	USB3.0 port at the rear panel)		
Others	Power	DC12V			
	Power	≪8W	≤10W	≤15W	
	Consumption			< 15VV	
	Working	-10°C-+55°C			
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions	Mini 1U case, 325mn	m(W)×245mm(D)×45mm(H)		
	Weight	≤1.1KG	≤1.25KG	≤1.45KG	
	Installation	Desk			
	Mode				

1.3.61 XVR71XXH Series

	Parameters	XVR7104H	XVR7108H	XVR7116H	
System	Main Processor	Industrial embedded n	nicro controller		
	OS	Embedded LINUX			
Video	Video Encode	H.264			
Parameters	Standard				
	Encode	1080P/720P/960H/D1	/HD1/2CIF/CIF		
	Resolution				
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s			
	Rate				
	Video Bit Rate	32Kbps-6144Kbps			
	Bit Stream Type	Video stream/compos	ite stream		
	Dual-Stream	Support			
Audio	Encode	G.711A/G.711U/PCM			
Parameters	Standard				
	Audio Sampling	8KHz,16Bit			
	Rate				
	Audio Bit Rate	64Kbps			
Video Port	Analog Video	4-ch BNC port	8-ch BN	IC 16-ch BNC	
	Input	(CVBS/CVI/AHD	port(CVBS/CVI/AHE	D port(CVBS/CVI/A	
		/other analog HD	Ŭ	ID HD /other analog	
		video self-adaptive)	video self-adaptive)	HD video	

	Parameters	XVR7104H	XVR7108H X	VR7116H
				self-adaptive)
	Network Video Input	 There is no IP channel by default. Max add 2 IP channel connections Analog /digital channel switch. Max 6 IP channel connections Connection bandwidth:0Mbp s-24Mbps 	 There is no IP channel by default. Max add 4 IP channel connections Analog /digital channel switch. Max 12IP channel connections Connection bandwidth:0Mbp s-48Mbps 	 There is no IP channel by default. Max add 8 IP channel connections Analog /digital channel switch. Max 24 IP channel connections Connection bandwidth:0 Mbps-96Mbp s
	Video Output	1-channel VGA output, 1-channel HDMI output (of the same video source), HDMI/ VGA video output at the same time.		
	Loop Output	N/A	1	
	Matrix Output	N/A	VGA/HDMI optional	
Audio Port	Audio Input Coaxial Audio Input	1-channel RCA port. N/A		
	Audio Output	1-channel RCA port.		
	Bidirectional Talk Input	Support (Reuse the a	udio port of the 1st chanr	nel)
Record	Record Mode	Schedule record/manu	al record/MD record/Alar	m record
	Playback Mode	Instant playback, norm smart playback	al playback, event playb	ack, mark playback,
	Record	Max 4-channel	Max 8-channel	Max 16-channel
	Playback	playback	playback	playback
	Backup Mode	HDD, burner, USB dev	ice, network backup	
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does not	support eSATA port	
	One HDD Space	6T		
Communication Port	Network	1 RJ45 port, 100Mbps Ethernet port	1 RJ45 port, 1000Mbps	Ethernet port
	Communication	RS485 port		

	Parameters	XVR7104H	XVR7108H	XVR7116H
	USB	2 USB2.0 ports(One	1 USB2.0 port and 1 USB3.0 port (Or	
		at the front panel and	USB2.0 port at the	e front panel and one
		one at the rear panel)	USB3.0 port at the r	ear panel)
Others	Power	DC12V		
	Power	≪8W	≤10W	≤15W
	Consumption	~000		<15W
	Working	-10°C-+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimensions	Mini 1U case, 325mm	n(W)×245mm(D)×45mm(H)	
	Weight	≤1.1KG	≤1.25KG	≤1.45KG
	Installation	Desk		
	Mode			

1.3.62 XVR21XXHS Series

	Parameters	XVR2104HS	XVR2108HS	XVR2116HS	
System	Main Processor	Industrial embedded m	nicro controller		
	OS	Embedded LINUX			
Video	Video Encode	H.264			
Parameters	Standard				
	Encode	1080N@12f/720P@12	2f/960H/D1/HD1/2CIF/0	CIF	
	Resolution				
	Video Frame	PAL:1~25f/s; NTSC:	1~30f/s		
	Rate				
	Video Bit Rate	t Rate 32Kbps-4096Kbps			
Bit Stream Type Video stream				Video stream	
	Dual-Stream	Support			
Audio	Encode	N/A			
Parameters	Standard				
	Audio Sampling	N/A			
	Rate				
	Audio Bit Rate	N/A			
Video Port	Analog Video	4-ch BNC	8-ch BNC	16-ch BNC	
	Input	port(CVBS/CVI/AHD	port(CVBS/CVI/AHD	port(CVBS/CVI/AHD	
		/other analog HD	/other analog HD	/other analog HD	
		video self-adaptive)	video self-adaptive)	video self-adaptive)	
	Network Video	• There is no IP	• There is no IP	• There is no IP	
	Input	channel by	channel by	channel by	
		default. Max	default. Max	default. Max	
		add 0 IP	add 0 IP	add 0 IP	
		channel	channel	channel	

	Parameters	XVR2104HS	XVR2108HS	XVR2116HS	
	Video Output	connection Analog /digital channel switch. Max 2 IP channel connections Connection bandwidth:0Mb ps-8Mbps 1-channel VGA output 1-channel HDMI output HDMI/ VGA video output	ut (of the same video so	 connection Analog /digital channel switch. Max 2 IP channel connections Connection bandwidth:0Mb ps-8Mbps 	
	Loop Output	N/A			
	Matrix Output	N/A			
Audio Port	Audio Input	N/A			
	Coaxial Audio Input	N/A			
	Audio Output	N/A			
	Bidirectional Talk Input	N/A			
Record	Record Mode	Schedule record/manu	ual record/MD record/A	larm record	
	Playback Mode	Instant playback, norn smart playback	nal playback, event pla	yback, mark playback,	
	Backup Mode	HDD, burner, USB dev	vice, network backup		
Alarm	Alarm Input	N/A	•		
	Alarm Output	N/A			
HDD	HDD Port	1 SATA port, does no	t support eSATA port		
	One HDD Space	6T			
Communication	Network	1 RJ45 port, 100Mbps	Ethernet port		
Port	Communication	RS485 port			
	USB	2 USB2.0 ports(One a	t the front panel and or	ne at the rear panel)	
Others	Power	DC12V			
	Power	≤10W			
	Consumption				
	(No HDD)				
	Working	-10℃−+55℃			
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions		0mm (W) x220mm (I		
	Weight (No	≤1.25KG	≤1.35KG	≤1.45KG	

Parameters	XVR2104HS	XVR2108HS	XVR2116HS
HDD)			
Installation	Desk		
Mode			

1.3.63 XVR41XXHS Series

	Parameters	XVR4104HS	XVR4108HS	XVR4116HS
System	Main Processor	Industrial embedded m	icro controller	
	OS	Embedded LINUX		
Video	Video Encode	H.264		
Parameters	Standard			
	Encode	1080N/720P/960H/D1	1080N@12f/720P@15f	/960H/D1/HD1/2CI
	Resolution	/HD1/2CIF/CIF/	F/CIF/	
	Video Frame Rate	PAL:1~25f/s; NTSC:	1~30f/s	
	Video Bit Rate	32Kbps-4096Kbps		
	Bit Stream Type	Video stream/composit	e stream	
	Dual-Stream	Support		
Audio Parameters	Encode Standard	G.711A/G.711U/PCM		
	Audio Sampling Rate	8KHz, 16Bit		
	Audio Bit Rate	64Kbps		
Video Port	Analog Video Input	4-ch BNC port (CVBS/CVI/AHD /other analog HD video self-adaptive)	8-ch BNC port(CVBS/CVI/AHD /other analog HD video self-adaptive)	16-chBNCport(CVBS/CVI/AHD /other analogHDvideoself-adaptive)
	Network Video Input	 There is no IP channel by default. Max add 1 IP channel connection Analog /digital channel switch. Max 5 IP channel connections Connection bandwidth:0Mbp s-20Mbps 	 There is no IP channel by default. Max add 2 IP channel connections. Analog /digital channel switch. Max 10 IP channel connections Connection bandwidth:0Mbp s-40Mbps 	 There is no IP channel by default. Max add 2 IP channel connections Analog /digital channel switch. Max 18 IP channel connections Connection bandwidth:0 Mbps-56Mbp

	Parameters	XVR4104HS	XVR4108HS	XVR4116HS	
				S	
	Video Output	1-channel VGA output	3		
		1-channel HDMI outpu	It (of the same video sour	ce),	
		HDMI/ VGA video outp	out at the same time.		
	Loop Output	N/A			
	Matrix Output	N/A			
Audio Port	Audio Input	1-channel RCA port.			
	Coaxial Audio	N/A			
	Input				
	Audio Output	1-channel RCA port.			
	Bidirectional	Reuse the audio input	output port.		
	Talk Input				
Record	Record Mode	Schedule record/manu	al record/MD record/Alar	m record	
	Playback Mode	le Instant playback, normal playback, event playback, mark p			
		smart playback	smart playback		
	Record	Max 4-channel	Max 8-channel	Max 16-channel	
	Playback	playback	playback	playback	
	Backup Mode	HDD, burner, USB dev	vice, network backup		
Alarm	Alarm Input	N/A			
	Alarm Output	N/A			
HDD	HDD Port	1 SATA port, does no	t support eSATA port		
	One HDD Space	6T			
Communication	Network	1 RJ45 port, 100Mbps	Ethernet port		
Port	Communication	RS485 port			
	USB	2 USB2.0 ports(One a	t the front panel and one a	at the rear panel)	
Others	Power	DC12V			
	Power				
	Consumption	≪7W	≪8W	≪10W	
	(No HDD)				
	Working	-10°C-+55°C	·		
	Temperature				
	Working	10%~90%			
	Humidity				
	Dimensions	Compact 1U case, 260	0mm (W) ×220mm (D)	×44mm (H)	
	Weight (No HDD)	≪0.85KG	≤0.95KG	≤1.05KG	
	Installation	Desk	-		
	Mode				

1.3.64 XVR51XXHS Series

Param	eters XVR5104HS	XVR5108HS	XVR5116HS
-------	-----------------	-----------	-----------

	Parameters	XVR5104HS	XVR5108HS	XVR5116HS		
System	Main Processor	Industrial embedded m	nicro controller	•		
	OS	Embedded LINUX				
Video Parameters	Video Encode Standard	H.264				
	Encode Resolution		1080P@15f/1080N/720P/960H/D1/HD1/2CIF/CIF			
	Video Frame Rate	PAL:1~25f/s; NTSC: 1~30f/s				
	Video Bit Rate	32Kbps-6144Kbps				
	Bit Stream Type	Video stream/composi	te stream			
	Dual-Stream	Support				
Audio Parameters	Encode Standard	G.711A/G.711U/PCM				
	Audio Sampling Rate	8KHz, 16Bit				
	Audio Bit Rate	ie 64Kbps				
Video Port	Analog Video Input	4-ch BNC port (CVBS/CVI/AHD /other analog HD video self-adaptive)	8-ch BNC port(CVBS/CVI/AHD /other analog HD video self-adaptive)	port(CVBS/CVI/A HD /other analog HD video self-adaptive)		
	Network Video Input	 There is no IP channel by default. Max add 2 IP channel connections Analog /digital channel switch. Max 6 IP channel connections. Connection bandwidth:0Mbp s-24Mbps 	 There is no IF channel by default. Max add 4 IP channel connection Analog /digital channel switch. Max 12 IF channel connections. Connection bandwidth:0Mbps -48Mbps 	 channel by default.Max add 8 IP channel connections Analog /digital channel switch. Max 24 IP channel 		
	Video Output	HDMI/ VGA video outp	t (of the same video sou	ırce),		
	Loop Output	N/A				
	Matrix Output	N/A		VGA/HDMI optional		

	Parameters	XVR5104HS	XVR5108HS	XVR5116HS
Audio Port	Audio Input	1-channel RCA port.		
	Coaxial Audio	N/A		
	Input			
	Audio Output	1-channel RCA port.		
	Bidirectional	Reuse the audio input/output port of the 1 st channel.		
	Talk Input			
Record	Record Mode	Schedule record/manu	al record/MD record/Alar	m record
	Playback Mode	Instant playback, norm	nal playback, event playb	ack, mark playback,
		smart playback		
	Record	Max 4-channel	Max 8-channel	Max 16-channel
	Playback	playback	playback	playback
	Backup Mode	HDD, burner, USB dev	vice, network backup	•
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	1 SATA port, does no	t support eSATA port	
	One HDD Space	6T		
Communication	Network	1 RJ45 port, 100Mbps	1 RJ45 port,	
Port		1000Mbps		
		Ethernet port		
	Communication	RS485 port		
	USB	2 USB2.0 ports(One at the front panel and 1 USB2.0 port and		
		one at the rear panel) 1 USB3.0 por		
		(One USB2.0 por		
		at the front pan		
				and one USB3.0
				port at the rear
				panel)
Others	Power	DC12V		
	Power			
	Consumption	≪7W	≪8W	≤10W
	(No HDD)			
	Working	-10°C-+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimensions	Compact 1U case, 260	0mm (W) ×220mm (D)	x44mm (H)
	Weight (No HDD)	≪0.85KG	≪0.95KG	≤1.05KG
	Installation Mode	Desk		

1.3.65 XVR7104HS Series

	Parameters	XVR7104HS
System	Main Processor	Industrial embedded micro controller
	OS	Embedded LINUX
Video	Video Encode	H.264
Parameters	Standard	
	Encode	1080P/720P/960H/D1/HD1/2CIF/CIF
	Resolution	
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s
	Rate	
	Video Bit Rate	32Kbps-6144Kbps
	Bit Stream Type	Video stream/composite stream
	Dual-Stream	Support
Audio	Encode	G.711A/G.711U/PCM
Parameters	Standard	
	Audio Sampling	8KHz, 16Bit
	Rate	
	Audio Bit Rate	64Kbps
Video Port	Analog Video	
	Input	self-adaptive)
	Network Video	• There is no IP channel by default. Max add 2 IP channel
	Input	connections.
		Analog/digital channel switch. Max 6 IP channel connections
		Connection bandwidth: 0Mbps-24Mbps.
	Video Output	1-channel VGA output,
		1-channel HDMI output (of the same video source),
		HDMI/ VGA video output at the same time.
	Loop Output	N/A
	Matrix Output	N/A
Audio Port	Audio Input	1-channel RCA port.
	Coaxial Audio	N/A
	Input	
	Audio Output	1-channel RCA port.
	Bidirectional	Reuse the audio input/output port of the 1 st channel.
Deservel	Talk Input	
Record	Record Mode	Schedule record/manual record/MD record/Alarm record
	Playback Mode	Instant playback, normal playback, event playback, mark playback,
	Deeluur Mede	smart playback
Alarm	Backup Mode	HDD, burner, USB device, network backup
Alarm	Alarm Input	N/A
	Alarm Output	
HDD	HDD Port	1 SATA port, does not support eSATA port
	One HDD Space	6Т

	Parameters	XVR7104HS
Communication	Network	1 RJ45 port, 100Mbps Ethernet port
Port	Communication	RS485 port
	USB	2 USB2.0 ports(One at the front panel and one at the rear panel)
Others	Power	DC12V
	Power	≤8W
	Consumption	
	(No HDD)	
	Working	-10℃-+55℃
	Temperature	
	Working	10%~90%
	Humidity	
	Dimensions	Compact 1U case, 260mm (W) x220mm (D) x44mm (H)
	Weight (No	0.85KG
	HDD)	
	Installation	Desk
	Mode	

1.3.66 XVR42XXA Series

1.3.00 XVK42					
Model	Parameters	XVR4204A XVR4208A XVR4216A			
System	Main Processor	High-performance indus	trial embedded micro cor	ntroller	
	OS	Embedded LINUX			
Video	Video Encode	H.264			
	Standard				
	Encode	1080N/720P/	1080N@12f/720P@15	f/960H/D1/HD1/2	
	Resolution	960H/D1/HD1/	CIF/CIF		
		2CIF/CIF/			
	Video Frame	e PAL:1~25f/s; NTSC: 1~30f/s			
	Rate				
	Video Bit Rate	32Kbps \sim 4096Kbps			
	Bit Stream	Video stream/composite	stream		
	Туре				
	Dual-Stream	Support			
Audio	Encode	G.711A, G.711U, PCM			
	Standard				
	Audio	8KHz,16Bit			
	Sampling Rate				
	Audio Bit Rate	64Kbps			

Model	Parameters	XVR4204A	XVR4208A	XVR4216A
Video Port	Analog Video Input Network Video	 4-ch BNC port (CVBS/CVI/AHD /other analog HD video self-adaptive) There is no IP 	 8-ch BNC port(CVBS/CVI/AHD /other analog HD video self-adaptive) There is no IP 	16-ch BNC port(CVBS/CVI /AHD /other analog HD video self-adaptive) • There is
	Input	channel by default. Max add 1 IP channel connection Analog /digital channel switch. Max 5 IP channel connections Connection bandwidth:0Mbps- 20Mbps	channel by default. Max add 2 IP channel connections Analog /digital channel switch. Max 10 IP channel connections Connection bandwidth:0Mbps- 40Mbps	no IP channel by default. Max add 2 IP channel connectio ns Analog /digital channel switch. Max 18 IP channel connectio ns Connectio n bandwidth :0Mbps-56 Mbps
	Video Output	1-ch VGA output, 1-ch HDMI output,		
		HDMI/ VGA video output video source)	at the same time (VGA/H	DMI of the same
	Loop Output	N/A		
	Matrix Output	N/A		
Audio Port	External Audio Input	4-ch, RCA port,		
	Coaxial Audio Input	N/A		
	Audio Output	1-ch RCA port		
	Bidirectional Talk Input	Support (Reuse the aud	lio port of the 1 st channel)	
Record	Record Mode	Auto record, manual reco	ord, motion detect record,	alarm record

Model	Parameters	XVR4204A	XVR4208A	XVR4216A	
	Playback Mode	Instant playback, normal	playback, event playback	, mark playback,	
		smart playback			
	Record	Max 4-ch playback	Max 8-ch playback	Max 16-ch	
	Playback			playback	
	Backup Mode	HDD, burner, flash disk,	network backup.		
Alarm	Alarm Input	8-ch alarm input	8-ch alarm input	16-ch alarm input	
	Alarm Output	3-ch alarm output			
HDD	HDD Port	2 SATA ports. Does not	support eSATA port.		
	Space/HDD	6T			
Communication	Network	1 RJ45 port, 100Mbps Ethernet port			
Port	Communication	RS485 port			
	USB	2 USB2.0 ports(One at the front panel and one at the rear panel)			
Other	Power	DC12V			
	Power	≤7W	≤8W	≤10W	
	Consumption				
	(No HDD)				
	Working Temperature	-10℃−+55℃			
	Working Humidity	10%~90%			
	Dimension	1U case, 375mm (W) ×280mm (D) ×50mm (H)			
	Weight				
	(No HDD)	≤1.5KG	≤1.65KG	≤1.8KG	
	Installation	Desk installation			
	Mode				

1.3.67 XVR42XXAN Series

Model	Parameters	XVR4204AN	XVR4208AN	XVR4216AN
System	Main Processor	or High-performance industrial embedded micro controller		controller
	OS	Embedded LINUX		
Video	Video Encode	H.264		
	Standard			
	Encode	1080N/720P/960H/	1080N@12fps/720P@	015fps/960H/D1/HD1/
	Resolution Video Frame Rate		2CIF/CIF/	
			1~30f/s	
	Video Bit Rate	Bit Rate 32Kbps~4096Kbps		
Bit Stream Type		Video stream/compos	ite stream	
	Dual-Stream	Stream Support		

Audio	Encode	G.711A, G.711U, PCM
	Standard	
	Audio	8KHz,16Bit
	Sampling Rate	
	Audio Bit Rate	64Kbps
Video Port	Analog Video	4-ch BNC 8-ch BNC 16-ch BNC
	Input	port(CVBS/CVI/AHD port(CVBS/CVI/AHD port(CVBS/CVI/AHD
		/other analog HD /other analog HD /other analog HD
		video self-adaptive) video self-adaptive) video self-adaptive)
	Network Video	There is no IP There is no IP There is no IP
	Input	channel by channel by channel by
		default. Max default. Max default. Max
		add 1 IP add 2 IP add 2 IP
		channel channel channel
		connection connections connections
		Analog Analog Analog Analog
		/digital channel /digital channel /digital channel
		switch. Max 5 switch. Max 10 switch. Max 18
		IP channel IP channel IP channel
		connections connections connections
		Connection Connection Connection
		bandwidth:0Mb bandwidth:0Mb bandwidth:0Mb
		ps-20Mbps ps-40Mbps ps-56Mbps
	Video Output	1-ch VGA output,
		1-ch HDMI output,
		HDMI/ VGA video output at the same time (VGA/HDMI of the same
		video source)
	Loop Output	N/A
	Matrix Output	N/A
Audio Port	External	1-ch,RCA port
	Audio Input	
	Coaxial Audio	N/A
	Input	
	Audio Output	1-ch RCA port
	Bidirectional	Support (Reuse the audio port of the 1 st channel)
	Talk Input	
Record	Record Mode	Auto record, manual record, motion detect record, alarm record
	Playback Mode	Instant playback, normal playback, event playback, mark playback,
		smart playback
	Record	Max 16-ch playback
	Playback	
	Backup Mode	HDD, burner, flash disk, network backup.
Alarm	Alarm Input	N/A

	Alarm Output	N/A		
HDD	HDD Port	2 SATA ports. Does not support eSA	TA port.	
	Space/HDD	6Т		
Communication	Network	1 RJ45 port, 100Mbps Ethernet port		
Port	Communication	RS485 port		
	USB	2 USB2.0 ports(One at the front pane	el and one at the rear panel)	
Other	Power	DC12V		
	Power	≤10W	≤20W	
	Consumption			
	(No HDD)			
	Working	-10°C−+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimension	1U case, 375mm (W) x280mm (D) x50mm (H)	
	Weight	≤1.8KG	≤3.3KG	
	(No HDD)		<0.010	
	Installation	Desk installation		
	Mode			

1.3.68 XVR52XXA Series

Model	Parameters		XVR5204A	XVR5208A	XVR5216A
System	Main Process	sor	High-performance industrial embedded micro controller		roller
	OS		Embedded LINUX		
Video	Video Encode		H.264		
	Standard				
	Encode		1080P@15f/1080N/720P	/960H/D1/HD1/2CIF/CIF	
	Resolution				
	Video Fra	me	PAL:1~25f/s; NTSC: 1~	-30f/s	
	RateVideo Bit RateBitStreamType				
			32Kbps \sim 6144Kbps		
			Video stream/composite	stream	
	Dual-Stream		Support		
Audio	Encode		G.711A, G.711U, PCM		
	Standard				
	Audio		8KHz, 16Bit		
	Sampling Rate				
	Audio Bit Ra	te	64Kbps		

video Output 1-ch VGA output, Video Output 1-ch VGA output, 1-ch HDMI output, 1-ch HDMI output,
1-ch HDMI output,
HDMI/ VGA video output at the same time (VGA/HDMI of the same video source)
Loop Output N/A
Matrix Output N/A VGA/HDMI optional
Audio Port External 4-ch, RCA port,
Audio Input
Coaxial Audio N/A Input
Audio Output 1-ch RCA port
Bidirectional Support (Reuse the audio port of the 1 st channel) Talk Input Support (Reuse the audio port of the 1 st channel)
Record Record Mode Auto record, manual record, motion detect record, alarm record

	Playback Mode	Instant playback, norma smart playback	l playback, event playback	, mark playback,	
	Record Playback	Max 4-ch playback	Max 8-ch playback	Max 16-ch playback	
	Backup Mode	HDD, burner, flash disk,	network backup.		
Alarm	Alarm Input	8-ch alarm input	8-ch alarm input	16-ch alarm input	
	Alarm Output	3-ch alarm output			
HDD	HDD Port	2 SATA ports. Does not	support eSATA port.		
	Space/HDD	6T			
Communicatio n Port	Network	1 RJ45 port, 100Mbps Ethernet port1100		1 RJ45 port, 1000Mbps Ethernet port	
	Communicatio n	RS485 port	RS485 port		
	USB	the rear panel)	the front panel and one at	1 USB2.0 portand 1 USB3.0port(OneUSB2.0 port atthe front panelandOneUSB3.0 port atthe rear panel)	
Other	Power	DC12V			
	Power Consumption (No HDD)	≤7W	≤8W	≤10W	
	Working Temperature	-10℃-+55℃			
	Working Humidity	10%~90%			
Dimension		1U case, 375mm (W) x280mm (D) x50mm (H)			
	Weight (No HDD)	≤1.5KG	≤1.65KG	≤1.8KG	
	Installation Mode	Desk installation			

1.3.69 XVR52XXAN Series

Model	Parameters	XVR5204AN	XVR5208AN	XVR5216AN
System	Main Processor	High-performance industrial embedded micro controller		controller
	OS	Embedded LINUX		
Video	Video Encode	H.264		
	Standard			

	Encode		
	Encode	1080P@15f/1080N/720P/960H/D1/HD1/2CIF/CIF	
	Resolution		
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s	
	Rate		
	Video Bit Rate	32Kbps~6144Kbps	
	Bit Stream	Video stream/composite stream	
	Туре		
	Dual-Stream	Support	
Audio	Encode	G.711A, G.711U, PCM	
	Standard		
	Audio	8KHz,16Bit	
	Sampling Rate		
	Audio Bit Rate	64Kbps	
Video Port	Analog Video	4-ch BNC port 8-ch BNC 16-ch BN	IC
	Input	(CVBS/CVI/AHD port(CVBS/CVI/AHD port(CVBS/CVI/AH	ID
		/other analog HD /other analog HD /other analog H	ID
		video self-adaptive) video self-adaptive) video self-adaptive	;)
	Network Video	There is no IP There is no IP There is no IP There is no IP	IP
	Input	channel by channel by channel	by
		default. Max default. Max default. Ma	ax
		add 2 IP add 4 IP add 8	IP
		channel channel channel	
		connections connections connections	
		Analog Analog Analog Analog	
		/digital channel /digital channel /digital channe	əl
		switch. Max 6 switch. Max 12 switch. Max 2	24
		IP channel IP channel IP chann	nel
		connections connections connections	
		Connection Connection Connection	
		bandwidth:0Mb bandwidth:0Mb bandwidth:0M	b
		ps-24Mbps ps-48Mbps ps-96Mbps	
	Video Output	1-ch VGA output,	
		1-ch HDMI output,	
		HDMI/ VGA video output at the same time (VGA/HDMI of the san	ne
		video source)	
	Loop Output	N/A	
	Matrix Output	N/A VGA/HDMI optiona	al
Audio Port	External	1-ch, RCA port	
	Audio Input		
	Coaxial Audio	N/A	
	Input		
		1.ch PCA port	
	Audio Output	1-ch RCA port	

	Bidirectional Talk Input	Support (Reuse the a	audio port of the 1 st cha	nnel)
Record	Record Mode	Auto record, manual record, motion detect record, alarm record		cord, alarm record
	Playback Mode	Instant playback, norn smart playback	nal playback, event play	yback, mark playback,
	Record	Max 16-ch playback		
	Playback			
	Backup Mode	HDD, burner, flash dis	sk, network backup.	
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	2 SATA ports. Does n	ot support eSATA port.	
	Space/HDD	6T		
Communication Port	Network	ation RS485 port 2 USB2.0 ports(One at the front panel and one at the rear panel)		1 RJ45 port, 1000Mbps Ethernet port
	Communication			
	USB			1 USB2.0 port and 1 USB3.0 port (One USB2.0 port at the front panel and one USB3.0 port at the rear panel)
Other	Power	DC12V		
	Power Consumption (No HDD)	≤7W	≤8W	≤10W
	Working Temperature	-10°C-+55°C		
	Working Humidity	10%~90%		
	Dimension 1U case, 37		/) x280mm (D) x50n	nm (H)
	Weight (No HDD)	≤1.5KG	≤1.65KG	≤1.8KG
	Installation Mode	Desk installation		

1.3.70 XVR72XXA Series

Model	Parameters	XVR7204A	XVR7208A	XVR7216A
System	Main Processor	High-performance industrial embedded micro controller		controller
	OS	Embedded LINUX		
Video	Video Encode	H.264		
	Standard			

	Encode	1080P/720P/960H/D1/HD1/2CIF/CIF
	Resolution	
	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s
	Rate	
	Video Bit Rate	32Kbps~6144Kbps
	Bit Stream	Video stream/composite stream
	Туре	
	Dual-Stream	Support
Audio	Encode	G.711A, G.711U, PCM
	Standard	
	Audio	8KHz,16Bit
	Sampling Rate	
	Audio Bit Rate	64Kbps
Video Port	Analog Video	4-ch BNC port 8-ch BNC 16-ch BNC
	Input	(CVBS/CVI/AHD port(CVBS/CVI/AHD port(CVBS/CVI/AHD /other analog HD /other analog HD /other analog HD
		/other analog HD /other analog HD /other analog HD video self-adaptive) video self-adaptive) video self-adaptive)
	Network Video	● There is no IP ● There is no IP ● There is no IP
	Input	channel by channel by channel by
	input	default. Max default. Max default. Max
		add 2 IP add 4 IP add 8 IP
		channel channel channel
		connections. connections connections
		Analog Analog Analog
		/digital channel /digital channel /digital channel
		switch. Max 6 switch. Max 12 switch. Max 24
		IP channel IP channel IP channel
		connections connections connections
		Connection Connection Connection
		bandwidth:0Mb bandwidth:0Mb bandwidth:0Mb
		ps-24Mbps ps-48Mbps ps-96Mbps
	Video Output	1-ch VGA output,
		1-ch HDMI output,
		HDMI/ VGA video output at the same time (VGA/HDMI of the same
		video source)
	Loop Output	
	Matrix Output	N/A VGA/HDMI optional
Audio Port	External	4-ch, RCA port,
	Audio Input	
	Coaxial Audio	N/A
	Input	
	Audio Output	1-ch RCA port
	1	1

	Disting of a wal			
	Bidirectional	Support (Reuse the audio port of the 1 st channel)		
	Talk Input			
Record	Record Mode			cord, alarm record
	Playback Mode			yback, mark playback,
	Record	Max 4-ch playback	Max 8-ch playback	Max 16-ch playback
	Playback			
	Backup Mode	HDD, burner, flash dis	sk, network backup.	
Alarm	Alarm Input	8-ch alarm input	8-ch alarm input	16-ch alarm input
	Alarm Output	3-ch alarm output		
HDD	HDD Port	2 SATA ports. Does not support eSATA port. 6T		
	Space/HDD			
Communication	Network	1 RJ45 port,	1 RJ45 port, 1000Mb	os Ethernet port
Port		100Mbps Ethernet		
		port		
	Communication	RS485 port		
	USB	2 USB2.0 ports(One	1 USB2.0 port and	1 USB3.0 port (One
		at the front panel	USB2.0 port at the	front panel and one
		and one at the rear	USB3.0 port at the rea	ar panel)
		panel)		
Other	Power	DC12V		
	Power	≤8W	≤10W	≤15W
	Consumption			
	(No HDD)			
	Working	-10°C-+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimension	1U case, 375mm (W) x280mm (D) x50mm (H)		
	Weight			
	(No HDD)	≤1.5KG	≤1.65KG	≤1.8KG
	Installation	Desk installation		
	Mode			

1.3.71 XVR72XXAN Series

Model	Parameters	XVR7204AN	XVR7208AN	XVR7216AN
System	Main Processor	High-performance industrial embedded micro controller		controller
	OS Embedded LINUX			
Video	Video Encode H.264			
	Standard			
Encode		1080P/720P/960H/D1/HD1/2CIF/CIF		
	Resolution			

	Video Frame	PAL:1~25f/s; NTSC: 1~30f/s	
	Rate		
	Video Bit Rate	32Kbps~6144Kbps	
	Bit Stream	Video stream/composite stream	
	Туре		
	Dual-Stream	Support	
Audio	Encode	G.711A, G.711U, PCM	
	Standard		
	Audio	8KHz,16Bit	
	Sampling Rate		
	Audio Bit Rate	64Kbps	
Video Port	Analog Video	4-ch BNC port 8-ch BNC 16-ch BNC	
	Input	(CVBS/CVI/AHD port(CVBS/CVI/AHD port(CVBS/CVI/AHD	
		/other analog HD /other analog HD /other analog HD	
		video self-adaptive) video self-adaptive) video self-adaptive)	
	Network Video	There is no IP There is no IP There is no IP	
	Input	channel by channel by channel by	
		default. Max default. Max default. Max	
		add 2 IP add 4 IP add 8 IP	
		channel channel channel	
		connections. connections connections	
		Analog Analog Analog Analog	
		/digital channel /digital channel /digital channel	
		switch. Max 6 switch. Max 12 switch. Max 24	
		IP channel IP channel IP channel connections connections connections	
		Connection Connection Connection Connection	
		bandwidth:0Mb bandwidth:0Mb bandwidth:0Mb ps-24Mbps ps-48Mbps ps-96Mbps	
		1-ch VGA output,	
	Video Output	1-ch HDMI output,	
		HDMI/ VGA video output at the same time (VGA/HDMI of the same	
		video source)	
	Loop Output	N/A	
	Matrix Output	N/A VGA/HDMI optional	
Audio Port	External	1-ch, RCA port,	
	Audio Input		
	Coaxial Audio	N/A	
	Input		
	Audio Output	1-ch RCA port	
	Bidirectional	rectionalSupport (Reuse the audio port of the 1 st channel)	
	Talk Input		

Record	Record Mode	Auto record, manual record, motion detect record, alarm record		
	Playback Mode	smart playback		
	Record	Max 4-ch playback	Max 8-ch playback	Max 16-ch playback
	Playback			
	Backup Mode	HDD, burner, flash disk, network backup.		
Alarm	Alarm Input	N/A		
	Alarm Output	N/A		
HDD	HDD Port	2 SATA ports. Does not support eSATA port. 6T		
	Space/HDD			
Communication	Network	1 RJ45 port,	rt, 1 RJ45 port, 1000Mbps Ethernet port	
Port		100Mbps Ethernet		
		port		
	Communication	RS485 port		
	USB	2 USB2.0 ports(One	1 USB2.0 port and	1 USB3.0 port (One
		at the front panel	USB2.0 port at the	front panel and one
		and one at the rear	USB3.0 port at the re-	ar panel)
		panel)		
Other	Power	DC12V		
	Power	≤8W	≤10W	≤15W
	Consumption			
	(No HDD)			
	Working	-10°C-+55°C		
	Temperature			
	Working	10%~90%		
	Humidity			
	Dimension	1U case, 375mm (W) x280mm (D) x50mm (H)		
	Weight (No HDD)	≤1.5KG	≤1.65KG	≤1.8KG
	Installation	Desk installation	1	1
	Mode			

2 Overview and Controls

This section provides information about front panel and rear panel. When you install this series DVR for the first time, please refer to this part first.

2.1 Front Panel

2.1.1 HCVR5104C/HCVR51XXC-V2/HCVR71XXC-V2/ HCVR4104/4108C-S2/ HCVR5104 5108C-S2/ HCVR7104C-S2/ HCVR2108C-S2/ HCVR410XC-S3/HCVR510XC-S3/7104C-S3/ XVR410XC/XVR510XC/7104C Series

The front panel is shown as below. See Figure 2-7.




Figure 2-1

Please refer to the following sheet for front panel button information.

SN	Name	Function
1	HDD status indictor light	The red light becomes on when HDD is abnormal.
2	Power indicator light	The red light becomes on when the power connection is OK.
3	Network status indicator light	The red light becomes on when the network connection is abnormal.

2.1.2 HCVR51XXH/HCVR51XXHE/ HCVR51XXH-V2 / HCVR51XXHE-V2/HCVR71XXH-V2 / HCVR71XXHE-V2 Series

The front panel is shown as below. See Figure 2-7.




Fig	ure	2-2

Please refer to the following sheet for front panel button in	nformation.
I loade feler to the felewing sheet for here parter batter in	normation.

SN	lcon	Name	Function
1	N.	USB port	To connect USB storage device, USB mouse and etc.
2	Alarm	Alarm indicator light	When an alarm occurs, the light becomes red to alert you.
3	NET	Network abnormal indicator light	Network error occurs or there is no network connection, the light becomes red to alert you.
3	HDD	HDD abnormal indicator light	HDD error occurs or HDD capacity is below specified threshold value, the light becomes red to alert you.
5	IR	IR Receiver	It is to receive the signal from the remote control.
6			Go to previous menu, or cancel current operation.
	ESC	ESC	When playback, click it to restore real-time monitor mode.
7	FN	Assist	One-window monitor mode, click this button to display assistant function: PTZ control and image color. Backspace function: in numeral control or text control, press it for 1.5seconds to delete the previous character before the cursor. In motion detection setup, working with Fn and direction keys to realize setup. In text mode, click it to switch between numeral, English character(small/capitalized) and etc. Realize other special functions.
8	Enter	ENTER	Confirm current operation Go to default button Go to menu
9	Ċ	Power button	Power button, press this button for three seconds to boot up or shut down DVR.
	▲、 ▼	Up Down	Activate current control, modify setup, and then move up and down. Increase/decrease numeral. Assistant function such as PTZ menu.
	◀、▶	Left Right	Shift current activated control, When playback, click these buttons to control playback bar.

2.1.3 HCVR51XXHC/ HCVR51XXHC-V2/ HCVR71XXHC-V2 Series

The interface is shown as below. See Figure 2-3.




Figure 2-3

Please refer to the following sheet for front panel button information.

SN	Icon	Name	Function
1	NET	Network abnormal	Network error occurs or there is no network
		indicator light	connection, the light becomes red to alert you.
2	PWR	Power indicator light	The red light becomes on when the power connection is OK.
		light	CONNECTION IS OK.
3	HDD	HDD abnormal	HDD error occurs or HDD capacity is below
		indicator light	specified threshold value, the light becomes red
			to alert you.

2.1.4 HCVR41XXHE-S2/ HCVR51XXH-S2/ HCVR51XXHE-S2/ HCVR710XH-S2/ HCVR710XHE-S2/ HCVR41XXHE-S3/HCVR51XXHE-S3/HCVR71XXH-S3/HCVR71X XHE-S3 /HCVR41XXHS-S2/ HCVR21XXHS-S2/ HCVR21XXHS-S3/HCVR41XXHS-S3/51XXHS-S3/7104HS-S3/ XVR41XXHE/XVR51H/XVR51XXHE/XVR71XXH/XVR71XXHE /HCVR41XXHS-S2/ HCVR21XXHS-S2/ XVR21XXHS/XVR41XXHS/51XXHS/7104HS/HCVR71XX-4M Series

The front panel is shown as below. See Figure 2-6.




Figure 2-4

Please refer to the following sheet for front panel button information.

Icon	Name	Function
HDD	HDD status indicator	The blue light is on when the HDD is malfunction.
	light	
NET	Network status indicator	The blue light is on when the network connection is
	light	abnormal.
POWER	Power status indicator light	The blue light is on when the power connection is
		OK.

Icon	Name	Function
مچ ه	USB2.0 port	Connect to peripheral USB 2.0 storage device,
		mouse, burner and etc.

2.1.5 HCVR52XXA-V2/ HCVR72XXA-V2 Series

The front panel is shown as below. See Figure 2-5.





Please refer to the following sheet for front panel button information.

Name	Icon	Function
Power button	Ċ	Power button, press this button for three seconds to boot up or shut down DVR.
Shift	Shift	In textbox, click this button to switch between numeral, English(Small/Capitalized),donation and etc.
		Activate current control, modify setup, and then move up and down.
Up/1Down/4	▲ 、▼	Increase/decrease numeral.
		Assistant function such as PTZ menu.
		In text mode, input number 1/4 (English character G/H/I)
		Shift current activated control,
Left/2 Right/3	• •	When playback, click these buttons to control playback bar. In text mode, input number 2(English character A/B/C) /3(English character D/E/F)
ESC ES	ESC	Go to previous menu, or cancel current operation.
		When playback, click it to restore real-time monitor mode.
		Confirm current operation
Enter	ENTER	Go to default button
		Go to menu
Record	REC	Manually stop/start recording, working with direction keys or numeral keys to select the recording channel.
Slow play/8	ŀ	Multiple slow play speeds or normal playback. In text mode, input number 8 (English character T/U/V).

		One-window monitor mode, click this button to display assistant function: PTZ control and image color.
		Backspace function: in numeral control or text control, press it for 1.5seconds to delete the previous character before the
Assistant	Fn	In motion detection setup, working with Fn and direction keys to realize setup.
		In text mode, click it to switch between numeral, English character(small/capitalized) and etc.
		Realize other special functions.
Fast play/7	••	Various fast speeds and normal playback. In text mode, input number 7 (English character P/Q/R/S).
Play previous/0	◀	In playback mode, playback the previous video In text mode, input number 0.
Reverse/Pause/6	◄	In normal playback or pause mode, click this button to reverse playback In reverse playback, click this button to pause playback.
Play Next/9	▶	In playback mode, playback the next video In menu setup, go to down ward of the dropdown list. In text mode, input number 9 (English character W/X/Y/Z)
Play/Pause /5	►	In normal playback click this button to pause playback In pause mode, click this button to resume playback. In text mode, input number 5(English character J/K/L).
USB port	~ * \$*	To connect USB storage device, USB mouse.
Network abnormal indication light	Net	Network error occurs or there is no network connection, the light becomes red to alert you.
HDD abnormal indication light	HDD	HDD error occurs or HDD capacity is below specified threshold value, the light becomes red to alert you.
Record light	1-16	System is recording or not. It becomes on when system is recording.
IR Receiver	IR	It is to receive the signal from the remote control.

2.1.6 HCVR42XXA-S2/ HCVR42XXAN-S2/ HCVR52XXA-S2/ HCVR5216AN-S2/HCVR720XA-S2/

HCVR42XXA-S3/HCVR42XXAN-S3/HCVR52XXA-S3/HCVR52XXAN-S3/HCVR72XXA-S3/HCVR7216AN-S3/XVR42XXA/XVR42XXAN/XVR 52XXA/XVR52XXAN/XVR72XXA/XVR7216AN/HCVR 72XXAN-4M Series

The front panel is shown as below. See Figure 2-6.




Figure 2-6

Please refer to the following sheet for front panel button information.

lcon	Name	Function
STATUS	Status indicator light	The blue light is on when the device is working
		properly.
HDD	HDD status indicator	The blue light is on when the HDD is malfunction.
	light	
NET	Network status indicator	The blue light is on when the network connection is
	light	abnormal.
POWER	Power status indicator light	The blue light is on when the power connection is
		OK.
م ی ا	USB2.0 port	Connect to peripheral USB 2.0 storage device,
		mouse, burner and etc.

2.1.7 HCVR42XXL-S2/HCVR44XXL-S2 Series

The front panel is shown as below. See Figure 2-7.




Figure 2-7

Please refer to the following sheet for front panel button information.

lcon	Name	Function
STATUS	Status indicator light	The blue light is on when the device is working properly.
HDD	HDD status indicator light	The blue light is on when the HDD is malfunction.
NET	Network status indicator light	The blue light is on when the network connection is abnormal.
POWER	Power status indicator light	The blue light is on when the power connection is OK.

Icon	Name	Function
م یں	USB2.0 port	Connect to peripheral USB 2.0 storage device,
		mouse, burner and etc.

2.1.8 HCVR52XXL-V2/ HCVR54XXL-V2 Series

The front panel is shown as in Figure 2-8.




Figure 2-8

Please refer to the following sheet for front panel button information.

Name	Icon	Function
Power button	Ċ	Power button, press this button for three seconds to boot up or shut down DVR.
Shift	Shift	In textbox, click this button to switch between numeral, English(Small/Capitalized),donation and etc.
Up/1 Down/4	▲、 ▼	Activate current control, modify setup, and then move up and down.
		Increase/decrease numeral.
		Assistant function such as PTZ menu.
		In text mode, input number 1/4 (English character G/H/I)
Left/2 Right/3	• •	Shift current activated control,
		When playback, click these buttons to control playback bar. In text mode, input number 2(English character A/B/C) /3(English character D/E/F)
ESC	ESC	Go to previous menu, or cancel current operation.
		When playback, click it to restore real-time monitor mode.
Enter	ENTER	Confirm current operation
		Go to default button
		Go to menu
Record	REC	Manually stop/start recording, working with direction keys or numeral keys to select the recording channel.

Slow play/8		Multiple slow play speeds or normal playback.		
	_	In text mode, input number 8 (English character T/U/V).		
Assistant Fn		One-window monitor mode, click this button to display		
		assistant function: PTZ control and image color.		
		Backspace function: in numeral control or text control, press		
		it for 1.5seconds to delete the previous character before the		
		In motion detection setup, working with Fn and direction keys		
		to realize setup.		
		In text mode, click it to switch between numeral, English		
		character(small/capitalized) and etc.		
		Realize other special functions.		
Fast play/7	•	Various fast speeds and normal playback.		
		In text mode, input number 7 (English character P/Q/R/S).		
Play previous/0	◀	In playback mode, playback the previous video		
		In text mode, input number 0.		
Reverse/Pause/6	◀	In normal playback or pause mode, click this button to		
		reverse		
		playback		
		In reverse playback, click this button to pause playback.		
Play Next/9		In playback mode, playback the next video		
		In menu setup, go to down ward of the dropdown list.		
		In text mode, input number 9 (English character W/X/Y/Z)		
Play/Pause /5	► II	In normal playback click this button to pause playback		
		In pause mode, click this button to resume playback.		
		In text mode, input number 5(English character J/K/L).		
USB port	ب	To connect USB storage device, USB mouse.		
Network	Net	Network error occurs or there is no network connection, the		
abnormal		light becomes red to alert you.		
indication light				
HDD abnormal	HDD	HDD error occurs or HDD capacity is below specified		
indication light		threshold value, the light becomes red to alert you.		
Record light	1-16	System is recording or not. It becomes on when system is recording.		

2.1.9 HCVR58XXS-V2 Series

This series products' front panel is shown as below. See Figure 2-9.

1 8 8 4 8 8 7 8 9 10 1 8 10 10 8 10 100 - 100 AC		
	L 2ARC 2017 () 468 5.K. 6640 ()	
	Zeons Bruv Bwayz	

Figure 2-9

Please refer to the following sheet for front panel button information.

Name	Icon	Function		
Power button	ባ	Power button, press this button for three seconds to boot up or shut down DVR.		
Number button	0-9	Input Arabic number Switch channel		
Input number more than 10	-/	If you want to input a number more than 10, please click this button and then input.		
Shift	↑	In textbox, click this button to switch between numeral, English(Small/Capitalized),donation and etc. Enable or disable tour.		
Fast play	*	Various fast speeds and normal playback.		
Slow play	Þ	Multiple slow play speeds or normal playback.		
Play/Pause	► II	In normal playback click this button to pause playback In pause mode, click this button to resume playback.		
Reverse/Pause	◄	In normal playback or pause mode, click this button to reverse playback In reverse playback, click this button to pause playback.		
Play previous		In playback mode, playback the previous video		
Play Next	▶	In playback mode, playback the next video In menu setup, go to down ward of the dropdown list.		
Up/		Activate current control, modify setup, and then move up and down.		
Down	▲ 、 ▼	Increase/decrease numeral.		
		Assistant function such as PTZ menu.		
Left/	• •	Shift current activated control, and then move left and right.		
Right		When playback, click these buttons to control playback bar.		

		Go to previous menu, or cancel current operation.	
ESC	ESC	When playback, click it to restore real-time monitor mode.	
		Confirm current operation	
Enter	ENTER	Go to default button	
		Go to menu	
		One-window monitor mode, click this button to display assistant function: PTZ control and image color.	
		Backspace function: in numeral control or text control, press it for 1.5 seconds to delete the previous character before the cursor.	
Accietant	5-	In motion detection setup, working with Fn and direction keys to realize setup.	
Assistant	Fn	In text mode, click it to switch between numeral, English character(small/capitalized) and etc.	
		In HDD management interface, you can click it to switch HDD record information and other information (Menu prompt)	
		Realize other special functions.	
Record	REC	Manually stop/start recording, working with direction keys or numeral keys to select the recording channel.	
Window switch	Mult	Click it to switch one-window/multiple-window.	
Shuttle(outer ring)		In real-time monitor mode it works as left/right direction key. Playback mode, counter clockwise to forward and clock wise to backward.	
Jog(inner dial)		Up/down direction key. Playback mode, turn the inner dial to realized frame by frame playback. (Only applies to some special versions.)	
USB port	دي .	To connect USB storage device, USB mouse, burner and etc.	
		For 4/8/16 channel device: indication light on means that the channel is in recording.	
Record light	1-32	For 32 channel device: Indication Light on: 1-16 channel is in recording Indication Light flashes: 17-32 channel is in recording Indication Light normally on: the corresponding channels are in recording	
Remote control indication light	ACT	Remote control indication light	

Status indication light	Status	The light is on if device operates properly.
Power indication light	PWR	Power indication light
IR Receiver	IR	It is to receive the signal from the remote control.

2.1.10 HCVR48XXS-S2 Series

The front panel is shown as below. See Figure 2-10.




Figure 2-10

Please refer to the following sheet for front panel button information.

lcon	Name	Function
STATUS	Status indicator light	The blue light is on when the device is working
		properly.
HDD	HDD status indicator	The blue light is on when the HDD is malfunction.
	light	
NET	Network status indicator	The blue light is on when the network connection is
	light	abnormal.
POWER	Power status indicator light	The blue light is on when the power connection is
		OK.
~ G	USB2.0 port	Connect to peripheral USB 2.0 storage device,
		mouse, burner and etc.

2.2 Rear Panel

2.2.1 HCVR5104C Series

The HCVR5104C rear panel is shown as below. See Figure 2-11.





Figure 2-11

Please refer to the following sheet for detailed information.

SN	Icon	Name	Note
1	VIDEO IN	Video input port	Connect to analog camera, video
			input signal.
2	•	USB2.0 port	Connect to USB storage device,
			mouse, burning DVD-ROM and
			etc.
3	VGA	VGA video output	VGA video output port. Output
		port	analog video signal. Can connect
			to the monitor to view ananlog
			video output.
4	HDMI	High definition	High definition audio and video
		media interface	signal output port. It transmits
			uncompressed high definition
			video and multiple-channel data to
			the HDMI port of the display
			device.
5		Network port	100M Ethernet port
6	DC 12V 	Power input port	Input 12V DC.
7	Ŧ	GND	Ground end


2.2.2 HCVR5104C-V2/HCVR5108C-V2 Series

The HCVR5104C-V2 rear panel is shown as below. See Figure 2-12.





The HCVR5108C-V2 rear panel is shown as below. See Figure 2-13.





SN	Icon	Name	Note
1	Ŧ	GND	Ground end
2	DC 12V -C-	Power input port	Input 12V DC.
3		Network port	100M Ethernet port
4	VGA	VGA video output	VGA video output port. Output
		port	analog video signal. Can connect
			to the monitor to view ananlog
			video output.
5	HDMI	High definition	High definition audio and video
		media interface	signal output port. It transmits
			uncompressed high definition

			video and multiple-channel data to the HDMI port of the display device.
6	•	USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.
7	VIDEO IN	Video input port	Connect to analog camera, video input signal.

2.2.3 HCVR7104C-V2 Series

The HCVR7104C-V2 rear panel is shown as below. See Figure 2-14.




Figure 2-14

SN	lcon	Name	Note
1	Ŧ	GND	Ground end
2	VGA	VGA video output	VGA video output port. Output
		port	analog video signal. Can connect
			to the monitor to view ananlog
			video output.
3	•	USB2.0 port	Connect to USB storage device,
			mouse, burning DVD-ROM and
			etc.
4	VIDEO IN	Video input port	Connect to analog camera, video
			input signal.
5	DC 12V -G-	Power input port	Input 12V DC.
6	HDMI	High definition	High definition audio and video
		media interface	signal output port. It transmits
			uncompressed high definition

		video and multiple-channel data to the HDMI port of the display device.
7	Network port	100M Ethernet port

2.2.4 HCVR4104/HCVR4108C-S2/HCVR2108C-S2 Series

The HCVR4104C-S2 series rear panel is shown as below. See Figure 2-15.




Figure 2-15

The HCVR4108C-S2/HCVR2108C-S2 series rear panel is shown as below. See Figure 2-16.




Figure 2-16

SN	Icon	Name	Note
1	Ť	GND	Ground end
2	•	USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.

3	6	Network port	100M Ethernet port
4	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
5	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
6	VIDEO IN	Video input port	Connect to analog camera, video input signal.
7	DC 12V 	Power input port	Input 12V DC.
8	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
9	AUDIO OUT	Audio output port	Connect to video output device such as sound box.

2.2.5 HCVR5104/5108C-S2 Series

The HCVR5104C-S2 series rear panel is shown as below. See Figure 2-17.




Figure 2-17

The HCVR5108C-S2 series rear panel is shown as below. See Figure 2-18.




Figure 2-18

Please refer to the following sheet for detailed information.

SN	lcon	Name	Note
1	Ŧ	GND	Ground end
2	•	USB2.0 port	Connect to USB storage device,
			mouse, burning DVD-ROM and
			etc.
3	VGA	VGA video output	VGA video output port. Output
		port	analog video signal. Can connect
			to the monitor to view ananlog
			video output.
4	AUDIO IN	Audio input port	Connect to audio input device
			such as speaker.
5	VIDEO IN	Video input port	Connect to analog camera, video
			input signal.
6	DC 12V =@=	Power input port	Input 12V DC.
7	2 2	Network port	100M Ethernet port
8	HDMI	High definition	High definition audio and video
		media interface	signal output port. It transmits
			uncompressed high definition
			video and multiple-channel data
			to the HDMI port of the display
			device.
9	AUDIO OUT	Audio output port	Connect to video output device
			such as sound box.

2.2.6 HCVR7104C-S2 Series

The HCVR7104C-S2 series rear panel is shown as below. See Figure 2-19.




Figure 2-19

Please refer to the following sheet for detailed information.

SN	lcon	Name	Note
1	Ŧ	GND	Ground end
2	•€	USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.
3	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
4	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
5	VIDEO IN	Video input port	Connect to analog camera, video input signal.
6	DC 12V 	Power input port	Input 12V DC.
7	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
8		Network port	100M Ethernet port
9	AUDIO OUT	Audio output port	Connect to video output device such as sound box.

2.2.7 HCVR410XC-S3/HCVR510XC-S3/7104C-S3/XVR410XC/XVR510XC/7 104C Series

These series rear panel is shown as below. See Figure 4-127.

The following figure is based on the HCVR4108C-S3/5108C-S3/XVR4108C/5108C series.




Figure 2-20

Please refer to the following sheet for detailed information.

SN	Icon	Name	Note
1	VIDEO IN	Video input port	Connect to analog camera, video
			input signal.
2	AUDIO IN	Audio input port	Connect to audio input device
			such as speaker.
3	VGA	VGA video output	VGA video output port. Output
		port	analog video signal. Can connect
			to the monitor to view analog
			video output.
4	Ŕ	Power cable	Use clamp to secure the power
		fastener	cable on the device in case there
			is any loss.
5	Ŧ	GND	Ground end
6	AUDIO OUT	Audio output port	Connect to video output device
			such as sound box.
7	HDMI	High definition	High definition audio and video
		media interface	signal output port. It transmits
			uncompressed high definition
			video and multiple-channel data
			to the HDMI port of the display
			device.
8	, 2 , -	Network port	100M Ethernet port
9	•	USB2.0 port	Connect to USB storage device,
			mouse, burning DVD-ROM and
			etc.

10	DC 12V ⊖-	Power input port	Input 12V DC.
----	--------------	------------------	---------------

2.2.8 HCVR5104H/HCVR5108H Series

The HCVR5104H series rear panel is shown as below. See Figure 2-21.




Figure 2-21

The HCVR5108H series rear panel is shown as below. See Figure 2-22.




Figure 2	2-22
----------	------

SN	Icon	Name	Note
1	VIDEO IN	Video input port	Connect to analog camera, video
			input signal.
2	AUDIO OUT	Audio output port	Connect to video output device
			such as sound box.
3	AUDIO IN	Audio input port	Connect to audio input device
			such as speaker.
4	VGA	VGA video output	VGA video output port. Output
		port	analog video signal. Can connect
			to the monitor to view ananlog
			video output.
5	HDMI	High definition	High definition audio and video
		media interface	signal output port. It transmits

			uncompressed high definition
			video and multiple-channel data
			to the HDMI port of the display
			device.
6	ţ	USB2.0 port	Connect to USB storage device,
			mouse, burning DVD-ROM and
			etc.
7		Network port	100M Ethernet port
	00		
8	Α	RS485 (RS-485)	RS485_A port. It is the cable A.
		communication port	You can connect to the control
			devices such as speed dome
			PTZ.
	В		RS485_B.It is the cable B. You
			can connect to the control devices
			such as speed dome PTZ.
9	DC 12V	Power input port	Input 12V DC.
10		Power on-off button	Power on/off button.
	السلب		
11	1	GND	Ground end

2.2.9 HCVR5104H-V2/HCVR5108H-V2/HCVR5116H-V2 Series

The HCVR5104H-V2 series rear panel is shown as below. See Figure 2-23.




Figure 2-23

The HCVR5108H-V2 series rear panel is shown as below. See Figure 2-24.




Figure 2-24

The HCVR5116H-V2 series rear panel is shown as below. See Figure 2-25.





Figure 2-25

SN	lcon	Name	Note
1	•	Power on-off button	Power on/off button.
2	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
3	•	USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.
4	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
5	VIDEO IN	Video input port	Connect to analog camera, video input signal.
6	Ŧ	GND	Ground end

7	DC12V	Power input port	Input 12V DC.
	-C-		•
8	А	RS485 (RS-485)	RS485_A port. It is the cable A.
		communication port	You can connect to the control
			devices such as speed dome
			PTZ.
	В		RS485_B.It is the cable B. You
			can connect to the control devices
			such as speed dome PTZ.
9		Network port	100M Ethernet port
10	HDMI	High definition	High definition audio and video
		media interface	signal output port. It transmits
			uncompressed high definition
			video and multiple-channel data
			to the HDMI port of the display
			device.
11	AUDIO OUT	Audio output port	Connect to video output device
			such as sound box.


2.2.10 HCVR5104HC/HCVR5108HC Series

The HCVR5104HC series rear panel is shown as below. See Figure 2-26.





The HCVR5108HC series rear panel is shown as below. See Figure 2-27.



Please refer to the following sheet for detailed information.

SN	Icon	Name	Note
1	VIDEO IN	Video input port	Connect to analog camera, video input signal.
2	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
3	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
4	∙⊊	USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.
5	66	Network port	100M Ethernet port
6	DC 12V -C-	Power input port	Input 12V DC.
7	Ŧ	GND	Ground end

2.2.11 HCVR5104HC-V2/HCVR5108HC-V2/HCVR5116HC-V2 Series The HCVR5104HC-V2 series rear panel is shown as below. See Figure 2-28.







Figure 2-28

The HCVR5108HC-V2 series rear panel is shown as below. See Figure 2-29.





The HCVR5116HC-V2 series rear panel is shown as below. See Figure 2-30.




Figure 2-30

Please refer to the following sheet for detailed information.

SN	lcon	Name	Note
1	DC 12V 	Power input port	Input 12V DC.
2		Network port	100M Ethernet port
3	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
4	•	USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.
5	VIDEO IN	Video input port	Connect to analog camera, video input signal.
6	Ŧ	GND	Ground end

7	HDMI	High	definition	High definition audio and video
		media ir	nterface	signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
8	•	Power button	on-off	Power on/off button.

2.2.12 HCVR5104HE/HCVR5108HE Series

The HCVR5104HE4 series rear panel is shown as below. See Figure 2-33.




Figure 2-31

The HCVR5108HE series rear panel is shown as below. See Figure 2-67.




Figure 2-32

SN	Icon	Name	Note			
1	VIDEO IN	Video input port	Connect	to	analog	camera,

			video input oignol
			video input signal.
2	AUDIO OUT	Audio output port	Connect to video output device
			such as sound box.
3	AUDIO IN	Audio input port	Connect to audio input device
			such as speaker.
4	VGA	VGA video output	VGA video output port. Output
		port	analog video signal. Can
			connect to the monitor to view
			ananlog video output.
5	HDMI		High definition audio and video
			signal output port. It transmits
		High definition	uncompressed high definition
		media interface	video and multiple-channel data
			to the HDMI port of the display
			device.
6	•=	USB2.0 port	Connect to USB storage
			device, mouse, burning
			DVD-ROM and etc.
7	- -	Network port	100M Ethernet port
8	А	RS485 (RS-485)	RS485_A port. It is the cable A.
		communication	You can connect to the control
		port	devices such as speed dome
			PTZ.
	В		RS485_B.It is the cable B. You
			can connect to the control
			devices such as speed dome
			PTZ.
9	DC 12V 	Power input port	Input 12V DC.
10		5 "	
		Power on-off	Power on/off button.
	رىيىسى	button	
11	5 6 7 8 - M01N02N03		
		Alarm input/Alarm	Input/output alarm signal.
		output	
12	1	GND	Ground end
L		I	1

2.2.13 HCVR5104HE-V2/HCVR5108HE-V2/HCVR5116HE-V2 Series

The HCVR5104HE-V2 series rear panel is shown as below. See Figure 2-33.




Figure 2-33

The HCVR5108HE-V2 series rear panel is shown as below. See Figure 2-67.




Figure 2-34

The HCVR5116HE-V2 series rear panel is shown as below. See Figure 2-35.





Figure 2-35

SN	lcon	Name	Note
1	•	Power on-off button	Power on/off button.

2	$\begin{array}{c ccccccccccccccccccccccccccccccccccc$	Alarm input/Alarm output	Input/output alarm signal.
3	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
4	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
5	VIDEO IN	Video input port	Connect to analog camera, video input signal.
6	<u> </u>	GND	Ground end
7	DC 12V 	Power input port	Input 12V DC.
8	AB	RS485 (RS-485) communication port	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ. RS485_B.It is the cable B. You can connect to the control devices such as speed dome
9		Network port	PTZ. 100M Ethernet port
10	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
11	•	USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.
12	AUDIO OUT	Audio output port	Connect to video output device such as sound box.

2.2.14 HCVR7104H-V2/HCVR7108H-V2 Series

The HCVR7104H-V2 series rear panel is shown as below. See Figure 2-36.





The HCVR7108H-V2 series rear panel is shown as below. See Figure 2-37.




Figure 2-37

SN	lcon	Name	Note
1	•	Power on-off button	Power on/off button.
2	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
3	•	USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.
4	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.

r	1	1	
5	AUDIO IN	Audio input port	Connect to audio input device
			such as speaker.
6	VIDEO IN	Video input port	Connect to analog camera,
			video input signal.
7	Ŧ	GND	Ground end
8	DC 12V 	Power input port	Input 12V DC.
9	А	RS485 (RS-485)	RS485_A port. It is the cable A.
		communication	You can connect to the control
		port	devices such as speed dome
			PTZ.
	В		RS485_B.It is the cable B. You
			can connect to the control
			devices such as speed dome
			PTZ.
10	P	Network port	100M Ethernet port
44			
11	AUDIO OUT	Audio output port	Connect to video output device
1			such as sound box.

2.2.15 HCVR7104HC-V2/HCVR7108HC-V2 Series

The HCVR7104HC-V2 series rear panel is shown as below. See Figure 2-38.





Figure 2-38

The HCVR7108HC-V2 series rear panel is shown as below. See Figure 2-39.





Please refer to the following sheet for detailed information.

SN	lcon	Name	Note
1	VGA	VGA video output	VGA video output port. Output
		port	analog video signal. Can connect
			to the monitor to view ananlog
			video output.
2	•=	USB2.0 port	Connect to USB storage device,
			mouse, burning DVD-ROM and
			etc.
3	VIDEO IN	Video input port	Connect to analog camera, video
			input signal.
4	<u> </u>	GND	Ground end
5	DC 12V 	Power input port	Input 12V DC.
6	HDMI	High definition	High definition audio and video
		media interface	signal output port. It transmits
			uncompressed high definition
			video and multiple-channel data
			to the HDMI port of the display
			device.
7		Network port	100M Ethernet port
8		Power on-off	
		button	Power on/off button.

2.2.16 HCVR7104HE-V2/HCVR7108HE-V2 Series

The HCVR7104HE-V2 series rear panel is shown as below. See Figure 2-40.




Figure 2-40

The HCVR7108HE-V2 series rear panel is shown as below. See Figure 2-41.




Figure 2-41

SN	Icon	Name	Note
1	5 6 7 8 WOINO2NO3 1 2 3 4 CI C2 C3 7 5 7 5 7 5 7 5 7 5 7 5 7 5 7 5 7 5 7 5	Alarm input/Alarm output	Input/output alarm signal.
2	•	Power on-off button	Power on/off button.
3	- -	Network port	100M Ethernet port
4	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
5	AUDIO IN	Audio input port	Connect to audio input device such as speaker.

6	VIDEO IN	Video input port	Connect to analog camera, video input signal.
7	÷	GND	Ground end 0
8	DC 12V	Power input port	Input 12V DC.
9	A	RS485 (RS-485)	RS485_A port. It is the cable A.
		communication	You can connect to the control
		port	devices such as speed dome
		_	PTZ.
	В		RS485_B.It is the cable B. You
			can connect to the control
			devices such as speed dome
			PTZ.
10	•	USB2.0 port	Connect to USB storage
			device, mouse, burning
			DVD-ROM and etc.
11	HDMI	High definition	High definition audio and video
		media interface	signal output port. It transmits
			uncompressed high definition
			video and multiple-channel data
			to the HDMI port of the display
			device.
12	AUDIO OUT	Audio output port	Connect to video output device
			such as sound box.

2.2.17 HCVR4104/4108/4116HE-S2 Series

The HCVR4104HE-S2 series rear panel is shown as below. See Figure 2-42.




Figure 2-42

The HCVR4108HE-S2 series rear panel is shown as below. See Figure 2-43.




Figure 2-43

The HCVR4116HE-S2 series rear panel is shown as below. See Figure 2-44.





Figure 2-44

SN	Icon	Name	Note
1	•	Power on-off button	Power on/off button.
2	5 6 7 8 WOINO2MO3 1 2 3 4 C1 C2 C3 5 5 5 7 5 7 5 7 5 7 5 7 5 7 5 7 5 7 5 7	Alarm input/Alarm output	Input/output alarm signal.
3	VGA	VGA video output	VGA video output port. Output
		port	analog video signal. Can
			connect to the monitor to view
			ananlog video output.
4	AUDIO IN	Audio input port	Connect to audio input device
			such as speaker.
5	AUDIO OUT	Audio output port	Connect to video output device
			such as sound box.

6	VIDEO IN	Video input port	Connect to analog camera,
			video input signal.
7	÷	GND	Ground end 0
8	DC 12V =_C=	Power input port	Input 12V DC.
9	А	RS485 (RS-485)	RS485_A port. It is the cable A.
		communication	You can connect to the control
		port	devices such as speed dome
			PTZ.
	В		RS485_B.It is the cable B. You
			can connect to the control
			devices such as speed dome
			PTZ.
10	•==	USB2.0 port	Connect to USB storage
			device, mouse, burning
			DVD-ROM and etc.
11		Network port	
	- 		100M Ethernet port
12	HDMI	High definition	High definition audio and video
		media interface	signal output port. It transmits
			uncompressed high definition
			video and multiple-channel data
			•
			to the HDMI port of the display
			device.

2.2.18 HCVR5104/5108/5116H-S2 Series

The HCVR5104H-S2 series rear panel is shown as below. See Figure 2-45.





The HCVR5108H-S2 series rear panel is shown as below. See Figure 2-46.




Figure 2-46

The HCVR5116H-S2 series rear panel is shown as below. See Figure 2-47.




Figure 2-47

SN	lcon	Name	Note
1	•	Power on-off button	Power on/off button.
2	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
3	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
4	VIDEO IN	Video input port	Connect to analog camera, video input signal.
5	DC 12V 	Power input port	Input 12V DC.
6	•	USB2.0 port	Connect to USB storage device,

			mouse, burning DVD-ROM and etc.
7	A B	RS485 (RS-485) communication port	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ. RS485_B.It is the cable B. You can connect to the control devices such as speed dome PTZ.
8	6	Network port	100M Ethernet port
9	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
10	AUDIO OUT	Audio output port	Connect to video output device such as sound box.
11	÷	GND	Ground end

2.2.19 HCVR5104/5108/5116HE-S2 Series

The HCVR5104HE-S2 series rear panel is shown as below. See Figure 2-48.




Figure 2-48

The HCVR5108HE-S2 series rear panel is shown as below. See Figure 2-49.




Figure 2-49

The HCVR5116HE-S2 series rear panel is shown as below. See Figure 2-50.




Figure 2-50

SN	Icon	Name	Note
1	• -	Power on-off button	Power on/off button.
2	5 6 7 8 401N02N03 1 2 3 4 4 C1 C2 C3 7 5 7 5 7 5 7 5 7 5 7 5 7 5 7 5 7 5 7 5	Alarm input/Alarm output	Input/output alarm signal.
3	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
4	AUDIO IN	Audio input port	Connect to audio input device such as speaker.

5	AUDIO OUT	Audio output port	Connect to video output device such as sound box.
6	VIDEO IN	Video input port	Connect to analog camera, video input signal.
7	÷	GND	Ground end
8	DC 12V 	Power input port	Input 12V DC.
9	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
10	A B	RS485 (RS-485) communication port	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ. RS485_B.It is the cable B. You can connect to the control devices such as speed dome
11		Network port	PTZ. 100M Ethernet port
12	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.

2.2.20 HCVR7104/7108H-S2 Series

The HCVR7104H-S2 series rear panel is shown as below. See Figure 2-51.




Figure 2-51

The HCVR7108H-S2 series rear panel is shown as below. See Figure 2-52.




Figure 2-52

SN	lcon	Name	Note
1	•	Power on-off button	Power on/off button.
2	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
3	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
4	VIDEO IN	Video input port	Connect to analog camera, video input signal.
5	DC 12V 	Power input port	Input 12V DC.
6	•	USB2.0 port	Connect to USB storage device,

	1		г
			mouse, burning DVD-ROM and
			etc.
7	А	RS485 (RS-485)	RS485_A port. It is the cable A.
		communication	You can connect to the control
		port	devices such as speed dome
			PTZ.
	В		RS485_B.It is the cable B. You
			can connect to the control
			devices such as speed dome
			PTZ.
8	HDMI	High definition	High definition audio and video
		media interface	signal output port. It transmits
			uncompressed high definition
			video and multiple-channel data
			to the HDMI port of the display
			device.
9		Network port	100M Ethernet port
10	AUDIO OUT	Audio output port	Connect to video output device
			such as sound box.
11	Ŧ	GND	Ground end

2.2.21 HCVR7104/7108HE-S2 Series

The HCVR7104HE-S2 series rear panel is shown as below. See Figure 2-53.




Figure 2-53

The HCVR7108HE-S2 series rear panel is shown as below. See Figure 2-54.




Figure 2-54

SN	lcon	Name	Note
1	•	Power on-off button	Power on/off button.
2	5 6 7 8 401N02N05 1 2 3 4 61 C2 C3 57775777777777777777 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	Alarm input/Alarm output	Input/output alarm signal.
3	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
4	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
5	AUDIO OUT	Audio output port	Connect to video output device such as sound box.
6	VIDEO IN	Video input port	Connect to analog camera, video input signal.
7	Ŧ	GND	Ground end
8	DC 12V =G=	Power input port	Input 12V DC.
9		USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.
10	A	RS485 (RS-485) communication port	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ.
	В		RS485_B.It is the cable B. You

			can connect to the control devices such as speed dome PTZ.
11	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
12		Network port	100M Ethernet port

2.2.22 HCVR41XXHE-S3/HCVR51XXHE-S3/HCVR71XXH-S3/HCVR71XXHE -S3 /XVR41XXHE/XVR51XXH/XVR51XXHE/XVR71XXH/XVR71XXHE Series

The

HCVR41XXHE-S3/HCVR51XXHE-S3/HCVR71XXHE-S3/XVR41XXHE/XVR51H/XVR51 XXHE/XVR71XXHE series rear panel is shown as below. See Figure 4-53. The following figure is based on HCVR4116HE-S3/HCVR5116HE-S3/HCVR7116HE-S3/ XVR4116HE/XVR5116HE/XVR7116HE series.




Figure 2-55

The HCVR71XXH-S3/XVR71XXH rear panel is shown as below. See Figure 4-52. The following figure is based on the HCVR7116H-S3/XVR7116H.




Figure 2-56

SN	lcon	Name	Note
1		Alarm input/Alarm output	Input/output alarm signal.
2	VIDEO IN	Video input port	Connect to analog camera, video input signal.
3	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
4	AUDIO	DB25 port	The 5th to the 16th-channel audio input port.
5	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
6	Ŧ	GND	Ground end
7	AUDIO OUT	Audio output port	Connect to video output device such as sound box.
8	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
9		USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.

10	6	Network port	100M Ethernet port
11	A B	RS485 (RS-485) communication port	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ. RS485_B.It is the cable B. You can connect to the control devices such as speed dome PTZ.
12	DC 12V 	Power input port	Input 12V DC.
13		Power on-off button	Power on/off button.
14		Power cable fastener	Use clamp to secure the power cable on the device in case there is any loss.

2.2.23 HCVR41XXHS-S2/ HCVR2108HS-S2/ HCVR2116HS-S2 Series

The HCVR4104HS-S2 series rear panel is shown as below. See Figure 2-57.




Figure 2-57

The HCVR4108HS-S2/HCVR2108HS-S2 series rear panel is shown as below. See Figure 2-58.





Figure 2-58

The HCVR4116HS-S2/ HCVR2116HS-S2 series rear panel is shown as below. See Figure 2-59.





SN	lcon	Name	Note
1	DC 12V 	Power input port	Input 12V DC.
2	А	RS485 (RS-485)	RS485_A port. It is the cable A.
		communication	You can connect to the control
		port	devices such as speed dome
			PTZ.
	В		RS485_B.It is the cable B. You
			can connect to the control
			devices such as speed dome
			PTZ.
3	•	USB2.0 port	Connect to USB storage device,
			mouse, burning DVD-ROM and
			etc.


4	50	Network port	100M Ethernet port
5	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
6	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
7	VIDEO IN	Video input port	Connect to analog camera, video input signal.
8	Ť	GND	Ground end
9	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
10	AUDIO OUT	Audio output port	Connect to video output device such as sound box.

2.2.24 HCVR21XXHS-S3/HCVR41XXHS-S3/51XXHS-S3/7104HS-S3 /XVR21XXHS/XVR41XXHS/51XXHS/7104HS Series

The

HCVR2116HS-S3/HCVR41XXHS-S3/51XXHS-S3/XVR2116HS/XVR41XXHS/XVR51XX HS series rear panel is shown as below. See Figure 2-60.

The following figure is based on the HCVR2116HS-S3/HCVR4116HS-S3/5116HS-S3 /XVR2116HS/XVR4116HS/XVR5116HS series product.





The HCVR7104HS-S3/XVR7104HS series rear panel is shown as below. See Figure 2-61.




Figure	2-61

SN	lcon	Name	Note
1	VIDEO IN	Video input port	Connect to analog camera, video input signal.
2	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
3	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view analog video output.
4		Power cable fastener	Use clamp to secure the power cable on the device in case there is any loss.
5	AUDIO OUT	Audio output port	Connect to video output device such as sound box.
6	HDMI	High definition media interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
7	٩٢	USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.
8	5 ⁰ 5	Network port	100M Ethernet port
9	A B	RS485 (RS-485) communication port	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ. RS485_B.It is the cable B. You can connect to the control devices such as speed dome

			PTZ.
10	DC 12V 	Power input port	Input 12V DC.
11	1	GND	Ground end

2.2.25 HCVR52XXA-V2/ HCVR72XXA-V2 Series

This series products' rear panel is shown as below. See Figure 2-62. The following figure is based on HCVR7204A-V2 series product.




Figure 2-62

SN	lcon	Name	Note
1		Power switch	Power on/off button.
2	1~4	Alarm input port 1~4	 There are two types; NO (normal open)/NC (normal close). When your alarm input device is using external power, please make sure the device and the DVR have the same ground.
	NO1~NO3	Alarm output port 1~3	 3 groups of alarm output ports. (Group 1: port NO1~C1,Group 2:port NO2~C2,Group 3:port NO3~C3)).Output alarm signal to the alarm device. Please make sure there is power to the external alarm device. NO: Normal open alarm output port. C: Alarm output public end.
3	DC12V 	Power input port	Input DC 12V/5A.
4	AB	RS-485 communicati on port	 RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ. RS485_B.It is the cable B. You can connect to the control devices such as speed dome PTZ.
5	AUDIO IN	Audio input port	It is to receive the analog audio signal output from the devices such as mike phone, pickup.

SN	lcon	Name	Note
6	VIDEO IN	Video input port	Connect to analog camera to input video signal.
7	Ŧ	GND	Alarm input ground port.
8	AUDIO OUT	Audio output port	Audio output port. It is to output the analog audio signal to the devices such as the sound box.
9	HDMI	High Definition Media Interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
10	•	USB2.0 port	USB2.0 port. Connect to mouse, USB storage device, USB burner and etc.
11	VGA	VGA video output port	VGA video output port. Output analog video signal. It can connect to the monitor to view analog video.
12	66	Network port	1000M Ethernet port

2.2.26 HCVR42XXA-S2/ HCVR4216AN-S2 Series

This HCVR4204A-S2 rear panel is shown as below. See Figure 2-63.




Figure 2-63

This HCVR4208A-S2 rear panel is shown as below. See Figure 2-64.




Figure 2-64

This HCVR4216A-S2 rear panel is shown as below. See Figure 2-65.




Figure 2-65

This HCVR4216AN-S2 rear panel is shown as below. See Figure 2-66.




Figure 2-66


SN	lcon	Name	Note
1		Power switch	Power on/off button.
2	1~8(16)	Alarm input port 1~8(16)	 There are two types; NO (normal open)/NC (normal close). When your alarm input device is using external power, please make sure the device and the DVR have the same ground.
	NO1~NO3	Alarm output port 1~3	 3 groups of alarm output ports. (Group 1: port NO1~C1,Group 2:port NO2~C2,Group 3:port NO3~C3)).Output alarm signal to the alarm device. Please make sure there is power to the external alarm device. NO: Normal open alarm output port. C: Alarm output public end.
3	C1~C3 VGA	VGA video	VGA video output port. Output analog video signal.
		output	Can connect to the monitor to view ananlog video output.

SN	lcon	Name	Note
4	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
5	VIDEO IN	Video input port	Connect to analog camera, video input signal.
6	Ŧ	GND	Alarm input ground port.
7	DC 12V -G-	Power input port	Input 12V DC.
8	•	USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.
9	A	RS485 (RS-485)	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ.
	В	communicati on port	RS485_B.It is the cable B. You can connect to the control devices such as speed dome PTZ.
10	<u>-</u>	Network port	1000M Ethernet port
11	HDMI	High Definition Media Interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
12	AUDIO OUT	Audio output port	Connect to video output device such as sound box.

2.2.27 HCVR4224/HCVR4232AN-S2 Series

The rear panel is shown as below. See Figure 2-67.

The following figure is based on the HCVR4232AN-V2 series product.



SN	lcon	Name		Note
1	VIDEO IN	Video	input	Connect to analog camera, video input signal.
-		port		

SN	Icon	Name	Note
2	VIDEO OUT	Video output port	Connect to output devices such as TV.
3	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
4	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
5		Power switch	Power on/off button.
6	Ŧ	GND	Alarm input ground port.
7	DC12V 	Power input port	Input 12V/5A DC.
8	A	RS485 (RS-485)	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ.
0	В	communicatio n port	RS485_B.It is the cable B. You can connect to the control devices such as speed dome PTZ.
9		Network port	1000M Ethernet port
10	HDMI	High Definition Media Interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
11	AUDIO OUT	Audio output port	Connect to video output device such as sound box.
12	ور	USB2.0 port	USB2.0 port. Connect to mouse, USB storage device, USB burner and etc.

2.2.28 HCVR52XXA-S2/ HCVR5216AN-S2 Series

This HCVR5204A-S2 products' rear panel is shown as below. See Figure 2-68.




Figure 2-68

This HCVR5208A-S2 products' rear panel is shown as below. See Figure 2-69.




Figure 2-69

This HCVR5216A-S2 products' rear panel is shown as below. See Figure 2-70.




Figure 2-70

This HCVR5216AN-S2 products' rear panel is shown as below. See Figure 2-71.




Figure 2-71

SN	lcon	Name	Note
1		Power switch	Power on/off button.
2	1~8(16)	Alarm input port 1~8(16)	 There are two types; NO (normal open)/NC (normal close). When your alarm input device is using external power, please make sure the device and the DVR have the same ground.

SN	Icon	Name	Note
	NO1~NO3 C1~C3	Alarm output port 1~3	 3 groups of alarm output ports. (Group 1: port NO1~C1,Group 2:port NO2~C2,Group 3:port NO3~C3)).Output alarm signal to the alarm device. Please make sure there is power to the external alarm device. NO: Normal open alarm output port. C: Alarm output public end.
3	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
4	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
5	VIDEO IN	Video input port	Connect to analog camera, video input signal.
6	Ŧ	GND	Alarm input ground port.
7	DC 12V 	Power input port	Input 12V DC.
8	•	USB2.0 port	Connect to USB storage device, mouse, burning DVD-ROM and etc.
9	A B	RS485 (RS-485) communicati on port	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ. RS485_B.It is the cable B. You can connect to the control devices such as speed dome PTZ.
10	HDMI	High Definition Media Interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
11	급	Network port	100M Ethernet port
12	AUDIO OUT	Audio output port	Connect to video output device such as sound box.

2.2.29 HCVR720XA-S2 Series

The HCVR7204A-S2 products' rear panel is shown as below. See Figure 2-72.




Figure 2-72

The HCVR7208A-S2 products' rear panel is shown as below. See Figure 2-73.




Figure 2-73

SN	lcon	Name	Note
1		Power switch	Power on/off button.
2	1~8(16)	Alarm input port 1~8(16)	 There are two types; NO (normal open)/NC (normal close). When your alarm input device is using external power, please make sure the device and the DVR have the same ground.
	NO1~NO3	Alarm output port 1~3	 3 groups of alarm output ports. (Group 1: port NO1~C1,Group 2:port NO2~C2,Group 3:port NO3~C3)).Output alarm signal to the alarm device. Please make sure there is power to the external alarm device. NO: Normal open alarm output port. C: Alarm output public end.
3	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
4	AUDIO IN	Audio input port	Connect to audio input device such as speaker.


SN	lcon	Name	Note
5	VIDEO IN	Video input	Connect to analog camera, video input signal.
		port	
6	÷	GND	Alarm input ground port.
7	DC 12V 	Power input port	Input 12V DC.
8	•	USB2.0 port	Connect to USB storage device, mouse, burning
			DVD-ROM and etc.
9	А	RS485	RS485_A port. It is the cable A. You can connect to
		(RS-485)	the control devices such as speed dome PTZ.
	В	communicati	RS485_B.It is the cable B. You can connect to the
		on port	control devices such as speed dome PTZ.
10	HDMI	High	High definition audio and video signal output port. It
		Definition	transmits uncompressed high definition video and
		Media	multiple-channel data to the HDMI port of the display
		Interface	device.
11		Network port	100M Ethernet port
12	AUDIO	Audio output	Connect to video output device such as sound box.
	OUT	port	

2.2.30 HCVR42XXA-S3/HCVR42XXAN-S3/HCVR52XXA-S3/HCVR52XXAN-S3/HCVR72XXA-S3/HCVR7216AN-S3/XVR42XXA/XVR42XXAN/XVR 52XXA/XVR52XXAN/XVR72XXA/XVR7216AN Series

The

HCVR42XXA-S3/HCVR52XXA-S3/HCVR72XXA-S3/XVR42XXA/XVR52XXA/XVR72XXA products' rear panel is shown as below. See Figure 2-74.

ThefollowingfigureisbasedontheHCVR4216A-S3/5216A-S3/7216A-S3/XVR4216A/XVR5216A/XVR7216A series product.





The HCVR42XXAN-S3/52XXAN-S3/7216AN-S3/XVR42XXAN/52XXAN/7216AN rear panel is shown as below. See Figure 2-75.

ThefollowingfigureisbasedontheHCVR4216AN-S3/5216AN-S3/XVR4216AN/XVR5216ANseries product.




Figure 2-75

Please refer to the following sheet for detailed information.

SN	lcon	Name	Note	
1	Ŧ	GND	Alarm input ground port.	
2	1~8(16)	Alarm input port 1~8(16)	 There are two types; NO (normal open)/NC (normal close). When your alarm input device is using external power, please make sure the device and the DVR have the same ground. 	
	NO1~NO3	Alarm output port 1~3	 3 groups of alarm output ports. (Group 1: port NO1~C1,Group 2:port NO2~C2,Group 3:port NO3~C3)).Output alarm signal to the alarm device. Please make sure there is power to the external alarm device. NO: Normal open alarm output port. C: Alarm output public end. 	
3	C1~C3 VIDEO IN	Video input port	Connect to analog camera, video input signal.	
4	AUDIO IN	Audio input port	Connect to audio input device such as speaker.	
5	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.	
6		Power switch	Power on/off button.	
7	AUDIO OUT	Audio output port	Connect to video output device such as sound box.	
8	HDMI	High Definition Media Interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.	

SN	lcon	Name	Note
9	•	USB2.0 port	Connect to USB storage device, mouse, burning
			DVD-ROM and etc.
10		Network port	100M Ethernet port
11	А	RS485	RS485_A port. It is the cable A. You can connect to
		(RS-485)	the control devices such as speed dome PTZ.
	В	communicati	RS485_B.It is the cable B. You can connect to the
		on port	control devices such as speed dome PTZ.
12	DC 12V -G-	Power input	Input 12V DC.
		port	
13	F	Power cable	Use clamp to secure the power cable on the device in
		fastener	case there is any loss.

2.2.31 HCVR52XXL-V2/ HCVR54XXL-V2/HCVR44L-S2 Series

This series products' rear panel is shown as below. See Figure 2-76. The following figure is based on the HCVR5416L-V2 series product.




Figure 2-76

The HCVR4432L-S2 rear panel is shown as below. See Figure 2-77.




Figure 2-77

SN	Icon	Name	Note
1		Power switch	Power on/off button.
2	RS-232	RS-232 debug COM.	It is for general COM debug to configure IP address or transfer transparent COM data.
3	1~16	Alarm input port 1~16	 There are four groups. The first group is from port 1 to port 4, the second group is from port 5 to port 8, the third group is from 9 to 12, and the fourth group is from 13 to 16. They are to receive the signal from the external alarm source. There are two types; NO (normal open)/NC (normal close). When your alarm input device is using external power, please make sure the device and the DVR have the same ground.
	NO1~NO5 C1~C5 NC5	Alarm output port 1~5	 5 groups of alarm output ports. (Group 1 : port NO1 ~ C1,Group 2:port NO2 ~ C2,Group 3:port NO3~C3, Group 4: port NO4~C4, Group 5: port NO5, C5, NC5).Output alarm signal to the alarm device. Please make sure there is power to the external alarm device. NO: Normal open alarm output port. C: Alarm output public end. NC: Normal close alarm output port.
	A	RS-485 communication port	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ.
	В		RS485_B.It is the cable B.


SN	Icon	Name	Note
			You can connect to the control devices such as speed dome PTZ.
	T+、T-、R+、R-	Four-wire full-duplex 485 port	Four-wire full-duplex 485 port. T+, T- is the output wire. R+, R- is the input wire.
	CTRL 12V	Control power output	Controller 12V power output. It is to control the on-off alarm relay output.
4	VIDEO OUT	Video output port	Connect to video output devices such as TV.
5	AUDIO OUT	Audio output port	Audio output port. It is to output the analog audio signal to the devices such as the sound box.
6	MIC OUT	Audio output port	 Audio output port. It is to output the analog audio signal to the devices such as the sound box. Bidirectional talk output. Audio output on 1-window video monitor. Audio output on 1-window video playback.
7	MIC IN	Audio input port	Bidirectional talk input port. It is to receive the analog audio signal output from the devices such as mike phone, pickup.
8	AUDIO IN	Audio input port	It is to receive the analog audio signal output from the devices such as mike phone, pickup.
9	VIDEO IN	Video input port	Connect to analog camera to input video signal.
10	66	Network port	1000M Ethernet port
11	VGA	VGA video output port	VGA video output port. Output analog video signal. It can connect to the monitor to view analog video.

SN	Icon	Name	Note
12	HDMI	High Definition Media Interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
13	eSATA	eSATA port	External SATA port. It can connect to the device of the SATA port. Please jump the HDD when there is peripheral connected HDD.
14	∙	USB2.0 port	USB2.0 port. Connect to mouse, USB storage device, USB burner and etc.
15		Power socket	Power socket
16	Ŧ	GND	GND

2.2.32 HCVR42XXL-S2 Series

The rear panel is shown as in Figure 2-78

The following figure is based on the HCVR4232L-V2 series product.





SN	lcon	Name		Note
1	VIDEO IN	Video port	input	Connect to analog camera, video input signal.
2	VIDEO OUT	Video port	output	Connect to output devices such as TV.

SN	Icon	Name	Note
	1~16	Alarm input port 1~16	 There are four groups. The first group is from port 1 to port 4, the second group is from port 5 to port 8, the third group is from 9 to 12, and the fourth group is from 13 to 16. They are to receive the signal from the external alarm source. There are two types; NO (normal open)/NC (normal close). When your alarm input device is using external power, please make sure the device and the DVR have the same ground.
3	NO1~NO3 C1~C3	Alarm output port 1~3	 3 groups of alarm output ports. (Group 1: port NO1~C1,Group 2:port NO2~C2,Group 3:port NO3~C3)).Output alarm signal to the alarm device. Please make sure there is power to the external alarm device. NO: Normal open alarm output port. C: Alarm output public end.
	Ŧ	GND	Alarm input ground port.
4		Power switch	Power on/off button.
5	RS-232	RS-232 debug COM.	It is for general COM debug to configure IP address or transfer transparent COM data.
6	VGA	VGA video output port	VGA video output port. Output analog video signal. Can connect to the monitor to view ananlog video output.
7	AUDIO IN	Audio input port	Connect to audio input device such as speaker.
8	DC12V 	Power input port	Input 12V/5A DC.
9	А	RS-485 communicatio	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ.
9	В	n port	RS485_B.It is the cable B. You can connect to the control devices such as speed dome PTZ.
10		Network port	1000M Ethernet port
11	HDMI	High Definition Media Interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
12	AUDIO OUT	Audio output port	Audio output port. It is to output the analog audio signal to the devices such as the sound box.

SN	lcon	Name	Note		
13	•	USB2.0 port	USB2.0 port. Connect to mouse, USB storage		
10	• •	device, USB burner and etc.			

2.2.33 HCVR58XXS-V2/HCVR48XXS-S2 Series

The rear panel is shown as in Figure 2-79.

The following figure is based on the HCVR5816S-V2 series product.




Figure 2-79

The HCVR4832S-S2 rear panel is shown as in Figure 2-80.




Figure 2-80

SN	Icon	Name	Note
1		Power socket Power socket	
2		Power switch	Power on/off button.
3	RS-232	RS-232 debug COM.	It is for general COM debug to configure IP address or transfer transparent COM data.

SN	Icon	Name	Note
4	1~16	Alarm input port 1~16	 There are four groups. The first group is from port 1 to port 4, the second group is from port 5 to port 8, the third group is from 9 to 12, and the fourth group is from 13 to 16. They are to receive the signal from the external alarm source. There are two types; NO (normal open)/NC (normal close). When your alarm input device is using external power, please make sure the device and the DVR have the same ground.
	NO1~NO5 C1~C5 NC5	Alarm output port 1~5	 5 groups of alarm output ports. (Group 1 : port NO1 ~ C1,Group 2:port NO2 ~ C2,Group 3:port NO3~C3, Group 4: port NO4~C4, Group 5: port NO5, C5, NC5).Output alarm signal to the alarm device. Please make sure there is power to the external alarm device. NO: Normal open alarm output port. C: Alarm output public end. NC: Normal close alarm output port.
	A	RS-485 communication port	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ.
	В		RS485_B.It is the cable B. You can connect to the control devices such as speed dome PTZ.
	T+、T-、R+、R-	Four-wire full-duplex 485 port	Four-wire full-duplex 485 port. T+, T- is the output wire. R+, R- is the input wire.
	CTRL 12V	Control power output	Controller 12V power output. It is to control the on-off alarm

SN	Icon	Name	Note
			relay output.
5	AUDIO OUT	Audio output portAudio output port. It is output the analog audio sign to the devices such as t sound box.	
6	MIC IN	Audio input port	Bidirectional talk input port. It is to receive the analog audio signal output from the devices such as mike phone, pickup.
7	AUDIO IN	Audio input port It is to receive the ana audio signal output from devices such as mike pho pickup.	
8	VIDEO IN	Video input port	Connect to analog camera to input video signal.
9	MIC OUT	Audio output port	 Audio output port. It is to output the analog audio signal to the devices such as the sound box. Bidirectional talk output. Audio output on 1-window video monitor. Audio output on 1-window video playback.
10	VIDEO OUT	Video output port	Connect to video output devices such as TV.
11		Network port	1000M Ethernet port
12	VGA	VGA video output port	VGA video output port. Output analog video signal. It can connect to the monitor to view analog video.
13	HDMI	High Definition Media Interface	High definition audio and video signal output port. It transmits uncompressed high definition video and multiple-channel data to the HDMI port of the display device.
14	eSATA	eSATA port	External SATA port. It can connect to the device of the SATA port. Please jump the

Icon	Name	Note
		HDD when there is peripheral
		connected HDD.
•	USB2.0 port	USB2.0 port. Connect to
		mouse, USB storage device,
		USB burner and etc.
Ť	GND	GND
	Icon ←← ↓	● C USB2.0 port

2.2.34 HCVR71XXH-4M Series

The rear panel is shown as in Figure 2-81.

The following figure is based on the HCVR7116H-4M series product.




Figure 2-81

Plages rofor	to the	following	shoot for	dotailod	information
Please refer	to the	; iuiuwing	Sheet IOI	uelaneu	inionnation.

SN	lcon	Name	Function
1	VIDEO IN	Video input port	Connect to analog camera, video input signal.
2	AUDIO IN	Audio input port	Connect to microphone and etc to input signal.
3	HDMI	High definition media interface	High definition audio and video signal output port. It transmits the same video signal as that of the VGA/TV or different video signal from that of the VGA/TV (support customized setup). Support mouse operation.
4	•	USB3.0 port	Connect to mouse, USB storage media, USB-burner and etc.
5	<u>с</u> С	Network port	1000M Ethernet port

SN	lcon	Name	Function
6	VGA	VGA video	VGA video output port. Output analog video signal. It can
		output port	connect to the monitor to view analog video.
7		Power switch	Power on/off button.
8	Ŧ	GND	Ground port
9 AUDIO OL	AUDIO OUT	Audio output	Connect to sound box and etc to output audio signal.
		port	
10	А	RS485	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ.
		communicatio	RS485_B.It is the cable B. You can connect to the control
	В	n port	devices such as speed dome PTZ.
11		Power socket	Power input port

2.2.35 HCVR72XXAN-4M Series

The rear panel is shown as in Figure 2-82. The following figure is based on the HCVR7208SAN-4M series product.




Figure 2-82

SN	lcon	Name	Function
1	VIDEO IN	Video inp port	t Connect to analog camera, video input signal.
2	AUDIO IN	Audio inp port	t Connect to microphone and etc to input signal.

SN	lcon	Name	Function
3	HDMI	High definition media	High definition audio and video signal output port. It transmits the same video signal as that of the VGA/TV or
		interface	different video signal from that of the VGA/TV (support
			customized setup).
			Support mouse operation.
4	6 6	Network port	1000M Ethernet port
5	VGA	VGA	VGA video output port
6	•	Power switch	Power on/off button.
7	GND	Power switch	Power on/off button.
8	AUDIO OUT	Audio output port	Connect to sound box and etc to output audio signal.
9	A	RS485 communicatio	RS485_A port. It is the cable A. You can connect to the control devices such as speed dome PTZ.
	В	n port	RS485_B.It is the cable B. You can connect to the control devices such as speed dome PTZ.
10	•€	USB3.0 port	Connect to mouse, USB storage media, USB-burner and etc.
11	\bigcirc	Power socket	Power input port

When connect the Ethernet port, please use crossover cable to connect the PC and use the straight cable to connect to the switch or router.

2.3 Connection Sample

2.3.1 Smart Box Series

Please refer to Figure 2-78 for connection sample.




Figure 2-83

2.3.2 Smart 1U Series

Please refer to Figure 2-84 for connection sample.

The following figure is based on the HCVR4108C-S3/5108C-S3/XVR4108C/5108C series.




Figure 2-84

2.3.3 Compact 1U Series

Please refer to Figure 2-78 for connection sample.

The following figure is based on the HCVR2116HS-S3/HCVR4116HS-S3/5116HS-S3 /XVR2116HS/XVR4116HS/5116HS series product.




Figure 2-85

2.3.4 Mini 1U Series

Please refer to Figure 2-86 for connection sample.

The following figure is based on HCVR4116HE-S3/HCVR5116HE-S3/HCVR7116HE-S3/XVR4116HE/XVR5116HE/XVR7116HE series.




Figure 2-86

2.3.5 1U Series

Please refer to the following figure for detailed information. See Figure 2-87. The following interface is based on the HCVR4216A-S3/HCVR5216A-S3/ HCVR7216A-S3/XVR4216A/XVR5216A/XVR7216A series product.




Figure 2-87

2.3.6 1.5U Series

The connection sample is shown as below. See Figure 2-88.

The following interface is based on the HCVR4232L-S2 series product.




Figure 2-88

2.3.7 2U Series

Please refer to the following figure for detailed information. See Figure 2-89. The following interface is based on the HCVR5816S-V2 series product.




Figure 2-89

2.4 Remote Control

The remote control interface is shown as in Figure 2-90.

Please note remote control is not our standard accessory and it is not included in the accessory bag.




Figure 2-90

Serial Number	Name	Function
1	Power button	Click it to boot up or shut down the device.
2	Address	Click it to input device number, so that you can control it.
3	Forward	Various forward speeds and normal speed playback.
4	Slow play	Multiple slow play speeds or normal playback.
5	Next record	In playback mode, playback the next video.
6	Previous record	In playback mode, playback the previous video.
7	Play/Pause	In pause mode, click this button to realize normal playback.
		In normal playback click this button to pause playback.
		In real-time monitor mode, click this button to enter video search
	Reverse/pause	menu. Reverse playback pause mode,

8		click this button to realize normal playback. In reverse playback click this button to pause playback.
9	Esc.	Go back to previous menu or cancel current operation (close upper interface or control)
10	Record	Start or stop record manually In record interface, working with the direction buttons to select the record channel. Click this button for at least 1.5 seconds, system can go to the Manual Record interface.
11	Direction keys	Switch current activated control, go to left or right. In playback mode, it is to control the playback process bar. Aux function(such as switch the PTZ menu)
12	Enter /menu key	go to default button go to the menu
13	Multiple-window switch	Switch between multiple-window and one-window.
14	Fn	In 1-ch monitor mode: pop up assistant function: PTZ control and Video color. Switch the PTZ control menu in PTZ control interface. In motion detection interface, working with direction keys to complete setup. In text mode, click it to delete character.
15	0-9 number key	Input password, channel or switch channel. Shift is the button to switch the input method.

2.5 Mouse Control

Left	click	System pops up password input dialogue box if you have not logged in.
mouse	;	In real-time monitor mode, you can go to the main menu.

	When you have selected one menu item, left click mouse to view menu
	content.
	Implement the control operation.
	Modify checkbox or motion detection status.
	Click combo box to pop up drop down list
	In input box, you can select input methods. Left click the corresponding button on the panel you can input numeral/English character (small/capitalized). Here ← stands for backspace button stands for space button.
	In English input mode: _stands for input a backspace icon and \leftarrow stands for deleting the previous character.
	A B C D E F G H I J K L M N O P Q R S T ⊔ U V W X Y Z ← u v w x y z ←
	In numeral input mode: _ stands for clear and \leftarrow stands for deleting the previous numeral.
	When input special sign, you can click corresponding numeral in the front panel to input. For example, click numeral 1 you can input"/", or you can click the numeral in the on-screen keyboard directly.
	1 / 2 : 3 . 4 ? 5 - 6 _ 7 @ 8 # 9 % 0 & □ ←
Double left	Implement special control operation such as double glick and item in
click mouse	Implement special control operation such as double click one item in the file list to playback the video.
	In multiple-window mode, double left click one channel to view in
	full-window.
	Double left click current video again to go back to previous
	multiple-window mode.

Right click mouse	In real-time monitor mode, pops up shortcut menu: one-window, four-window, nine-window and sixteen-window, Pan/Tilt/Zoom, color setting, search, record, alarm input, alarm output, main menu. Among which, Pan/Tilt/Zoom and color setting applies for current selected channel. If you are in multiple-window mode, system automatically switches to the corresponding channel.
	View 1 ► View 4
	 ₽TZ 1 Auto Focus Auto Setting
	 Q Search ● Manual ● ■ Remote Device ☆ Main Menu
	Exit current menu without saving the modification.
Press	In numeral input box: Increase or decrease numeral value.
middle	Switch the items in the check box.
button	Page up or page down
Move mouse	Select current control or move control
Drag	Select motion detection zone
mouse	Select privacy mask zone.

2.6 Virtual Keyboard & Front Panel

2.6.1 Virtual Keyboard

The system supports two input methods: numeral input and English character (small and capitalized) input.

Move the cursor to the text column, the text is shown as blue, input button pops up on the right. Click that button to switch between numeral input and English input (capitalized and small), Use > or < to shift between small character and capitalized character.

2.6.2 Front Panel

Move the cursor to the text column. Click Fn key and use direction keys to select number you wanted. Please click enter button to input.

3 Installation and Connections

Note: All the installation and operations here should conform to your local electric safety rules.

3.1 Check Unpacked DVR

When you receive the DVR from the forwarding agent, please check whether there is any visible damage. The protective materials used for the package of the DVR can protect most accidental clashes during transportation. Then you can open the box to check the accessories.

Please check the items in accordance with the list. Finally you can remove the protective film of the DVR.

Note

Remote control is not a standard accessory and it is not included in the accessory bag.

3.2 About Front Panel and Rear Panel

The model in the front panel is very important; please check according to your purchase order.

The label in the rear panel is very important too. Usually we need you to represent the serial number when we provide the service after sales.

3.3 HDD Installation



Shut down the device and then unplug the power cable before you open the case to replace the HDD!

All figures listed below for reference only!

This series DVR has 1 to 8 HDDs (no limitation for capacity). Please use HDD of 7200rpm or higher. Usually we do not recommend the HDD for the PC. You can refer to the Appendix for recommended HDD brand.

Please follow the instructions listed below to install hard disk.

3.3.1 Smart Box Series

Please make sure the metal surface of the HDD is facing up when you are installing! This series product has only one 2.5-inch SATA HDD.

Please follow the instructions below to install HDD.








(1) Draw out the HDD bracket
(2) Make sure the HDD metal surface is facing up and then put the HDD into the bracket horizontally. After the HDD is in the proper position, the columns on the two sides can lock the screw holes of the HDD to secure it.

When you remove the HDD, please refer to the following figure to pull the spring up and then remove the HDD.



3.3.2 Smart 1U Series

The smart 1U series includes HCVR5104C/HCVR51XXC-V2/HCVR71XXC-V2/ HCVR4104/4108C-S2/ HCVR5104 5108C-S2/ HCVR7104C-S2/ HCVR2108C-S2/ XVR410XC/XVR510XC/7104C series. The series DVR has one SATA HDD.



①. Loosen the screws of the upper cover and side panel.



O Fix four screws in the HDD

(Turn just three rounds).



③ Place the HDD in

accordance with the four holes in the bottom.

④ Turn the device upside down and

then turn the screws in firmly.


⑦ Put the cover in accordance with


the clip and then place the upper cover back.

3.3.3 Compact 1U and Mini 1U Series

- The mini 1U series includes HCVR51XXH/51XXHC/51XXHE/51XXH-V2/HC-V2/HE-V2/71XXH-V2/71XXHC-V2/7 1XXHE-V2/ HCVR41XXHE-S2/ HCVR51XXH-S2/ HCVR51XXHE-S2/ HCVR710XH-S2/ HCVR710XHE-S2/ XVR41XXHE/XVR51XXHE/XVR71XXH/XVR71XXHE and etc.
- The compact 1U series includes HCVR41XXHS-S2/ HCVR2108HS-S2/ HCVR2116HS-S2/HCVR21XXHS-S2/ XVR21XXHS/XVR41XXHS/51XXHS/7104HS and etc..

The series DVR has one SATA HDD.







③Place the HDD in accordance with the four holes in the bottom.

(6) Connect the HDD cable and

power cable.

8 Secure the screws in the rear panel and the side panel.


(5) Fix the HDD firmly.












④Turn the device upside down and then turn the screws in firmly.



⑤Fix the HDD firmly.



6 Connect the HDD cable and power cable.



⑦Put the cover in accordance with the clip and then place the upper cover and the side panel. back.

⁽⁸⁾Secure the screws in the rear panel

Important:

- You can connect the HDD data cable and the power cable first and then fix the HDD in the device.
- Please pay attention to the front cover. It adopts the vertical sliding design. You need to push the clip first and then put down.

3.3.4 The 1U Series

The 1U series includes HCVR52XXA-V2/HCVR72XXA-V2/HCVR42XXA-S2/HCVR4216AN-S2/HCVR52XXA-S2/ HCVR5216AN-S2/HCVR720XA-S2/XVR42XXA/XVR4216AN/XVR52XXA/XVR5216AN/X VR72XXA/XVR7216AN and etc.

This series DVR has two SATA HDDs.



 Loosen the screws of the upper cover and side panel. Remove the cover.



② Fix four screws in the HDD (Turn just three rounds).



③ Place the HDD in accordance with the four holes in the bottom.



④Turn the device upside down and then turn the screws in firmly.



(5)Connect the HDD cable and power cable.



⁽⁶⁾Put the cover in accordance with the clip and then place the upper cover back. Secure the screws in the rear panel and the side panel.

3.3.5 The 1.5U Series

The 1.5U series includes HCVR52XXL-V2/ HCVR54XXL-V2/HCVR44L-S2 and etc. This series DVR max has four SATA HDDs. Please use HDD of 7200rpm or higher.




 (\fbox) Loosen the screws of the

upper cover. Remove the cover.



(2) Line up the HDD to the four holes of the HDD of bracket. Use four screws to fix HDD.



(3) Connect the one end of the HDD cable to the HDD.



(4) Connect the other end of (5)

(5) Connect the power cable

(6) Put the cover back and fix the screws to secure firmly.

the HDD cable to the to the HDD. mainboard.

3.3.6 The 2U Series

The 2U series includes HCVR58XXS-V2/HCVR48XXS-V2 and etc. This series DVR max supports 8 SATA HDDs. Please use HDD of 7200rpm or higher.



 Loosen the screws of the upper cover and side panel. Remove the cover.



② Fix the HDD(s) on the bracket. Remove the top bracket if you want to install HDD to the bottom bracket.



③Connect the one end of the HDD cable to the HDD.



(4) Connect the other end of the HDD cable to the mainboard.



5Connect the power cable to the HDD.



(6)Put the cover back and fix the screws to secure firmly.

Important:

If the HDD amount is less than four, you do not need to install the HDD bracket. When there is a bracket, please make sure the installation direction of HDDs is the same.

3.3.7 Rack Installation

The DVR occupies 1.5U/2U rack units of vertical rack space.

- Use twelve screws to fix the unit
- Please make sure the indoor temperature is below 35 °C (95°f).

- Please make sure there is 15cm (6 inches) space around the device to guarantee sound ventilation.
- Please install from the bottom to the top.
- If there are more accessories connected in the rack, please take precaution measures in case the rack power is overload.

3.4 Connecting Power Supply

Please check input voltage and device power button match or not.

We recommend you use UPS to guarantee steady operation, DVR life span, and other peripheral equipments operation such as cameras.

3.5 Connecting Video Input and Output Devices

3.5.1 Connecting Video Input

The video input interface is BNC. The input video format includes: PAL/NTSC BNC (1.0V_{P-P}, 75\Omega.) .

The input video format: BNC (0.8VP-P, 75 $\Omega)$,

The video signal should comply with your national standards.

The input video signal shall have high SNR, low distortion; low interference, natural color and suitable lightness.

Guarantee the stability and reliability of the camera signal:

The camera shall be installed in a cool, dry place away from direct sunlight, inflammable, explosive substances and etc.

The camera and the DVR should have the same grounding to ensure the normal operation of the camera.

Guarantee stability and reliability of the transmission line.

Please use high quality, sound shielded BNC. Please select suitable BNC model according to the transmission distance.

If the distance is too long, you should use twisted pair cable, and you can add video compensation devices or use optical fiber to ensure video quality.

You should keep the video signal away from the strong electromagnetic interference, especially the high tension current.

Keep connection lugs in well contact

The signal line and shielded wire should be fixed firmly and in well connection. Avoid dry joint, lap welding and oxidation.

3.5.2 Connecting Video Output

Video output includes a BNC(PAL/NTSC, 1.0VP- P, 75Ω) output, a VGA output and a HDMI output.

System supports BNC, VGA and HDMI output at the same time.

When you are using pc-type monitor to replace the monitor, please pay attention to the following points:

- To defer aging, do not allow the pc monitor to run for a long time.
- Regular demagnetization will keep device maintain proper status.

• Keep it away from strong electromagnetic interference devices.

Using TV as video output device is not a reliable substitution method. You also need to reduce the working hour and control the interference from power supply and other devices. The low quality TV may result in device damage.

3.6 Connecting Audio Input & Output, Bidirectional Audio

3.6.1 Audio Input

BNC port is adopted for audio input port.

Due to high impedance of audio input, please use active sound pick-up.

Audio transmission is similar to video transmission. Try to avoid interference, dry joint, loose contact and it shall be away from high tension current.

3.6.2 Audio Output

The audio output signal parameter is usually over 200mv 1K Ω (BNC). It can directly connect to low impedance earphone, active sound box or amplifier-drive audio output device.

If the sound box and the pick-up cannot be separated spatially, it is easy to arouse squeaking. In this case you can adopt the following measures:

- Use better sound pick-up with better directing property.
- Reduce the volume of the sound box.
- Using more sound-absorbing materials in decoration can reduce voice echo and improve acoustics environment.
- Adjust the layout to reduce happening of the squeaking.

3.7 Alarm Input and Output Connection

Please read the followings before connecting.

1. Alarm input

- a. Please make sure alarm input mode is grounding alarm input.
- b. Grounding signal is needed for alarm input.
- c. Alarm input needs the low level voltage signal.
- d. Alarm input mode can be either NC (normal Open) or NO (Normal Close)

e. When you are connecting two DVRs or you are connecting one DVR and one other device, please use a relay to separate them,

2. Alarm output

The alarm output port should not be connected to high power load directly (It shall be less than 1A) to avoid high current which may result in relay damage. Please use the co contactor to realize the connection between the alarm output port and the load.

3. How to connect PTZ decoder

a. Ensure the decoder has the same grounding with DVR, otherwise you may not control the PTZ. Shielded twisted wire is recommended and the shielded layer is used to connect to the grounding.

b. Avoid high voltage. Ensure proper wiring and some thunder protection measures.

c. For too long signal wires, 120Ω should be parallel connected between A, B lines on the far end to reduce reflection and guarantee the signal quality.

- d. "485 A, B" of DVR cannot parallel connect with "485 port" of other device.
- e. The voltage between of A,B lines of the decoder should be less than 5v.

4. Please make sure the front-end device has soundly earthed.

Improper grounding may result in chip damage.

3.7.1 Alarm Input and Output Details

Important

Please refer to the specifications for the alarm input and output channel amount. Do not merely count the alarm input and out channel amount according to the ports on the rear panel.

<u>5 25 25 25 25 25 25 25 25 25 25 25 25 25</u>

1	2	3	4	÷	5	6	7	8	Ŧ	9	10	11	12	Ŧ	13	14	15	18	Ŧ	T+	τ-	R• [₽—
ر م												ک م ''										ן הן	2

Figure 3-1

[
1, 2, 3, 4, 5, 6,	ALARM 1 to ALARM 16. The alarm becomes active in low voltage.
7, 8, 9, 10, 11,	
12, 13, 14, 15, 16	
In the second line,	There are six groups of normal open activation output (on/off button)
from the left to the	
right:	
NO1 C1,	
NO2 C2,	
NO3 C3,	
NO4 C4,	
NO5 C5,	
NO6 C6.	
CTRL 12V	Control power output. For external alarm, you need to close the
	device power to cancel the alarm.
	Voltage current; 500mA.
+12V	Rated current.
	Voltage current; 500mA.

Ŧ	Earth cable.
485 A/B	485 communication port. They are used to control devices such as decoder. 120Ω should be parallel connected between A, B lines if there are too many PTZ decoders.
T+,T-,R+,R-	They are four-wire full-duplex RS485 port T+ T-: output wire R+ R-: input wire

3.7.2 Alarm Input Port

Please refer to the following sheet for more information.

- Grounding alarm inputs. Normal open or Normal close type)
- Please parallel connect COM end and GND end of the alarm detector (Provide external power to the alarm detector).
- Please parallel connect the Ground of the DVR and the ground of the alarm detector.
- Please connect the NC port of the alarm sensor to the DVR alarm input(ALARM)
- Use the same ground with that of DVR if you use external power to the alarm device.




Figure 3-2

3.7.3 Alarm Output Port

- Provide external power to external alarm device.
- To avoid overloading, please read the following relay parameters sheet carefully.
- RS485 A/B cable is for the A/B cable of the PTZ decoder.
- T+,T-,R+,R- are four-wire double duplex RS485 port.
 - T+ T-: output wire

R+ R-: input wire

Model:	JRC-27F	
Material of the	Silver	
touch		
Rating	Rated switch capacity	30VDC 2A, 125VAC 1A
Resistance	Maximum switch power	125VA 160W
Load)	Maximum switch voltage	250VAC, 220VDC

Relay Specification

	Maximum switch currency	1A
Insulation	Between touches with same polarity	1000VAC 1minute
	Between touches with different polarity	1000VAC 1minute
	Between touch and winding	1000VAC 1minute
Surge voltage	Between touches with same polarity	1500V (10×160us)
Length of open time	3ms max	
Length of close time	3ms max	
Longevity	Mechanical	50×106 times (3Hz)
	Electrical	200×103 times (0.5Hz)
Temperature	-40℃ ~+70℃	

3.8 RS485

When the DVR receives a camera control command, it transmits that command up the coaxial cable to the PTZ device. RS485 is a single-direction protocol; the PTZ device can't return any data to the unit. To enable the operation, connect the PTZ device to the RS485 (A,B) input on the DVR.

Since RS485 is disabled by default for each camera, you must enable the PTZ settings first. This series DVRs support multiple protocols such as Pelco-D, Pelco-P.

To connect PTZ devices to the DVR:

1. Connect RS485 A,B on the DVR rear panel.

2. Connect the other end of the cable to the proper pins in the connector on the camera.

3. Please follow the instructions to configure a camera to enable each PTZ device on the DVR.




Figure 3-3

3.9 Other Interfaces

There are still other interfaces on the DVR, such as USB ports.

4 Overview of Navigation and Controls

4.1 Boot up and Shutdown

4.1.1 Boot up

Before the boot up, please make sure:

- The rated input voltage matches the device power on-off button. Please make sure the power wire connection is OK. Then click the power on-off button.
- Always use the stable current, if necessary UPS is a best alternative measure.

Please follow the steps listed below to boot up the device.

- Connect the device to the monitor and then connect a mouse.
- Connect power cable.
- Click the power button at the front or rear panel and then boot up the device. After device booted up, the system is in multiple-channel display mode by default.

4.1.2 Shutdown

Note

- When you see corresponding dialogue box "System is shutting down..." Do not click power on-off button directly.
- Do not unplug the power cable or click power on-off button to shutdown device directly when device is running (especially when it is recording.)

There are three ways for you to log out.

a) Main menu (**RECOMMENDED**)

From Main Menu->Shutdown, select shutdown from dropdown list. Click OK button, you can see device shuts down.

b) From power on-off button on the front panel or remote control

Press the power on-off button on the DVR front panel or remote control for more than 3 seconds to shutdown the device.

c) From power on-off button on the rear panel.

4.1.3 Auto Resume after Power Failure

The system can automatically backup video and resume previous working status after power failure.

4.1.4 Replace Button Battery

Please make sure to use the same battery model if possible.

We recommend replace battery regularly (such as one-year) to guarantee system time accuracy.

Note:

Before replacement, please save the system setup, otherwise, you may lose the data completely!

4.2 Set/Reset Password

4.2.1 Set Password

For your own safety, please set your administrator default password after you first boot up the device.

After system booted up, you can see the following interface if it is your first time to use or you have restored default setup. See Figure 4-1. Please input a password and then input again to set a password.

- You can set security questions here to reset the password in case you forgot. System supports customized setup. Please note you need to set two security questions at the same time. When you reset the password, you need to answer these two security questions too.
 - ADMIN SECURITY

 User Name

 admin

 Enter Password

 Confirm Password

 Secure Questions (Optional)

 Question 1

 What's your favorite pet?

 Answer

 Question 2

 What's your first car model?

 OK
- For reset information, please refer to chapter 4.2.2.

Figure 4-1

After you complete the setup, click OK button, system pops up the following interface for you to confirm. Click OK button to exit. See Figure 4-2.

Message	
Successfully set the password!	
*	
ОК	
UK OK	

Figure 4-2

4.2.2 Reset Password

H

Once you forgot password, you can answer the security questions you set in chapter 4.2.1 to reset the password.

In login inter	face, click See Figure 4-3.
	SYSTEM LOGIN
	User Name (admin 🔽 🔂 Password
	OK Cancel

Figure 4-3

System pops up the following dialogue box, please answer the security questions and then input the new password twice. See Figure 4-4.

	Reset
Question 1	What's your favorite pet?
Answer	
Question 2	What's your first car model?
Answer	
Reset password o	f (admin)
New Password	
Confirm Password	
	Reset Cancel

Figure 4-4

4.3 Startup Wizard

After device successfully booted up, it goes to startup wizard.

Click Cancel/Next button, you can see system goes to login interface.

Tips

Check the box Startup button here, system goes to startup wizard again when it boots up the next time.

Cancel the Startup button, system goes to the login interface directly when it boots up the next time.



Figure 4-5

Click Cancel button or Next Step button, system goes to login interface. See Figure 4-6. System consists of three accounts:

- Username: admin. Password: admin. (administrator, local and network)
- Username: 888888. Password: 888888. (administrator, local only)
- **Username**: default. **Password**: default (hidden user). Hidden user "default" is for system interior use only and can not be deleted. When there is no login user, hidden user "default" automatically login. You can set some rights such as monitor for this user so that you can view some channel view without login.

SYSTEM LOGIN
User Name (admin) 🔂 Password
OK Cancel

Figure 4-6



- For security reason, please modify password after you first login.
- Continuous three times login failure will result in system alarm and five times login failure will result in account lock!
- Please reboot the device or wait for 30 minutes to try again if your account has been locked.

After input corresponding user name and password, you can click OK button. System goes to the startup wizard.

- When there are all analog channels, the startup wizard includes general, encode, schedule, record control, network, P2P.
- When there is an IP channel, the startup wizard includes general, network, P2P, remote device and schedule.

Click OK button, you can go to General interface. See Figure 4-7. For detailed information, please refer to chapter 4.11.5.1.

		GENERAI			
General	Date&Time	Holiday			
Device Name	HCVR)			
Device No.	(8)			
Language	ENGLISH -)			
Video Standard	PAL)			
HDD Full	Overwrite 🔻)			
Pack Mode	Time Length) (60			
Realtime Play	(5)min.			
Auto Logout	(10)min.			
🛃 IPC Time Sync	24)h			
Navigation Bar					
Mouse Sensitivity	Slow	– Fast			
Default					(Apply)
			Back	Next	Cancel

Figure 4-7

Note

You can only see the remote device interface if you have set IP channel (Chapter 4.11.1.3.5)

Click Next button, you can go to network interface. See Figure 4-8.

For detailed information, please refer to chapter 4.10.3.

	NETWORK
IP Version MAC Address Mode IP Address Subnet Mask Default Gateway Preferred DNS Alternate DNS	$\begin{array}{c c c c c c c c c c c c c c c c c c c $
MTU	(1500 LAN Download
Default	Back Next Cancel

Figure 4-8

Click Next button, you can set P2P function. Scan the QR code, download the App to the cellphone, you can use the smart phone to add the device. See Figure 4-9.



227

Now you can go to the remote device interface to add the camera to the corresponding channel. See Figure 4-10.

For detailed information, please refer to chapter4.11.1.1.

Please note you can not see the following interface if there is no digital channel. You can go to Main menu->Setting->Camera->Channel type to set IP channel first. Please refer to chapter 4.11.1.3.5 for detailed setup information.

				REMOTE	DEVICE			
0	Ec	lit IF	P Addres	s Mai	nufacturer		Туре]
IP Sear	roh)	Add	 	ual Add)		Show F	ilter (► IPC ▼
							<u> </u>	
Added D	Device							
Added E Chann		dit De	elete	Status	IP Addre	ess F	Port	Device Nam
		dit De	elete	Status	IP Addre	ess F	Port	Device Nam
		dit De	elete	Status	IP Addre	ess F	Port	Device Nam
Chann	nel Ed	dit De		Status	IP Addre		Port	
Chann	nel Ed	dit De		Status	IP Addre			

Figure 4-10

Click Next button, you can go to Encode interface. See Figure 4-11. For detailed information, please refer to chapter 4.11.1.3.

		ENCODE)	
Encode	Snapshot	Overlay		
Channel		Svc		
Туре	Regular	Sub Stream	1 💽	
Compression	(H.264H	• (H.264H	\mathbf{P}	
Resolution	(1280*720(720)	-) (352*288(CIF		
Frame Rate(FP:	S) (25	• 6	\square	
Bit Rate Type	CBR	CBR	$\overline{\mathbf{P}}$	
			_	
l Frame Interval	(1S	• (15	\mathbf{P}	
Bit Rate(Kb/S)	2048 🔻	160 🔻		
Reference Bit R	ate 1536-4096Kb/S	40-256Kb/S		
Audio/Video				
Audio Format	(G711a	Audio Sourc	e (LOCAL	\mathbb{D}
Audio Sampling	Rate (8K	•		
(Default)	Сору			(Apply)
		Back	Next	Cancel

Figure 4-11

Click Next button, you can go to Schedule interface. See Figure 4-12. For detailed information, please refer to chapter 4.11.4.1.

Channel (1 了	Pre-recor	d (4	S	ec. 🚺	Rec	lunda						
	Regular 2 4) 8	10	Alarm 12	14	ПМ 16	D&Ala 18	ırm 20	Intel 22 2 ⁴		
🗖 Sunday											٢	\$
🗖 Monday											٢	4
🗖 Tuesday											٢	\$
🗢 Wednesday											٢	\$
🗢 Thursday											٢	4
🗢 Friday												4
🗖 Saturday												\$
(Default)	Сору										Apply	

Figure 4-12

Click Finish button, system pops up a dialogue box. Click the OK button, the startup wizard is complete. See Figure 4-13.




Figure 4-13

4.4 Live Viewing

After you logged in, the system is in live viewing mode. You can see system date, time, channel name and window No. If you want to change system date and time, you can refer to general settings (Main Menu->Setting->System->General). If you want to modify the channel name, please refer to the display settings (Main Menu->Camera->CAM name)



<u>Tips</u>

- Preview drag: If you want to change position of channel 1 and channel 2 when you are previewing, you can left click mouse in the channel 1 and then drag to channel 2, release mouse you can switch channel 1 and channel 2 positions.
- Use mouse middle button to control window split: You can use mouse middle button to switch window split amount.

Please note you can not switch position of one analog channel and one digital channel.

Preview Control

The preview control function has the following features.

- Support preview playback.
 - In the preview desktop, system can playback previous 5-60 minutes record of current channel. Please go to the Main Menu->General to set real-time playback time.
 - Support drag and play function. You can use your mouse to select any playback start time.
 - ♦ Support playback, pause and exit function.

- Right now, system does not support slow playback and backward playback function.
- Support digital zoom function.
- Support real-time backup function.

You can follow the contents listed below for the operation instruction.

Preview control interface

Move you mouse to the top centre of the video of current channel, you can see system pops up the preview control interface. See Figure 4-14 and Figure 4-15. If your mouse stays in this area for more than 6 seconds and has no operation, the control bar automatically hides.




Figure 4-15 Digital Channel

1) Realtime playback

It is to playback the previous 5-60 minutes record of current channel.

Please go to the Main menu->Setting->->System->General to set real-time playback time.

System may pop up a dialogue box if there is no such record in current channel.

2) Digital zoom

It is to zoom in specified zone of current channel. It supports zoom in function of multiple-channel.

Click button S, the button is shown as S.

There are two ways for you to zoom in.

• Drag the mouse to select a zone, you can view an interface show as Figure 4-16.






Figure 4-16

• Put the middle button at the centre of the zone you want to zoom in, and move the mouse, you can view an interface shown as in Figure 4-17.



Figure 4-17

Right click mouse to cancel zoom and go back to the original interface.

3) Manual record function

It is to backup the video of current channel to the USB device. System can not backup the video of multiple-channel at the same time.

Click button system begins recording. Click it again, system stops recording. You can find the record file on the flash disk.

4) Manual Snapshot

Click Loss of the state of the

You can go to the Search interface (chapter 4.9.1) to view.

5) Mute (For analog channel only)

Click to mute. Click again to enable audio function when preview.

Please note this function is for one-window mode only.

6) Bidirectional talk (For digital channel only)

If the connected front-end device supports bidirectional talk function, you can click this

button. Click button $\underbrace{\mathbb{W}}$ to start bidirectional talk function the icon now is shown as $\underbrace{\mathbb{W}}$. Now the rest bidirectional talk buttons of digital channel becomes null too.

Click I again, you can cancel bidirectional talk and the bidirectional talk buttons of

other digital channels become as Ψ

7) Remote device (For digital channel only)

Shortcut menu. Click it to go to the remote device interface to add/delete remote device or view its corresponding information. Please refer to chapter 4.11.1.1 for detailed information.


4.5 Right-Click Menu

On the preview interface, right click mouse, you can view menu interface shown as in Figure 4-18.

Tips

After you go to the corresponding interface, right click mouse to go back to the upper-level.

- Window split mode: You can select window amount and then select channels.
- PTZ: Click it to go to PTZ interface.
- Auto focus: Please make sure you connected network camera supports this function.
- Color setting: Set video corresponding information.
- Search: Click it to go to Search interface to search and playback a record file.
- Record control: Enable/disable record channel.
- Remote device: Click it to add remote device.
- Main menu: Go to system main menu interface.



4.5.1 Window Switch

System supports 1/4/8/9-window (The options here depend on your product channel amount). You can select from the dropdown list. See Figure 4-19.





4.5.2 Previous Screen/Next Screen

Click it to go to the previous screen/next screen. For example, if you are using 4-split mode, the first screen is displaying the channel 1-4, click Next screen, you can view channel 5-8.

4.5.3 PTZ Control

The PTZ setup is shown as in See Figure 4-20.

Please note the commend name is grey once device does not support this function. The PTZ operation is only valid in one-window mode.

Here you can control PTZ direction, speed, zoom, focus, iris, preset, tour, scan, pattern aux function, light and wiper, rotation and etc.

Speed is to control PTZ movement speed. The value ranges from 1 to 8. The speed 8 is faster than speed 1. You can use the remote control to click the small keyboard to set.

You can click and the zoom, focus and iris to zoom in/out, definition and brightness.

The PTZ rotation supports 8 directions. If you are using direction buttons on the front panel, there are only four directions: up/down/left/right.




Figure 4-20

In the middle of the eight direction arrows, there is a 3D intelligent positioning key. See Figure 4-21. Please make sure your protocol supports this function and you need to use mouse to control.

Click this key, system goes back to the single screen mode. Drag the mouse in the screen to adjust section size. The dragged zone supports 4X to 16X speeds. It can realize PTZ automatically. The smaller zone you dragged, the higher the speed.



Name	Function	function	Shortcut	Function	function	Shortcut
	key		key	key		key
Zoom	•	Near	È	•	Far	••
Focus	•	Near	◀	•	Far	▶
Iris	•	close	◀	•	Open	▶

In Figure 4-20, click to open the menu, you can set preset, tour, pattern, scan and etc. See Figure 4-22.



Figure 4-22

Please refer to the following sheet for detailed information.

Please note the above interface may vary due to different protocols. The button is grey and can not be selected once the current function is null.

Right click mouse or click the ESC button at the front panel to go back to the Figure 4-20.

lcon	Function	Icon	Function
•	Preset		Flip
	Tour	Ð	Reset
~	Pattern		Aux
	Scan	0	Aux on-off button
•	Rotate	0	Go to menu

4.5.3.1 PTZ Function Setup

Click you can go to the following interface to set preset, tour, pattern, and scan. See Figure 4-23.



Figure 4-23

Preset Setup

In Figure 4-23, click preset button and use eight direction arrows to adjust camera to the proper position. The interface is shown as in Figure 4-24.

Click Set button and then input preset number.

Click Set button to save current preset.



Figure 4-24

Tour Setup

In Figure 4-23, click tour button.

Input tour value and preset No. Click Add preset button to add current preset to the tour. See Figure 4-25.

Tips

Repeat the above steps to add more presets to the tour. Click Del preset button to remove it from the tour. Please note some protocols do not support delete preset function.





Pattern Setup

In Figure 4-23, click Pattern button and input pattern number.

Click Begin button to start direction operation. Or you can go back to Figure 4-20 to operate zoom/focus/iris/direction operation.

In Figure 4-23, click End button.



Figure 4-26

Scan Setup

In Figure 4-23, click Scan button.

Use direction buttons to set camera left limit and then click Left button.

Use direction buttons to set camera right limit and then click Right button. Now the scan setup process is complete.



Figure 4-27

4.5.3.2 Call PTZ Function Call Preset

In Figure 4-22, input preset value and then click to call a preset. Click again to stop call.

Call Pattern

In Figure 4-22, input pattern value and then click to call a pattern. Click again to stop call.

Call Tour

In Figure 4-22, input tour value and then click to stop call.

Call Scan

In Figure 4-22, input Scan value and then click to call a tour. Click again to stop call.

Rotate

In Figure 4-22, click to enable the camera to rotate.

System supports preset, tour, pattern, scan, rotate, light and etc function.

Note:

- Preset, tour and pattern all need the value to be the control parameters. You can define it as you require.
- You need to refer to your camera user's manual for Aux definition. In some cases, it can be used for special process.

Aux

Click , system goes to the following interface. The options here are defined by the protocol. The aux number is corresponding to the aux on-off button of the decoder. See Figure 4-28.

4.5.4 Auto Focus

It is to set auto focus function. Please make sure the camera supports this function.

Figure 4-28

4.5.5 Color

Here you can set hue, brightness, contrast, saturation, gain, white level, color mode and etc. See Figure 4-29.







to call a tour. Click again



	COLOR	
Time Period	(Time Period 1	
Effective Time 🗹	(00:00 - 24:00	
Sharpness 🔺		1
Chroma 🔫		50
Brightness 🔅	_	50
Contrast 🕕	_	50
Saturation 省		50
Color mode	(Standard 🔽	
EQ 🗖	•	⁰ ╋ Ҁ ⊘
Position 😁		8
Customized	Default OK	Cancel



Please refer to the following sheet for detailed information.

Item	Note
Period	There are two periods in one day. You can set different sharpness, brightness, and contrast setup for different
	periods.
Effective Time	Check the box here to enable this function and then set period time.
	The value here is to adjust the edge of the video. The
	value ranges from 0 to 100. The larger the value is, the
Sharpness	clear the edge is and vice versa. Please note there is
	noise if the value here is too high. The default value is 50
	and the recommended value ranges from 40 to 60.
Brightness	It is to adjust monitor window bright. The value ranges from 0 to 100. The default value is 50.
	The larger the number, the bright the video is. When you
	input the value here, the bright section and the dark
	section of the video will be adjusted accordingly. You
	can use this function when the whole video is too dark or
	too bright. Please note the video may become hazy if the
	value is too high. The recommended value ranges from
	40 to 60.
Contrast	It is to adjust monitor window contrast. The value ranges

Item	Note
	from 0 to 100. The default value is 50.
	The larger the number, the higher the contrast is. You can use this function when the whole video bright is OK but the contrast is not proper. Please note the video may become hazy if the value is too low. If this value is too
	high, the dark section may lack brightness while the bright section may over exposure .The recommended value ranges from 40 to 60.
Saturation	It is to adjust monitor window saturation. The value ranges from 0 to 100. The default value is 50.
	The larger the number, the strong the color is. This value has no effect on the general brightness of the whole video. The video color may become too strong if the value is too high. For the grey part of the video, the
	distortion may occur if the white balance is not accurate. Please note the video may not be attractive if the value is too low. The recommended value ranges from 40 to 60.
Gain	The gain adjust is to set the gain value. The default value may vary due to different device models. The smaller the value, the low the noise. But the brightness is also too low in the dark environments. It can enhance the video brightness if the value is high. But the video noise may become too clear.
Color mode	It includes several modes such as standard, color, bright, gentle. Select a color mode, the sharpness, brightness, contrast and etc can automatically switch to corresponding setup.
EQ	Click Of the adjust image equalization value.
	to the best effect. This function is for analog channel only.
Image position	It is to adjust the image position on the screen. The value here refers to the pixel. The default pixel value is 16. This function is for analog channel only.

4.5.6 Display It is to set display output mode. There are two modes: full screen (4:3)/image original rate

(16:9). Icon emeans current display output mode. See Figure 4-30.




Figure 4-30

4.5.7 Face Search

It is to display human face record list, and view human face recognition record file.

4.5.8 Search

Please refer to chapter 4.9.1 for detailed information.

4.5.9 Record Control

Please refer to chapter 4.11.4.3 for detailed information.

4.5.10 Alarm Output

Please refer to chapter 4.11.3.6 for detailed information.

4.5.11 Remote Device

Please refer to chapter 4.11.1.1 for detailed information.

4.5.12 Video Matrix

Please refer to chapter 4.11.5.3 for detailed information.

4.5.13 Main menu

Please refer to chapter 4.8 for detailed information.

4.6 Navigation Bar

You need to go to the Main menu->Setting->System->General to enable navigation bar function; otherwise you can not see the following interface. The navigation bar is shown as below. See Figure 4-31.

	□ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □ □
Figure 4-3	1
4.6.1 Main Menu	
Click button Click button	interface.
4.6.2 Output Screen	
Select corresponding window-split mode and ou	Jtput channels.
4.6.3 Previous/Next Screen Click to go to the previous screen, click	to go to the next screen. For
example, if you are using 4-split mode, the firs	t screen is displaying the channel 1-4,
click you can view channel 5-8.	
4.6.4 Tour	
Click button 🔃 to enable tour, the icon becom	es , you can see the tour is in
process.	
4.6.5 Favorites	
Click system pops up add/edit favorites. See	e Figure 4-32.
Add to Favorites Edit Favorites	
	▼參ୣ▲₽
	0



4.6.6 Channel

It is to pop up channel tree. You can left click to select a channel on the tree and then drag it to the preview window on the left pane.

4.6.7 PTZ

Click, system goes to the PTZ control interface. Please refer to chapter 4.5.3.

4.6.8 Color

Click button (Section 2014), system goes to the color interface. Please refer to chapter 4.5.5.

4.6.9 Search

Click button, system goes to search interface. Please refer to chapter 4.9.1

4.6.10 Alarm Status

Click button A, system goes to alarm status interface. It is to view device status and channel status. Please refer to chapter 4.11.3.

4.6.11 Channel Info

Click button even goes to the channel information setup interface. It is to view information of the corresponding channel. See Figure 4-33.

				CHANNEI	LINFO			
Channel	Motion	Video Loss	Tamperin	g Record Statu	s Record Mode	Resolution	Frame Rate	Bit Rat
	0	Â	0	0	Pre-record	1280*720	25	:
2		Â		0	Pre-record	1280*720	25	
3		Ā	<u> </u>		Pre-record	1280*720	25	
4					Pre-record	1280*720	25	
5		Â		0	Pre-record	1280*720	25	
6		Ā	<u> </u>		Pre-record	1280*720	25	
7		Ā	0		Pre-record	1280*720	25	
8	Ö	Ā	Ö	Ö	Pre-record	1280*720	25	
9	<u> </u>	Ā	<u> </u>		Pre-record	1280*720	25	
10	Ö	Ā	Ō	ĕ	Pre-record	1280*720	25	
11	Ö	Ā	Ö	ĕ	Pre-record	1280*720	25	
12	Ö	Ā	Ö	ē	Pre-record	1280*720	25	
13	Ö	Ā	Ö	ĕ	Pre-record	1280*720	25	
14	Ö	Ā	Ö	ĕ	Pre-record	1280*720	25	
15				ē				
16		0		ĕ	Pre-record	960*480	25	
•								>
Defect								
Refresh								



4.6.12 Remote Device

Click system goes to an interface for you to view remote device information. Please refer to chapter 4.11.1.1.

4.6.13 Network

Click, system goes to the network interface. It is to set network IP address, default gateway and etc. Please refer to chapter 4.11.2.

4.6.14 HDD Manager

Click System goes to the HDD manager interface. It is to view and manage HDD information. Please refer to chapter 4.11.4.2.

4.6.15 USB Manager

Click , system goes to the USB Manager interface. It is to view USB information, backup and update. Please refer to chapter 4.9.3, chapter 4.10.4, chapter 4.11.5.10, and chapter 4.11.5.12 for detailed information.

4.7 USB Device Auto Pop-up

After you inserted the USB device, system can auto detect it and pop up the following dialogue box. It allows you to conveniently backup file, log, configuration or update system. See Figure 4-34. Please refer to chapter 4.9.3, chapter 4.10.4, chapter 4.11.5.10, and chapter 4.11.5.12 for detailed information.



Figure 4-34

4.8 Main Menu

The main menu interface is shown as below. See Figure 4-35.

		MAIN MENU			
OPERATE SEARCH	FACE SEARCH	BACKUP	SHUTDOWN		
INFO SYSTEM	EVENT	NETWORK	LOG		
SETTING CAMERA	NETWORK	EVENT	STORAGE	SYSTEM	

Figure 4-35

4.9 Operation

4.9.1 Search

Click search button in the main menu, search interface is shown as below. See Figure 4-36.

Usually there are three file types:

- R: Regular recording file.
- A: External alarm recording file.
- M: Motion detection recording file
- Orange: Intelligent recording file.



Figure 4-36

Please refer to the following sheet for more information.

SN	Name	Function
1	Display	Here is to display the searched picture or file.
	window	 Support 1/4/9/16-window playback.
		 Here you can select to search the picture or the recorded file. You can select to play from the read write UDD, from parinhered device or from
		 You can select to play from the read-write HDD, from peripheral device or from redundancy HDD.
		• Before you select to play from the peripheral device, please connect the
		corresponding peripheral device. You can view all record files of the root directory
	Search	of the peripheral device. Click the Browse button; you can select the file you want to
2	type	play.
		• Check the box here; you can enable splice playback function. Please refer to
		chapter 4.9.1.4 for detailed information.
		Important
		• Redundancy HDD does not support picture backup function, but it
		supports picture playback function. You can select to play from redundancy
		HDD if there are pictures on the redundancy HDD.
		• The blue highlighted date means there is picture or file. Otherwise, there is no
3	Calendar	picture or file.
		• In any play mode, click the date you want to see, you can see the

		corresponding record file trace in the time bar.
		 Playback mode: 1/4/9/16/customized. (It may vary due to different series.)
		 In 1-window playback mode: you can select 1-16 channels. A window playback mode: you can select 1 channels.
	Playback	♦ In 4-window playback mode: you can select 4 channels according to your
	mode	requirement.
	and	\diamond In 9-window playback mode, you can switch between 1-8 and 9-16 channels.
4	channel	\diamond In 16-window playback mode, you can switch between 1-16 and 17-32
	selection	channels.
	pane.	\diamond In customized mode, you can select one or more channel(s) you want to
	pane.	playback at the same time. See chapter 4.9.1.4.
		• The time bar will change once you modify the playback mode or the channel
		option.
		The card number search interface is shown as below. Here you can view card
	Card	number/field setup bar. You cam implement advanced search.
5	number search	
	Search	CARD 📝 🔤 Conternation of the content of the conte
	Mark file	Click it to go to mark file list interface. You can view all mark information of current
6		channel by time. Please refer to chapter 4.9.1.3 for detailed information.
	list button	Please note only the product of this icon supports mark function.
		• Double click it, you can view the picture/record file list of current day.
		• The file list is to display the first channel of the record file.
		● The system can display max 128 files in one time. Use the ◀ and ► or the
		mouse to view the file. Select one item, and then double click the mouse or click the
		ENTER button to playback.
		 You can input the period in the following interface to begin accurate search.
	File list	• File type: R—regular record; A—external alarm record; M—Motion detect
7	switch	record.
	button	
		• Lock file. Click the file you want to lock and click the button Lie to lock. The
		file you locked will not be overwritten.
		 Search locked file: Click the button to view the locked file.
		Play/Pause
		There are three ways for you to begin playback.
	Playback control	 The play button Double click the valid period of the time bar
8		 Double click the valid period of the time bar. Double click the item in the file list.
		In slow play mode, click it to switch between play/pause.
	pane.	
		Stop Backward play
		In normal play mode, left click the button, the file begins backward play.

	1	
		Click it again to pause current play.
		In backward play mode, click ►/ II to restore normal play.
		 In playback mode, click it to play the next or the previous section. You can click continuously when you are watching the files from the same channel. In normal play mode, when you pause current play, you can click < and ▶ to begin frame by frame playback. In frame by frame playback mode, click ▶/II to restore normal playback.
		Slow play
		In playback mode, click it to realize various slow play modes such as slow play 1, slow play 2, and etc.
		 Fast forward In playback mode, click to realize various fast play modes such as fast play 1,fast play 2 and etc.
		Note: The actual play speed has relationship with the software version.
		Smart search
		The volume of the playback
		Click the snapshot button in the full-screen mode, the system can snapshot 1 picture. System supports custom snap picture saved path. Please connect the peripheral device first, click snap button on the full-screen mode, you can select or create path. Click Start button, the snapshot picture can be saved to the specified path.
		Mark button. Please note this function is for some series product only. Please make sure there is a mark button in the playback control pane. You can refer to chapter 4.9.1.3 for detailed information.
		• It is to display the record type and its period in current search criteria.
9	Time bar	 In 4-window playback mode, there are corresponding four time bars. In other playback mode, there is only one time bar. Use the mouse to click one point of the color zone in the time bar, system begins playback. The time bar is beginning with 0 o'clock when you are setting the configuration. The time bar zooms in the period of the current playback time when you are playing the file. The green color stands for the regular record file. The red color stands for the external alarm record file. The yellow stands for the motion detect record file.
		•The option includes: 24H, 12H, 1H and 30M. The smaller the unit, the larger the
10	Time bar unit	 The option includes. 24H, 12H, 1H and solvi. The smaller the unit, the larger the zoom rate. You can accurately set the time in the time bar to playback the record. The time bar is beginning with 0 o'clock when you are setting the configuration. The time bar zooms in the period of the current playback time when you are playing the file.

11	Backup	 Select the file(s) you want to backup from the file list. You can check from the list. Then click the backup button, now you can see the backup menu. System supports customized path setup. After select or create new folder, click the Start button to begin the backup operation. The record file(s) will be saved in the specified folder. Check the file again you can cancel current selection. System max supports to display 32 files from one channel. After you clip on record file, click Backup button you can save it. For one device, if there is a backup in process, you can not start a new backup operation.
12	Clip	 It is to edit the file. Please play the file you want to edit and then click this button when you want to edit. You can see the corresponding slide bars in the time bar of the corresponding channel. You can adjust the slide bar or input the accurate time to set the file end time. After you set, you can click Clip button again to edit the second period. You can see the slide bar restore its previous position. Click Backup button after clip, you can save current contents in a new file. You can clip for one channel or multiple-channel. The multiple-channel click operation is similar with the one-channel operation. Please note: System max supports 1024 files backup at the same time. You can not operate clip operation if there is any file has been checked in the file list.
13	Record type	In any play mode, the time bar will change once you modify the search type.
		Other Functions
14	Smart search	 When system is playing, you can select a zone in the window to begin smart search. Click the motion detect button to begin play. Once the motion detect play has begun, click button again will terminate current motion detect file play. There is no motion detect zone by default. If you select to play other file in the file list, system switches to motion detect play of other file. During the motion detect play process, you can not implement operations such as change time bar, begin backward playback or frame by frame playback. Please refer to chapter 4.9.1.1 Smart Search for detailed operation.
15	Other channel synchroni zation switch to play	When playing the file, click the number button, system can switch to the same period of the corresponding channel to play.

	when playback	
16	Sync	In pane 13 of Figure 4-36, click Sync button, you can playback the files of different channels occurred at the same time.
17	Digital zoom	When the system is in full-screen playback mode, left click the mouse in the screen. Drag your mouse in the screen to select a section and then left click mouse to realize digital zoom. You can right click mouse to exit.
18	Manually switch channel when playback	During the file playback process, you can switch to other channel via the dropdown list or rolling the mouse. This function is null if there is no record file or system is in smart search process.

4.9.1.1 Smart Search

During the multiple-channel playback mode, double click one channel and then click the

button, system begins smart search. System supports 396(22*18 PAL) and 330(22*15 NTSC) zones. Please left click mouse to select smart search zones. See Figure 4-37.




Figure 4-37

Click the , you can go to the smart search playback. Click it again, system stops smart search playback.

Important

• System does not support motion detect zone setup during the full-screen mode.

• During the multiple-channel playback, system stops playback of rest channels if you implement one-channel smart search.

4.9.1.2 Accurate playback by time

Select records from one day, click the list, you can go to the file list interface. You can input time at the top right corner to search records by time. See image on the left side of

the Figure 4-38 For example, input time 11:00.00 and then click Search button, you can view all the record files after 11:00.00 (The records includes current time.). See image on the right side of the Figure 4-38 Double click a file name to playback. **Note**

- After you searched files, system implement accurate playback once you click Play for the first time.
- System does not support accurate playback for picture.
- System supports synchronization playback and non-synchronous playback. The synchronization playback supports all channels and non-synchronous playback only supports accurately playback of current select channel.




Figure 4-38

4.9.1.3 Mark Playback

Please make sure your purchased device support this function. You can use this function only if you can see the mark playback icon on the Search interface (Figure 4-36).

When you are playback record, you can mark the record when there is important information. After playback, you can use time or the mark key words to search corresponding record and then play. It is very easy for you to get the important video information.

Add Mark

When system is playback, click Mark button, you can go to the following interface. See Figure 4-39.

Add Mark
Mark Time (2013-09-27 10:01:08 Mark Name (
Default OK Cancel

Figure 4-39

Playback Mark

During 1-window playback mode, click mark file list button in Figure 4-36, you can go to mark file list interface. Double click one mark file, you can begin playback from the mark time.

• Play before mark time

Here you can set to begin playback from previous N seconds of the mark time.

Note

Usually, system can playbacks previous N seconds record if there is such kind of record file. Otherwise, system playbacks from the previous X seconds when there is such as kind of record.



Click the mark manager button on the Search interface (Figure 4-36); you can go to Mark Manager interface. See Figure 4-40. System can manage all the record mark information of current channel by default. You can view all mark information of current channel by time.

Marks Manager
Channel 1 Start Time 2013 - 09 - 27 00 : 00 : 00 End Time 2013 - 09 - 28 00 : 00 : 00 1 CH Mark Time Mark Name 1 1 2013-09-27 10:00:12 report
•
Delete

Figure 4-40

Modify

Double click one mark information item, you can see system pops up a dialogue box for you to change mark information. You can only change mark name here.

Delete

Here you can check the mark information item you want to delete and then click Delete button, you can remove one mark item. .

Note

- After you go to the mark management interface, system needs to pause current playback. System resume playback after you exit mark management interface.
- If the mark file you want to playback has been removed, system begins playback from the first file in the list.

4.9.1.4 Customized Playback

You can select one or more channel(s) to playback at the same time.

From main menu->Search or you can right click mouse on the preview interface and then select Search, you can go to Figure 4-36.

In pane 4, click , you can see the following interface. See Figure 4-41.



Figure 4-41

Now you can select one or more channel(s) and then click Q to search record(s).

System supports one or more channels. The window split mode can auto adjust according to the channel amount. System max supports 16-split.

Click button to select all channels at the same time.

Click **C**, system begins playback.

4.9.1.5 Splice Playback

For the large record file, you can use splice playback function to play the same file in several sections at the same time. It is very convenient for you to find the video footages you desire.

On the main menu, click Search button, or right click mouse and then select Search. You can go to the Figure 4-36.

On the right pane, check the box to enable splice playback function, and then set channel, date, split mode. The splice playback interface is shown as below. Each section has a triangle; time. See 4-42. small you can adjust it to set Figure 0:30 0:35 0:40 0:45 0:50

Figure 4-42

Note

Select split mode, so that the record can be spliced in several sections.

Select splice file.

- Click Playback, system playbacks from the first of current date by default.
- Click time bar, system playbacks from the time you click.
- Click 📕, you can select on the file list.

Note

- The splice playback is for 1-window playback mode.
- System supports 1/4/8/16-split mode. Slight different may be found here.
- The min period of each section is 5 minutes. For the record is less than 20 minutes, if you select 4-split mode (or more than 4-split mode), system can auto adjust so that the each section period is 5 minutes. In this situation, some channel may have no video.

4.9.2 Human Face Search

On the preview window, right click mouse and then select face search, or from the main menu, click Face search, you can go to the following interface. See Figure 4-43.




Figure 4-43

Please refer to the following sheet for detailed information.

SN	Name	Function
1	Display	• It is to display human face detection file list. The latest file is at the
	pan	top. \
		• Click Export, you can export the selected file to the USB device.
		There are two types: image/record.
		\diamond Image: Export the recognized human face image.
		\diamond Record: Export the record file before and after 10 seconds
		when the DVR recognizes the human face.
2	Playback	Play the searched record file or image. Double click to playback in full
	pane	screen.
3	Search	Set date, start time and end time, click Search button, you can view the
	pane	corresponding file list.

4.9.3 Backup

DVR support CD-RW, DVD burner, USB device backup, network download and eSATA. Here we introduce USB, eSATA backup. You can refer to Chapter 7 Web Client Operation for network download backup operation.

Click backup button, you can see an interface is shown as in Figure 4-44. Here is for you to view devices information.

You can view backup device name and its total space and free space. The device includes CD-RW, DVD burner, USB device, flash disk, eSATA backup.

BACKUP
Device Nan (sdc1(USB DISK)) (Browse) 0.00 KB(Space Needed) 13.78 GB/15.00 GB(Free/Total)
Type All • Start Time 2013 - 10 - 18 00 : 00 : 00 Record CH 1 End Time 2013 - 10 - 18 12 : 11 : 34 File Format DAV • Add (Remove)
O Channel Type Start Time End Time Size(KB)
*
Start

Figure 4-44

Select backup device and then set channel, file start time and end time.

Click add button, system begins search. All matched files are listed below. System automatically calculates the capacity needed and remained. See Figure 4-45.

Type Start Tir	Al me 🔞	2013 - 10 -	<i>i</i>) Record CH (1	\neg		
End Tir	ne 💽	2013 - 10 -	18 12:11:34	File Format	Ī (C	Add	(emove
43	🗸 Ch	annel Type	Start Time	End Time	Size(KB)		-
1	✓ 1	R	13-10-14 22:00:00	13-10-14 23:00:00	48176		
2	🔽 1	R	13-10-14 23:00:00	13-10-15 00:00:00	48037		
3	✓ 1	R	13-10-15 00:00:00	13-10-15 00:28:50	22528		
4	🗹 1	R	13-10-15 00:28:50	13-10-15 01:00:00	24668		
5	✓ 1	R	13-10-15 01:00:00	13-10-15 02:00:00	46815	3	
6	<u>v</u> 1	R	13-10-15 02:00:00	13-10-15 03:00:00	47802		
7	🗹 1	R	13-10-15 03:00:00	13-10-15 04:00:00	47566		
8	🗹 1	R	13-10-15 04:00:00	13-10-15 05:00:00	47468		
9	✓ 1	R	13-10-15 05:00:00	13-10-15 06:00:00	47358		
10	🗹 1	R	13-10-15 06:00:00	13-10-15 07:00:00	47773		
11	✓ 1	R	13-10-15 07:00:00	13-10-15 08:00:00	47229		
12	<u>v</u> 1	R	13-10-15 08:00:00	13-10-15 09:00:00	47865		
13	<u>v</u> 1	R	13-10-15 09:00:00	13-10-15 09:03:02	2780		
1/	1	P	12 10 15 00-05-55	12 10 15 00-57-22	10060		
							Start)
1/		P	12 10 15 00.05.55	12 10 15 00-57-22	10060	\subset	Start

Figure 4-45

System only backup files with a $~~\checkmark~$ before channel name. You can use Fn or cancel

button to delete $\sqrt{}$ after file serial number.

Click Start button, system begins copy. At the same time, the backup button becomes stop button. You can view the remaining time and process bar at the left bottom. See Figure 4-46.

		(sdc1(USB DISI Space Needed)	13.78 GB/15.00	GB(Free/Total)		Browse
Туре	(All 🔤)			
Start Tir	ne	3 2013 - 10 -	10 00:00:00) Record CH (1	-	
End Tin	ne	3 2013 - 10 -	18 12 : 11 : 34) File Format (DAV	$\overline{\mathbf{P}}$ $\overline{\mathbf{P}}$	Add (Remove)
43		Channel Type	Start Time	End Time	Size(KB)	^
1		1 R	13-10-14 22:00:00	13-10-14 23:00:00	48176	
2	\checkmark	1 R	13-10-14 23:00:00	13-10-15 00:00:00	48037	
3	\checkmark	1 R	13-10-15 00:00:00	13-10-15 00:28:50	22528	
4	\checkmark	1 R	13-10-15 00:28:50	13-10-15 01:00:00	24668	
5		1 R	13-10-15 01:00:00	13-10-15 02:00:00	46815	
6		1 R	13-10-15 02:00:00	13-10-15 03:00:00	47802	
7		1 R	13-10-15 03:00:00	13-10-15 04:00:00	47566	
8		1 R	13-10-15 04:00:00	13-10-15 05:00:00	47468	
9		1 R	13-10-15 05:00:00	13-10-15 06:00:00	47358	
10		1 R	13-10-15 06:00:00	13-10-15 07:00:00	47773	
11		1 R	13-10-15 07:00:00	13-10-15 08:00:00	47229	
12		1 R	13-10-15 08:00:00	13-10-15 09:00:00	47865	
13		1 R	13-10-15 09:00:00	13-10-15 09:03:02	2780	
<u>_1/</u>		1 D	12 10 15 00-05-55	12 10 15 00-57-22	10960	
						Stop
Remair	ning	time 0:2:59		4		



When the system completes backup, you can see a dialogue box prompting successful backup.

• File format: Click the file format; you can see there are two options: DAV/ASF. The file name format usually is: Channel number+Record type+Time. In the file name, the YDM format is Y+M+D+H+M+S. File extension name is .day.

Tips:

During backup process, you can click ESC to exit current interface for other operation. The system will not terminate backup process.

Note:

When you click stop button during the burning process, the stop function becomes activated immediately. For example, if there are ten files, when you click stop system just backup five files, system only save the previous 5 files in the device (But you can view ten file names).

4.9.4 Shut Down

In Figure 4-35, select Shut Down, you can go to the following interface. See Figure 4-47. There are three options: Shutdown/logout/reboot.

For the user who does not have the shut down right, please input corresponding password to shut down.



Figure 4-47

4.10 Information

4.10.1 System Info

Here is for you to view system information. There are total four items: HDD (hard disk information), record, BPS (data stream statistics), version. See Figure 4-48.

			INFO				
SYSTEM	EVEN	т 🛼	NETWORK	🚺 LOG			
HDD RECORD REC ESTIMATE BPS	SATA	1 2 - O					
VERSION	1*	Туре	Total Space	Free Space	Status	S.M.A.R.T	
	All 1*	- Read/Write	1.81 TB 1.81 TB	1.64 TB 1.64 TB	- Normal	-	
			I.01 ID	1.04 I D			

Figure 4-48

4.10.1.1 HDD Information

Here is to list hard disk type, total space, free space, video start time and status. See Figure 4-49.

• SATA: 1-2 here means system max supports 2 HDDS. o means current HDD is

normal. X means there is error. - means there is no HDD. If disk is damaged, system shows as "?". Please remove the broken hard disk before you add a new one.

- SN: You can view the HDD amount the device connected to. * means the second HDD is current working HDD.
- Type: The corresponding HDD properties.
- Total space: The HDD total capacity.
- Free space: The HDD free capacity.
- Status: HDD can work properly or not.
- SMART: Display HDD information. See Figure 4-50.

			INFO			
SYSTEM	📆 EVEN	л 🔜	NETWORK	🚺 LOG		
HDD RECORD REC ESTIMATE BPS	SATA	1 2 - O				
VERSION	1* All 1*	Type Read/Write	Total Space 1.81 TB 1.81 TB	Free Space 1.64 TB 1.64 TB	Status Normal	S.M.A.R.T
					-	_

Figure 4-49

Double click one HDD information; you can see the HDD SMART information. . See Figure 4-50.

Modle ST	2000V×000-1CU164					
	E4TXG4					
Status OK						
Describe:						
Smart ID	Attribute	Threshol	d Value	Worst Value	Status	▲
1	Read Error Rate	6	116	91	OK	
3	Spin Up Time	0	96	95	OK	
4	Start/Stop Count	20	100	100	OK	
5	Reallocated Sector Count	10	100	100	OK	
7	Seek Error Rate	30	72	60	OK	
9	Power On Hours Count	0	93	93	OK	
10	Spin-up Retry Count	97	100	100	OK	
12	Power On/Off Count	20	100	100	OK	
184	End-to-End Error	99	100	100	OK	
187	Reported Uncorrect	0	86	86	OK	
188	Command Timeout	0	100	99	OK	
189	High Fly Writes	0	1	1	OK	
191	G-Sense Error Rate	0	100	100	OK	
192	Power-Off Retract Cycle	0	100	100	OK	
193	Load/Unload Cycle Count	0	100	100	OK	La
	Tenenevetine	^	- 11	<u> </u>		

Figure 4-50

4.10.1.2 Record Info

It is to view record start time and end time. See Figure 4-51.

	INFO
SYSTEM	🔂 EVENT 🔄 NETWORK 隊 LOG
HDD RECORD REC ESTIMATE BPS VERSION	SATA 1 2 - O Start Time End Time
	All 2015-12-07 16:59:43 2016-01-13 15:09:30 1* 2015-12-07 16:59:43 2015-12-11 13:17:43 2015-12-14 15:15:54 2015-12-14 19:35:54 2016-01-13 09:46:28 2016-01-13 15:09:30

Figure 4-51

4.10.1.3 Record Estimate

System can calculate the record time based on the HDD space, or you can input the

			INFO		
SYSTEM	📆 EVENT	-	NETWORK	🚺 LOG	
HDD					
RECORD	Channel	Edit	Bit Rate(Kb/S)	Record Time	Resolution 🔺
	✓ 1	1	2048	24	1280*720(720P)
REC ESTIMATE	∠ 2	1	2048	24	1280*720(720P)
BPS	✓ 3 ✓ 4	1	2048	24	1280*720(720P)
VERSION	✓ 4 ✓ 5	1	2048	24	1280*720(720P)
	✓ 5 ✓ 6	<u> </u>	2048 2048	24 24	1280*720(720P)
	✓ 6 ✓ 7	1	2048	24 24	1280*720(720P) 1280*720(720P)
	✓ / ✓ 8	1	2048	24 24	1280*720(720P)
	✓ ° ✓ 9	1	2048	24	1280*720(720P)
	v j ✓ 10	<i>,</i>	2048	24	1280*720(720P)
	× 10 ✓ 11	1	2048	24	1280*720(720P)
	12	1	2048	24	1280*720(720P)
	<u> </u>	<u></u>	2010		
	Known Sp	ace	Known Time		
	Capacity (0)TB = (0	GB Sel	ect)
	Time (0		 Daγs		
				for reference only. Ple	ease be cautious
	when you are	e calculati	ng record period.		

record time you want to calculate the HDD space you need. See Figure 4-52.

Figure 4-52

Click *label{eq:click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-click-cl*

system can calculate the record time based on the channel setup and HDD space.



Figure 4-53

• Calculate the record period based on the HDD space

Check the channel you want to record file.

Click Known Space and then click the Select button to set HDD. Click OK button. Now you can see the record period (such as 5 days). See Figure 4-54.

HDD RECORD	Channel Edit	NETWORK Bit Rate(Kb/S) 2048	LOG Record Time	Resolution 🔺
RECORD	🗹 1 🥖			Resolution 🔺
	🗹 1 🥖			Resolution 🔺
		2048		
	2 /		24	1280*720(720P)
REC ESTIMATE		2048	24	1280*720(720P)
BPS		2048	24	1280*720(720P)
	4 🥖	2048	24	1280*720(720P)
VERSION	✓ 5 /	2048	24	1280*720(720P)
		2048	24	1280*720(720P)
		2048	24	1280*720(720P)
	8 🥖	2048	24	1280*720(720P)
	9 🥖	2048	24	1280*720(720P)
	10 🧪	2048	24	1280*720(720P)
	🗹 11 🧪	2048	24	1280*720(720P)
		2048	24	1280*720(720P) 🖵
	12	2040	24	
	Known Space	Known Time		
	Capacity (4.000	TB = (4000		ect
	Time (5	Days		
		estimation data here is ulating record period.	for reference only. Ple	ase be cautious
	when you are calc	alaang record period.		

Figure 4-54

• Calculate the HDD space based on the record period

Check the channel you want to record file.

Input days(s) you want to records, system can auto calculate the HDD space needed (such as 5.109TB). See Figure 4-55.

HDD RECORD REC ESTIMATE BPS VERSION	EVENT Channel Chane		NETWORK Bit Rate(Kb/S) 2048 2048 2048 2048 2048 2048 2048 2048	Record Time 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24 24	Resolution ▲ 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P)
RECORD REC ESTIMATE BPS VERSION	1 2 3 4 5 6 7 8 9 7 8 9 10		2048 2048 2048 2048 2048 2048 2048 2048	24 24 24 24 24 24 24 24 24 24 24 24	1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P)
RECORD REC ESTIMATE BPS VERSION	1 2 3 4 5 6 7 8 9 7 8 9 10		2048 2048 2048 2048 2048 2048 2048 2048	24 24 24 24 24 24 24 24 24 24 24 24	1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P)
REC ESTIMATE BPS VERSION	2 3 4 5 6 7 8 9 10	111111111	2048 2048 2048 2048 2048 2048 2048 2048	24 24 24 24 24 24 24 24 24 24	1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P)
BPS VERSION	3 4 5 6 7 8 9 10	11111111	2048 2048 2048 2048 2048 2048 2048 2048	24 24 24 24 24 24 24 24 24	1280*720(720P) 1280*720(720P) 1280*720(720P) 1280*720(720P) 1280*720(720P) 1280*720(720P) 1280*720(720P) 1280*720(720P)
VERSION	5 6 7 8 9 9 5 10	1111111	2048 2048 2048 2048 2048 2048 2048	24 24 24 24 24 24 24	1280*720(720P) 1280*720(720P) 1280*720(720P) 1280*720(720P) 1280*720(720P) 1280*720(720P) 1280*720(720P)
VERSION	5 6 7 8 9 9 5 10	1111111	2048 2048 2048 2048 2048 2048	24 24 24 24 24 24	1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P) 1280°720(720P)
	✓ 8 ✓ 9 ✓ 10	111111	2048 2048 2048 2048 2048	24 24 24 24 24	1280*720(720P) 1280*720(720P) 1280*720(720P) 1280*720(720P) 1280*720(720P)
	✓ 8 ✓ 9 ✓ 10	11111	2048 2048 2048	24 24 24 24	1280*720(720P) 1280*720(720P) 1280*720(720P)
	✓ 8 ✓ 9 ✓ 10	1111	2048 2048	24 24	1280*720(720P) 1280*720(720P)
	v 10	11	2048	24	1280*720(720P)
	v 10	1,			
		/	0010		
			2048	24	1280*720(720P)
	✓ 11	1	2048	24	1280*720(720P)
ť	12	/	2048	24	1280*720(720P) 🚽
	40		2040	24	
	Known Sp	ace	Known Time		
	Time (7) Daγs		
	Capacity (5.	100		GB	
	Note: The re	cord estir	mation data here is	for reference only. Ple	ease be cautious
	when you an	e calculat	ting record period.		

Figure 4-55

4.10.1.4 BPS

Here is for you to view current video data stream (KB/s) and occupied hard disk storage (MB/h). See Figure 4-56.

	INFO
SYSTEM	📷 EVENT 🖳 NETWORK 🚺 LOG
HDD	Channel Kb/S Resolution Wave
RECORD	1 91 1280*720 <u>[</u>
REC ESTIMATE	2 93 1280*720
BPS	3 93 1280*720
VERSION	4 92 1280 ⁺ 720
VERSION	5 90 1280 ⁺ 720
	6 91 1280*720 1
	7 92 1280*720
	8 92 1280*720
	9 93 1280*720
	10 93 1280*720
	11 91 1280*720
	12 93 1280*720
	13 93 1280*720
	14 92 1280*720
	15 0
	16 65 960*480

Figure 4-56

4.10.1.5 Version

Here is for you to view some version information such as version number, built date, serial number and etc. See Figure 4-57.

		INFO		
SYSTEM	EVENT		🚺 LOG	
HDD RECORD REC ESTIMATE BPS VERSION	System Version	2015-09-24 3.2.7.59066 1E025A2YAZT9012 2.4.1		

Figure 4-57

4.10.2 Event

It is to display device status and channel status. See Figure 4-58.



Figure 4-58

4.10.3 Network

4.10.3.1 Online Users

Here is for you to manage online users. See Figure 4-59.

You can disconnect one user or block one user if you have proper system right. Max disconnection setup is 65535 seconds.

System detects there is any newly added or deleted user in each five seconds and refresh the list automatically.

		INFO		
SYSTEM	EVENT		📜 LOG	
ONLINE USERS LOAD TEST	User Name admin Block for 60	IP 10.15.6.144	User Login Time 2013-10-21 03:26:05 PM	Block for

Figure 4-59

4.10.3.2 Network Load

Network load is shown as in Figure 4-60. Here you can view the follow statistics of the device network adapter.

Here you can view information of all connected network adapters. The connection status is shown as offline if connection is disconnected. Click one network adapter, you can view the flow statistics such as send rate and receive rate at the top panel.



Figure 4-60

4.10.3.3 Network Test

Network test interface is shown as in Figure 4-61.

- Destination IP: Please input valid IPV4 address or domain name.
- Test: Click it to test the connection with the destination IP address. The test results can display average delay and packet loss rate and you can also view the network status as OK, bad, no connection and etc.
- Network Sniffer backup: Please insert USB2.0 device and click the Refresh button, you can view the device on the following column. You can use the dropdown list to select peripheral device. Click Browse button to select the snap path. The steps here are same as preview backup operation.

You can view all connected network adapter names (including Ethernet, PPPoE, WIFI,

and 3G), you can click the button on the right panel to begin Sniffer. Click the grey stop button to stop. Please note system can not Sniffer several network adapters at the same time.

After Sniffer began, you can exit to implement corresponding network operation such as

login WEB, monitor. Please go back to Sniffer interface to click stop Sniffer. System can save the packets to the specified path. The file is named after "Network adapter name+time". You can use software such as Wireshark to open the packets on the PC for the professional engineer to solve complicated problems.

		INFO		
SYSTEM	📆 EVENT		🚺 LOG	
ONLINE USERS LOAD TEST	Network Test Destination IP Test Result			Test
	Network Sniffe Device Name Address	r Packet Backup (sdb1(USB DISK)	Refresh) Browse
	LAN1	IP 10.15.6.144	Sniffer Packet Size 0KB	Sniffer Packet Backup
	<u> </u>	_	_	

Figure 4-61

4.10.4 Log

4.10.4.1 Local Log

Here is for you to view system log file. System lists the following information. See Figure 4-62.

Log types include system operation, configuration operation, data management, alarm event, record operation, account manager, log clear, file operation and etc. It optimized reboot log. There are only three types: normal reboot, abnormal reboot and protection reboot. 0x02、0x03、0x04 is included in the protection reboot type.

- Start time/end time: Pleased select start time and end time, then click search button. You can view the log files in a list. System max displays 100 logs in one page. It can max save 1024 log files. Please use page up/down button on the interface or the front panel to view more.
- Backup: Please select a folder you want to save; you can click the backup button to save the log files. After the backup, you can see there is a folder named Log_time on the backup path. Double click the folder, you can see the log file
- Details: Click the Details button or double click the log item, you can view the detailed information. See Figure 4-63. Here you can use rolling bar to view information, or you can use Page up/Page down to view other log information.

SYSTEM EVENT NETWORK LOG LOG Type All • Start Time 2014 - 08 - 21 00 : 00 : 00 Details Search Start Time 2014 - 08 - 22 00 : 00 : 00 Details Search 38 Log Time Event • 1 27 2014-08-21 13:29:45 <video 4="" :="" loss=""></video>
Type All Start Time 2014 - 08 - 21 00 : 00 : 00 End Time 2014 - 08 - 22 00 : 00 : 00 Details 38 Log Time Event *
28 2014-08-21 13:29:45 HDD totals<1>, Current working HDD<1> 29 2014-08-21 13:32:25 User logged in <admin> 30 2014-08-21 13:33:45 Save Channel Name Config 31 2014-08-21 13:33:45 Save Channel Name Config 32 2014-08-21 13:33:45 Save Channel Name Config 33 2014-08-21 13:33:45 Save Channel Name Config 34 2014-08-21 13:33:45 Save OVERLAY Config 35 2014-08-21 13:33:45 Save OVERLAY Config 36 2014-08-21 13:33:45 Save OVERLAY Config 37 2014-08-21 13:33:45 Save OVERLAY Config 38 2014-08-21 13:47:25 User logged in<10.15.6.140></admin>
1/1 Jump To 1 GO

Figure 4-62

Select an item on the list and then click the Details button or double click the log item, you can view the detailed information such as log time, log type, log user, IP address and etc. See Figure 4-63.

	Detailed Information	
Log Time Log Type	2014-08-21 13:47:25 User Management>User logged in	
IP Address User	10.15.6.140 admin	
Previous		ОК

Figure 4-63

Note

- If there is no HDD, system max supports 1024 logs.
- If you have connected to the unformatted HDD, system max supports 5000 logs.
- If you have connected to the formatted HDD, system max supports 500,000 logs.
- System operation logs are saved in system memory. Other types of logs are saved in the HDD. If there is no HDD, other types of logs are saved in the system memory too.
- The logs are safe when you format the HDD. But the logs may become loss once you removed the HDD.

4.11 Setting

4.11.1 Camera

4.11.1.1 Remote Device (For digital channel only)

4.11.1.1.1 Remote Device

In the main menu, from Camera ->Remote, you can go to an interface shown as in Figure 4-64. Here you can add/delete remote device and view its corresponding information.

- IP search: Click it to search IP address. It includes device IP address, port, device name, manufacturer, type. Use your mouse to click the item name, you can refresh display order. Click IP address, system displays IP address from small to large. Click IP address again, you can see icon, system displays IP address from large to small. You can click other items to view information conveniently. For the network device already added to the device, you can see there is a small icon "*" after the SN in case there is repeatedly add operation.
- Add: Click it to connect to the selected device and add it to the Added device list. Support Batch add.

You can see the corresponding dialogue box if all digital-channel has connected to the front-end.

System can not add new device if the device you want to add has the same IP and TCP port as the device in the list.

- Show filter: You can use it to display the specified devices from the added device.
- Edit: Click button is or double click a device in the list, you can change channel setup.
- Delete: Please select one device in the Added device list and then click to remove.
- Status: means connection is OK and means connection failed.
- Delete: Select a device on the Added device list, click Delete button, system disconnect device first and then remove its name from the list.
- Manual add: Click it to add the IPC manually. The port number is 37777. The default user name is admin and password is admin.

	×.	SETTING			
	📻 NETWORK	D EVENT	STORAGE	SYSTEM	
REMOTE IMAGE	Remote	Status	Firmware		
ENCODE	8 E		Manufacturer	Туре	<u> </u>
	1 🗌 😅	10.15.7.111	Private	IPC	
CAM NAME	2	10.15.10.41	Private	IPC	
CHANNEL TYPE	3 📑 🛃	10.15.11.108 * 10.15.55.11	Private Private	IPC-HFW1220S IPC	
UPGRADE	4 ✓ 5 ✓	10.15.67.23	Private	IPC-HDBW8281	_
	6	192.168.1.52	Private	IPC-HFW8351E	
	7	192.168.1.120	Private	IPC	-
		400 400 4 000			
	(IP Search) (Add (Manual	Add)	Show Filter	
	Channel E	dit Delete Stat			ce Nam
	1 Jelete) 10.15.55.11		2AAN0(

Figure 4-64

Click the Manual Add button; you can go to the following interface. See Figure 4-65. Channel number: The dropdown list here displays unconnected channel number. You can go to Figure 4-64 to set remote channel connection.

Please note:

- This series product supports the IPC from many popular manufactures such as Sony, Hitachi, Axis, Samsung, Dynacolor, Arecont, Onvif and Dahua.
- System default IP address is 192.168.0.0 if you do not input IP address. System will not add current IP address.
- You can not add two or more devices in the Manual Add interface (Figure 4-65). Click O K button, system connects to the corresponding front-end device of current channel on the interface.

	Manual Add
Channel	(25
Manufacturer	Private
IP Address	(192.168.0.0
TCP Port	37777
User	admin
Password	••••
Remote Channel	1
Decoder Buffer	280 msec
	OK Cancel

Figure 4-65

- Show filer: It is to filter the searched device.
 - None: it is to display all searched devices.
 - IPC: It is to display all cameras.
 - DVR: It is to display all storage devices such as NVR, DVR.
- Change IP:
 - Clickel, you can change the information such as IP address, subnet mask, and default gateway, user name, password of the checked device. See Figure 4-66.

	Modify IP
IP Address (10 . 15 . 3 . 23
Subnet Mask	255 . 255 . 0 . 0
Default Gateway (10 . 15 . 0 . 1
User Name (admin
Password (
	OK Cancel

Figure 4-66

 \diamond You can check several devices at the same time and then click the edit

button See Figure 4-3. Please check Batch modify button and then input start IP, end IP and default gateway.

	Modify IP	
Batch Modify		
Start Address	(10 . 15 . 3 .	23
Subnet Mask	255 . 255 . 0 .	0
Default Gateway	(10 . 15 . 0 .	1
User Name	admin	
Password		
	OK Cancel	

Figure 4-67

• IP Export

System can export the Added device list to your local USB device.

Please insert the USB device and then click the Export button; you can see the following interface. See Figure 4-68.

		Browse			
Device Name Total Space	(sdb1(USB DISK))) (14.43 GB	Refresh Free Space (11.72 GB			
Address	(
Name			Size	Type Folder	Delete •
(New Folder)	Format				
			ОК		Cancel

Figure 4-68

Select the directory and then click the OK button. System pops up a dialogue box to remind you successfully exported. Please click OK button to exit.

Note

The exported file extension name is .CVS. The file information includes IP address, port, remote channel number, manufacturer, user name and password.

IP Import

Click Import button, you can see the following interface. See Figure 4-69.



Figure 4-69

Select the import file and then click the OK button. System pops up a dialogue box to remind you successfully exported. Please click OK button to exit.

Note:

If the imported IP has conflicted with current added device, system pops up a dialogue box to remind you. You have two options:

- OK: Click OK button, system uses the imported setup to overlay current one.
- Cancel: Click Cancel button, system adds the new IP setup.

- You can edit the exported .CVS file. Do not change the file format; otherwise it may result in import failure.
- Does not support customized protocol import and export.
- The import and export device shall have the same language format.
 - 4.11.1.1.2 Channel Status

Here you can view the IPC status of the corresponding channel such as motion detect, video loss, tampering, alarm and etc. See Figure 4-70.

• IPC status: Front-end does not support. Front-end supports. There is alarm event from current front-end.



- Connection status: Connection succeeded.
- Refresh: Click it to get latest front-end channel status.

		SETTIN	G		
	👬 NETWORK	To EVENT	STORAGE	SYSTEM	
REMOTE IMAGE ENCODE	Remote Device Status	Status	Firmware		
CAM NAME CHANNEL TYPE UPGRADE	Channel Stat 17 18	10101111	MD Video		
	• Refresh		_		

Figure 4-70

4.11.1.1.3 Firmware

It is to view channel, IP address, manufacturer, type, system version, SN, video input, audio input, and etc. See Figure 4-71.



Figure 4-71

4.11.1.2 Image

For analog channel, the camera interface is shown as in Figure 4-72. For digital channel, the camera interface is shown as in Figure 4-73.

- Channel: Select a channel from the dropdown list.
- Cable type: It is to set the cable type of the corresponding analog channel. When the setup here matches the actual cable you are using, you can get the best image effect. The default setup is COAXIAL.
- COAXIAL: When the corresponding channel is using coaxial cable, please select COAXIAL.
- ♦ UTP: When the corresponding channel is using UTP cable, please select UTP. Usually we recommend 10Ohm UTP cable.
- Saturation: It is to adjust monitor window saturation. The value ranges from 0 to 100. The default value is 50. The larger the number, the strong the color is. This value has no effect on the general brightness of the whole video. The video color may become too strong if the value is too high. For the grey part of the video, the distortion may occur if the white balance is not accurate. Please note the video may not be attractive if the value is too low. The recommended value ranges from 40 to 60.
- Brightness: It is to adjust monitor window bright. The value ranges from 0 to 100. The default value is 50. The larger the number is, the bright the video is. When you input the value here, the bright section and the dark section of the video will be adjusted accordingly. You can use this function when the whole video is too dark or too bright. Please note the video may become hazy if the value is too high. The recommended value ranges from 40 to 60.
- Contrast: It is to adjust monitor window contrast. The value ranges from 0 to 100. The default value is 50. The larger the number is, the higher the contrast is. You can use this function when the whole video bright is OK but the contrast is not proper. Please note the video may become hazy if the value is too low. If this value is too high, the dark section may lack brightness while the bright section may over exposure .The recommended value ranges from 40 to 60.
- Sharpness: The value here is to adjust the edge of the video. The value ranges from 0 to 100. The larger the value is, the clear the edge is and vice versa. Please note there is noise if the value here is too high. The default value is 50 and the recommended value ranges from 40 to 60.
- Mirror: It is to switch video up and bottom limit. This function is disabled by default.
- Flip: It is to switch video left and right limit. This function is disabled by default.
- BLC: It includes several options: BLC/WDR/HLC/OFF.
- BLC: The device auto exposures according to the environments situation so that the darkest area of the video is cleared
- WDR: For the WDR scene, this function can lower the high bright section and enhance the brightness of the low bright section. So that you can view these two sections clearly at the same time. The value ranges from 1 to 100. When you switch the camera from no-WDR mode to the WDR mode, system may lose several seconds record video.

- HLC: After you enabled HLC function, the device can lower the brightness of the brightest section according to the HLC control level. It can reduce the area of the halo and lower the brightness of the whole video.
- ♦ OFF: It is to disable the BLC function. Please note this function is disabled by default.
- Profile: It is to set the white balance mode. It has effect on the general hue of the video. This function is on by default. You can select the different scene mode such as auto, sunny, cloudy, home, office, night, disable and etc to adjust the video to the best quality.
- ♦ Auto: The auto white balance is on. System can auto compensate the color temperature to make sure the vide color is proper.
- Sunny: The threshold of the white balance is in the sunny mode.
- ♦ Night: The threshold of the white balance is in the night mode.
- Customized: You can set the gain of the red/blue channel. The value reneges from 0 to 100.
- Day/night. It is to set device color and the B/W mode switch. The default setup is auto.
- ♦ Color: Device outputs the color video.
- Auto: Device auto select to output the color or the B/W video according to the device feature (The general bright of the video or there is IR light or not.)
- ♦ B/W: The device outputs the black and white video.
- Sensor: It is to set when there is peripheral connected IR light.
- Image enhancement: It is to enhance video quality. The larger the value is, the clearer the video is. But the noise may become large too.
- 2D NR: It is to process the noise of the single image. The video may become soft after process. The larger the value is, the better the effect is.
- 3D NR: it is to process the multiple-frame (at least two frames). It is to use the frame information between the following two frames to reduce noise. The larger the value is, the better the effect is.

	_	SETTING			
CAMERA	뺽 NETWORK	To EVENT	STORAGE	SYSTEM	
IMAGE ENCODE CAM NAME CHANNEL TYPE	Channel Period Effective Time Saturation Brightness Contrast Hue Sharpness Image Enhance NR	1 Time Period 1 ♥ 00:00 - 24 50 50 50 50 50 50 50 50 50 50	Cable Type	COAXIAL	
	Default		Save	Cancel Apply	J

Figure 4-72

		SETTING	
		EVENT	STORAGE 🛃 SYSTEM
REMOTE IMAGE ENCODE	Channel	4	Config Files Day
CAM NAME	Auto Iris	• On O Off	Saturation 50
CHANNEL TYPE	Mirror	O On O Off	Brightness 50 Contrast 50
	Flip	Clockwise 90	Chroma 50
	3D Denoise BLC Mode Profile	On O Off Off Auto	
	Day & Night	Auto	Save Cancel Apply

4.11.1.3 Encode

It is to set video bit stream, picture bit stream, video overlay parameter and etc.

4.11.1.3.1 Video

Video setting includes the following items. See Figure 4-74.

- Channel: Select the channel you want.
- SVC: SVC is so called scaled video coding. Check the box to enable this function. During the network transmission process, system discards unimportant frames when the bandwidth is not sufficient or the decode capability is low. It is to guarantee video quality and transmission fluency.
- Type: Please select from the dropdown list. There are three options: regular/motion detect/alarm. You can set the various encode parameters for different record types.
- Compression: System supports H.264H, H.264, H.264B, and MJPEG.
 - H.264H: It is the High Profile compression algorithm. It has the high encode compression rate. It can achieve high quality encode at low bit stream. Usually we recommend this type.
 - ♦ H.264 is the general compression algorithm.
 - ♦ H.264B is the Baseline algorithm. Its compression rate is low. For the same video quality, it has high bit stream requirements.
- Smart codec: Select Start from the dropdown list to enable smart codec function. The DVR can auto reduce the video bit stream of the non-important surveillance object to save the storage space.
- Resolution: For analog channel, system supports various resolutions, you can select from the dropdown list. Please note the option may vary due to different series. For digital channel, the resolution here refers to the capability of the network camera.
- Frame rate: It ranges from 1f/s to 25f/s in NTSC mode and 1f/s to 30f/s in PAL mode.
- Bit rate type: System supports two types: CBR and VBR. In VBR mode, you can set video quality.
- Quality: There are six levels ranging from 1 to 6. The sixth level has the highest image quality.
- Video/audio: You can enable or disable the video/audio.
- Audio format: Please select from the dropdown list. There are three options: G711a/G711u/PCM.
- Audio source: Please select from the dropdown list. There are two options: local/HDCVI. For local mode, the audio signal is from the Audio In port. For HDCVI mode, the audio signal is from the coaxial cable of the camera.

CAMERA NETWORK EVENT STORAGE SYSTEM REMOTE IMAGE Encode Snapshot Overlay IMAGE Channel 1 • CAM NAME CHANNEL TYPE UPGRADE Channel 1 • Smart Codec Stop • H.264H • Frame Rate(FPS) 15 • 15 • Bit Rate Type CBR • 15 • I Frame Interval 1 • 1 • Bit Rate(Kb/S) 2048 • 320 •	
IMAGE Encode Snapsnot Overlay IMAGE Channel 1 • CAM NAME Type Regular • Sub Stream1 • CHANNEL TYPE Compression H.264H • H.264H • UPGRADE Smart Codec Stop • • • Resolution 1920*1080(1080P) • 352*288(CIF) • Frame Rate(FPS) 15 • 15 • Bit Rate Type CBR • CBR • I Frame Interval 1S • 1S •	
ENCODE Type Regular Sub Stream1 CAM NAME Compression H.264H H.264H UPGRADE Smart Codec Stop H.264H VPGRADE Resolution 1920*1080(1080P) 352*288(CIF) Frame Rate(FPS) 15 15 Bit Rate Type CBR CBR I Frame Interval 1S 1S	
CHANNEL TYPE Compression H.264H H.264H UPGRADE Smart Codec Stop Image: Compression Stop Resolution 1920*1080(1080P) 352*288(CIF) Image: Compression Frame Rate(FPS) 15 Image: Compression Image: Compression I Frame Interval 1 Image: Compression Image: Compression I Frame Interval 1 Image: Compression Image: Compression	
UPGRADE Smart Codec Stop Resolution 1920*1080(1080P) • 352*288(CIF) • Frame Rate(FPS) 15 • 15 • Bit Rate Type CBR • CBR • I Frame Interval 1S • 1S •	
OPGRADE Resolution 1920*1080(1080P) • 352*288(CIF) • Frame Rate(FPS) 15 • Bit Rate Type CBR • I Frame Interval 1S •	
Frame Rate(FPS) 15 Bit Rate Type CBR I Frame Interval 1S	
Bit Rate Type CBR CBR CBR	
I Frame Interval (1S)	
Bit Rate(Kb/S) (2048) (320)	
Reference Bit Rate 640-6144Kb/S 32-640Kb/S	
Audio Format G711a Audio Source (LOCAL)
Default Copy Save Cancel Appl	

Figure 4-74

4.11.1.3.2 Snapshot

Here you can set snapshot mode, picture size, quality and frequency. See Figure 4-75.

- Snapshot mode: There are two modes: regular and trigger. If you set timing mode, you need to set snapshot frequency. If you set trigger snapshot, you need to set snapshot activation operation.
- Image size: Here you can set snapshot picture size.
- Image quality: Here you can set snapshot quality. The value ranges from 1 to 6.
- Interval: It is for you to set timing (schedule) snapshot interval.

		SETTING		_
	📻 NETWORK	T EVENT	STORAGE	SYSTEM
REMOTE IMAGE	Encode	Snapshot	Overlay	
ENCODE CAM NAME	Manual Snap Channel	(1) /Time		
CHANNEL TYPE UPGRADE	Mode Image Size	Timing • (352*288(CIF) •)		
	Image Quality			
	Default	Сору	ОК	Cancel Apply

Figure 4-75

4.11.1.3.3 Overlay

Overlay interface is shown as in Figure 4-76.

- Cover area: Here is for you to set cover area. You can drag you mouse to set proper section size. In one channel video, system max supports 4 zones in one channel.
- Preview/monitor: privacy mask has two types. Preview and Monitor. Preview means the privacy mask zone can not be viewed by user when system is in preview status. Monitor means the privacy mask zone can not be view by the user when system is in monitor status.
- Time display: You can select system displays time or not when you playback. Please click set button and then drag the title to the corresponding position in the screen.
- Channel display: You can select system displays channel number or not when you playback. Please click set button and then drag the title to the corresponding position in the screen.
- Copy: After you complete the setup, you can click Copy button to copy current setup to other channel(s). You can see an interface is shown as in Figure 4-77. You can see current channel number is grey. Please check the number to select the channel or you can check the box ALL. Please click the OK button in Figure 4-77 and Figure 4-76 respectively to complete the setup.

Please highlight icon 🔳 to select the corresponding function.

		SETTIN	NG	
CAMERA	📻 NETWORK	To EVENT	STORAGE	SYSTEM
REMOTE IMAGE	Encode	Snapshot	Overlay	
ENCODE CAM NAME		1 Preview D F	Record Set	1234
CHANNEL TYPE UPGRADE	Time Display Channel Display		Record Set	
	Default C	ору	Save	Cancel Apply

Figure 4-76

Сору
1234
OK Cancel

Figure 4-77

4.11.1.3.4 Channel Name

It is to modify channel name. It max supports 31-character. See Figure 4-78.

Please note for digital channel, you can only modify the channel name of the connected network camera.

		SETTING		
CAMERA	👬 NETWORK	EVENT	STORAGE	SYSTEM
REMOTE IMAGE ENCODE CAM NAME CHANNEL TYPE UPGRADE	CAM 1 CAM 3 CAM 5 CAM 7 CAM 9 CAM 11 CAM 13 CAM 15	1 3 5 7 9 11 13 15 	CAM 2 CAM 4 CAM 6 CAM 8 CAM 10 CAM 12 CAM 14 CAM 16	2 4 6 8 10 12 14 16 Cancel Apply

Figure 4-78

4.11.1.3.5 Channel Type

It is to set channel type. Each channel supports analog standard definition connections/analog HD connection/network camera connection (Slight function difference may be found). For the IP channel, you need to set from the last channel. Please note DVR needs to restart to activate new setup.

The interface is shown as in Figure 4-79.

		SETTIN	IG		
	📻 NETWORI	K 📆 EVENT	STORAGE	SYSTEM	
IMAGE			Analog		
ENCODE	Channel	AUTO 🕢 🛛 CVI 🔲	Analog		
CAM NAME	1				
CHANNEL TYPE	2			<u> </u>	
	4			<u> </u>	
	5		<u> </u>	Ō	
	6				
	7		- $ -$	<u> </u>	
	9		+ $+$ $+$ $+$ $+$ $+$ $+$ $+$ $+$ $+$		
	10				
	11		<u> </u>	Ō	
	12				
	13				
	14			<u> </u>	
	16			- H	
	*Tips:Disabl		/ou can add one IP chani	nel. IP channel	
		begin from the last chan			
					-
	Default	Add IP CAM	Save) Cancel 🤇	Apply

Important notice about XVR series product:

- Nowadays, there are mainly two analog signal types on today market: analog standard definition (CVBS) and analog HD (CVI, AHD or Other). For XVR series product, each channel supports all types of signal connection (analog signal/IP signal). For analog signal connection, the default setup is AUTO, that is to say, no matter what analog signal (CVBS, CVI, AHD or other analog HD signal) connected; the XVR can automatically recognize the signal and display the proper image. There is no need to set manually.
- If the auto recognition error occurred, XVR series product supports manual setup too. The manual setup featuring high recognition speed and usually there is no error. For example, in Figure 4-80, you can set channel 1 to connect to CVI camera, channel 2 to connect to AHD camera, channel 3 to connect to CVBS camera.

		SETTING		
🥰 CAMERA	📆 NETWORI	K 📷 EVENT	STORAGE	SYSTEM
IMAGE ENCODE	Channel		Analog AHD CVBS	
CAM NAME	1			
CHANNEL TYPE	3			
	5			
	6		ō ō	
	7			
	8		<u> </u>	+ $+$ $+$ $ +$ $ +$ $ +$ $ +$ $ +$ $ +$ $+$ $+$ $+$ $+$ $+$ $+$ $+$ $+$ $+$
	10			
	11		d d	
	12			
	13			
	14			
	16			
	*Tips:Disabl	Add IP CAM		Cancel Apply

Figure 4-80

Important

Add/cancel IP CAM function is for some 4/8/16-channel series product only.

 Add IP CAM: Click it; you can add corresponding X IP channels. Here X refers to the product channel amount such as 4/8/16. System needs to restart to activate new setup. See Figure 4-81.

	SETTING				
	📻 NETWORK 🛛 👼 EVENT 🛛 🔂 STORAGE 🛛 🛃 SYSTEM				
IMAGE Analog ENCODE AUTO CVI AHD CVBS OTHER I CAM NAME 1 2 2 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0					
	OK Cancel 16 Image: Concel in the last of t	J			

Figure 4-81

For example, there is a 4-channel analog device, after the A/D switch, it can max supports 4 analog channels and 4 IP channels. Once it has become the 3+1 mode (3 analog

channels+1 IP channel), you click Add IP CAM button, system becomes 3+5 mode (3 analog channels+5 IP channel).

• Cancel IP CAM: Click it, you can cancel IP channel. System needs to restart to restore original status.




Figure 4-82

4.11.1.3.1 Upgrade



XVR series product does not support upgrade function via coaxible cable. That is to say, you cannot use this interface to upgrade the connected CVI camera if you are using XVR.

It is to update the online camera.

From main menu->setting->camera->remote upgrade, the interface is shown as below. See Figure 4-83.

Click Browse button and then select the upgrade file. Then select a channel (or you can select device type filter to select several devices at the same time.)

Click Start upgrade button to update. You can see the corresponding dialogue once the upgrade is finish.

	SETTING
	📅 NETWORK 📷 EVENT 🧏 STORAGE 🛛 🛃 SYSTEM
REMOTE IMAGE	Upgrade
ENCODE	Update File Browse
CAM NAME CHANNEL TYPE	Device(0/1) Type None
UPGRADE	Channel IP Address Status Status Type System V
	Start Upgrade

Figure 4-83

4.11.2 Network

4.11.2.1 TCP/IP

The single network adapter interface is shown as in Figure 4-84 and the dual network adapters interface is shown as in Figure 4-85

- Network Mode : Includes multiple access, fault tolerance, and load balancing
 - Multiple-address mode: eth0 and eth1 operate separately. You can use the services such as HTTP, RTP service via eth00 or the eth1. Usually you need to set one default card (default setup is etho) to request the auto network service form the device-end such as DHCP, email, FTP and etc. In multiple-address mode, system network status is shown as offline once one card is offline.
 - Network fault-tolerance: In this mode, device uses bond0 to communicate with the external devices. You can focus on one host IP address. At the same time, you need to set one master card. Usually there is only one running card (master card).System can enable alternate card when the master card is malfunction. The system is shown as offline once these two cards are both offline. Please note these two cards shall be in the same LAN.
 - Load balance: In this mode, device uses bond0 to communicate with the external device. The eth0 and eth1 are both working now and bearing the network load. Their network load are general the same. The system is shown as offline once these two cards are both offline. Please note these two cards shall be in the same LAN.
- Default Network Card: Please select eth0/eth1/bond0(optional) after enable multiple-access function

• Main Network Card: Please select eth0/eth1 (optional).after enable multiple access function.

Note: Some series support the above three configurations and supports functions as multiple-access, fault-tolerance and load balancing.

- IP Version: There are two options: IPv4 and IPv6. Right now, system supports these two IP address format and you can access via them.
- MAC address: The host in the LAN can get a unique MAC address. It is for you to access in the LAN. It is read-only.
- IP address: Here you can use up/down button (▲▼) or input the corresponding number to input IP address. Then you can set the corresponding subnet mask the default gateway.
- Default gateway: Here you can input the default gateway. Please note system needs to check the validity of all IPv6 addresses. The IP address and the default gateway shall be in the same IP section. That is to say, the specified length of the subnet prefix shall have the same string.
- DHCP: It is to auto search IP. When enable DHCP function, you can not modify IP/Subnet mask /Gateway. These values are from DHCP function. If you have not enabled DHCP function, IP/Subnet mask/Gateway display as zero. You need to disable DHCP function to view current IP information. Besides, when PPPoE is operating, you can not modify IP/Subnet mask /Gateway.
- MTU: It is to set MTU value of the network adapter. The value ranges from 1280-7200 bytes. The default setup is 1500 bytes. Please note MTU modification may result in network adapter reboot and network becomes off. That is to say, MTU modification can affect current network service. System may pop up dialog box for you to confirm setup when you want to change MTU setup. Click OK button to confirm current reboot, or you can click Cancel button to terminate current modification. Before the modification, you can check the MTU of the gateway; the MTU of the DVR shall be the same as or is lower than the MTU of the gateway. In this way, you can reduce packets and enhance network transmission efficiency.

The following MTU value is for reference only.

- 1500: Ethernet information packet max value and it is also the default value. It is the typical setup when there is no PPPoE or VPN. It is the default setup of some router, switch or the network adapter.
- ♦ 1492: Recommend value for PPPoE.
- ♦ 1468: Recommend value for DHCP.
- Preferred DNS server: DNS server IP address.
- Alternate DNS server: DNS server alternate address.
- Transfer mode: Here you can select the priority between fluency/video qualities.
- LAN download: System can process the downloaded data first if you enable this function. The download speed is 1.5X or 2.0X of the normal speed.
- LAN download: System can process the downloaded data first if you enable this function. The download speed is 1.5X or 2.0X of the normal speed.

After completing all the setups please click save button, system goes back to the previous menu.

		SETTING		_
N CAMERA	📻 NETWORK	EVENT	STORAGE	SYSTEM
TCP/IP CONNECTION WIFI 3G/4G PPPoE DDNS IP FILTER EMAIL FTP	IP Version MAC Address Mode IP Address Subnet Mask Default Gateway Preferred DNS Alternate DNS	IPv4 • 90:02:A9:97:92:44 • • STATIC • DHC 10 15 • 255 255 • 10 15 • 10 15 • 10 1 • 10 1 • 10 1 •	145 Test 0 1 80	
UPnP SNMP MULTICAST REGISTER ALARM CENTER P2P	MTU Default	(1500 LAN Download	Save	Cancel Apply

Figure 4-84

	SETTING					
	📻 NETWORK	The Event Storage System				
TCP/IP CONNECTION WIFI 3G/4G PPPoE DDNS IP FILTER EMAIL FTP UPnP SNIMP	Net Mode Ethernet Card MAC Address Mode IP Address Subnet Mask Default Gateway Preferred DNS Alternate DNS	Multi-address Default Ethernet Port Ethernet1 Ethernet1 IP Version IPv4 (14:10:25:10:10:10) IPv4 • STATIC O DHCP I0 15 (10 15 0 0 (10 15 0 1 (10 15 0 1 (10 1 2 80 (10 1 2 81				
MULTICAST REGISTER ALARM CENTER P2P	MTU	(1500 LAN Download Save Cancel Apply				

Figure 4-85

4.11.2.2 Connection

The connection setup interface is shown as in Figure 4-86.

- Max connection: system support maximal 128 users. 0 means there is no connection limit.
- TCP port: Default value is 37777.
- UDP port: Default value is 37778.

- HTTP port: Default value is 80.
- HTTPS port: Default value is 443.
- RTSP port: Default value is 554.

Important: System needs to reboot after you changed and saved any setup of the above four ports. Please make sure the port values here do not conflict.

		SETTING
SAMERA		📷 EVENT 🔤 STORAGE 📑 SYSTEM
TCP/IP		
TCP/IP CONNECTION WIFI 3G PPPoE DDNS IP FILTER EMAIL FTP UPnP SNMP MULTICAST REGISTER ALARM CENTRE P2P	Max Connection TCP Port UDP Port HTTP Port HTTPS Port RTSP Port	128 (0-128) 37777 (1025 - 65535) 37778 (1025 - 65535) 80 (1 - 65535) 443 (1 - 65535) 554 (1 - 65535)
1 21	Default	Save Cancel Apply

Figure 4-86

4.11.2.3 WIFI

The WIFI interface is shown as below. See Figure 4-87.

- Auto connect WIFI: Check the box here, system automatically connects to the previous WIFI hotspot.
- Refresh: You can click it to search the hotspot list again. It can automatically add the information such as the password if you have set it before.
- Disconnect: Here you can click it to turn off the connection.
- Connect: Here you can click it to connect to the hotspot. System needs to turn off current connection and then connect to a new hotspot if there is connection of you selected one.

Figure 4-87

• WIFI working status: Here you can view current connection status.

Please note:

- After successful connection, you can see WIFI connection icon at the top right corner of the preview interface.
- When the hotspot verification type is WEP, system displays as AUTO since the device can not detect its encryption type.
- System does not support verification type WPA and WPA2. The display may become abnormal for the verification type and encryption type.

After device successfully connected to the WIFI, you can view the hotspot name, IP address, subnet mask, default gateway and etc.

4.11.2.4 3G

3G setup interface is shown as below. See Figure 4-88.

Please refer to the following contents for the parameter information.

- Pane 1: Display 3G signal intensity after you enabled 3G function.
- Pane 2: Display 3G module configuration information after you enabled 3G function.
- Pane 3: Display 3G module status information after you enabled 3G function.

It is to display current wireless network signal intensity such as EVDO, CDMA1x, WCDMA, WCDMA, EDGE and etc.

- 3G module: It is to display current wireless network adapter name.
- 3G Enable/Disable: Check the box here to enable 3G module.
- Network type: There are various network types for different 3G network modules. You can select according to your requirements.

- APN: It is the wireless connection server. It is to set you access the wireless network via which method.
- AUTH: It is the authentication mode. It supports PAP/CHAP.
- Dial number: Please input 3G network dialup number you got from your ISP.
- User name: It is the user name for you to login the 3G network.
- Password: It is the password for you to login the 3G network.
- Pulse interval: You can set dialup duration. Once you disable the extra stream, the connection time begins. For example, if you input 5 seconds here, then 3G network connection period is 5 seconds. The device automatically disconnect when time is up. If there is no extra stream, 3G network connection is valid all the time. If the alive time is 0, then the 3G network connection is valid all the time.
- Dial: Here you can enable or disable 3G network connection/disconnection manually.
- 3G wireless network: Here is to display wireless network status, SIM card status, dial status. If the 3G connection is OK, then you can see the device IP address the wireless network automatically allocates.

		SETTING				
SAMERA		📆 EVENT		SYSTEM		
TCP/IP CONNECTION	No signal					1
WIFI	Ethernet Card (P 🗖	Enable			
3G PPPoE	Network Type (
DDNS	APN (2
IP FILTER						
EMAIL	Dial Number (
FTP	User Name (User Password (
UPnP) 0)s		Dial		
SNMP	Wireless Network					
MULTICAST	Module State :	IP /	Address -			3
REGISTER ALARM CENTRE	SIM State -	Sul	onet Mask -			
P2P	PPP State -	Del	fault Gateway -			
1 21						
	Default		ОК	Cancel	\pply	
<u>H</u>						

Figure 4-88

4.11.2.5 PPPoE

PPPoE interface is shown as in Figure 4-89.

Input "PPPoE name" and "PPPoE password" you get from your ISP (Internet service provider).

Click save button, you need to restart to activate your configuration.

After rebooting, DVR will connect to internet automatically. The IP in the PPPoE is the DVR dynamic value. You can access this IP to visit the unit.

	_	SETTING			
SAMERA		To EVENT	STORAGE	SYSTEM	
TCP/IP CONNECTION WIFI 3G PPPoE DDNS IP FILTER EMAIL FTP UPnP SNMP MULTICAST REGISTER ALARM CENTRE P2P		D . O . O . O D . O . O . O			
	Default		ОК	Cancel App	y)

Figure 4-89

4.11.2.6 DDNS Setup

DDNS setup interface is shown as in Figure 4-90.

You need a PC of fixed IP in the internet and there is the DDNS software running in this PC. In other words, this PC is a DNS (domain name server).

In network DDNS, please select DDNS type and highlight enable item. Them please input your PPPoE name you get from you IPS and server IP (PC with DDNS). Click save button and then reboot system.

Click save button, system prompts for rebooting to get all setup activated.

After rebooting, open IE and input as below:

http: //(DDNS server IP)/(virtual directory name)/webtest.htm

e.g.: http: //10.6.2.85/DVR _DDNS/webtest.htm.)

Now you can open DDNSServer web search page.

		SETTING		
		To EVENT	STORAGE	SYSTEM
TCP/IP CONNECTION WIFI 3G PPPoE DDNS	Server IP www. Domain Mode	hua DDNS → ww.dahuaddns.com) Default O Custo		
IP FILTER EMAIL FTP	Domain Name 🤇 Email	201310131633) .quickddns.com Please input email a	address.
UPnP SNMP MULTICAST REGISTER			that is idle for more than le reclaim if your email a	one year. You can get a ddress setup is right.
ALARM CENTRE P2P	(Default) (T	est	ОК	Cancel Apply

Figure 4-90

Please note DDNS type includes: CN99 DDNS, NO-IP DDNS, Dahua DDNS, Dyndns DDNS and sysdns DDNS. All the DDNS can be valid at the same time, you can select as you requirement.

Private DDNS function shall work with special DDNS server and special Professional Surveillance Software (PSS).

Dahua DDNS and Client-end Introduction

1) Background Introduction

Device IP is not fixed if you use ADSL to login the network. The DDNS function allows you to access the DVR via the registered domain name. Besides the general DDNS, the Dahua DDNS works with the device from the manufacturer so that it can add the extension function.

2) Function Introduction

The Dahua DDNS client has the same function as other DDNS client end. It realizes the bonding of the domain name and the IP address. Right now, current DDNS server is for our own devices only. You need to refresh the bonding relationship of the domain and the IP regularly. There is no user name, password or the ID registration on the server. At the same time, each device has a default domain name (Generated by MAC address) for your option. You can also use customized valid domain name (has not registered.).

3) Operation

Before you use Dahua DDNS, you need to enable this service and set proper server address, port value and domain name.

- Server address: www.dahuaddns.com
- Port number: 80

• Domain name: There are two modes: Default domain name and customized domain name.

Except default domain name registration, you can also use customized domain name (You can input your self-defined domain name.) After successful registration, you can use domain name to login installed of the device IP.

• User name: It is optional. You can input your commonly used email address.

Important

- Do not register frequently. The interval between two registrations shall be more than 60 seconds. Too many registration requests may result in server attack.
- System may take back the domain name that is idle for one year. You can get a notification email before the cancel operation if your email address setup is OK.

4.11.2.7 IP Filter

IP filter interface is shown as in Figure 4-91. You can add IP in the following list. The list supports max 64 IP addresses. System supports valid address of IPv4 and IPv6. **Please note system needs to check the validity of all IPv6 addresses and implement optimization.**

After you enabled trusted sites function, only the IP listed below can access current DVR. If you enable blocked sites function, the following listed IP addresses can not access current DVR.

- Enable: Highlight the box here, you can check the trusted site function and blocked sites function. You can not see these two modes if the Enable button is grey.
- Type: You can select trusted site and blacklist from the dropdown list. You can view the IP address on the following column.
- Start address/end address: Select one type from the dropdown list, you can input IP address in the start address and end address. Now you can click Add IP address or Add IP section to add.
 - a) For the newly added IP address, it is in enable status by default. Remove the $\sqrt{}$ before the item, and then current item is not in the list.
 - b) System max supports 64 items.

 - d) System automatically removes space if there is any space before or after the newly added IP address.
 - e) System only checks start address if you add IP address. System check start address and end address if you add IP section and the end address shall be larger than the start address.
 - f) System may check newly added IP address exists or not. System does not add if input IP address does not exist.
- Delete: Click it to remove specified item.
- Edit: Click it to edit start address and end address. See Figure 4-92. System can check the IP address validity after the edit operation and implement IPv6 optimization.

• Default: Click it to restore default setup. In this case, the trusted sites and blocked sites are both null.

Note:

- If you enabled trusted sites, only the IP in the trusted sites list can access the device.
- If you enabled blocked sites, the IP in the blocked sites can not access the device.
- System supports add MAC address.

		SETTIN	IG			
CAMERA		To EVENT	STORAGE	्रि ऽ।	/STEM	
TCP/IP CONNECTION WIFI 3G PPPoE DDNS	Start Address (End Address (Trusted Sites)		(Add IP Addr (Add IP Segr	nent	
IP FILTER EMAIL FTP UPnP SNMP MULTICAST REGISTER ALARM CENTRE	Start Ad	dress	End Address	Edit	Delete	
P2P	Default	_	ОК	Cance	I Apply	J

Figure 4-91

Edit
Start Address 10.15.6.140 123 End Address 10.15.6.145
OK Cancel



4.11.2.8 Email

The email interface is shown as below. See Figure 4-93.

- SMTP server: Please input your email SMTP server IP here.
- Port: Please input corresponding port value here.
- User name: Please input the user name to login the sender email box.
- Password: Please input the corresponding password here.
- Sender: Please input sender email box here.

- Title: Please input email subject here. System support English character and Arabic number. Max 32-digit.
- Receiver: Please input receiver email address here. System max supports 3 email boxes. System automatically filters same addresses if you input one receiver repeatedly.
- SSL enable: System supports SSL encryption box.
- Interval: The send interval ranges from 0 to 3600 seconds. 0 means there is no interval.
- Health email enable: Please check the box here to enable this function. This function allows the system to send out the test email to check the connection is OK or not.
- Interval: Please check the above box to enable this function and then set the corresponding interval. System can send out the email regularly as you set here. Click the Test button, you can see the corresponding dialogue box to see the email connection is OK or not.

Please note system will not send out the email immediately when the alarm occurs. When the alarm, motion detection or the abnormity event activates the email, system sends out the email according to the interval you specified here. This function is very useful when there are too many emails activated by the abnormity events, which may result in heavy load for the email server.

	SETTING	
	🛜 NETWORK 🛛 👼 EVENT 🛛 💁 STORAGE 🛛 🛃 SYSTEM	
TCP/IP CONNECTION	Enable	
WIFI	SMTP Server (MailServer) Port (25)	
3G/4G	Anonymous	
PPPoE	User Name Password	
DDNS		
IP FILTER	Receiver	
EMAIL	Sender	
FTP	Subject (HCVR ALERT) Attachment	
UPnP	Encrypt Type NONE	
SNMP	Interval 120 sec.	
MULTICAST	Health Enable 🔲	
REGISTER	Interval 60 min.	
ALARM CENTER		
P2P		
	Default Test Save Cancel Apply	

Figure 4-93

4.11.2.9 FTP

You need to download or buy FTP service tool (such as Ser-U FTP SERVER) to establish

FTP service.

Please install Ser-U FTP SERVER first. From "start" -> "program" -> Serv-U FTP Server -> Serv-U Administator. Now you can set user password and FTP folder. Please note you need to grant write right to FTP upload user. See Figure 4-94.

Serv-U Administrator - << Local Serv File Edit User View Window Help	er >> X
🗑 🗙 🙀 🗢 🗈 🖻 🕺 K 🖻 🛍	🛷 🍙 🖇
× Serv-U Servers Setings Activity Domains Part 2 chonghy Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Activity Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Settings Se	×
< <local server="">> [System Administrator]</local>	Down: 0.000 kBps / Up: 0.000 kBps 3 of 32767 Sockets 0 (0) Users 0 Xfers

Figure 4-94

You can use a PC or FTP login tool to test setup is right or not.

For example, you can login user ZHY to <u>FTP://10.10.7.7</u> and then test it can modify or delete folder or not. See Figure 4-95.

Interne	t Explorer		X
?	To log on to ti	his FTP server, type a user name and password.	
	FTP server:	10.10.7.7	
	<u>U</u> ser name:		
	Password:		
	After you log	on, you can add this server to your Favorites and return to it easily	·.
	Log on and	onymously	
		Log On Cancel	

Figure 4-95

System also supports upload multiple DVRs to one FTP server. You can create multiple folders under this FTP.

FTP interface is shown as in Figure 4-96.

Please highlight the icon 📕 in front of Enable to activate FTP function.

Here you can input FTP server address, port and remote directory. When remote directory is null, system automatically create folders according to the IP, time and channel.

User name and password is the account information for you to login the FTP.

File length is upload file length. When setup is larger than the actual file length, system will upload the whole file. When setup here is smaller than the actual file length, system only

uploads the set length and auto ignore the left section. When interval value is 0, system uploads all corresponding files.

After completed channel and weekday setup, you can set two periods for one each channel.

Click the Test button, you can see the corresponding dialogue box to see the FTP connection is OK or not.

	SETTING	
SAMERA	TRANSPORT REVENT	
TCP/IP CONNECTION WIFI	Enable	
3G PPPoE DDNS	Server IP 0 . 0 . 0 . 0 Port 21 User Name	
ip filter Email FTP	Image Upload Interval 2s	
UPnP SNMP MULTICAST REGISTER ALARM CENTRE P2P	Channel 1 Weekday Thu Time Period 1 00 : 00 00 : 00 - 24 : 00 Time Period 2 00 : 00	
	Default Test OK Cancel Apply	

Figure 4-96

4.11.2.10 UPnP

The UPNP protocol is to establish a mapping relationship between the LAN and the WAN. Please input the router IP address in the LAN in Figure 4-84. See Figure 4-97.

- UPNP on/off : Turn on or off the UPNP function of the device.
- Status: When the UPNP is offline, it shows as "Unknown". When the UPNP works it shows "Success"
- Router LAN IP: It is the router IP in the LAN.
- WAN IP: It is the router IP in the WAN.
- Port Mapping list: The port mapping list here is the one to one relationship with the router's port mapping setting.
- List:
 - ♦ Service name: Defined by user.
 - ♦ Protocol: Protocol type
 - \diamond Internal port: Port that has been mapped in the router.
 - ♦ External port: Port that has been mapped locally.

- Default: UPNP default port setting is the HTTP, TCP and UDP of the DVR.
- Add to the list: Click it to add the mapping relationship.
- Delete: Click it to remove one mapping item.

Double click one item; you can change the corresponding mapping information. See Figure 4-98.

Important:

When you are setting the router external port, please use 1024~5000 port. Do not use well-known port 1~255 and the system port 256~1023 to avoid conflict.

For the TCP and UDP, please make sure the internal port and external port are the same to guarantee the proper data transmission.

	SETTIN	G	
		STORAGE	SYSTEM
TCP/IP CONNECTION WIFI 3G PPPoE DDNS	PAT O Enable ● Disab UPnP Status Router LAN IP 0 . 0 . 0 WAN IP 0 . 0 . 0 PAT Table	· 0 · 0	
IP FILTER EMAIL FTP UPnP SNMP MULTICAST REGISTER ALARM CENTRE	7 Service Name 1 HTTP 2 TCP 3 UDP 4 RTSP 5 RTSP 6 SNMP 7 HTTPS	Protocol Int.Port TCP 80 TCP 37777 UDP 37778 UDP 554 TCP 554 UDP 161 TCP 443	Ext.Port 80 37777 37778 554 554 161 443
P2P	Default Add Delete	ОК	Cancel Apply

Figure 4-97

	PORT INFO
Service Name Protocol Int.Port Ext.Port	(TCP (TCP (37777 (37777) (37777)
	OK Cancel

Figure 4-98

4.11.2.11 SNMP

SNMP is an abbreviation of Simple Network Management Protocol. It provides the basic network management frame of the network management system. The SNMP widely used in many environments. It is used in many network device, software and system. You can set in the following interface. See Figure 4-99.

		SETTING		
STAMERA	NETWORK	Devent	STORAGE	SYSTEM
TCP/IP				
CONNECTION	Enable			
WIFI	SNMP Version	✓ V1 ✓ V2		
3G	SNMP Port	(161		
PPPoE	Read-Community	/ (public		
DDNS	Write-Community	(private		
IP FILTER	Trap Address			
EMAIL	Trap Port	(162)		
FTP				
UPnP				
SNMP				
MULTICAST				
REGISTER				
ALARM CENTRE				
P2P				
	Default		(Save	Cancel Apply
-				

Figure 4-99

Please enable the SNMP function. Use the corresponding software tool (MIB Builder and MG-SOFT MIB Browser. You still need two MIB file: BASE-SNMP-MIB, DVR-SNMP-MIB) to connect to the device. You can get the device corresponding configuration information after successfully connection.

Please follow the steps listed below to configure.

- In Figure 4-99, check the box to enable the SNMP function. Input the IP address of the PC than is running the software in the Trap address. You can use default setup for the rest items.
- Compile the above mentioned two MIB file via the software MIB Builder.
- Run MG-SOFT MIB Browser to load the file from the previous step to the software.
- Input the device IP you want to manage in the MG-SOFT MIB Browser. Please set the corresponding version for your future reference.
- Open the tree list on the MG-SOFT MIB Browser; you can get the device configuration. Here you can see the device has how many video channels, audio channels, application version and etc.

Note

Port conflict occurs when SNMP port and Trap port are the same.

4.11.2.12 Multicast

Multicast setup interface is shown as in Figure 4-100.

	SETTING
SAMERA	
TCP/IP CONNECTION WIFI 3G PPPoE DDNS IP FILTER EMAIL FTP UPnP SNMP MULTICAST REGISTER ALARM CENTRE P2P	✓ Enable IP Address 239 . 255 . 42 . 42 Port 36666
	Default OK Cancel Apply

Figure 4-100

Here you can set a multiple cast group. Please refer to the following sheet for detailed information.

• IP multiple cast group address

-224.0.0.0-239.255.255.255

-"D" address space

• The higher four-bit of the first byte="1110"

• Reserved local multiple cast group address

-224.0.0.0-224.0.0.255

-TTL=1 When sending out telegraph

-For example

224.0.0.1 All systems in the sub-net

- 224.0.0.2 All routers in the sub-net
- 224.0.0.4 DVMRP router

224.0.0.5 OSPF router

224.0.0.13 PIMv2 router

Administrative scoped addressees

-239.0.0.0-239.255.255.255

-Private address space

- Like the single broadcast address of RFC1918
- Can not be used in Internet transmission
- Used for multiple cast broadcast in limited space.

Except the above mentioned addresses of special meaning, you can use other addresses. For example:

Multiple cast IP: 235.8.8.36

Multiple cast PORT: 3666.

After you logged in the Web, the Web can automatically get multiple cast address and add it to the multiple cast groups. You can enable real-time monitor function to view the view. Please note multiple cast function applies to special series only.

4.11.2.13 Auto register

This function allows the device to auto register to the proxy you specified. In this way, you can use the client-end to access the DVR and etc via the proxy. Here the proxy has a switch function. In the network service, device supports the server address of IPv4 or domain.

Please follow the steps listed below to use this function.

Please set proxy server address, port, and sub-device name at the device-end. Please enable the auto register function, the device can auto register to the proxy server.

1) The setup interface is shown as in Figure 4-101.

Important

Do not input network default port such as TCP port number.

		SETTING		
SAMERA		To EVENT	STORAGE	SYSTEM
TCP/IP				
CONNECTION	🗹 Enable			
WIFI	No. (1			
3G	Server IP (0.0.0.	1 K		
PPPoE	Port (8000			
DDNS				
IP FILTER				
EMAIL				
FTP				
UPnP				
SNMP				
MULTICAST				
REGISTER				
ALARM CENTRE				
P2P				
	Default		(Save	Cancel Apply

Figure 4-101

2) The proxy server software developed from the SDK. Please open the software and input the global setup. Please make sure the auto connection port here is the same as the port you set in the previous step.

3) Now you can add device. Please do not input default port number such as the TCP port

in the mapping port number. The device ID here shall be the same with the ID you input in Figure 4-101. Click Add button to complete the setup.

4) Now you can boot up the proxy server. When you see the network status is Y, it means your registration is OK. You can view the proxy server when the device is online.

Important

The server IP address can also be domain. But you need to register a domain name before you run proxy device server.

4.11.2.14 Alarm Centre

This interface is reserved for you to develop. See Figure 4-102.

		SETTING		
		To EVENT		SYSTEM
TCP/IP CONNECTION WIFI 3G PPPoE DDNS IP FILTER EMAIL FTP UPnP SNMP MULTICAST REGISTER ALARM CENTRE P2P	Enable Protocol Type	Private	2	
	Default		ОК	Cancel Apply

Figure 4-102

4.11.2.15 P2P

You can use your cell phone to scan the QR code and add it to the cell phone client. Via the SN from scanning the QR code, you can access the device in the WAN. Please refer to the P2P operation manual included in the resources CD.

From main menu->Setting->Network->P2P, you can go to the following interface, the P2P interface is shown as in Figure 4-103.

		SETT		
	T NETWORK	To EVENT	STORAGE	SYSTEM
TCP/IP CONNECTION WIFI 3G/4G PPPoE DDNS IP FILTER EMAIL FTP UPnP SNMP MULTICAST REGISTER ALARM CENTER P2P	Enable Status Offline Cell Phon		Device SN	
	Default		Save	Cancel Apply

Figure 4-103

• Android:

Open Google Play app in your smart phone. Search gDMSS Lite or gDMSS Plus, download it and install.

• iOS:

Open App Store app in your smart phone. Search iDMSS Lite or iDMSS Plus, download it and install.

Please follow the steps listed below.



- Open App; tap **International** to go to the Liv preview.
- Tap 🗮 at the top left corner, you can see the main menu.
- Tap Device manager button, you can use several modes (P2P/DDNS/IP and etc) to

add the device. Click ^[] to save current setup. Tap Start Live preview to view all-channel video from the connected device. See Figure 4-104.

e Pi	2P 🔚
Register Mode:	P2P
Name:	
SN:	M
Username:	admin
Password:	•••••
Live Preview:	Extra >
Playback:	Extra >
<u>&</u> ,	Check VTO
Start Live	e Preview

Figure 4-104

4.11.3 Event

4.11.3.1 Detect

In the main menu, from Setting->Event->Detect, you can see motion detect interface. See Figure 4-105.There is three detection types: motion detection, video loss, tampering.

- The video loss has no detection region and sensitivity setup and tampering has no detection region setup.
- You can see motion detect icon if current channel has enabled motion detect alarm.
- You can drag you mouse to set motion detect region. Please click OK button to save current region setup. Right click mouse to exit current interface.
- For digital channel, the detect function refers to support detection function of the front-end and support local activation function. The front-end can get enable/disable status, sensitivity and region setup. You can get corresponding prompt if front-end can not get the above information. You can change front-end setup if it can get.

4.11.3.1.1 Motion Detect

After analysis video, system can generate a video loss alarm when the detected moving signal reached the sensitivity you set here.

Detection menu is shown as below. See Figure 4-105.

- Event type: From the dropdown list you can select motion detection type.
- Channel: Select a channel from the dropdown list to set motion detect function.
- Enable: Check the box here to enable motion detect function.

- Region: Click select button, the interface is shown as in Figure 4-106. Here you can set motion detection zone. There are four zones for you to set. Please select a zone first and then left drag the mouse to select a zone. The corresponding color zone displays different detection zone. You can click Fn button to switch between the arm mode and disarm mode. In arm mode, you can click the direction buttons to move the green rectangle to set the motion detection zone. After you completed the setup, please click ENTER button to exit current setup. Do remember click save button to save current setup. If you click ESC button to exit the region setup interface system will not save your zone setup.
- Sensitivity: System supports 6 levels. The sixth level has the highest sensitivity.
- Anti-dither: Here you can set anti-dither time. The value ranges from 5 to 600s. The anti-dither time refers to the alarm signal lasts time. It can be seem as the alarm signal activation stays such as the buzzer, tour, PTZ activation, snapshot, channel record. The stay time here does not include the latch time. During the alarm process, the alarm signal can begin an anti-dither time if system detects the local alarm again. The screen prompt, alarm upload, email and etc will not be activated. For example, if you set the anti-dither time as 10 second, you can see the each activation may last 10s if the local alarm is activated. During the process, if system detects another local alarm signal at the fifth second, the buzzer, tour, PTZ activation, snapshot, record channel will begin another 10s while the screen prompt, alarm upload, email will not be activated again. After 10s, if system detects another alarm signal, it can generate an alarm since the anti-dither time is out.
- Period: Click set button, you can see an interface is shown as in Figure 4-108. Here you can set motion detect period. System only enables motion detect operation in the specified periods. It is not for video loss or the tampering. There are two ways for you to set periods. Please note system only supports 6 periods in one day.
- ♦ In Figure 4-108, Select icon of several dates, all checked items can be edited

together. Now the icon is shown as . Click to delete a record type from one period.

- ♦ In Figure 4-108. Click button after one date or a holiday, you can see an interface shown as in Figure 4-109. There are four record types: regular, motion detection (MD), Alarm, MD & alarm.
- Alarm output: when an alarm occurs, system enables peripheral alarm devices.
- Latch: when motion detection complete, system auto delays detecting for a specified time. The value ranges from 1-300(Unit: second)
- Show message: System can pop up a message to alarm you in the local host screen if you enabled this function.
- Alarm upload: System can upload the alarm signal to the network (including alarm centre) if you enabled current function.
- Send email: System can send out email to alert you when an alarm occurs.

- Record channel: System auto activates motion detection channel(s) to record once an alarm occurs. Please make sure you have set MD record in Schedule interface(Main Menu->Setting->Schedule) and schedule record in manual record interface(Main Menu->Advanced->Manual Record)
- PTZ activation: Here you can set PTZ movement when an alarm occurs. Such as go to preset, tour &pattern when there is an alarm. Click "select" button, you can see an interface is shown as in Figure 4-107.
- Record Delay: System can delay the record for specified time after alarm ended. The value ranges from 10s to 300s.
- Tour: Here you can enable tour function when alarm occurs. System one-window tour.
- Snapshot: You can enable this function to snapshot image when a motion detect alarm occurs.
- Video matrix Check the box here to enable this function. When an alarm occurs, SPOT OUT port displays device video output. It displays video (1-window tour) from alarm activation channel you select at the Record channel item.
- Buzzer: Highlight the icon to enable this function. The buzzer beeps when alarm occurs.
- Log: Check the box here, system can record motion detect log.
- Test: Click it to test current motion detect setup (do not need to save). Click Select button after Region, you can set motion detect area.
- Voice prompts: Check the box here to trigger audio broadcast function. You can select specified audio file here. System can play the audio file once the corresponding event occurs.

Please highlight icon to select the corresponding function. After all the setups please click save button, system goes back to the previous menu.

Note:

In motion detection mode, you can not use copy/paste to set channel setup since the video in each channel may not be the same.

In Figure 4-106, you can left click mouse and then drag it to set a region for motion detection. Click Fn to switch between arm/withdraw motion detection. After setting, click enter button to exit.

		SETTING		
SAMERA		EVENT	STORAGE	SYSTEM
VIDEO DETECT ALARM ABNORMALITY ALARM OUTPUT	Motion Detect Channel Enable	Video Loss		nosis
	Period Alarm Out Show Message PTZ Activation Tour Snapshot Video Matrix Voice Prompts	Set 123456 123456 Buzzer File Name (None	Delay (10)78901121314)789101121314 (DLog	

Figure 4-105



Figure 4-106

CAM 1None•0CAM 2None•CAM 3None•0CAM 4None•CAM 5None•0CAM 6None•CAM 7None•0CAM 8None•	
OK Cancel	_





Figure 4-108

Time Period
Current Date: Sun
Period 1 (00:00 - 24:00)
Period 2 (00 : 00 - 24 : 00)
Period 3 (00:00 - 24:00)
Period 4 (00:00 - 24:00)
Period 5 00 :00 - 24: 00
Period 6 (00 : 00 - 24 : 00
Сору
🗋 All 👘 Sun 🗋 Mon 🗋 Tue 🗋 Wed 🗋 Thu 🗍 Fri 🗋 Sat
Save

Figure 4-109

Motion detect here only has relationship with the sensitivity and region setup. It has no relationship with other setups.

4.11.3.1.2 Video Loss

In Figure 4-105, select video loss from the type list. You can see the interface is shown as in Figure 4-110. This function allows you to be informed when video loss phenomenon occurred. You can enable alarm output channel and then enable show message function.

Tips:

You can enable preset/tour/pattern activation operation when video loss occurs. Please refer to chapter 4.11.3.1.1 motion detection for detailed information.

		SETTING		
STAMERA		EVENT	STORAGE	SYSTEM
VIDEO DETECT	Motion Detect	Video Loss	Tampering Dia	gnosis
ABNORMALITY	Channel			
ALARM OUTPUT	Enable			
	Period	Set	CAM AntiDi	sec.
	Alarm Out	123	Latch (10	sec.
	Show Message	Alarm Upload	Send Email	
	Record Channel	123456	17891011111	41516
	PTZ Activation	Set	Delay (10	sec.
	Tour	123456	078900112130	41516
	Snapshot	123456	7890112130	41516
	Buzzer	✓Log		
	Voice Prompts	File Name None		
	Default Cop	У	Save	Cancel Apply

Figure 4-110

4.11.3.1.3 Tampering

When someone viciously masks the lens, or the output video is in one-color due to the environments light change, the system can alert you to guarantee video continuity. Tampering interface is shown as in Figure 4-111. You can enable "Alarm output "or "Show message" function when tampering alarm occurs.

• Sensitivity: The value ranges from 1 to 6. It mainly concerns the brightness. The level 6 has the higher sensitivity than level 1. The default setup is 3.

Tips:

You can enable preset/tour/pattern activation operation when video loss occurs. Please refer to chapter 4.11.3.1.1 motion detection for detailed information.

Note:

- In Detect interface, copy/paste function is only valid for the same type, which means you can not copy a channel setup in video loss mode to tampering mode.
- About Default function. Since detection channel and detection type may not be the same, system can only restore default setup of current detect type. For example, if you click Default button at the tampering interface, you can only restore default tampering setup. It is null for other detect types.
- System only enables tampering function during the period you set here. It is null for motion detect or video loss type.

		SETTING	
STAMERA		iz EVENT	STORAGE 🛃 SYSTEM
VIDEO DETECT	Motion Detect	Video Loss	Tampering Diagnosis
ABNORMALITY	Channel		
ALARM OUTPUT	Enable		Sensitivity 3
	Period	Set	CAM AntiDi () sec.
	Alarm Out	123	Latch 10sec.
	Show Message	Alarm Upload	Send Email
	Record Channe	123456	0789111113141516
	PTZ Activation	Set	Delay (10)sec.
	Tour	123456)789011213141516
	Snapshot	123456)78910111213141516
	Buzzer	⊾Log	
	Voice Prompts	File Name None	
	Default Cop	ογ	Save Cancel Apply

Figure 4-111

4.11.3.1.4 Diagnosis

Note

This function is for some series only.

System can trigger an alarm when the stripe, noise, color cast, out of focus, over exposure event occurred. See Figure 4-112.

Please refer to chapter 4.11.3.1.1 motion detection for detailed information.

		SETTING		
	📆 NETWORK	iz event	STORAGE	SYSTEM
VIDEO DETECT ALARM	Motion Detect	Video Loss	Tampering	Diagnosis
ABNORMALITY ALARM OUTPUT	Enable		/ 	et)
	Period ✔Alarm Out	Set 123	Latch (10	sec.
	Send Email Buzzer Voice Prompts	⊘ Log File Name(Non	e v)	
	Default Co	ру	Save	Cancel Apply



This function allows you to be informed when video is blurry, over exposure or color cast occurs. You can enable alarm output channel and then enable show message function. Click the Rule Set button, or move the cursor to Set button and then click the Enter button on the front panel, the interface is shown as below. See Figure 4-113. You can check corresponding type and then input alarm threshold.

- Stripe: The strip occurs when the device is old or there is electronic interference. There may be cross strip, vertical strip, slanting strip and etc.
- Noise: The video noise refers to the blurry video, poor video quality. It may result from the optical system distortion or the hardware problem during the video transmission when recording.
- Color cast: Usually the video is color containing RGB. When these three colors displayed in abnormal rate, we can say color cast occurred.
- Out of focus: The clear video presents abundant video details. The video definition decreases when the distortion event occurs. The out of focus event may result from many sources such as video transmission, processing and etc.
- Over exposure: The color brightness refers to the image pixel intensity. Black is the darkest and the white is the brightest. We use number 0 to stand for black and use number 255 to stand for white. Once the brightness threshold of the whole image has exceeded the threshold value, it means the image is over exposure.
- Threshold: The value ranges from 1 to 30. System can generate an alarm once the value is higher than the threshold you set here.



Figure 4-113

Note

Video analysis alarm can trigger PTZ preset, tour, and pattern.

Please refer to chapter 4.11.3.1.1 motion detection for detailed information.

4.11.3.2 Intelligence (Optional)



The intelligence function is optional. The intelligence function and the

human face detection can not be valid at the same time!

From main menu->Setting->Event, you can go to the intelligence interface. It includes four interfaces: Tripwire/intrusion/object/scene.

4.11.3.2.1 Tripwire (Optional)

Note:

- The tripwire function is valid once your network camera or your DVR supports this function.
- If your purchased DVR supports the tripwire function, it supports one analog channel. It is not for the digital channel.

System generates an alarm once there is any object crossing the tripwire in the specified direction.

From main menu->Setting->Event->Intelligence->Tripwire, the interface is shown as below. See Figure 4-114.

SETTING						
		Devent	STORAGE	SYSTEM		
VIDEO DETECT	Tripwire	Intrusion A	Abandoned			
FACE DETECT	Channel	(1				
ALARM ABNORMALITY	Enable		RULE	Set		
ABNORMALITY ALARM OUTPUT	Period	Set				
	Alarm Out	123	Latch	(10 sec.		
	Send Email					
	Record Channe	1 1234	56789101	112113116		
	PTZ Activation	Set) Delay	(10) sec.		
	Tour	1234	56789101	112113113		
	Snapshot	1234	56789101)121316		
	Buzzer	Log				
	☐Voice Prompts	File Name	None			
	Default		Save	Cancel Apply		

Figure 4-114

Check the Enable box to enable tripwire function. Click Rule setup to draw the tripwire. See Figure 4-115.





Figure 4-115

Select SN (Line1/2/3/4) and direction, and then input customized rule name.

- Line1/2/3/4: System supports four tripwires. Each SN stands for one tripwire.
- Direction (): System can generate an alarm once there is any object crossing in the specified direction.

Now you can draw a rule. Left click mouse to draw a tripwire. The tripwire can be a direct line, curve or polygon. Right click mouse to complete.

Click 🖳 to draw filte	er object.	
Ine1 I X Ine2 2 X Ine3 1 X Ine4 4 X		
Name (<u>line1</u>) A To B OK	ас	
	çQ	
	<u></u>	



Select the blue line and then use mouse to adjust zone size.

Note

Each rule can set two sizes (min size/max size). Once the object is smaller than the min size or larger than the max size, there is no alarm. Please make sure the max size is larger than the min size.

Click Ok to complete the rule setup.

Tips

Click K to delete the corresponding rule.

You can refer to the following information to set other parameters.

- Channel: Select a channel from the dropdown list to set tripwire function.
- Enable: Check the box here to enable tripwire function.
- Rule: input customized rule name here.
- Period: Click set button, you can see an interface is shown as in Figure 4-108. Here you can set tripwire period. System only enables tripwire operation in the specified periods. There are two ways for you to set periods. Please note system only supports 6 periods in one day.

♦ In Figure 4-108, Select icon of several dates, all checked items can be edited

together. Now the icon is shown as Click I to delete a record type from one period.

- ♦ In Figure 4-108. Click button after one date or a holiday, you can see an interface shown as in Figure 4-109.
- Alarm output: when an alarm occurs, system enables peripheral alarm devices.
- Latch: when tripwire complete, system auto delays detecting for a specified time. The value ranges from 0-300(Unit: second). The default setup is 10 seconds. The o second means there is no delaying time.
- Show message: System can pop up a message to alarm you in the local host screen if you enabled this function.
- Alarm upload: System can upload the alarm signal to the network (including alarm centre) if you enabled current function.
- Send email: System can send out email to alert you when an alarm occurs.
- Record channel: System auto activates tripwire channel(s) to record once an alarm occurs. Please make sure you have set intelligent record in Schedule interface(Main Menu->Setting->Schedule) and schedule record in manual record interface(Main Menu->Advanced->Manual Record)
- PTZ activation: Here you can set PTZ movement when an alarm occurs. Such as go to preset, tour &pattern when there is an alarm. Click "select" button, you can see an interface is shown as in Figure 4-107.
- Record Delay: System can delay the record for specified time after alarm ended. The value ranges from 10s to 300s.
- Tour: Here you can enable tour function when an alarm occurs. System one-window tour.
- Snapshot: You can enable this function to snapshot image when a motion detect alarm occurs.
- Buzzer: Highlight the icon to enable this function. The buzzer beeps when an alarm occurs.

	PTZ	Activation				
CAM 1 CAM 3 CAM 5 CAM 7 CAM 9 CAM 11 CAM 13	None 0 None 0	CAM 2 CAM 2 CAM 4 CAM 6 CAM 8 CAM 10 CAM 12 CAM 14	None 0 None 0			
CAM 15	None 0	CAM 16	None 0			
OK Cancel						






Figure 4-118

Current Date: Sun Period 1 00:00 •24:00 • Period 3 00:00 •24:00 • Period 4 60:00 •24:00 • Period 5 00:00 •24:00 • Period 6 00:00 •24:00 • Period 6 00:00 •24:00 • Period 6 00:00 •24:00 • Copy • • • • All • Sun • Mon • Tue • Wed • Thu • Fri • Sate		Time Period	
Period 2 00 :00 - 24:00 Period 3 00 :00 - 24:00 Period 4 00 :00 - 24:00 Period 5 00 :00 - 24:00 Period 6 00 :00 - 24:00 Copy All Sun Mon Tue Wed Thu Fri Sat	Current Date: Sur		
Period 3 00 :00 - 24: 00 Period 4 00 :00 - 24: 00 Period 5 00 :00 - 24: 00 Period 6 00 :00 - 24: 00 Copy All Sun Mon Tue Wed Thu Fri Sat	Period 1 (00 :00	- 24: 00	
Period 4 00 :00 - 24 : 00 Period 5 00 :00 - 24 : 00 Copy Sun O Mon O Tue O Wed O Thu O Fri O Sat	Period 2 (00:00	- 24: 00	
Period 5 00 :00 - 24 : 00 Period 6 00 :00 - 24 : 00 Copy	Period 3 00 :00	· 24: 00	
Period 6 00 :00 -24:00 Copy	Period 4 00 :00	- 24: 00	
Copy	Period 5 00 :00	- 24: 00	
All 🔲 Sun 🗋 Mon 🗋 Tue 🗋 Wed 🗍 Thu 🗍 Fri 🗋 Sat	Period 6 (00 :00	- 24: 00	
	Сору		
	🔲 All	🔲 Sun 🔲 Mon 🔲 Tue 🔲 Wed 💭 Thu 💭 Fri 💭 Sat	

Figure 4-119

4.11.3.2.2 Intrusion (Cross warning zone)

Note:

- The intrusion function is valid once your network camera or your DVR supports this function.
- If your purchased DVR supports the intrusion function, it supports one analog channel. It is not for the digital channel.

System generates an alarm once there is any object entering or exiting the zone in the specified direction.

From main menu->Setting->Event->Intelligence->Intrusion, the intrusion interface is shown as below. See Figure 4-120.

SETTING						
	📷 NETWORK	📷 EVENT	STORAGE	SYSTEM		
VIDEO DETECT	Tripwire	Intrusion	Abandoned			
FACE DETECT	Channel	(1	\square			
ALARM ABNORMALITY	Enable		RULE	Set		
ALARM OUTPUT	Period	Set				
	Alarm Out	123	Latch	(10) sec.		
	Send Email	el 1 234	567891011	121316		
	PTZ Activation	Set) Delay	(10) sec.		
	☐Tour ☐Snapshot	1234 1234	567891011 567891011	222		
	Buzzer					
	Voice Prompts	File Name(None			
	Default		Save			
	Default		Save	Cancel Apply		

Figure 4-120

Check the enable box to enable intrusion function.

Click Rule setup to draw the zone. See Figure 4-121.

area1 1 C X area2 2 C X area3 3 C X area4 4 C X		^	×
Name (area1)	<u></u>		
ОК			



Select SN (Area1/2/3/4) and direction, and then input customized rule name.

• Area1/2/3/4: System supports four zones. Each SN stands for one zone.



): System can generate an alarm once there is

any object enter/exit (Or both) the zone.

Now you can draw a rule. Left click mouse to draw a line first and then right click mouse to draw another line until you draw a rectangle, you can right click mouse to exit. Click Ok to complete the rule setup.

Tips

Click to delete the corresponding rule.

You can refer to the chapter 4.11.3.2.1 to set parameters.

4.11.3.2.3 Object protection (Optional)

Note:

- The object protection function is valid once your network camera or your DVR supports this function.
- If your purchased DVR supports the object protection function, it supports one analog channel. It is not for the digital channel.

System generates an alarm when the object missing/abandoned object alarm occurs. From main menu->Setting->Event-> Intelligence ->Object, the object protection interface is shown as below. See Figure 4-122.

SETTING						
ST CAMERA	📻 NETWORK	EVENT	STORAGE	SYSTEM		
VIDEO DETECT	Tripwire	Intrusion	Abandoned			
FACE DETECT	Channel	(1				
ALARM ABNORMALITY	Enable		RULE	Set		
ALARM OUTPUT	Period	Set				
	Alarm Out	123	Latch	(10) sec.		
	Send Email	123	4567891011	121316		
	PTZ Activation	Set	Delay	(10 sec.		
	☐ Tour ☐ Snapshot	123 103	4567891011 4567891011	121316 107676		
	☐Voice Prompts	File Nam	ne (None 🔻 🔻			
	Default		(Save	Cancel Apply		

Figure 4-122

Check the enable box to enable object detect function. Click Rule setup to draw the rule.




Figure 4-123

Select SN (object1/2/3/4) and direction, and then input customized rule name.

- Object1/2/3/4: System supports four zones. Each SN stands for one zone.
- Direction (): For icon , system can generate an alarm once the

object left in the one for the specified time. For icon _____, system can generate an

alarm once the object is out of the zone for the specified time.

Period: It refers to the object in/out the zone time.

Now you can draw a rule. Left click mouse to draw a line, until you draw a rectangle, you can right click mouse.

Click Ok to complete the rule setup.

Tips

Click K to delete the corresponding rule.

You can refer to the chapter 4.11.3.2.1 to set parameters.

4.11.3.3 Face Detect (Optional)

\wedge

The face detection function is optional. The intelligence function and the human face detection can not be valid at the same time!

Note

- The face detection function is valid once your network camera or your DVR supports this function.
- If your purchased DVR supports the face detection function, it supports one analog channel. It is not for the digital channel.

System can detect and filter the human face via analyzing the video. When it detects the human face in the specified zone, it can draw the rectangle around the human face

and trigger record, snapshot, alarm operation and etc. See Figure 4-124.

- Channel: Select a channel you want to enable face detect function.
- Alarm face number: Once the detected human face number reaches the threshold you set here, system can generate an alarm.
- Human face RO (region of interest): Check the box, system can highlight the human face region.
- Enable: Check the box here to enable face detect function.

For detailed setup information, please refer to chapter 4.11.3.2.1.

		SETTING		
		TA EVENT	STORAGE	SYSTEM
VIDEO DETECT INTELLIGENCE FACE DETECT	Channel Enable	(<u>1</u>	→ Target Filter	Set
ALARM ABNORMALITY ALARM OUTPUT	Period ✔Alarm Out ─Send Email	<u>Set</u> 123	Latch	(10 sec.
	Record Channel	1234 (Set	Delay	[2][3][6] (10
	Snapshot I Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot Snapshot	1234€ ✓Log File Name(N	06789000	121316
	Default		Save	Cancel Apply

Figure 4-124

4.11.3.4 Alarm

▲ Important

XVR series product does not support HDCVI alarm function (Figure 4-127).

Before operation, please make sure you have properly connected alarm devices such as buzzer.

In the main menu, from Setting->Event->Alarm, you can see alarm setup interface. For analog channel, the interface is shown as in Figure 4-125 and Figure 4-126 For HDCVI channel, there are three alarm types. See Figure 4-125 to Figure 4-127. For digital channel, there are four alarm types. See Figure 4-125 to Figure 4-129.

- Local alarm: The alarm signal system detects from the alarm input port.
- Network alarm: It is the alarm signal from the network.
- HDCVI: System can get the camera temperature, smoke, external alarm and set corresponding alarm activation operation.
- IPC external alarm: It is the on-off alarm signal from the front-end device and can activate the local HDVR.
- IPC offline alarm: Once you select this item, system can generate an alarm when the front-end IPC disconnects with the local HDVR. The alarm can activate record, PTZ, snap and etc. The alarm can last until the IPC and the HDVR connection resumes.

Important

- If it is your first time to boot up the device, the disconnection status of the front-end network camera will not be regarded as offline. After one successfully connection, all the disconnection events will be regarded as IPC offline event.
- When IPC offline alarm occurs, the record and snapshot function of digital channel is null.
- Alarm in: Here is for you to select channel number.
- Type: normal open or normal close.
- PTZ activation: Here you can set PTZ movement when alarm occurs. Such as go to preset, tour& pattern when there is an alarm. Click "select" button, you can see an interface is shown as in Figure 4-130.
- Period: Click set button, you can see an interface is shown as in Figure 4-131. There are two ways for you to set periods. There are max 6 periods in one day. There are four record types: regular, motion detection (MD), Alarm, MD & alarm.
 - ♦ In Figure 4-131, Select icon of several dates, all checked items can be

edited together. Now the icon is shown as . Click to delete a record type from one period.

- ♦ In Figure 4-131. Click button after one date or a holiday, you can see an interface shown as in Figure 4-132. There are four record types: regular, motion detection (MD), Alarm, MD & alarm.
- Anti-dither: Here you can set anti-dither time. Here you can set anti-dither time. The value ranges from 5 to 600s. The anti-dither time refers to the alarm signal lasts time. It can be seem as the alarm signal activation stays such as the buzzer, tour, PTZ activation, snapshot, channel record. The stay time here does not include the latch time. During the alarm process, the alarm signal can begin an anti-dither time if system detects the local alarm again. The screen prompt, alarm upload, email and etc will not be activated. For example, if you set the anti-dither time as 10 second, you can see the each activation may last 10s if the local alarm is activated. During the process, if system detects another local alarm signal at the fifth second, the buzzer, tour, PTZ activation, snapshot, record channel will begin another 10s while the

screen prompt, alarm upload, email will not be activated again. After 10s, if system detects another alarm signal, it can generate an alarm since the anti-dither time is out.

- Show message: System can pop up a message to alarm you in the local host screen if you enabled this function.
- Alarm upload: System can upload the alarm signal to the network (including alarm centre) if you enabled current function.
- Send email: System can send out email to alert you when alarm occurs.
- Record channel: you can select proper channel to record alarm video (Multiple choices). At the same time you need to set alarm record in schedule interface (Main Menu->Setting->Schedule) and select schedule record in manual record interface (Main Menu->Advance->Manual Record).
- Latch: Here is for you to set proper delay duration. Value ranges from 10 to 300 seconds. System automatically delays specified seconds in turning off alarm and activated output after external alarm cancelled.
- Tour: Here you can enable tour function when alarm occurs. System supports 1/8-window tour. Please note the tour setup here has higher priority than the tour setup you set in the Display interface. Once there two tours are both enabled, system can enable the alarm tour as you set here when an alarm occurred. If there is no alarm, system implements the tour setup in the Display interface.
- Snapshot: System can snapshot corresponding channel when an alarm occurs. Please note the activation snapshot has the higher priority than schedule snapshot. If you have enabled these two types at the same time, system can activate the activation snapshot when alarm occurs, and otherwise system just operates the schedule snapshot.
- Video matrix Check the box here to enable this function. When an alarm occurs, SPOT OUT port displays device video output. It displays video (1-window tour) from alarm activation channel you select at the Record channel item.
- Log: Check the box here, system can record local alarm log.
- Buzzer: Highlight the icon to enable this function. The buzzer beeps when alarm occurs.
- Voice prompts: Check the box here to trigger audio broadcast function. You can select specified audio file here. System can play the audio file once the corresponding event occurs.

Please note, network alarm means the alarm signal from the TCP/IP. You can use NET SDK to activate network alarm. Comparing with the local alarm, there is no type, anti-dither, alarm upload function.

Please highlight icon to select the corresponding function. After setting all the setups please click save button, system goes back to the previous menu.

		SETTING			
🥰 CAMERA 🛛 👼 I		🙀 EVENT	STOR/	AGE 🛛 🛃 SY	'STEM
VIDEO DETECT	Local	Net	HDCVI	IPC Ext	IPC Offline
	Jarm In (1	Alarm Name	(Alarm In1	
ALARM OUTPUT	nable (Туре	(NO 🔻	
-					
P	'eriod ((Set	Anti-dither 5)sec	
6	Alarm Out 🛛 🛛	123	Latch (1	0sec	
	Show Message 🛛	🗹 Alarm Upload	Send Ema		
6	Record Channel (123456(7891011)1213141516	
C	PTZ Activation (Set	Delay 🚺	0 sec	
G	ZTour (123456	7891011)1213141516	
G	Snapshot (123456(789111)1213141516	
	Video Matrix (Buzzer	✓Log		
C	Voice Prompts	File Name (None	•		
	Default Copy			Save) Cance	

Figure 4-125

		SETTING			
STAMERA	📷 NETWORK	📷 EVENT	STORAC	GE 📑 SY:	STEM
VIDEO DETECT	Local	Net	HDCVI	IPC Ext	IPC Offline
ABNORMALITY	Alarm In		Alarm Name	Alarm In1	
ALARM OUTPUT	Enable 				
	Period	Set			
	Alarm Out	123	Latch (10	sec.	
	Show Message		Send Email		
	Record Channe	123450	6789111	1213141516	
	PTZ Activation	Set	Delay (10	sec.	
	Tour	123450	57891011(1213141516	
	Snapshot	123450	5789101(1213141516	
	∏ Video Matri×	Buzzer	✓Log		
	Voice Prompts	File Name (Non	e 🔻		
	Default Co	ру	Sa	ive Cancel	Apply

Figure 4-126

	(SETTIN	G		
SAMERA	📆 NETWORK	📷 EVENT	STORAGE	E 🛃 SYS	STEM
VIDEO DETECT	Local	Net	HDCVI	IPC Ext	IPC Offline
ABNORMALITY ALARM OUTPUT	Alarm In Enable) Alarm Name 🛛 🤘	larm In1	
	Period ✔Alarm Out	Set) 123	Latch (10	sec.	
	Show Message Record Channel	123450 Set	Send Email 3789101112 Delay (10	13141516 	
	☐Tour ☐Snapshot	123450	57890011	13141516	
	₩Video Matrix	Buzzer File Name None	₽Log		
	Default Co	ру	Sav	e Cancel	Apply

Figure 4-127

_		SETTING			
CAMERA	ត NETWORK	📷 EVENT	STORAGE	E 🛛 🏹 SYS	STEM
VIDEO DETECT	Local	Net		IPC Ext	IPC Offline
ALARM					
ABNORMALITY	Channel	(15 🔻	Alarm Name)
ALARM OUTPUT	Enable		Туре 🚺	1C)	
	Period	Set	Anti-dither (0	sec.	
	🗹 Alarm Out	123	Latch (0	sec.	
	Show Message	e 🔲 Alarm Upload	Send Email		
	Record Chann	el 123456	078911112	13141516	
	PTZ Activation	Set	Delay (10		
	Tour	123456	0789101112	13141516	
	Snapshot	123456	0789101112	13141516	
	Video Matrix	Buzzer	Log		
	□Voice Prompts	File Name(None			
	(Default) (Co	ру)	(Savi	e) (Cancel	

Figure 4-128

		SETTING			_
	涉 NETWORK	Devent	STORAC	ie 📑 🧕 s'	/STEM
VIDEO DETECT ALARM ABNORMALITY ALARM OUTPUT	Local Channel Enable	Net (15 🗸	HDCVI	IPC Ext	IPC Offline
	 Alarm Out Show Message Record Channe PTZ Activation Tour Snapshot 	123456 Set 123456 123456	789011 ^{Delay} (10 789011 789011		
	Video Matrix	Buzzer File Name None		ve Cance	el Apply

Figure 4-129

		PTZ	Activation		
CAM 1 CAM 3 CAM 5 CAM 7	None None None None		CAM 2 CAM 4 CAM 6 CAM 8	None None None None	
_	_	ОК	Cancel		_

Figure 4-130





	Time Period
Current Date: Sun	
Period 1 (00 : 00 - 24 : 00	
Period 2 (00 : 00 - 24 : 00)	
Period 3 (00 : 00 - 24 : 00)	
Period 4 (00 : 00 - 24 : 00)	
Period 5 (00 : 00 - 24 : 00)	
Period 6 (00 : 00 - 24 : 00)	
Copy	
🗋 All 🦳 Sun 🗋 Mon	🗋 Tue 🗋 Wed 🔲 Thu 🔲 Fri 🗋 Sat
	Save

Figure 4-132

4.11.3.5 Abnormality

There are three types: HDD/Network/user.

- \diamond HDD: HDD error, no disk, no space. See Figure 4-133 and Figure 4-134.
- \diamond Network: Disconnection, IP conflict, MAC conflict. See Figure 4-135.
- ♦ User:Illegal login. See Figure 4-136.
- Alarm output: Please select alarm activation output port (multiple choices).
- Less than: System can alarm you when the HDD space is less than the threshold you set here (For HDD no space type only).

- Latch: Here you can set corresponding delaying time. The value ranges from 1s-300s. System automatically delays specified seconds in turning off alarm and activated output after external alarm cancelled.
- Show message: system can pop up the message in the local screen to alert you when alarm occurs.
- Alarm upload: System can upload the alarm signal to the network (including alarm centre) if you enabled current function. For disconnection event, IP conflict event and MAC conflict event, this function is null.
- Send email: System can send out email to alert you when alarm occurs.
- Buzzer: Highlight the icon to enable this function. The buzzer beeps when alarm occurs.
- Log: Check the box here, system can record HDD event log.
- Voice prompts: Check the box here to trigger audio broadcast function. You can select specified audio file here. System can play the audio file once the corresponding event occurs.

		SETTING		
		EVENT	STORAGE	SYSTEM
VIDEO DETECT ALARM	HDD	Network	User	
ABNORMALITY	Event Type	No HDD		
ALARM OUTPUT	Enable			
	Alarm Out	123	Latch (10	sec.
	Show Message	Alarm Upload	Send Email	
	Buzzer	⊡Log		
	☐Voice Prompts	File Name None	>	
	<u>.</u>		(Save)	Cancel Apply

Figure 4-133

	(SETTING		
		D EVENT	STORAGE	SYSTEM
VIDEO DETECT ALARM	HDD	Network	User	
ABNORMALITY	Event Type	(HDD No Space)		
ALARM OUTPUT	Enable		Less (20	%
	✓Alarm Out	123456	Latch (10]sec.
		File Name (None		
			(Save)	Cancel Apply

Figure 4-134

_		SETTING		
CAMERA	👬 NETWORK	📷 EVENT	STORAGE	SYSTEM
VIDEO DETECT ALARM	HDD	Network	User	
ABNORMALITY ALARM OUTPUT	Event Type Enable	Net Disconne)	
	Alarm Out	123	Latch (10	sec.
	Show Messag Record Chan Buzzer	je nel 123456 ✔Log))sec.
	Voice Prompt		·)sec.
			(Save)	Cancel Apply
		_		

Figure 4-135

	(SETTING		
SAMERA	👘 NETWORK	D EVENT	STORAGE	SYSTEM
VIDEO DETECT ALARM	HDD	Network	User	
ABNORMALITY	Event Type	(Illegal Login 🔻	Attempt(s)	
ALARM OUTPUT	Enable		Lock Time 30	min.
	Alarm Out	123	Latch (10	sec.
		🗹 Alarm Upload	Send Email	_
	Buzzer	✓Log		
	Voice Prompts	File Name None		
			(Save	Cancel Apply

Figure 4-136

4.11.3.6 Alarm Output

Here is for you to set proper alarm output such as schedule, manual.

Please highlight icon to select the corresponding alarm output. After all the setups please click OK button, system goes back to the previous menu. See Figure 4-137.

		SETTING		
CAMERA		EVENT	STORAGE	SYSTEM
DETECT ALARM ABNORMALITY ALARM OUTPUT	Alarm Type Schedule Manual Stop Status Alarm Release	Ali 1 2 3 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	OK	Cancel Apply

Figure 4-137

4.11.4 Storage

4.11.4.1 Schedule

4.11.4.1.1 Record

Note:

You need to have proper rights to implement the following operations. Please make sure the HDDs have been properly installed.

After the system booted up, it is in default 24-hour regular mode. You can set record type and time in schedule interface.

In the main menu, from Setting->Storage->Schedule, you can go to schedule menu. See Figure 4-141.

Please note you need to go to main menu->Setting->System->General->Holiday to set holiday date first, otherwise, there is no holiday setup item.

- Channel: Please select the channel number first. You can select "all" if you want to set for the whole channels.
- ♦ Sync connection icon. Select icon of several dates, all checked items

can be edited together. Now the icon is shown as

- \diamond **Solution**: Click it to delete a record type from one period.
- Record Type: Please check the box to select corresponding record type. There are four types: Regular/MD (motion detect)/Alarm/MD&Alarm.
- Week day: There are eight options: ranges from Saturday to Sunday and all.

- Holiday: It is to set holiday setup. Please note you need to go to the General interface (Main Menu->System->General) to add holiday first. Otherwise you can not see this item.
- Pre-record: System can pre-record the video before the event occurs into the file. The value ranges from 1 to 30 seconds depending on the bit stream.
- Redundancy: System supports redundancy backup function. You can highlight Redundancy button to activate this function. Please note, before enable this function, please set at least one HDD as redundant. (Main menu->Setting->Storage->HDD Manager). Please note this function is null if there is only one HDD.
- Period setup: Click button after one date or a holiday, you can see an interface shown as in Figure 4-142. There are four record types: regular, motion detection (MD), Alarm, MD & alarm.

Please following the steps listed below to draw the period manually.

♦ Select a channel you want to set. See Figure 4-138.



Figure 4-138

♦ Set record type. See Figure 4-139.



Figure 4-139

 Please draw manually to set record period. There are six periods in one day. See Figure 4-140.



Figure 4-140

Please highlight icon to select the corresponding function. After completing all the setups please click save button, system goes back to the previous menu.

There are color bars for your reference. Green color stands for regular recording, yellow color stands for motion detection and red color stands for alarm recording. The white means the MD and alarm record is valid. Once you have set to record when the MD and alarm occurs, system will not record neither motion detect occurs nor the alarm occurs.



Figure 4-141

Period 1 (00 :00	- 24 : 00	📃 Regular	D MD	Alarm	MD&Ala
Period 2 00 :00	- 24 : 00	Regular	D MD	Alarm	MD&Ala
Period 3 00 :00	- 24 : 00	Regular	□ MD	Alarm	MD&Ala
Period 4 00 :00	- 24:00	Regular	DWD	Alarm	MD&Ala
Period 5 00 :00	- 24:00	Regular	□ MD	Alarm	MD&Ala
Period 6 (00 :00	- 24 : 00	Regular	DMD	Alarm	MD&Ala
Сору					
	iun ()Mon ()T	ue 🛛 Wed 🗍 Thu (]Fri (]Sat	×	
	iun ()Mon ()T	ue 🛛 Wed 🔵 Thu (]Fri []Sat	k	

Figure 4-142

4.11.4.1.1.1 Quick Setup

Copy function allows you to copy one channel setup to another. After setting in channel 1, click Copy button, you can go to interface Figure 4-143. You can see current channel name is grey such as channel 1. Now you can select the channel you wan to paste such as channel 5/6/7. If you wan to save current setup of channel 1 to all channels, you can click the first box "ALL". Click the OK button to save current copy setup. Click the OK button in the Encode interface, the copy function succeeded.



Figure 4-143

4.11.4.1.1.2 Redundancy

Redundancy function allows you to memorize record file in several disks. When there is file damage occurred in one disk, there is a spare one in the other disk. You can use this function to maintain data reliability and safety.

- In the main menu, from Setting->Storage-> Schedule, you can highlight redundancy button to enable this function.
- In the main menu, from Main menu->Setting->Storage->HDD Manager, you can set one or more disk(s) as redundant. You can select from the dropdown list. System auto overwrites old files once hard disk is full.

Please note only read/write disk or read-only disk can backup file and support file search function, so you need to set at least one read-write disk otherwise you can not record video.

Note

About redundancy setup:

- If current channel is not recording, current setup gets activated when the channel begin recording the next time.
- If current channel is recording now, current setup will get activated right away, the current file will be packet and form a file, then system begins recording as you have just set.

After all the setups please click save button, system goes back to the previous menu. **Playback or search in the redundant disk.**

There are two ways for you to playback or search in the redundant disk.

- Set redundant disk(s) as read-only disk or read-write disk (Main menu->Setting->Storage->HDD Manager)). System needs to reboot to get setup activated. Now you can search or playback file in redundant disk.
- Dismantle the disk and play it in another PC.

4.11.4.1.2 Snapshot

4.11.4.1.2.1 Schedule Snapshot

- On the preview interface, right click mouse and then select Manual->Record, or in the main menu, from Setting->Storage->Record, check the box to enable snapshot function of corresponding channels. See Figure 4-144.
- In main menu, from Setting->Camera->Encode->Snapshot interface, here you can input snapshot mode as regular, size, quality and frequency. See Figure 4-145.
- In main menu, from Setting->Camera->Encode->Schedule interface, please enable snapshot function. See interface on the right of Figure 4-146.

Please refer to the following figure for detailed information.

			SETTING			
CAMERA		ľ	EVENT	STORAGE	SYSTEM	
SCHEDULE HDD MANAGE RECORD HDD DETECT	Main Stream Schedule Manual Stop Sub Stream Schedule Manual Stop Snapshot Open Stop	All 0 0 0 0 0 0				
		_		ОК	Cancel Ap	oly)

Figure 4-144

		SETTING		
		The Event	STORAGE	SYSTEM
REMOTE	Encode	Snapshot Overla	у	
IMAGE ENCODE	Manual Snap	1 /Time		
CAM NAME CHANNEL TYPE	Channel Mode			
	Image Size	(Regular) (CIF)		
	Image Quality Interval	(4 (1S)		
	interval			
	(Default) (Cany	(ок)	
		Сору		Cancel Apply

Figure 4-145



Figure 4-146

^{4.11.4.1.2.2} Trigger Snapshot

Please follow the steps listed below to enable the activation snapshot function. After you enabled this function, system can snapshot when the corresponding alarm occurred.

- In main menu, from Setting->Camera->Encode->Snapshot interface, here you can input snapshot mode as trigger, size, quality and frequency. See Figure 4-147.
- In main menu, from Setting->Event->Detect, please enable snapshot function for specified channels (Figure 4-148). Or In main menu, from Setting->Event->Alarm (Figure 4-149) please enable snapshot function for specified channels.

		SETTING		
		EVENT	STORAGE	SYSTEM
REMOTE	Encode	Snapshot Over	ay	
ENCODE CAM NAME	Manual Snap	(1) /Time		
CHANNEL TYPE	Chappel Mode	Trigger		
	lmage Size Image Quality			
	Interval	(4 v) (1 S v)		
	Default	Сору	ОК	Cancel Apply

Figure 4-147

	SETTING
SAMERA	
VIDEO DETECT ALARM	Motion Detect Video Loss Tampering Diagnosis
ABNORMALITY	Channel 1 Region Set
ALARM OUTPUT	Enable 🖌
	Period (Set) Anti-dither (5)sec.
	✓Alarm Out 123 Latch 10 sec.
	Show Message Alarm Upload Send Email
	✓Record Channel 1234567891011213141516
	PTZ Activation Set Delay (10 sec.
	✓Snapshot 1234567891011213141516
	Video Matrix Buzzer Log
	□Voice Prompts File Name(None ▼
	Default Copy Test Save Cancel Apply

Figure 4-148

		SETTING			
		EVENT	STOR	AGE 🛛 🛃 SY	STEM
VIDEO DETECT	Local	Net	HDCVI	IPC Ext	IPC Offline
ALARM					
ABNORMALITY	Alarm In		Alarm Name	(Alarm In1	
ALARM OUTPUT	Enable		Туре	NO	
	Period	Set	Anti-dither (5sec.	
	Alarm Out	123	Latch (10 sec.	
	Show Message	Alarm Upload	Send Em	ail	
	Record Channel	123456	789101	11213141516	
	PTZ Activation	Set	Delay (10 sec.	
	Tour	123456	789101	11213141516	
	Snapshot	123456	789101	11213141516	
	Video Matrix	Buzzer	✓Log		
	Voice Prompts	File Name None			
	Default Cop	у		Save Cancel	Apply

Figure 4-149

Please note the activation snapshot has the higher priority than schedule snapshot. If you have enabled these two types at the same time, system can activate the activation snapshot when alarm occurs, and otherwise system just operates the schedule snapshot.

4.11.4.1.2.4 Image FTP

In the main menu, from Setting->Network->FTP, you can set FTP server information. Please enable FTP function and then click save button. See Figure 4-150. Please boot up corresponding FTP server.

Please enable schedule snapshot (Chapter 4.11.4.1.2.1) or activation snapshot (Chapter 4.11.4.1.2.2) first, now system can upload the image file to the FTP server.

	SETTING	
R CAMERA	TRANSPORT TRANSPORT	
TCP/IP CONNECTION WIFI 3G PPPoE DDNS IP FILTER EMAIL	Enable Server IP 0 · 0 · 0 Port 21 User Name	
FTP UPnP SNMP MULTICAST REGISTER ALARM CENTRE P2P	Channel 1 Image: Channel Please input the corresponding information information information here, if you just upload the image FTP. Weekday Image Image	

Figure 4-150

4.11.4.2 HDD Manager

Here is for you to view and implement hard disk management. See Figure 4-151. You can see current HDD type, status, capacity and etc. The operation includes format HDD, and change HDD property (read and write/read-only/redundancy).

	SETTING	
	📻 NETWORK 🛛 👼 EVENT	STORAGE
SCHEDULE HDD MANAGE RECORD HDD DETECT	SATA 1 2 - O	
	1* Device Name Type All - 1* SATA-2 Read/Write	Status Free Space/Total Space - 1.64 TB/1.81 TB ★ Normal 1.64 TB/1.81 TB
	Refresh Format	Save Cancel Apply

Figure 4-151

4.11.4.3 Record

4.11.4.3.1 Record Control

Note:

You need to have proper rights to implement the following operations. Please make sure the HDD has been properly installed.

There are three ways for you to go to manual record menu.

- Right click mouse and then select Manual->Record.
- In the main menu, from Setting->Storage->Record.
- In live viewing mode, click record button in the front panel or record button in the remote control.

System supports main stream and sub stream. There are three statuses: schedule/manual/stop. See Figure 4-152. Please highlight icon " \bigcirc " to select corresponding channel.

- Manual: The highest priority. After manual setup, all selected channels will begin ordinary recording.
- Schedule: Channel records as you have set in recording setup (Main Menu->Setting->System->>Schedule)
- Stop: Current channel stops recording.
- All: Check All button after the corresponding status to enable/disable all-channel schedule/manual record or enable/disable all channels to stop record.

CAMERA SCHEDULE HDD MANAGE RECORD HDD DETECT Schedule O Stop O Schedule O O Stop O O Schedule O O Stop O Schedule O Schedule O O Stop O Stop O O Stop O O O Stop O O O O O O O O O O O O O O O O O O Stop O O O O O O O O O O O O O O O O O O O O O O O O O O O O O O O O O O O <th></th> <th></th> <th>SETTING</th> <th></th> <th></th>			SETTING		
HDD MANAGE RECORD HDD DETECT Manual Schedule O O O Manual Schedule O O Manual O O Manual O Manual Hold Manual Manual Manual Manual Manual	R CAMERA		EVENT	STORAGE	SYSTEM
Snapshot Open • • • • • Stop • • • • • OK Cancel Apply	HDD MANAGE RECORD	Schedule Manual Stop Sub Stream Schedule Manual Stop Snapshot Open		OK	Cancel Apply

Figure 4-152

4.11.4.3.2 Snapshot Operation

Check the corresponding box to enable/disable schedule snapshot function. See Figure 4-153.

		SETTING		
		To EVENT	STORAGE	SYSTEM
SCHEDULE HDD MANAGE RECORD HDD DETECT	Main Stream Schedule Manual Stop Sub Stream Schedule Manual Stop Snapshot Open Stop	All 1 2 3 4 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0		
			ОК	Cancel Apply

Figure 4-153

Tips

You can check All button after the corresponding status to enable/disable all-channel

snapshot function.

4.11.4.4 HDD Detect

The HDD detect function is to detect HDD current status so that you can clearly understand the HDD performance and replace the malfunction HDD. There are two detect types:

- Quick detect is to detect via the universal system files. System can quickly complete the HDD scan. If you want to use this function, please make sure the HDD is in use now. If the HDD is removed from other device, please make sure the write-data once was full after it installed on current device.
- Global detect adopts Windows mode to scan. It may take a long time and may affect the HDD that is recording.

4.11.4.4.1 Manual Detect

The manual detect interface is shown as below. See Figure 4-154.

Please select detect type and HDD. Click start detect to begin. You can view the corresponding detect information. See Figure 4-155.



Figure 4-154

	SETTING		
		AGE 🛃 SYS	TEM
SCHEDULE HDD MANAGE	Manual Detect Detect Report		
RECORD	Type Quick Detect HDD SATA - 1) (Start Detect)	(Stop Detect)
HDD DETECT		III Good III Bad III = 103 MB	Block
		Detected HDD No.	
		Total Space	232.89 GB
		Error	
		Current HDD	
		Detect Speed	10.00 GB/S
		Process	100.00 %
		Detect Time	00:00:01
		Remaining Time	00:00:00

Figure 4-155

4.11.4.4.2 Detect Report

After the detect operation, you can go to the detect report to view corresponding information.

The detect report interface is shown as below. See Figure 4-156.




Figure 4-156

Click the item you can see the detailed information such as detect result. See Figure 4-157.

Details		
	 Good ■ Bad ■ = 103 MB Detected HDD No. Total Space Error HDD Port No. 	
		_

Figure 4-157

4.11.5 System

4.11.5.1 General

4.11.5.1.1 Device

General setting includes the following items. See Figure 4-158.

- Device ID: Please input a corresponding device name here.
- Device No: Here you can set device number.
- Language: System supports various languages: Chinese (simplified), Chinese (Traditional), English, Italian, Japanese, French, Spanish (All languages listed here are optional. Slight difference maybe found in various series.)
- Video standard: There are two formats: NTSC and PAL.
- HDD full: Here is for you to select working mode when hard disk is full. There are two
 options: stop recording or rewrite. If current working HDD is overwritten or the current
 HDD is full while the next HDD is no empty, then system stops recording, If the
 current HDD is full and then next HDD is not empty, then system overwrites the
 previous files.
- Pack duration: Here is for you to specify record duration. The value ranges from 1 to 120 minutes. Default value is 60 minutes.
- Real-time playback: It is to set playback time you can view in the preview interface. The value ranges from 5 to 60 minutes.

- Auto logout: Here is for you to set auto logout interval once login user remains inactive for a specified time. Value ranges from 0 to 60 minutes.
- IPC Time Sync: You can input an interval here to synchronize the DVR time and IPC time.
- Navigation bar: Check the box here, system displays the navigation bar on the interface.
- Startup wizard: Once you check the box here, system will go to the startup wizard directly when the system restarts the next time. Otherwise, it will go to the login interface.
- Mouse property: You can set double click speed via dragging the slide bard. You can Click Default button to restore default setup.

	(SETTING		
	👘 NETWORK	To EVENT	STORAGE	SYSTEM
GENERAL DISPLAY	General	Date&Time	Holiday	
VIDEO MATRIX	Device Name Device No.	(HCVR)		
PTZ ATM/POS	Language			
VOICE ACCOUNT	Video Standard HDD Full	(NTSC)		
AUTO MAINTAIN IMP/EXP	Pack Mode Realtime Play	Time Length	60 min. min.	
DEFAULT UPGRADE	Auto Logout 🛃 IPC Time Sync		nin. 1	
	🖌 Navigation Bar	Slow	Fast	
	incuse certaining			
	Default		(Save)	Cancel Apply

Figure 4-158

4.11.5.1.2 Date and Time

The interface is shown as in Figure 4-159.

- Date format: There are three types: YYYYY-MM-DD: MM-DD-YYYYY or DD-MM-YYYY.
- Date separator: There are three denotations to separate date: dot, beeline and solidus.
- DST: Here you can set DST time and date. Here you can set start time and end time by setting corresponding week setup or by setting corresponding date setup.
- NTP: It is to set NTP server information.

	SETTING
😪 CAMERA	T NETWORK DE EVENT
GENERAL DISPLAY VIDEO MATRIX PTZ ATM/POS VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	General Date & Time Holiday Date Format (YYYY MM) Time Format (24-HOUR) Date Separator • Date Separator • System Time (2016 - 01 - 14 15: 56: 39) (GMT+08:00) System Time (2016 - 01 - 14 15: 56: 39) (GMT+08:00) DST DST DST DST DST Type O Week • Date Start Time (2000 - 01 - 01) 00: 00) End Time (2000 - 01 - 01) 00: 00) Ind Time (2000 - 01 - 01) 00: 00) Ind Time (2000 - 01 - 01) 00: 00) Ind Time (2000 - 01 - 01) 00: 00) Ind Time (2000 - 01 - 01) 00: 00) Ind Time (2000 - 01 - 01) 00: 00) Ind Time (2000 - 01 - 01) 00: 00) Ind Time (2000 - 01 - 01) 00: 00) Ind Time (2000 - 01 - 01) 00: 00) Ind Time (2000 - 01 - 01) 00: 00) Ind Time (2000 - 01 - 01) 00: 00) Ind Time (123) Interval (60) min.
_	(Default) (Save) (Cancel) (Apply)

Figure 4-159

4.11.5.1.3 Holiday

Holiday setup interface is shown as in Figure 4-160. Click Add new holiday button, you can input new holiday information. See Figure 4-161. Here you can set holiday name, repeat mode and start/end time.

Note

- When you enable Holiday settings and schedule setup at the same time, holiday setting has the priority. If the selected day is a holiday, then system records as you set in holiday setting. If it is not a holiday, system records as you set in Schedule interface. Please note
- Please note, there is no year setup on the holiday setup. For example, if you set 30th Oct, 2012 as a holiday, then the date of 30th Oct in each year will be set as a holiday.

SETTING						
CAMERA	💏 NETWO	DRK 🔂 E	EVENT	STORAGE	SYSTEM	
GENERAL DISPLAY	Gen	eral Date	&Time H	oliday		
VIDEO MATRIX PTZ ATM/POS VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	0	Status	Nam	e		
					(Add a Hol	iday)

Figure 4-160

Add New Holidays
Holiday Name
Repeat Mode 🛛 O Once Only 🌑 All-Year
Holiday Range 🌘 Date 🛛 O Week
Start Time 2013 - 10 - 18
End Time 2013 - 10 - 18
Add More
Add Cancel

Figure 4-161

4.11.5.2 Display

4.11.5.2.1 Display

Display setup interface is shown as below. See Figure 4-162.

- Time display: You can select to display time or not when system is playback.
- Channel display: You can select to channel name or not when system is playback.

- Image original rate: Check the box here, the video can be displayed at its actual size.
- Transparency: Here is for you to adjust menu transparency. The higher the value is, the more transparent the menu is.
- Resolution: There are four options: 1920×1080, 1280×1024(default),1280× 720,1024×768. Please note the system needs to reboot to activate current setup.
- Preview enhance: Check the box; it can optimize the video quality of the preview video.
- Video matrix: Check the box to enable video matrix function.

Please highlight icon 📕 to select the corresponding function.

After completing all the setups please click save button, system goes back to the previous menu.

SETTING						
CAMERA	듉 NETWORK	📆 EVENT	STORAGE	SYSTEM		
GENERAL DISPLAY VIDEO MATRIX PTZ ATM/POS VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	Display Time Display Channel Display Image Origina Preview Enha Transparency Resolution 1280 Video Matrix	I Rate ncement 0%	Zero-Channel	Cancel Apply		
		_				

Figure 4-162

4.11.5.2.2 TV Adjust

Note

This function is for some series only.

Here is for you to adjust TV output setup. See Figure 4-163.

Please drag slide bar to adjust each item.

After all the setups please click OK button, system goes back to the previous menu.

SETTING							
SAMERA	👬 NETWORK	EVENT	STORAGE	SYSTEM			
GENERAL	Display	TV Adjust To	ur Zero Channel	Favorites			
DISPLAY RS232 PTZ ATM/POS ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	Display Top Margin Bottom Margin Left Margin Right Margin Brightness		ur Zero Channel	Favorites			
	Default		(OK	Cancel Appl	y		

Figure 4-163

4.11.5.2.3 Tour

Here you can activate tour function. Click Setup button, you can see an interface shown as in Figure 4-164

- Enable tour: Highlight box here to enable this function.
- Interval: System supports 1/8/-window tour. Input proper interval value here. The value ranges from 5-120 seconds. It is for schedule tour/alarm/motion detect tour.
- Split: You can select window split mode from the dropdown list.
- Channel group: It is to display all channel groups on current split mode. You can edit and delete a channel group here. Double click an item in the list; you can edit its channel group setup. Right now system max supports 32.
- Add: Under specified window split mode, click it to add channel group.
- Delete: Click it to remove selected channel group.
- Move up: Click it to move current selected channel up.
- Move down: Click it to move current selected channel down.
- Default: Click it to restore default setup.

Tips:

Use mouse or Shift button to switch I and I button to enable /disable tour.

means the tour funciton is enabled and 🙆 meas tour funciton is disabled.

• On the navigation bar, click is or to enable/disable tour function.

Figure 4-164

4.11.5.2.4 Zero-channel Encoding

Click zero-channel encoding button, you can go to the following interface. See Figure 4-165. Here you can enable and set zero-channel encoding function so that you can view several video sources at one channel.

- Enable: This function is disabled by default. Check the box here to enable this function so that you can control the zero-channel encoding function at the WEB.
- Compression: System default setup is H.264. You can set according to device capability.
- Resolution: The resolution value may vary due to different device capabilities. Please select from the dropdown list.
- Frame rate: The frame rate value may vary due to different device capabilities. Please select from the dropdown list.
- Bit Rate: The bit rate value may vary due to different device capabilities and frame rate setups. Please select from the dropdown list.
- Save: Click the Save button to save current setup. If this function is disabled, you can not operate zero-channel encoding function at the WEB, the video is black or null even you operate when the function is disabled. After you enabled this function, login

the Web and you can select zero-channel encoding mode at the right corner of the

interface		. Select a n	node; you car	n view tl	he local previ	ew video.
		SETTI	NG			
	📷 NETWORK	D EVENT	STOR.	AGE	SYSTEM	
GENERAL	Display	Tour	Zero-Channel]		
DISPLAY VIDEO MATRIX PTZ ATM/POS VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	Enable Compression Resolution Frame Rate(FPS) Bit Rate(Kb/S)	(704*480(D1)) (30				
	Default			Save (Cancel (Apply

Figure 4-165

4.11.5.3 Video Matrix

Here you can set matrix output channel and its interval. You can set HDMI2 port tour and its interval See Figure 4-166.

- Enable tour: Check the box here to enable this function.
- Interval: Input proper interval value here.
- Resolution: The resolution of the tour window. Please note this function is for HDMI only.
- Split: You can select window split mode from the dropdown list. For BNC, it supports 1-split mode only. For HDMI, it supports 1/4/9/16-split mode. Some series product support 24/36-split. Please refer to the actual product.
- Add: Under specified window split mode, click it to add channel group. See Figure 4-167.
- Modify: Double click a channel or select a channel and then click Modify button, you can change current channel setup. See Figure 4-168.
- Delete: Click it to remove selected channel group.
- Move up: Click it to move current selected channel up.

- Move down: Click it to move current selected channel down.
- Default: Click it to restore default setup.

CAMERA CAMERA CONSPLAY CIDEO MATRIX PTZ ATM/POS VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE
DISPLAY Enable Interval 5 sec. VIDEO MATRIX Resolution 1280x720 PTZ Window Split View 1 ATM/POS 1 1 VOICE 2 2 ACCOUNT 3 3 AUTO MAINITAIN 5 5 IMP/EXP 6 6 DEFAULT 8 8 UPGRADE 9 9
Default Save Cancel Apply

Figure 4-166

Add Group
1234567891011213141516 Group Order:
OK Cancel

Figure 4-167



Figure 4-168

4.11.5.4 RS232

RS232 interface is shown as below. There are five items. See Figure 4-169.

- Function: There are various devices for you to select. Console is for you to use the COM or mini-end software to upgrade or debug the program. The control keyboard is for you to control the device via the special keyboard. Transparent COM (adapter) is to connect to the PC to transfer data directly. Protocol COM is for card overlay function. Network keyboard is for you to use the special keyboard to control the device. PTZ matrix is to connect to the peripheral matrix control.
- Baud rate: You can select proper baud rate.
- Data bit: You can select proper data bit. The value ranges from 5 to 8.
- Stop bit: There are two values: 1/2.
- Parity: There are five choices: none/odd/even/space mark.
- System default setup is:
- Function: Console
- Baud rate:115200
- Data bit:8
- Stop bit:1
- Parity: None

After completing all the setups please click save button, system goes back to the previous menu.

		SETTING			
📆 CAMERA		D EVENT	STORAGE	SYSTEM	
GENERAL DISPLAY VIDEO MATRIX RS232 PTZ ATM/POS ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	Function (Console Baudrate (115200 Data Bits (8 Stop Bits (1 Parity (None				
	Default		Save	Cancel Apply	

Figure 4-169

4.11.5.5 PTZ

The pan/tilt/zoom setup includes the following items. Please select channel first. See Figure 4-170.

- PTZ type: There are two options: local/remote. Please select remote if you are connecting to the network PTZ.
- Control mode: You can select control mode from the dropdown list. There are two options: Serial/HDCVI. For HDCVI series product, please select HDCVI. The control signal is sent to the PTZ via the coaxial cable. For the serial mode, the control signal is sent to the PTZ via the RS485 port.
- Protocol: If the control mode is HDCVI, please select HDCVI protocol. The default setup is HDCVI3.0
- Address: input corresponding PTZ address.
- Baud rate: Select baud rate.
- Data bit: Select data bit.
- Stop bit: Select stop bit.
- Parity: There are three choices: none/odd/even.

After completed all the setups please click save button, system goes back to the previous menu.

GENERAL DISPLAY		THE EVENT		SYSTEM
VIDEO MATRIX PTZ ATM/POS VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	Channel PTZ Type Control Mode Protocol Address Baudrate Data Bits Stop Bits Parity	1 Local HDCVI HDCVI3.0 1 9600 8 1 None None		
	Default (Сору	Save	Cancel Apply

Figure 4-170

For digital channel, the interface is shown as below. See Figure 4-171.

		SETTI	NG	
STAMERA	듉 NETWORK	To EVENT	STORAGE	SYSTEM
GENERAL DISPLAY VIDEO MATRIX PTZ ATM/POS VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	Channel PTZ Type	12 Remote		
	Default	Сору	Save	Cancel Apply

Figure 4-171

4.11.5.6 ATM/POS

The ATM/POS function is for financial areas. It includes Sniffer, information analysis and title overlay function. The Sniffer mode includes COM and network.

4.11.5.6.1 COM Type

The COM interface is shown as below. See Figure 4-172.

- Protocol: Please select from the dropdown list.
- Setting: Click COM setting button, the interface is shown as in RS232 interface. Please refer to Chapter 5.3.4 RS232.
- Overlay channel: Please select the channel you want to overlay the card number.
- Overlay mode: There are two options: preview and encode. Preview means overlay the card number in the local monitor video. Encode means overlay the card number in the record file.
- Overlay Position: Here you can select the proper overlay position from the dropdown list.

		SETTING		
CAMERA				SYSTEM
GENERAL DISPLAY RS232 PTZ	Com Current Sniffer Me	Net ode is COM		
ATM/POS ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	Protocol Overlay Channel Overlay Mode Overlay Position	Preview Encode		
			Save	Cancel Apply

Figure 4-172

4.11.5.6.2 Network Type

The network type interface is shown as below. See Figure 4-173.

Please use network type if you using network to connect to the device. The interface is generally the same as the COM mode. The protocol depends on your self-develop protocol. The setup may vary since connected device or the protocol is not the same. Here we take the ATM/POS protocol to continue.

• Protocol: It is to set COM sniffer protocol. You need to select protocol according to

your own development situation.

- Overlay mode: There are two options: preview and encode. Preview means overlay the card number in the local monitor video. Encode means overlay the card number in the record file. You can view the corresponding information when playback.
- Overlay Position: Here you can select the proper overlay position from the dropdown list.
- Data group: There are total four groups IP.
- Source IP: Source IP refers to host IP address that sends out information (usually it is the device host.)
- Destination IP: Destination IP refers to other systems that receive information.
- Source port/destination port: Please input according to your own situation.
- Record channel: It is for you to check record channel. The record channel applies to one group (optional) only.
- Frame ID: Six frame ID groups verification can guarantee information validity and legal. You need to input start position, length, key and etc according to your communication protocol and data packet contents.

		SETTING				
SAMERA		To EVENT	STORA	GE	SYSTEM	
GENERAL	Com	Net				
DISPLAY RS232	Protocol	ATM/POS		Current Si	niffer Mode is CON	1
PTZ	Overlay Mode			Overlay P	osition (Top Left	\square
ATM/POS	Data Group	Data Group1 🔻				
ACCOUNT	Source IP	0.0.0.	0 Port	0	\supset	
AUTO MAINTAIN	Destination IP	0.0.0.	0 Port	0	Ď	
IMP/EXP	Overlay Channel	123			-	
DEFAULT		StartPosition Length	Key			
UPGRADE	Frame ID1		\subseteq			
	Frame ID2		\subseteq	Dat	\equiv	
	Frame ID3 Frame ID4		\leq		\equiv	
	Frame ID4 Frame ID5	$ \begin{array}{c} 1 \\ 0 \\ 1 \end{array} $	\leq		\equiv	
	Frame ID6	$ \begin{array}{c} 1 \\ 1 \end{array} $ 0	\ge	Dat	\equiv	
			\square			
			Sa	ave (Cancel A	oply

Figure 4-173

<u>In</u> Figure 4-173, click data button after frame ID the interface is shown as in Figure 4-174. Here you can set field start position, length, and overlay title.

Field1 (1 Field2 (1 Field3 (1	Length Title	
		 Save Cancel

Figure 4-174

4.11.5.7 Voice

The audio function is to manage audio files and set schedule play function. It is to realize audio broadcast activation function.

4.11.5.7.1 File List

Here you can add audio file, listen to the audio file, or rename/delete audio file. Here you can also set audio volume. See Figure 4-175.

	SETTING		
CAMERA	😿 NETWORK 🛛 👼 EVENT	STORAGE	
GENERAL DISPLAY VIDEO MATRIX RS232 PTZ ATM/POS VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	File Manage Schedule Tile Name 1 File Name 1 When You Know.mp3	Size Play Rename Delete	
	VOICE : USB Mode	Volume Add	

Figure 4-175

Click Add button, you can add audio file and import the audio file via the USB device. See Figure 4-176.

		Add				
Device Name Total Space	(sdc1(USB DISK))) (14.43 GB	Refresh Free Space	(12.07 GB			
Address						
Name			Size	Туре	Delete	^
🗆 🦳 SD				Folder	×	
English 🗌				Folder		
5563277	_20140225			Folder		
Import						
					ок 🤇	Cancel

Figure 4-176

The audio file can be saved on the HDD or on the USB device.

- In Figure 4-175, when it is HDD mode, the newly added audio file can be saved on the HDD automatically. You do not need to connect to the USB device if you want to use it the next time.
- In Figure 4-175, when it is USB mode, after you imported, you need to connect the USB device all the time; otherwise, the audio link function may fail. So, if you want to use the audio trigger function, please make sure the audio file is on the UBS device and the USB device has connected to the DVR before the DVR boots up. You need to make sure the USB device connection is always there if you want to manage and use the audio file function.
- If there is a USB device (containing the audio file) and the HDD (containing the audio file) at the same time, the HDD mode has higher priority. That is to say, DVR uses the audio file from the HDD.

4.11.5.8 Account

Here is for you to implement account management. See Figure 4-177. Here you can:

- Add new user
- Modify user
- Add group
- Modify group
- Modify password.

For account management please note:

• For the user account name and the user group, the string max length is 6-byte. The backspace in front of or at the back of the string is invalid. There can be backspace in the middle. The string includes the valid character, letter, number, underline, subtraction sign, and dot.

- The default user amount is 64 and the default group amount is 20. System account adopts two-level management: group and user. No limit to group or user amount.
- For group or user management, there are two levels: admin and user.
- The user name and group name can consist of eight bytes. One name can only be used once. There are three default users: admin/888888 and hidden user "default".
- Hidden user "default" is for system interior use only and can not be deleted. When there is no login user, hidden user "default" automatically login. You can set some rights such as monitor for this user so that you can view some channel view without login.
- One user should belong to one group. User right can not exceed group right.
- About reusable function: this function allows multiple users use the same account to login.
- About user account and MAC. When you add a new user, you can input the MAC address of current user. Only the user of the same MAC address can access the device remotely.(MAC address is for the device of the same LAN.) If you leave MAC address item in blank when you add a new user, the user of any MAC address can access the device remotely. You can set or change MAC address when you add or modify a user. The MAC address function is also valid for PSS login. Please note current function does not support IPV6.

After all the setups please click save button, system goes back to the previous menu.



Figure 4-177

4.11.5.8.1 Add User

Click modify user button *C* in Figure 4-177, the interface is shown as in Figure 4-178.

Please input the user name, password, select the group it belongs to from the dropdown list.

Then you can check the corresponding rights for current user.

For convenient user management, usually we recommend the general user right is lower than the admin account.

- Username: admin. Password: admin. (administrator, local and network)
- Username: 888888. Password: 888888. (administrator, local only)
- **Username**: default. **Password**: default (hidden user). Hidden user "default" is for system interior use only and can not be deleted. When there is no login user, hidden user "default" automatically login. You can set some rights such as monitor for this user so that you can view some channels without login.

	Ad	d User
User Name Password Memo Group (admin Authority_		Confirm Password
System All ALCOUNT PTZ	Playback Monitor	✓ DISCONNECT USER ✓ DEFAULT&UPGRADE ✓ MANUAL CONTROL ✓ BACKUP
Color Comera	STORAGE	 ✓ EVENT ✓ NETWORK ✓ SHUTDOWN
		Save Cancel

Figure 4-178

When you create a new user, you can input the corresponding MAC address of current user. If you leave this item in blank, any MAC address user can share this user account to login. Please note system needs to check the validity of MAC. Only the 12-digit 0-f format address can pass the validity verification. System only saves small character even you input capitalized one. You can see the corresponding prompt if there is any illegal input.

Click the Set button after the period, you can set valid period to use current account. See Figure 4-179.





Click Set button, you can set six periods in one day. See Figure 4-180. Check the box after the period, you can enable current setup.

Period
Current Date: Sunday
Period 1 (00 : 00 - 24 : 00 🛛
Period 2 00 : 00 - 24 : 00
Period 3 00 : 00 - 24 : 00
Period 4 00 : 00 - 24 : 00
Period 5 00 : 00 - 24 : 00
Period 6 00 : 00 - 24 : 00
Сору
🗋 All 🛃 Sunday 🗋 Monday 🗋 Tuesday 🗋 Wednesday 💭 Thursday 💭 Friday 💭 Saturday
ОК

Figure 4-180

4.11.5.8.2 Modify user

Click / you can go to the following interface to change user information. See Figure 4-181.

For admin, 888888, and default (hidden user), you can not change period setup.

	Mo	odify User	
User Name (defau	ılt 🔪		
Modify Password 🛛 🔲		User MAC	
Old Password		User Name	
New Password		Group (user 🔻	
Confirm Password		Memo (default account	
Authority			
System PI	ayback Monitor		
🔲 All			
	SYSTEM	🔲 DISCONNECT USER 📃 DEFAULT&UPGRADE	
PTZ		MANUAL CONTROL 🔲 BACKUP	
	STORAGE		
	CLEAR LOG	SHUTDOWN	
		Save Cancel	

Figure 4-181

4.11.5.8.3 Change Password

In Figure 4-181, check the Modify password box, you can change password. Please input old password, and then input new password twice to confirm.

The password can contain 32-byte and the space at the begin or at the end of the password are null. It can contain in the middle of the password. For the user of account right, it can change the password of other users.

4.11.5.8.4 Add/Modify Group

In Figure 4-177, click Group button, you can see the following interface. See Figure 4-182.

	SETTING	
STAMERA	📅 NETWORK 🛛 👼 EVENT 🔤 STORAGE 🔄 SYSTEM	
GENERAL DISPLAY VIDEO MATRIX	User Group Secure Question 2 Group Name Modify Delete Memo 1 admin ✓ X administrator group	
PTZ ATM/POS VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	2 user 🖌 🗴 user group	
	(Add Group)	

Figure 4-182

Click add group button in Figure 4-182 , the interface is shown as below. See Figure 4-183.

Here you can input group name and then input some memo information if necessary. There are total 98 rights such as control panel, shut down, real-time monitor, playback, record, record file backup, PTZ, user account, system information view, alarm input/output setup, system setup, log view, clear log, upgrade system, control device and etc.

AULT&UPGRADE
KUP
WORK

Figure 4-183

4.11.5.8.5 Security Question

The security question is shown as below. See Figure 4-184. Here you can change security questions.

SETTING				
	📻 NETWORK	To EVENT	STORAGE	SYSTEM
GENERAL DISPLAY	User	Group	Secure Question	
VIDEO MATRIX	Please set a secu	urity question so	that you can find the passwo	ord of (admin) again.
PTZ ATM/POS	Question 1 (Wh	at's your favorite	pet?	
VOICE	Answer 🤇			
ACCOUNT AUTO MAINTAIN	Question 2 (Wh	at's your first car	model?	
IMP/EXP DEFAULT	Answer			
UPGRADE				
				Set Delete

Figure 4-184

4.11.5.9 Auto Maintain

Here you can set auto-reboot time and auto-delete old files setup. You can set to delete the files for the specified days. See Figure 4-185.

You can select proper setup from dropdown list.

After all the setups please click save button, system goes back to the previous menu.

	SETTIN	G	
😋 CAMERA	📅 NETWORK 🛛 📆 EVENT	STORAGE	SYSTEM
GENERAL DISPLAY VIDEO MATRIX PTZ ATM/POS VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	Auto Reboot Tuesday • at 02:00 Auto-Delete Old Files Customized • 22	Day(s) Ago	
		Save	Cancel Apply

Figure 4-185

4.11.5.10 Config Backup

The configuration file backup interface is shown as below. See Figure 4-186. This function allows you to import/export system configuration. You can use this function when there are several devices need the same setup.

- Export: Please connect the peripheral device first and then go to the following interface. Click Export button, you can see there is a corresponding "Config_Time" folder. Double click the folder, you can view some backup files.
- Import: Here you can import the configuration files from the peripheral device to current device. You need to select a folder first. You can see a dialogue box asking you to select a folder if you are selecting a file. System pops up a dialogue box if there is no configuration file under current folder. After successfully import, system needs to reboot to activate new setup.
- Format: Click Format button, system pops up a dialogue box for you to confirm current operation. System begins format process after you click the OK button.

Note:

- System can not open config backup interface again if there is backup operation in the process.
- System refreshes device when you go to the config backup every time and set current directory as the root directory of the peripheral device.
- If you go to the configuration backup interface first and then insert the peripheral device, please click Refresh button to view the newly added device.

CAMERA 😿 NETWORK 📷 EVENT STORAGE SYSTEM			SETTING			
	STATES CAMERA	📷 NETWORK	EVENT	STORAGE	SYSTE	EM
DISPLAY Device Name sdc1(USB DISK) Refresh VIDEO MATRIX Total Space 14.43 GB Free Space 4.67 GB PTZ Address //	VIDEO MATRIX PTZ	Total Space	(14.43 GB		(4.67 GB	
ATM/POS VOICE VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT UPGRADE	VOICE ACCOUNT AUTO MAINTAIN IMP/EXP DEFAULT					
New Folder) Format Import Export		(New Folder)	Format Import) (Export)		

Figure 4-186

4.11.5.11 Default

Click default icon, system pops up a dialogue box. You can highlight is to restore default factory setup. See Figure 4-187.

- Camera
- Network
- Event
- Storage
- System

Please highlight icon 🔳 to select the corresponding function.

Click factory default button, you can restore factory default setup.

After all the setups please click save button, system goes back to the previous menu.

Warning!

System menu color, language, time display mode, video format, IP address, user account will not maintain previous setup after default operation!

SETTING								
	👬 NETWORK	To EVENT	STORAGE	SYSTEM				
GENERAL DISPLAY VIDEO MATRIX		etting entries that you w	ant to default.					
PTZ ATM/POS VOICE ACCOUNT	CAMERA EVENT	NETWORK						
AUTO MAINTAIN IMP/EXP DEFAULT								
UPGRADE								
	(Factory Default)		Save	Cancel Apply				

Figure 4-187

4.11.5.12 Update

Here is for you to view hardware features, software version, built date, release SN information and etc. You can also update system here. See Figure 4-188.

• Start: Please insert the USB device that have the update file to the device and then click the Start button to begin the update.

Important

Please make sure the upgrade file name shall be update.bin.

🧺 CAMERA 🛛 📻 NETWORK 🛛 👼 EVENT 🛛 🛃 SYSTEM	
	EM
GENERAL UPGRADE DISPLAY If you need to upgrade system now,please insert USB upgrade disk,then press the start button to start upgrade.Don't shut down the power during upgrade! PTZ ATM/POS VOICE Start ACCOUNT Start AUTO MAINTAIN MP/EXP DEFAULT UPGRADE	ess the start

Figure 4-188

5 WEB OPERATION

Slightly difference may be found in the interface due to different series.

5.1 Network Connection

Before web client operation, please check the following items:

- Network connection is right
- DVR and PC network setup is right. Please refer to network setup(main menu->Setting->Network)
- Use order ping ***.***.***(* DVR IP address) to check connection is OK or not. Usually the return TTL value should be less than 255.
- Current series product supports various browsers such as Safari, fire fox browser, Google browser. Device supports multiple-channel monitor, PTZ control, DVR parameter setup on the Apple PC.

5.2 Login

Open IE and input DVR address in the address column. For example, if your DVR IP is 10.10.3.16, then please input http:// 10.10.3.16 in IE address column.

System pops up warning information to ask you whether install control or not. Please click Install button. See Figure 5-1.

Please ins	tall controls
Install	Cancel


Figure 5-1

After installation, the interface is shown as below. See Figure 5-2.

Please input your user name and password.

Default factory name is admin and password is admin.

Note: For security reasons, please modify your password after you first login.





System pops up the following dialogue box for you to change default administrator password. See Figure 5-3.

Lines Misses		
User Name	admin	
Old Password	1	
New Password		
	Low Middle Hi	igh
Confirm Password	-	
For your account security, t s), and special character(s) together.	
For your device safety, the name in case there is illega		the same as the user
laine in case tilere is lilega	n account usage.	
	Save Can	

Figure 5-3

For you own safety, please change the default password after you first login.

Click Cancel button, system pops up the following dialogue box to confirm the exit. See Figure 5-4.


Check the box here, system will not pop up the change password interface the next time.

28 G S	22035 32 32	(3) 32 (2005) 231 (2005)	
For your device s	afety, please chan	ge admin default password! A	Are you
sure to quit chan	aina now?		
Do not promp	t admin to change	e its default password.	
	Save	Cancel	

Figure 5-4

5.3 LAN Mode

For the LAN mode, after you logged in, you can see the main window. See Figure 5-5.





This main window can be divided into the following sections.

- Section 1: there are five function buttons: Live (chapter 5.4), setup (chapter 5.8), search (chapter 5.10), alarm (chapter 5.11), face search (chapter 5.11)and logout (chapter 5.13).
- Section 2: There are channel number and one button: Start all. Start all button is to enable/disable all-channel real-time monitor. Click it the button becomes yellow. See Figure 5-6.



Figure 5-6

Please refer to Figure 5-7 for main stream and extra stream switch information.

CAM 1	M
Main Stream	
Sub Stream	
CAM 2	

Figure 5-7

• Section 3: Start dialogue button.

You can click this button to enable audio talk. Click [\checkmark] to select bidirectional talk mode. There are four options: DEFAULT, G711a, G711u and PCM. After you enable the bidirectional talk, the Start talk button becomes End Talk button and it becomes yellow. See Figure 5-8.

Please note, if audio input port from the device to the client-end is using the first channel audio input port. During the bidirectional talk process, system will not encode the audio data from the 1-channel.





• Section 4: Instant record button. Click it, the button becomes yellow and system begins manual record. See Figure 5-9. Click it again, system restores previous record mode..



Figure 5-9

• Section 5: Local play button.

The Web can playback the saved (Extension name is dav) files in the PC-end. Click local play button, system pops up the following interface for you to select local play file. See Figure 5-10.

Open	? 🗙
Look jn: 📴 Desktop	
 My Documents My Computer My Network Places Access IBM AOL Double-Click to Start EarthLink Internet 30 Days 	Norton AntiVirus Norton AntiVirus NinkVantage Technologies Wireless Manager 2008_04_08 1 s Free CCF09042008_00000
File name: Files of type: Record files (*.	*) Cancel

Figure 5-10

- Section 6: From the left to the right ,you can see video quality/fluency/ full screen/1-window/4-window/6-window/8-window/9-window/13-window/16-window/20window/25-window/36-window.. You can set video fluency and real-time feature priority.
- Section 7: PTZ operation panel. Please refer to chapter 5.5 for detailed information.
- Section 8: Image setup and alarm setup. Please refer to chapter 5.6 for detailed information.
- Section 9: From left to right, it is to set video quality, video latency, full screen, 1-window, 4-window.
- Section 10: Zero-channel encoding. This function allows you to view several-channel in one window. It supports 1/4-channel mode. Please go to chapter 4.11.5.2.4 to enable zero-channel encoding function first.

5.4 Real-time Monitor

In section 2, left click the channel name you want to view, you can see the corresponding video in current window.

On the top left corner, you can view device IP, channel number, network monitor bit stream. See Figure 5-11.




Figure 5-11

On the top right corer, there are six unction buttons. See Figure 5-12.




Figure 5-12

- 1: Digital zoom: Click this button and then left drag the mouse in the zone to zoom in. right click mouse system restores original status.
- 2: Local record. When you click local record button, the system begins recording and this button becomes highlighted. You can go to system folder RecordDownload to view the recorded file.
- 3: Snapshot picture. You can snapshoot important video. All images are memorized in system client folder PictureDownload (default).
- 4: Audio :Turn on or off audio.(It has no relationship with system audio setup)
- 5: Close video.

5.5 PTZ

Before PTZ operation, please make sure you have properly set PTZ protocol. (Please refer to chapter 5.8.5.5).


There are eight direction keys. In the middle of the eight direction keys, there is a 3D intelligent positioning key.

Click 3D intelligent positioning key, system goes back to the single screen mode. Drag the mouse in the screen to adjust section size. It can realize PTZ automatically.

Please refer to the following sheet for PTZ setup information.

Parameter	Function
Scan	Select Scan from the dropdown list.
	 Click Set button, you can set scan left and right limit.
	• Use direction buttons to move the camera to you desired location
	and then click left limit button. Then move the camera again and
	then click right limit button to set a right limit.
Preset	Select Preset from the dropdown list.
	 Turn the camera to the corresponding position and Input the
	preset value. Click Add button to add a preset.
Tour	Select Tour from the dropdown list.
	 Input preset value in the column. Click Add preset button, you
	have added one preset in the tour.
	• Repeat the above procedures you can add more presets in one
	tour.
	• Or you can click delete preset button to remove one preset from
	the tour.

Parameter	Function
Pattern	Select Pattern from the dropdown list.
	• You can input pattern value and then click Start button to begin
	PTZ movement such as zoom, focus, iris, direction and etc. Then
	you can click Add button to set one pattern.
Aux	Please input the corresponding aux value here.
	• You can select one option and then click AUX on or AUX off
	button.
Light and wiper	You can turn on or turn off the light/wiper.



5.6 Image/Relay-out

Select one monitor channel video and then click Image button in section 8, the interface is shown as Figure 5-14.

5.6.1 Image

Here you can adjust its brightness, contrast, hue and saturation. (Current channel border becomes green).

Or you can click Reset button to restore system default setup.

Image Setup Relay-out
»;=∎
●■
1 = =
�∎!⊞
Reset

Figure 5-14

5.6.2 Relay output

Here you can enable or disable the alarm signal of the corresponding port. See Figure 5-15.



Figure 5-15

5.7 WAN Login

In WAN mode, after you logged in, the interface is shown as below. See Figure 5-16.




Figure 5-16

Please refer to the following contents for LAN and WAN login difference.

1) In the WAN mode, system opens the main stream of the first channel to monitor by default. The open/close button on the left pane is null.

2) You can select different channels and different monitor modes at the bottom of the interface.

Important

The window display mode and the channel number are by default. For example, for the 16-channel, the max window split mode is 16.

3) Multiple-channel monitor, system adopts extra stream to monitor by default. Double click one channel, system switches to single channel and system uses main stream to monitor. You can view there are two icons at the left top corner of the channel number for you reference. M stands for main stream. S stands for sub stream (extra stream).

4) If you login via the WAN mode, system does not support alarm activation to open the video function in the Alarm setup interface.

Important

- For multiple-channel monitor mode, system adopts extra stream to monitor by default. You can not modify manually. All channels are trying to synchronize. Please note the synchronization effect still depends on your network environments.
- For bandwidth consideration, system can not support monitor and playback at the same time. System auto closes monitor or playback interface when you are searching setup in the configuration interface. It is to enhance search speed.

5.8 Setup

5.8.1 Camera

5.8.1.1 Remote Device (For digital channel only)

Domoto	daviaa	intorfooo	10	ahawa	~~	holow	000	Figure 5-	17
Remole	Gevice	intenace	IS	SHOWH	as	Delow	See	FIGURE 5-	17
110111010	401100	1111011000		01101111	~~	0010111	000	i igaio o	

No.			IP Ad	dress	Port		Device ID	Manufactu	rer	Туре
1			10.15	5.82	8086			Onvif		
2			10.15	5.5.88	8091			Onvif		
3			10.15.	6.169	8093			Onvif		
4			10.15.	.6.218	80			Onvif		
5			10.15.	.6.247	80			Onvif		
6			10.15.	.6.252	80			Onvif		
7			10.15	5.6.85	8093			Onvif		
8			10.15	5.6.86	8090			Onvif		
	Channel	Modify	Delete	Status	IP Address	Port	Device ID	Remote Channel	Manufacturer	Туре
	17	2	•	₽.	10.15.6.99	37777	YZC3CW20700015	1	Private	IPC-HFW5100
	19	1	•		10.15.6.218	37777	YZC3FW08600043	1	Private	IPC-HDBW5100
	21	2	•	E	10.15.6.169	40009	PZB1KN00800001	1	Private	SD6X83-HN
	22	2	0		10.15.6.169	40009	PZB1KN00800001	1	Private	SD6X83-HN



Channel	18	
Manufacturer	Private	~
IP Address	192.168.0.0	
TCP Port	37777	(1~65535)
User Name	admin	
Password	••••	
Remote Channel No.	1	
Decode Buffer	280	ms (80~480)

Figure 5-18

Please refer to the following sheet for log parameter information.

Parameter	Function					
Device	Click Device search button, you can view the searched device					
search	information on the list. It includes device IP address, port, device					
	name, manufacturer and type.					
Add	Select a device in the list and then click Add button, system can					
	connect the device automatically and add it to the Added device list.					
	Or you can double click one item in the list to add a device.					
Modify	Click 혼 or any device in the Added device list, you can change the					
	corresponding channel setup.					
Delete	Click 😰, you can delete the remote connection of the corresponding					
	channel.					
Connection	E : Connection succeeded.					
status	: Connection failed.					
Delete	Select a device in the Added device list and then click Delete button, system can disconnect the device and remove it from the Added device list.					

Parameter	Function
Manual Add	Click it, the interface is shown as in Figure 5-18. Here you can add network camera manually. You can select a channel from the dropdown list (Here only shows disconnection channel.)
	 Note: System supports manufactures such as Panasonic, Sony, Dynacolor, Samsung, AXIS, Arecont, Dahua and Onvif standard protocol. If you do not input IP address here. System uses default IP 192.168.0.0 and system does not connect to this IP. Can not add two devices at the same time. Click OK button here, system only connect to the corresponding device of current channel.

5.8.1.2 Conditions

Here you can view device property information. The setups become valid immediately after you set.

The analog channel is shown as in Figure 5-19.

Conditions									
		2016-08-24 00):51:25	Channel 1		-	Cable Ty	pe COAXIAL	 •
				Period	V 00 : 00	- 24 : 00	00 : 00 -	24 : 00	
				Saturation	é ——(5 0	0-	50	
				Brightness		5 0	0	50	
				Contrast		5 0	0	50	
				Hue	9	5 0	0	50	
				Sharpness	-0-	1	-0	1	
				Color Mode	Standar	d 💌	Standard	•	
			Ima	ge Enhance	-0-	30	-0	30	
				NR	(5 0	0-	50	
CAM 1									
Customized	Default	Cancel							

Figure 5-19

The digital channel is shown as in Figure 5-20.

Conditions						
Ser yn	2014-08-18 09.17 29	Channel	4	-		
1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1		Configuration Files	Day	~		
1111					Saturation 🖀 ———————————————————————————————————	50
	1/2	Mirror	O 0n 💿	Off	Brightness 🔅 🗌	50
					Contrast D	50
					Chroma 🏶 ———————————————————————————————————	50
		Flip	Flip 180	×		
		BLC Mode	Off	~		
1		Profile	Auto	~		
		Day & Night	Auto	~		
60						
Default	Save Refresh					

Figure 5-20

Please refer to the following sheet for detailed information.

Parameter	Function
Channel	Please select a channel from the dropdown list.
Cable type	 It is to set the cable type of the corresponding analog channel. When the setup here matches the actual cable you are using, you can get the best image effect. The default setup is COAXIAL. COAXIAL: When the corresponding channel is using coaxial cable, please select COAXIAL. UTP: When the corresponding channel is using UTP cable, please select UTP. Usually we recommend 100hm UTP cable.
Period	It divides one day (24 hours) to two periods. You can set different hue, brightness, and contrast for different periods.
Hue	It is to adjust monitor video brightness and darkness level. The default value is 50. The bigger the value is, the large the contrast between the bright and dark section is and vice versa.
Brightness	It is to adjust monitor window brightness. The default value is 50. The larger the number is , the bright the video is. When you input the value here, the bright section and the dark section of the video will be adjusted accordingly. You can use this function when the whole video is too dark or too bright. Please note the video may become hazy if the value is too high. The value ranges from 0 to 100.The recommended value ranges from 40 to 60.
Contrast	It is to adjust monitor window contrast. The value ranges from 0 to 100. The default value is 50.
	The larger the number is, the higher the contrast is. You can use this function when the whole video bright is OK but the contrast

	is not proper. Please note the video may become hazy if the value is too low. If this value is too high, the dark section may lack brightness while the bright section may over exposure .The recommended value ranges from 40 to 60.
Saturation	It is to adjust monitor window saturation. The value ranges from 0 to 100. The default value is 50.
	The larger the number is, the strong the color is. This value has no effect on the general brightness of the whole video. The video color may become too strong if the value is too high. For the grey part of the video, the distortion may occur if the white balance is not accurate. Please note the video may not be attractive if the value is too low. The recommended value ranges from 40 to 60.
Color mode	It includes several modes such as standard, color. You can select corresponding color mode here, you can see hue, brightness, and contrast and etc will adjust accordingly.

5.8.1.3 Encode

5.8.1.3.1 Encode

The encode interface is shown as below. See Figure 5-21.

Encode	Snapshot	Overlay	Path		
Channel	1	•			
Main Stream			Sub Stream		
Code-Stream Type	Regular	•	Video Enable		
Compression	H.264H	•	Compression	H.264H	•
Smart Codec	Stop	•			
Resolution	1920*1080(1080P)	•	Resolution	352*288(CIF)	•
Frame Rate(FPS)	15	•	Frame Rate(FPS)	15	•
Bit Rate Type	CBR	•	Bit Rate Type	CBR	•
Bit Rate	2048	▼ Kb/S	Bit Rate	320	Kb/S
Reference Bit Rate	640-6144Kb/S		Reference Bit Rate	32-640Kb/S	
I Frame Interval	1sec.	•	I Frame Interval	1sec.	•
Audio Enable			Audio Enable		
	0744			0744	_
Audio Format	G711a	•	Audio Format	G711a	-
Audio Source	LOCAL	•	Audio Source	LOCAL	•
Watermark Enable			Watermark String		
	Сору	Save	Refresh	Default	

Figure 5-21

Parameter Function

Channel	Please select a channel from the dropdown list.
SVC	SVC is so called scaled video coding. Check the box to enable this function. During the network transmission process, system discards unimportant frames when the bandwidth is not sufficient or the decode capability is low. It is to guarantee video quality and transmission fluency.
Video enable	Check the box here to enable extra stream video. This item is enabled by default.
Code stream type	It includes main stream, motion stream and alarm stream. You can select different encode frame rates form different recorded events.
	System supports active control frame function (ACF). It allows you to record in different frame rates.
	For example, you can use high frame rate to record important events, record scheduled event in lower frame rate and it allows you to set different frame rates for motion detection record and alarm record.
Smart Codec	Select Start from the dropdown list to enable smart codec function. The DVR can auto reduce the video bit stream of the non-important surveillance object to save the storage space.
Compression	 Compression: System supports H.264H, H.264, H.264B, and MJPEG. H.264H: It is the High Profile compression algorithm. It has the high encode compression rate. It can achieve high quality encode at low bit stream. Usually we recommend this type. H.264 is the general compression algorithm. H.264B is the Baseline algorithm. Its compression rate is low. For the same video quality, it has high bit stream requirements.
Resolution	For analog channel, system supports various resolutions, you can select from the dropdown list. Please note the option may vary due to different series. For digital channel, the resolution here refers to the capability of the network camera.
Frame Rate	PAL: 1~25f/s; NTSC: 1~30f/s.
Bit Rate	 Main stream: You can set bit rate here to change video quality. The large the bit rate is , the better the quality is. Please refer to recommend bit rate for the detailed information. Extra stream: In CBR, the bit rate here is the max value. In dynamic video, system needs to low frame rate or video quality to guarantee the value. The value is null in VBR mode.
Reference bit rate	Recommended bit rate value according to the resolution and frame rate you have set.

I Frame	Here you can set the P frame amount between two I frames. The value ranges from 1 to 150. Default value is 50. Recommended value is frame rate *2.
Audio source	Please select from the dropdown list. There are two options: Normal/HDCVI. In the normal mode, the audio signal comes from the Audio In. In the HDCVI mode, the audio signal comes from the coaxial cable of the camera.
Watermark enable	This function allows you to verify the video is tampered or not. Here you can select watermark bit stream, watermark mode and watermark character. Default character is DigitalCCTV. The max length is 85-digit. The character can only include number, character and underline.

5.8.1.3.2 Snapshot

The snapshot interface is shown as in Figure 5-22.

Encode	Snapshot	Overlay	Path	
Channel	1	•		
Mode	Timing	•		
Image Size	352*288(CIF)	•		
Quality	4	•		
Snapshot Frequenc	y 1 SPL	•		
	Сору	Save Ref	resh Default	

Figure 5-22

Please refer to the following sheet for detailed information.

Parameter	Function
Snapshot type	 There are two modes: Regular (schedule) and Trigger. Regular snapshot is valid during the specified period you set. Trigger snapshot only is valid when motion detect alarm, tampering alarm or local activation alarm occurs.
Image size	It is the same with the resolution of the main stream.
Quality	It is to set the image quality. There are six levels.
Interval	It is to set snapshot frequency. The value ranges from 1s to 7s. Or you can set customized value. The max setup is 3600s/picture.
Сору	Click it; you can copy current channel setup to other channel(s).

5.8.1.3.3 Video Overlay

The video overlay interface is shown as in Figure 5-23.

Encode	Snapshot	Overlay	Path
	2013	I-10-24 17∶00÷05	Cover-Area Cover-Area Preview Monitor Channel Display Setup Time Display Setup
CAM 1	Save	Refresh Default	

Figure 5-23

Please refer to the following sheet for detailed information.

Parameter	Function				
Cover-area	Check Preview or Monitor first.				
	Click Set button, you can privacy mask the specified video in the preview or monitor video.				
	System max supports 4 privacy mask zones.				
Time Title	You can enable this function so that system overlays time information in video window.				
	You can use the mouse to drag the time title position.				
	You can view time title on the live video of the WEB or the playback video.				
Channel Title	You can enable this function so that system overlays channel information in video window.				
	You can use the mouse to drag the channel title position.				
	You can view channel title on the live video of the WEB or the playback video.				

5.8.1.3.4 Path

The storage path interface is shown as in Figure 5-24.

Here you can set snap image saved path (I) in the preview interface) and the record

storage path (in the preview interface). The default setup is C:\PictureDownload and C:\RecordDownload.

Please click the Save button to save current setup.

	/ .	· · · · ·	Path
Snapshot Path	C:\PictureDownload		Browse
Record Path	C:\RecordDownload		Browse
	Save	Default	

Figure 5-24

5.8.1.4 Channel Name

Here you can set channel name. See Figure 5-25.

Please note this function is for analog channel only. The digital channel name here is read-only.

Camera Name				
Observation	0.004	Observation	0.000	
Channel 1	CAM 1	Channel 2	CAM 2	
Channel 3	CAM 3	Channel 4	CAM 4	
Channel 5	CAM 5	Channel 6	CAM 6	
Channel 7	CAM 7	Channel 8	CAM 8	
Channel 9	CAM 9	Channel 10	CAM 10	
Channel 11	CAM 11	Channel 12	CAM 12	
Channel 13	CAM 13	Channel 14	CAM 14	
Channel 15	CAM 15	Channel 16	CAM 1	
	Save	Refresh D	Default	

Figure 5-25

5.8.1.5 Channel Type

It is to set channel type. Each channel supports analog camera (analog standard definition/HDCVI) /network camera connection. Please note DVR needs to restart to activate new setup. The network camera connection shall begin with the last channel. For the 16-channel (or higher) series product, please go to the next page to set. See Figure 5-26.

Important notice about XVR series product:

- Nowadays, there are mainly two analog signal types on today market: analog standard definition (CVBS) and analog HD (CVI, AHD or Other). For XVR series product, each channel supports all types of signal connection (analog signal/IP signal). For analog signal connection, the default setup is AUTO, that is to say, no matter what analog signal (CVBS, CVI, AHD or other analog HD signal) connected; the XVR can automatically recognize the signal and display the proper image. There is no need to set manually.
- If the auto recognition error occurred, XVR series product supports manual setup too. The manual setup featuring high recognition speed and usually there is no error. For example, you can set channel 1 to connect to CVI camera, channel 2 to connect to AHD camera, channel 3 to connect to CVBS camera.

Analog OTHER P AUTO CVI AHD CVBS OTHER P 1 // // // ////////////////////////////////////	HANNEL TYPE							
AUTOL CVIL AHDIL CVIDS OTHER INF 1 V 0 0 0 0 2 V 0 0 0 0 3 V 0 0 0 0 4 V 0 0 0 0 5 V 0 0 0 0 6 V 0 0 0 0 7 V 0 0 0 0 8 V 0 0 0 0 9 V 0 0 0 0 11 V 0 0 0 0 13 V 0 0 0 0 14 V 0 0 0 0 15 V 0 0 0 0 16 V 0 0 0 0		-	-	Analog	-	-		
1 1 1 1 1 1 1 2 1 1 1 1 1 1 1 3 1 1 1 1 1 1 1 1 4 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 </th <th>Channel —</th> <th>AUTO 📃</th> <th>CVI 🔲</th> <th>AHD 🔳</th> <th>CVBS 🔳</th> <th>OTHER</th> <th>IP 📘</th> <th></th>	Channel —	AUTO 📃	CVI 🔲	AHD 🔳	CVBS 🔳	OTHER	IP 📘	
3 7 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	1	1						^
4 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7	2							
5 7 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	3	1						
6 / 1 1 1 1 7 / 1 1 1 1 1 8 / 1 1 1 1 1 1 9 / 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 </th <th>4</th> <th>V</th> <th></th> <th></th> <th></th> <th></th> <th></th> <th></th>	4	V						
7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7 7	5	\checkmark						
8 7 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	6							
9 7 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1	7	\checkmark						
10 11 12 13 14 15 16	8							
11 12 13 14 15 16	9	\checkmark						
12 Image: Constraint of the last channel.	10	\checkmark						
13 Image: Constraint of the setup shall begin from the last channel.	11	\checkmark						
14 Image: Constraint of the setup shall begin from the last channel.	12	\checkmark						
15 Image: Constraint of the setup shall begin from the last channel.	13	\checkmark						
16 Image: Constraint of the setup shall begin from the last channel. *Tips:Disable one analog channel, you can add one IP channel. IP channel setup shall begin from the last channel.	14							
*Tips:Disable one analog channel, you can add one IP channel. IP channel setup shall begin from the last channel.	15	\checkmark						
	16	V						-
Save Refresh Default Add IP CAM	*Tips:Disable o	ne analog channel,	you can add one IP c	hannel. IP channel se	etup shall begin from	the last channel.		
Save Refresh Default Add IP CAM								
			Save	Refresh	Default	Add IP CAM		

Figure 5-26

5.8.2 Network

5.8.2.1 TCP/IP

The single-Ethernet port interface is shown as in Figure 5-27.

TCP/IP		
Ethernet Port	Ethernet Port1	•
IP Version	IPv4	-
MAC Address	90 , 02 , a9 , da ,	9c . 77
Mode	STATIC O DH	ICP
IP Address	10 . 15 . 6	. 145
Subnet Mask	255 . 255 . 0	. 0
Default Gateway	10 . 15 . 0	. 1
Preferred DNS	10 . 1 . 2	. 80
Alternate DNS	10 . 1 . 2	. 81
MTU	1500	
MTU	1500	
	LAN Download	
	Save	Ref

Figure 5-27

The dual-Ethernet port interface is shown as in Figure 5-28.

TCP/IP	
Network Mode	Multi-address
Default Card	Ethernet Card1
Ethernet Card	Ethernet Card1
Mode	● STATIC ○ DHCP
MAC Address	20 : 13 : 10 : 13 : 16 : 33
MTU	1500
IP Version	IPv4
IP Address	10 . 15 . 6 . 252
Subnet Mask	255 . 255 . 0 . 0
Default Gateway	10 . 15 . 0 . 1
Preferred DNS	8.8.8.8
Alternate DNS	8 . 8 . 4 . 4
LAN Download	
	Save Refresh

Figure 5-28

Parameter	Function				
Mode	There are two modes: static mode and the DHCP mode.				
	 The IP/submask/gateway are null when you select the DHCP mode to auto search the IP. 				
	 If you select the static mode, you need to set the 				

	IP/submask/gateway manually.
	 If you select the DHCP mode, you can view the IP/submask/gateway from the DHCP.
	 If you switch from the DHCP mode to the static mode, you need to reset the IP parameters.
	 Besides, IP/submask/gateway and DHCP are read-only when the PPPoE dial is OK.
Mac Address	It is to display host Mac address.
IP Version	It is to select IP version. IPV4 or IPV6.
	You can access the IP address of these two versions.
IP Address	Please use the keyboard to input the corresponding number to modify the IP address and then set the corresponding subnet mask and the default gateway.
Preferred DNS	DNS IP address.
Alternate DNS	Alternate DNS IP address.
	es of IPv6 version, default gateway, preferred DNS and e input value shall be 128-digit. It shall not be left in blank.
LAN load	System can process the downloaded data first if you enable this function. The download speed is 1.5X or 2.0X of the normal speed.

5.8.2.2 Connection

The connection interface is shown as in Figure 5-29.

n 128	(0~128)				
37777	(200~65535)				
37778	(200~65535)				
80	(1~65535)				
443	(128~65535)				
554	(128~65535)				
rtsp:// <user name="">:<passw< th=""><th>ord>@<ip address="">:<port>/cam/realmonitor?channel=1&subtype=0</port></ip></th></passw<></user>	ord>@ <ip address="">:<port>/cam/realmonitor?channel=1&subtype=0</port></ip>				
channel: Channel, 1-32; sub	ype: Code-Stream Type, Main Stream 0, Sub Stream 1.				
Save	fresh Default				
n	37777 37778 80 443 554 rtsp:// <user name="">:<passw channel: Channel, 1-32, subl</passw </user>				

Figure 5-29

Parameter	Function
Max connection	It is the max Web connection for the same device. The value ranges from 1 to 120. The default setup is 120.
TCP port	The default value is 37777. You can input the actual port number if necessary.
UDP port	The default value is 37778. You can input the actual port number if necessary.

HTTP port	The default value is 80. You can input the actual port number if necessary.
HTTPS	The default value is 443. You can input the actual port number if necessary.
RTSP port	The default value is 554.

5.8.2.3 WIFI

Please note this function is for the device of WIFI module.

The WIFI interface is shown as in Figure 5-30.

WIFI				
WIFI Auto Connect				Search SSID
SSID List				
	SSID	Connect mode	Authorize Mode	Signal Intensity
				<u> </u>
WIFI Working Info				
Current Hotspot				
IP Address				
Subnet Mask				
Default Gateway				
Save	Refresh			

Figure 5-30

Please check the box to enable WIFI function and then click the Search SSID button. Now you can view all the wireless network information in the following list. Double click a name to connect to it. Click Refresh button, you can view latest connection status.

5.8.2.4 3G

5.8.2.4.1 CDMA/GPRS

The CDMA/GPRS interface is shown as in Figure 5-31.

CDMA/GPRS Setup	Mobile Setup	
WLAN Type	No Service	Y Enable
APN		Dial/SMS Activate
AUTH	PAP	V
Dial No.		
User Name		
Password		
Pulse Interval		Second
WLAN Status		
IP Address		
Wireless Signal	Search	
	Save	Refresh Default

Figure 5-31

Parameter	Function				
WLAN type	Here you can select 3G network type to distinguish the 3G module from different ISP. The types include WCDMA, CDMA1x and etc.				
APN/Dial No.	Here is the important parameter of PPP.				
Authorization	It includes PAP,CHAP,NO_AUTH.				
Pulse interval	It is to set time to end 3G connection after you close extra stream monitor. For example, if you input 60 here, system ends 3G connection after you close extra stream monitor 60 seconds				
Important					
 If the pulse interval is 0, then system does not end 3G connection after you close the extra stream monitor. 					
 Pulse interval here is for extra stream only. This item is null if you are using main stream to monitor. 					

5.8.2.4.2 Mobile

The mobile setup interface is shown as in Figure 5-32.

Here you can activate or turn off the 3G connected phone or mobile phone, or the phone you set to get alarm message.

CDMA/GPRS	S Setup Mot	ile Setup								
Send SM	s		SMS Activate			🗌 Tel Activa	te			
Receiver		+	Sender		+	Caller		-		
Title	DVR Message	Save	Refre	sh Defa	ult					



5.8.2.5 PPPoE

The PPPoE interface is shown as in Figure 5-33.

Input the PPPoE user name and password you get from the IPS (internet service provider) and enable PPPoE function. Please save current setup and then reboot the device to get the setup activated.

Device connects to the internet via PPPoE after reboot. You can get the IP address in the WAN from the IP address column.

Please note, you need to use previous IP address in the LAN to login the device. Please go to the IP address item to via the device current device information. You can access the client-end via this new address.

PPPoE	
Enable	
User Name	
Password	
IP Address	0.0.0
	0.0.0
	Save Refresh Default

Figure 5-33

5.8.2.6 DDNS

The DDNS interface is shown as in Figure 5-34.

The DDNS is to set to connect the various servers so that you can access the system via the server. Please go to the corresponding service website to apply a domain name and then access the system via the domain. It works even your IP address has changed.

Please select DDNS from the dropdown list (Multiple choices). Before you use this function, please make sure your purchased device support current function.

DDNS	
Enable	
Enable	
DDNS Type	Dahua DDNS
Server IP	www.quickddns.com
Domain Mode	 Default O Custom Name
Domain Name	9002A9BA3738 .quickddns.com Test
Email	(Optional)Please input email address.
	Save Refresh Default
	Boldar

Figure 5-34

Please refer to the following sheet for detailed information.

Parameter	Function
Server Type	You can select DDNS protocol from the dropdown list and then enable DDNS function.
Server IP	DDNS server IP address
Server Port	DDNS server port.
Domain Name	Your self-defined domain name.
User	The user name you input to log in the server.
Password	The password you input to log in the server.
Update period	Device sends out alive signal to the server regularly. You can set interval value between the device and DDNS server here.

Dahua DDNS and Client-end Introduction

1) Background Introduction

Device IP is not fixed if you use ADSL to login the network. The DDNS function allows you to access the DVR via the registered domain name. Besides the general DDNS, the Dahua DDNS works with the device from the manufacturer so that it can add the extension function.

2) Function Introduction

The Dahua DDNS client has the same function as other DDNS client end. It realizes the bonding of the domain name and the IP address. Right now, current DDNS server is for our own devices only. You need to refresh the bonding relationship of the domain and the IP regularly. There is no user name, password or the ID registration on the server. At the same time, each device has a default domain name (Generated by MAC address) for your option. You can also use customized valid domain name (has not registered.).

3) Operation

Before you use Dahua DDNS, you need to enable this service and set proper server address, port value and domain name.

- Server address: www.dahuaddns.com
- Port number: 80
- Domain name: There are two modes: Default domain name and customized domain name.

Except default domain name registration, you can also use customized domain name (You can input your self-defined domain name.) After successful registration, you can use domain name to login installed of the device IP.

• User name: It is optional. You can input your commonly used email address.

Important

- Do not register frequently. The interval between two registrations shall be more than 60 seconds. Too many registration requests may result in server attack.
- System may take back the domain name that is idle for one year. You can get a notification email before the cancel operation if your email address setup is OK.

5.8.2.7 IP filter

The IP filter interface is shown as in Figure 5-35.

After you enabled trusted sites function, only the IP listed below can access current DVR. If you enable blocked sites function, the following listed IP addresses can not access current DVR.

Trusted Site			
	IP Address	Edit	Delete
Add	1		

Figure 5-35

5.8.2.8 Email

✓ Enable SMTP Server 123.58.178.201 Port 25 ✓ Anonymous User Name dongqiang721 Password ●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●	Email		
Port 25 ✓ Anonymous User Name User Name dongqiang721 Password •••••••• Sender dongqiang721@126.com Encrypt Type NONE Subject DVR ALERT Receiver dongqiang0721@126.com t+ dongqiang0721@126.com mail Test Health Enable Minute (30-1440) Email Test 	Enable		
✓ Anonymous User Name dongqiang721 Password	SMTP Server	123.58.178.201	
User Name dongqiang721 Password Sender dongqiang721@126.com Encrypt Type NONE Subject DVR ALERT Attachment Receiver	Port	25	
Password ●●●●●●● Sender dongqiang721@126.com Encrypt Type NONE Subject DVR ALERT Subject DVR ALERT Receiver ●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●●	Anonymous		
Sender dongqiang721@126.com Encrypt Type NONE Subject DVR ALERT Receiver Interval Interval 130 Health Enable Gold Minute (30~1440)	User Name	dongqiang721	
Encrypt Type NONE Subject DVR ALERT Attachment Receiver dongqiang0721@126.com Interval 130 Second (0~3600) Health Enable 60 Minute (30~1440) Email Test	Password	•••••	
Subject DVR ALERT Attachment Receiver dongqiang0721@126.com interval 130 Second (0~3600) Health Enable 60 Minute (30~1440) Email Test	Sender	dongqiang721@126.com	
Receiver dongqiang0721@126.com - Interval 130 Second (0~3600) Health Enable 60 Minute (30~1440) Email Test	Encrypt Type	NONE	
dongqiang0721@126.com	Subject	DVR ALERT	
Interval 130 Second (0~3600) Health Enable 60 Minute (30~1440) Email Test	Receiver		÷
Health Enable 60 Minute (30~1440) Email Test		dongqiang0721@126.com	
Health Enable 60 Minute (30~1440)			
Email Test	Interval	130 Second (0~3600)	
	Health Enable	60 Minute (30~1440)	
Save Refresh Default		Email Test	
		Save Refresh Default	7

The email interface is shown as in Figure 5-36.

Figure 5-36

Parameter	Function
Enable	Please check the box here to enable email function.
SMTP Server	Input server address and then enable this function.
Port	Default value is 25. You can modify it if necessary.
Anonymity	For the server supports the anonymity function. You can auto login anonymously. You do not need to input the user name. password and the sender information.
User Name	The user name of the sender email account.
Password	The password of sender email account.
Sender	Sender email address.
Authentication (Encryption mode)	You can select SSL or none.
Subject	Input email subject here.
Attachment	System can send out the email of the snapshot picture once you check the box here.
Receiver	Input receiver email address here. Max three addresses. It supports SSL, TLS email box.
Interval	The send interval ranges from 0 to 3600 seconds. 0 means there is no interval. Please note system will not send out the email immediately when the alarm occurs. When the alarm, motion detection or the abnormity event activates the email, system sends out the email according to the interval you specified here. This

Parameter	Function
	function is very useful when there are too many emails activated by the abnormity events, which may result in heavy load for the email server.
Health mail enable	Please check the box here to enable this function.
Update period (interval)	This function allows the system to send out the test email to check the connection is OK or not. Please check the box to enable this function and then set the corresponding interval. System can send out the email regularly as you set here.
Email test	The system will automatically sent out a email once to test the connection is OK or not .Before the email test, please save the email setup information.

5.8.2.9 FTP

The FTP interface is shown as in Figure 5-37.

It is to set FTP IP, port and etc for remote storage.

10 . 18 . 116 . 89 *
21 *
dq
•••••
65535 M
2 Second
1
Thursday
00 : 00 - 24 : 00 Alarm V MD Regular
00 : 00 - 24 : 00
FTP Test
Save Refresh Default

Figure 5-37

5.8.2.10 UPnP

It allows you to establish the mapping relationship between the LAN and the public network.

Here you can also add, modify or remove UPnP item. See Figure 5-38.

- In the Windows OS, From Start->Control Panel->Add or remove programs. Click the "Add/Remove Windows Components" and then select the "Network Services" from the Windows Components Wizard.
- Click the Details button and then check the "Internet Gateway Device Discovery and Control client" and "UPnP User Interface". Please click OK to begin installation.
- Enable UPnP from the Web. If your UPnP is enabled in the Windows OS, the DVR can auto detect it via the "My Network Places"

AN IP	0.0.	0.0					
VAN IP	0.0.	0.0					
Port Mappin							
No.		Service Name	Protocol	Internal Port	External Port	Modify	Delete
1		HTTP	TCP	80	80	<u>2</u>	•
2		TCP	TCP	37777	37777	<u>/</u>	•
3	V	UDP	UDP	37778	37778	2	•
4		RTSP	UDP	554	554	1	•
5		RTSP	TCP	554	554	2	•
6		SNMP	UDP	161	161	1	•
7		HTTPS	TCP	443	443	2	•

Figure 5-38

5.8.2.11 SNMP

The SNMP interface is shown as in Figure 5-39.

The SNMP allows the communication between the network management work station software and the proxy of the managed device. It is reserved for the 3rd party to develop.

	SNMP			
~	Enable			
	SNMP Port	161	(0~65535)	
	Read Community	public		
	Write Community	private		
	Trap Address			
	Trap Port	162	(0~65535)	
	SNMP Version	✓ V1 ✓ V2		
		Save	Refresh Default	

Figure 5-39

Parameter	Function
SNMP Port	The listening port of the proxy program of the device. It is a UDP port not a TCP port. The value ranges from 1 to 65535. The default value is 161
Read Community	It is a string. It is a command between the manage process and the proxy process. It defined the authentication, access control and the management relationship between one proxy and one group of the managers. Please make sure the device and the proxy are the same. The read community will read all the objects the SNMP supported in the specified name. The default setup is public.
Write Community	It is a string. It is a command between the manage process and the proxy process. It defined the authentication, access control and the management relationship between one proxy

Parameter	Function
	and one group of the managers. Please make sure the device and the proxy are the same. The read community will read/write/access all the objects the SNMP supported in the specified name. The default setup is write.
Trap address	The destination address of the Trap information from the proxy program of the device.
Trap port	The destination port of the Trap information from the proxy program of the device. It is for the gateway device and the client-end PC in the LAN to exchange the information. It is a non-protocol connection port. It has no effect on the network applications. It is a UDP port not TCP port. The value ranges from 1 to 165535. The default value is 162.
SNMP version	 Check V1, system only processes the information of V1. Check V2, system only processes the information of V2.

5.8.2.12 Multicast

The multicast interface is shown as in Figure 5-40.

Multicast is a transmission mode of data packet. When there is multiple-host to receive the same data packet, multiple-cast is the best option to reduce the broad width and the CPU load. The source host can just send out one data to transit. This function also depends on the relationship of the group member and group of the outer.

Multicast	
Enable	
IP Address	239 , 255 , 42 , 42 (224.0.0.~239.255.255.255)
Port	36666 (1~65500)
	Save Refresh Default

Figure 5-40

5.8.2.13 Auto Register

The auto register interface is shown as below. See Figure 5-41.

This function allows the device to auto register to the proxy you specified. In this way, you can use the client-end to access the DVR and etc via the proxy. Here the proxy has a switch function. In the network service, device supports the server address of IPv4 or domain.

Please follow the steps listed below to use this function.

Please set proxy server address, port, and sub-device name at the device-end. Please enable the auto register function, the device can auto register to the proxy server.

Auto Register	
Enable	
Server IP	0.0.0.0
Port	8000
Sub-device ID	0
	Save Refresh Default

5.8.2.14 Alarm Centre

The alarm centre interface is shown as below. See Figure 5-42.

This interface is reserved for you to develop. System can upload alarm signal to the alarm centre when local alarm occurs.

Before you use alarm centre, please set server IP, port and etc. When an alarm occurs, system can send out data as the protocol defined, so the client-end can get the data.

Alarm Centre	
Enable	
Protocol Type	Private
Server IP	10 . 1 . 0 . 2
Port	1
Selfreport Time	Everyday 💽 at 08:00
	Save Refresh Default

Figure 5-42

5.8.2.15 P2P

You can use your cell phone to scan the QR code and add it to the cell phone client. Via the SN from scanning the QR code, you can access the device in the WAN. Please refer to the P2P operation manual included in the resources CD.

The P2P interface is shown as in Figure 5-43.

Check the Enable box to enable P2P function and then click the Save button. Now you can view the device status and SN.

Enable Status Offline		
Onine		
Cell Phone Clie	ient Device SN	
回連次	in estimated at	
- 318		
- 1643) 1643)		
- 690	御 岩浅道	
	and three we	
Scan QR to Do	ownload 1E025A2YAZT9012	
	Save Refresh	

Figure 5-43

5.8.2.16 HTTPS

In this interface, you can set to make sure the PC can successfully login via the HTTPS. It is to guarantee communication data security. The reliable and stable technology can secure the user information security and device safety. See Figure 5-44.

Note

- You need to implement server certificate again if you have changed device IP.
- You need to download root certificate if it is your first time to use HTTPS on current PC.

HTTPS			
Create Server Certif	ficate Download Root Certificate		



5.8.2.16.1 Create Server Certificate

If it is your first time to use this function, please follow the steps listed below.

In Figure 5-44, click Create Server Certificate button, input country name, state name and etc. Click Create button. See Figure 5-45.

Note

Please make sure the IP or domain information is the same as your device IP or domain name.

38			
	38	38	38



You can see the corresponding prompt. See Figure 5-46. Now the server certificate is successfully created.

Create Server Certificate	Download Root Certificate		
Create Succeed			

Figure 5-46

5.8.2.16.2 Download root certificate

In Figure 5-44, click Download Root Certificate button, system pops up a dialogue box. See Figure 5-47.



Figure 5-47

Click Open button, you can go to the following interface. See Figure 5-48.

🕎 Certifica	ate Information
	ertificate is not trusted. To enable trust, tificate in the Trusted Root Certification
Authorities sto	re.
Issued to:	Product Root CA
Issued by:	: Product Root CA
ξ.	2013-6-18 to 2023-6-16

Figure 5-48

Click Install certificate button, you can go to certificate wizard. See Figure 5-49.



Figure 5-49

Click Next button to continue. Now you can select a location for the certificate. See Figure 5-50.

Certificate stores are system area	as where certificates are kept.
	a certificate store, or you can specify a location for
Automatically select the cell	rtificate store based on the type of certificate
OPlace all certificates in the f	following store
Certificate store:	
	Browse

Figure 5-50

Click Next button, you can see the certificate import process is complete. See Figure 5-51.

Certificate Import Wizard	Wizard You have successfully compl wizard.	
	You have specified the follow Certificate Store Selected Content	ving settings: Automatically determined by t Certificate
	< mini	Finish Cancel

Figure 5-51

Click Finish button, you can see system pops up a security warning dialogue box. See Figure 5-52.




Figure 5-52

Click Yes button, system pops up the following dialogue box, you can see the certificate download is complete. See Figure 5-53.

Certificate Import Wizard 🛛 🔀					
٩	The import was successful.				
	ОК				

Figure 5-53

5.8.2.16.3 View and set HTTPS port

From Setup->Network->Connection, you can see the following interface. See Figure 5-54.

You can see HTTPS default value is 443.

Connection				
_				
Max Connection	128	(0~128)		
TCP Port	37777	(200~65535)		
UDP Port	37778	(200~65535)		
HTTP Port	80	(1~65535)		
HTTPS Port	443	(128~65535)		
RTSP Port	554	(128~65535)		
RTSP Format	rtsp:// <username>:<password>@<ipaddress>:<port>/cam/realmonitor?channel=1&subtype=0</port></ipaddress></password></username>			
	channel: Channel, 1-32; subtype: Code-Stream Type, Main Stream 0, Sub Stream 1.			
	Save Refresh Default			

Figure 5-54

5.8.2.16.4 Login

Open the browser and then input https://xx.xx.xx.xx:port.

xx.xx.xx.xx: is your device IP or domain mane.

Port is your HTTPS port. If you are using default HTTPS value 443, you do not need to add port information here. You can input <u>https://xx.xx.xx.xx</u> to access.

Now you can see the login interface if your setup is right.

5.8.3 Event

5.8.3.1 Video detect

5.8.3.1.1 Motion Detect

The motion detect interface is shown as in Figure 5-55.

Motion Detect	Video Loss	Tampering	Diagnosis	
Enable	1	•		
Period Anti-dither	Setup 5 sec. (0-	-600)		
Region	Setup			
Record Channel	Setup			
Delay	10 sec. (1	0-300)		
Alarm Out	1 2 3			
Latch	10 sec. (0	~300)		
PTZ Activation	Setup			
✓ Tour	Setup			
🗸 Snapshot	Setup			
Video Matrix				
Voice Prompts	File Name None	•		
Show Message	🔲 Send Email 🔲 Bi	uzzer 🔲 Message 🔲	Log	
Alarm Upload				
	Сору	Save	fresh Default	

Figure 5-55

Thu	irsday	y	~		Co	p	l.
	00	1	00]-	24	:	00
	00	1.20	00	-	24	÷	00
	00		00	-	24	-	00
	00		00	-	24	÷	00
	00	1	00	-	24	:	00
	00		00	-	24	;	00
	Save	F.			Car	nc	el

Figure 5-56




Figure 5-57

Channel 1	None	•	0
Channel 2	None	•	0
Channel 3	None	•	0
Channel 4	None	•	0
Channel 5	None	•	0
Channel 6	None		0
Channel 7	None	•	0
Channel 8	None	•	0

Figure 5-58

Parameter	Function
Enable	You need to check the box to enable motion detection function. Please select a channel from the dropdown list.
Period	Motion detection function becomes activated in the specified periods. See Figure 5-56.
	There are six periods in one day. Please draw a circle to enable corresponding period.
	Click OK button, system goes back to motion detection interface, please click save button to exit.

Parameter	Function
Anti-dither	System only memorizes one event during the anti-dither period. The value ranges from 5s to 600s.
Sensitivity	There are six levels. The sixth level has the highest sensitivity.
Region	If you select motion detection type, you can click this button to set motion detection zone. The interface is shown as in Figure 5-57. Here you can set motion detection zone. There are four zones for you to set. Please select a zone first and then left drag the mouse to select a zone. The corresponding color zone displays different detection zone. You can click Fn button to switch between the arm mode and disarm mode. In arm mode, you can click the direction buttons to move the green rectangle to set the motion detection zone. After you completed the setup, please click ENTER button to exit current setup. Do remember click save button to save current setup. If you click ESC button to exit the region setup interface system will not save your zone setup.
Record channel	System auto activates motion detection channel(s) to record once an alarm occurs. Please note you need to set motion detect record period and go to Storage-> Schedule to set current channel as schedule record.
Record Delay	System can delay the record for specified time after alarm ended. The value ranges from 10s to 300s.
Alarm out	Enable alarm activation function. You need to select alarm output port so that system can activate corresponding alarm device when an alarm occurs.
Latch	System can delay the alarm output for specified time after an alarm ended. The value ranges from 1s to 300s.
Video Matrix	This function is for motion detect only. Check the box here to enable video matrix function. Right now system supports one-channel tour function. System takes "first come and first serve" principle to deal with the activated tour. System will process the new tour when a new alarm occurs after previous alarm ended. Otherwise it restores the previous output status before the alarm activation.
Snapshot	You need to check the box here to enable this function. You can set corresponding channel to snapshot when motion detect alarm occurs.
Show message	System can pop up a message to alarm you in the local host screen if you enabled this function.
Buzzer	Check the box here to enable this function. The buzzer beeps when an alarm occurs.
Alarm upload	System can upload the alarm signal to the centre (Including alarm centre.
Message	When 3G network connection is OK, system can send out a message when motion detect occurs.
Send Email	If you enabled this function, System can send out an email to alert you when an alarm occurs.

Tour	You need to check the box here to enable this function. System begins 1-wiindow or multiple-window tour display among the channel(s) you set to record when an alarm occurs.
PTZ Activation	Here you can set PTZ movement when alarm occurs. Such as go to preset X. See Figure 5-58.
Log	Check the box here, system can record motion detect event log.

5.8.3.1.2 Video Loss

The video loss interface is shown as in Figure 5-59.

After analysis video, system can generate a video loss alarm when the detected moving signal reached the sensitivity you set here.

Please note video loss does not support anti-dither, sensitivity, region setup. For rest setups, please refer to chapter 5.8.3.1.1 motion detect for detailed information.

Motion Detect	Video Loss	Tampering	Diagnosis	
Enable	1	•		
Period CAM AntiDither	Setup 0 sec. (0	-300)		
Record Channel Delay	Setup 10 sec. (10-300)		
 Alarm Out Latch 	1 2 3 10 sec. (0			
 PTZ Activation Tour 	Setup Setup			
Snapshot Voice Prompts	Setup File Name None			
Show Message			Log	
Alarm Upload	Сору	Save	efresh Default	

Figure 5-59

5.8.3.1.3 Tampering

The tampering interface is shown as in Figure 5-60.

After analysis video, system can generate a tampering alarm when the detected moving signal reached the sensitivity you set here.

For detailed setups, please refer to chapter 5.8.3.1.1 motion detect for detailed information.

Motion Detect	Video Loss Tampering Diagnosis	
Enable	1	
Period Sensitivity	Setup 3 💌	
Record Channel Delay	Setup 10 sec. (10-300)	
 Alarm Out Latch 	1 2 3 10 sec. (0~300)	
PTZ Activation Tour	Setup Setup	
Snapshot	Setup	
Voice Prompts Show Message	File Name None 💌	
Alarm Upload	Send Ennan E Buzzer E Message V Log	
	Copy Save Refresh Default	

Figure 5-60

5.8.3.1.4 Diagnosis

System can trigger an alarm when the stripe, noise, color cast, out of focus, over exposure event occurred. See Figure 5-61.

Motion Detect	Video Loss	Tampering	Diagnosis	
Channel	1	✓ Set		
Enable				
Period	Set			
Alarm Out	123			
Latch	10 sec. (0-	~300)		
Voice Prompts	File Name None	•		
🔲 Send Email 🛛 🛛	uzzer 🔲 Message 🔽	Log		
	Save	Refresh	efault	

Figure 5-61

Click Set button, you can check the corresponding box to select diagnosis type. See Figure 5-62.

Diagnosis			×
Stripe	v 0-	30	
Noise	v -0-	<mark></mark> 30	
Color Cast	v —0-	30	
Out of Focus	v —0-	30	
Overexposure	v —0-	30	
	Save	Cancel	

Figure 5-62

Note

Video diagnosis alarm can trigger PTZ preset, tour, and pattern.

For detailed setups, please refer to chapter 5.8.3.1.1 motion detect for detailed information.

5.8.3.2 Intelligence (Optional)



The intelligence function is optional. The intelligence function and the

human face detection can not be valid at the same time!

From main menu->Setup->Event->IVS, you can go to the IVS interface. It includes three interfaces: Tripwire/intrusion/object.

5.8.3.2.1 Tripwire

Note:

- The tripwire function is valid once your network camera or your DVR supports this function.
- If your purchased DVR supports the tripwire function, it supports one analog channel. It is not for the digital channel.

From main menu->Setup->Event->IVS->Tripwire, you can see the following interface. See Figure 5-63.

System generates an alarm once there is any object crossing the tripwire in the specified direction.

Tripwire	Intrusion	Abandoned				
A MARK	· · · ·	2014-07-03 09:31:53	Tripwire		2	•
			Period	Set.		
			No.	1	M	
E-MAR AND			Name	line1		
E.			DIRECTION	Both		
			Record CH	Set		
S	STATE OF THE OWNER OF THE OWNER OF		Delay	10 sec.	(10~300)	
Contraction of the local division of the loc		A DESCRIPTION OF TAXABLE PARTY.	Atarm Out	1 2 3 4	5 6 7 8	
			Latch	10 sec.	(1~300)	
Channel I			PTZ Activation	Set		
	_		Tour	Set		
Draw,Rule		Clear	Snapshot	Set		
	Max Size Min Size	Draw Target Clear	Atarm Upload	Send Email	Buzzer 🕑 Log	
			ОК	Refresh	efault	

Figure 5-63

Check the Tripwire box to enable tripwire function.

Select SN (Line1/2/3/4) and direction, and then input customized rule name.

- No. and Line1/2/3/4: System supports four tripwires. Each SN stands for one tripwire.
- Direction: There are three options: A->B, B->A, both. System can generate an alarm once there is any object crossing in the specified direction.

Now you can draw a rule. Click Draw rule button and then left click mouse to draw a tripwire. The tripwire can be a direct line, curve or polygon. Right click mouse to complete. See Figure 5-64.

	2014-07-03 09:38:07	Tripwire		2	-
		Period	Set		
		No.	1		
		Name	line1		
		DIRECTION	Both		
		Record CH	Set		
		Delay	10	sec. (10~300)	
\sim		Alarm Out	123	4 5 6 7 8	
\sim		Latch	10	sec. (1~300)	
Channel 1		PTZ Activation	Set		
		Tour	Set		
Draw Rule	Clear	Snapshot	Set		
Target Filter Max Size	Draw Target Clear	Alarm Upload	Send	Email 🔲 Buzzer 🗹 Log	
		ок	Refresh	Default	

Figure 5-64




Figure 5-65

Select the blue line and then use mouse to adjust zone size.

Note

Each rule can set two sizes (min size/max size). Once the object is smaller than the min size or larger than the max size, there is no alarm. Please make sure the max size is larger than the min size.

Click Ok to complete the rule setup.

For detailed setups, please refer to chapter 5.8.3.1.1 motion detect for detailed information.

5.8.3.2.2 Intrusion (Cross warning zone)

Note:

- The intrusion function is valid once your network camera or your DVR supports this function.
- If your purchased DVR supports the intrusion function, it supports one analog channel.
 It is not for the digital channel.

From main menu->Setup->Event->IVS->Intrusion, the intrusion interface is shown as below. See Figure 5-66.

Tripwire	Intrusion	Abandoned				
- 12-8	8-	2014-07-03 09:49:18	Intrusion		2	•
	- Article		Period	Set		
			No.	1		
E. College			Name	area1		
			DIRECTION	Both	M	
V-Starks			Record CH	Set		
			Delay	10	sec. (10-300)	
			Alarm Out	123	4 5 6 7 8	
			Latch	10	sec. (1~300)	
Cliancel 1			PTZ Activation	Set		
	_		Tour	Set		
Draw Rule		Clear	Snapshot	Set		
	Max Size	Draw Target Clear	Alarm Upload	Send E	Email 🔲 Buzzer 🕑 Log	
0	Min Size		ок	Refresh	Default	

Figure 5-66

Check the Intrusion box to enable intrusion function.

Select SN (Area1/2/3/4) and direction, and then input customized rule name.

- No. and Area1/2/3/4: System supports four zones. Each SN stands for one zone.
- Direction: There are three options: A->B, B->A, both. System can generate an alarm once there is any object enter/exit (Or both) the zone.

Now you can draw a rule. Left click mouse to draw a line first and then right click mouse to draw another line until you draw a rectangle, you can right click mouse to exit. Click Ok to complete the rule setup.

Click Draw Rule to draw the zone. See Figure 5-67.

Tripwire	Intrusion	Abandoned				
	/- ···	2014-07-03 09:53:57	Intrusion		2	•
			Period	Set		
			No.	1	2	
			Name	area1		
7. III			DIRECTION	Both	×	
3			Record CH	Set		
	and the second second		Delay	10 sec. (1	0~300)	
			Alarm Out	1 2 3 4 5	6 7 8	
1.00			Latch	10 sec. (1	-300)	
Channel 1			PTZ Activation	Set		
	_		Tour	Set		
Draw Rule		Clear	Snapshot	Set		
Charles and a second second	Max Size	Draw Target Clear	Alarm Upload	Send Email	🗌 Buzzer 🕑 Log	
U	Min Size		ОК	Refresh De	fault	



For detailed setups, please refer to chapter 5.8.3.1.1 motion detect for detailed information.

5.8.3.2.3 Object Detect

Note:

- The object detection function is valid once your network camera or your DVR supports this function.
- If your purchased DVR supports the object detection function, it supports one analog channel. It is not for the digital channel.

From main menu->Setup->Event->IVS->Object, the object interface is shown as below. See Figure 5-68.

Tripwire	Intrusion	Object				
	1-1	2014-07-03 09:52:01	Object		2	•
	A		Period	Set		
	II III		No.	1	N	
E State of the second			Rule Type	Abandoned	<u>×</u>	
	N		Name	object1		
B. Aller			Period	10	(5)	
			Record CH	Set		
100 million and the owner of the		-	Delay	10 s	sec. (10~300)	
1000 - 100			Alarm Out	1 2 3 4	1 5 6 7 8	
Channel 1			Latch	10 5	sec. (1~300)	
			PTZ Activation	Set		
Draw Rule		Clear	Tour	Set		
Target Filter 💿 🕯	lax Size		Snapshot	Set		
	lin Size	Draw Target Clear	Atarm Upload	Send En	mail 🔲 Buzzer 🗹 Log	
			ок	Refresh	Default	

Figure 5-68

Check the Object box to enable object detect function.

Select SN (object1/2/3/4) and rule type, and then input customized rule name.

- No. and Object1/2/3/4: System supports four zones. Each SN stands for one zone.
- Rule type: Please select from the dropdown list. There are two types: Missing object detect/abandoned object detect.
- Period: It refers to the object in/out the zone time.

Click

Draw Rule

to draw the rule. See Figure 5-69.

Tripwire	Intrusion	Object	-			
and the second	1	2014-07-03 09:58	21 Object		2	•
			Period	Set		
	III)		No.	1		
			Rule Type	Abandoned	~	
2010	N'		Name	object1		
3	Pobject1	1	Period	10	(9)	
			Record CH	Set		
and the second value of th		_	Delay	10 se	c. (10~300)	
			Alarm Out	1 2 3 4	5 6 7 8	
Charged 1			Latch	10 se	c (1~300)	
			PTZ Activation	Set		
Draw Rule		Cle	ar 🗌 Tour	Set		
Target Filter 💿 M	lax Site		Snapshot	Set		
	lin Size	Draw Target Cle	ar 🗌 🗌 Alarm Upload	Send Ema	ell 🔲 Buzzer 🕑 Log	
			ОК	Refresh	Default	

Figure 5-69

Now you can draw a rule. Left click mouse to draw a line, until you draw a rectangle, you can right click mouse.

Click Ok to complete the rule setup.

For detailed setups, please refer to chapter 5.8.3.1.1 motion detect for detailed information.

5.8.3.3 Face Detect (Optional)

The face detection function is optional. The intelligence function and the

human face detection can not be valid at the same time!

When camera detects human face, system can draw a rectangle around the human face and generate an alarm.

From main menu->Setup->Event->Face detect, the interface is shown as in Figure 5-70.

- Enable face boost: Check the box here, system can enhance the human face display pane.
- Sensitivity: System supports 6 levels. The sixth level has the highest sensitivity.

For detailed setups, please refer to chapter 5.8.3.1.1.

FACE DETECT	
Enable	22 💌
🔽 Human Face ROI	
Alarm Face No.	1 (1~35)
Period	Setup
Record Channel	Setup
Delay	sec. (10~300)
Alarm Out	1 2 3 4 5 6
Latch	sec. (0~300)
PTZ Activation	Setup
🔲 Tour	Setup
🔲 Snapshot	Setup
Voice Prompts	File Name
🔲 Send Email 🔲 E	uzzer 🔲 Message 📄 Log
	Save Refresh

Figure 5-70

5.8.3.4 Alarm

Before operation, please make sure you have properly connected alarm devices such as buzzer. The input mode includes local alarm and network alarm.

5.8.3.4.1 Local Alarm

The local alarm interface is shown as in Figure 5-71. It refers to alarm from the local device.

Local Alarm	Net Alarm	IPC External Alarm IPC Offline Alarm
Enable	1	✓ Alarm Name Alarm In1
Period Anti-dither	Setup 5 sec. ((0-600) Type NO 💌
Record Channel Delay	Setup 10 sec. ((10-300)
Alarm Out Latch	1 2 3 10 sec. ((0~300)
 PTZ Activation Tour Snapshot Video Matrix 	Setup Setup Setup	
 Voice Prompts Show Message Alarm Upload 	File Name None	Buzzer 🗌 Message 🔽 Log
	Сору	Save Refresh Default

Figure 5-71

Thu	ursday	~	Cop	by 🖉
	00 ; 0	- 00	24 ;	00
	00 : 0	- 00	24 :	00
	00 : 0	- 00	24 ;	00
	00 : 0	- 00	24 ;	00
	00 ; (- 00	24 :	00
	00 : 0	- 00	24 :	00
	Save		Can	cel

Figure 5-72

Channel 1	None	-	0
Channel 2	None	•	0
Channel 3	None		0
Channel 4	None	•	0
Channel 5	None	•	0
Channel 6	None	•	0
Channel 7	None	•	0
Channel 8	None		0

Figure 5-73

Please refer to the following sheet for detailed information.

Parameter	Function
Enable	You need to check the box to enable this function. Please select a channel from the dropdown list.
Period	This function becomes activated in the specified periods.
	There are six periods in one day. Please draw a circle to enable corresponding period.
	Select date. If you do not select, current setup applies to today only. You can select all week column to apply to the whole week.
	Click OK button, system goes back to local alarm interface, please click save button to exit.
Anti-dither	System only memorizes one event during the anti-dither period. The value ranges from 5s to 600s.
Sensor type	There are two options: NO/NC.
Record channel	System auto activates motion detection channel(s) to record once an alarm occurs. Please note you need to set alarm record period and go to Storage-> Schedule to set current channel as schedule record.
Record Delay	System can delay the record for specified time after alarm ended. The value ranges from 10s to 300s.
Alarm out	Enable alarm activation function. You need to select alarm output port so that system can activate corresponding alarm device when an alarm occurs.
Latch	System can delay the alarm output for specified time after an alarm ended. The value ranges from 1s to 300s.
Show message	System can pop up a message to alarm you in the local host screen if you enabled this function.

Parameter	Function
Buzzer	Check the box here to enable this function. The buzzer beeps when an alarm occurs.
Alarm upload	System can upload the alarm signal to the centre (Including alarm centre).
Send Email	If you enabled this function, System can send out an email to alert you when an alarm occurs.
Tour	You need to check the box here to enable this function. System begins 1-wiindow or multiple-window tour display among the channel(s) you set to record when an alarm occurs.
PTZ Activation	Here you can set PTZ movement when alarm occurs. Such as go to preset X.
Log	Check the box here, system can record local alarm event log.

5.8.3.4.2 Net Alarm

The network alarm interface is shown as in Figure 5-74.

Network alarm refers to the alarm signal from the network. System does not anti-dither and sensor type setup. For setup information, please refer to chapter 5.8.3.4.1.

Local Alarm	Net Alarm	IPC External Alarm	IPC Offline Alarm	
Enable	1	▼ Alarm Name	Alarm In1	
Period	Setup			
Record Channel	Setup			
Delay	10 sec. (1	10-300)		
Alarm Out	1 2 3			
Latch	10 sec. (0)~300)		
PTZ Activation	Setup			
Tour	Setup			
Snapshot	Setup			
Video Matrix				
Voice Prompts	File Name None	•		
📄 Show Message	🔲 Send Email 🔲 B	uzzer 🔲 Message 🔽	Log	
	Сору	Save	efresh Default	

Figure 5-74

5.8.3.4.3 IPC External Alarm

IPC external alarm interface is shown as below. See Figure 5-75. For setup information,

please refer to chapter 5.8.3.4.1.

Local Alarm	Net Alarm	IPC External Alarm	IPC Offline Alarm	
Channel	15	Alarm Name Ala	arm In1]
Period Anti-dither	Setup	(0-600) Type NO	•	
And-differ	sec.	(0-600) Type NO	•	
Record Channel	Setup			
Delay	10 sec.	(10-300)		
Alarm Out	1 2 3			
Latch	10 sec.	(0~300)		
PTZ Activation	Setup			
Tour	Setup			
Snapshot	Setup			
Video Matrix				
Voice Prompts	File Name None	•		
Show Message	🔲 Send Email 🔲	Buzzer 🔲 Message 🔽 L	og	
Alarm Upload				
	Сору	Save Refr	esh Default	

Figure 5-75

5.8.3.4.4 IPC Offline Alarm

IPC offline alarm is shown as in Figure 5-76. For setup information, please refer to chapter 5.8.3.4.1.

Local Alarm	Net Alarm IPC External Alarm IPC Offline Alarm
Channel	15 💌
Record Channel Delay	Setup 10 sec. (10-300)
 Alarm Out Latch 	1 2 3 10 sec. (0~300)
 PTZ Activation Tour Snapshot Video Matrix 	Setup Setup
Voice Prompts	File Name None 💌
🔲 Show Message	📄 Send Email 📄 Buzzer 📄 Message 🔽 Log
🔽 Alarm Upload	
	Copy Save Refresh Default

Figure 5-76

5.8.3.5 Abnormality

It includes three types: HDD/Network/User. See Figure 5-77 and Figure 2-77.

- HDD includes: No disk, disk error, disk no space.
- Network includes net disconnection, IP conflict, and MAC conflict.
- User: It includes illegal login.

HDD	Network User	
Event Type	No HDD	
Enable		
📝 Alarm Out	1 2 3	
Latch	10 sec. (0~300)	
Voice Prompts	File Name None 💌	
✓ Show Message	📄 Send Email 🔽 Buzzer 📄 Message 🔽 Log	
🔽 Alarm Upload		
	Save Refresh	

Figure 5-77

HDD	Network User
Event Type	Disconnect
Enable	
Alarm Out	1 2 3
Latch	10 sec. (0~300)
Voice Prompts	File Name None 💌
Show Message	📄 Send Email 📄 Buzzer 📄 Message 🔽 Log
Record Channel	Setup
Delay	10 sec. (10-300)
	Save Refresh

Figure 5-78

HDD	Network	User
Event Type	Disconnect 🗸]
Enable		
Alarm Out	1 2 3	
Latch	10 sec. (0~300)
Voice Prompts	File Name None	▼
Show Message	🔲 Send Email 🔲 Buzzer	🔲 Message 🛛 Log
Record Channel	Setup	
Delay	10 sec. (10-300))
	Save	efresh

Figure 5-79

Parameter	Function
Event Type	The abnormal events include: No disk, disk error, disk no space, net disconnection, IP conflict and MAC conflict.
	You can set one or more items here.
	Less than: You can set the minimum percentage value here (For disk not space only). The device can alarm when capacity is not sufficient.
	You need to draw a circle to enable this function.
Enable	Check the box here to enable selected function.
Alarm Out	Please select corresponding alarm output channel when an alarm occurs. You need to check the box to enable this function.
Latch	The alarm output can delay for the specified time after an alarm stops. Th
	value ranges from 0s to 300s. The default setup is 10 seconds. The o
	second means there is no delaying time.
Attempt(s)	It is to set login attempt times. Once the login attempt exceeds the
	threshold you set here, current account will be locked. This function is
	illegal login only.
Lock time	It is to set account lock time once its login attempt has exceeded the
	threshold you set. This function is for illegal login only.
Show message	System can pop up a message to alarm you in the local host screen if you enabled this function.
Alarm upload	System can upload the alarm signal to the centre (Including alarm centre.

Parameter	Function
Send Email	If you enabled this function, System can send out an email to alert you when an alarm occurs.
Buzzer	Check the box here to enable this function. The buzzer beeps when an alarm occurs.
Log	Check the box here, system can record the network event alarm log.

5.8.3.6 Alarm Output

It is to set alarm output mode. See Figure 5-80.

Alarm Out		
Alarm Type	All 1 2 3	
Schedule	\odot \odot \odot \odot	
Manual	0 0 0 0	
Stop	0 0 0 0	
Status		
	Alarm Release	
	Save Refresh	

Figure 5-80

5.8.4 Storage

5.8.4.1 Schedule

5.8.4.1.1 Schedule Record

In this interfaces, you can add or remove the schedule record setup. See Figure 5-81. There are three record modes: general (auto), motion detect and alarm. There are six periods in one day.

You can view the current time period setup from the color bar.

- Green color stands for the general record/snapshot.
- Yellow color stands for the motion detect record/snapshot..
- Red color stands for the alarm record/snapshot.
- Blue color stands for MD&alarm record/snapshot.




Figure 5-81

Time Period 1	00:00	24:00	Regular		Alarm	MD&Alarm
Time Period 2	00:00	24:00	Regular	D MD	Alarm	MD&Alarm
ime Period 3	00:00	24:00	Regular	🗆 MD	🗌 Alarm	MD&Alarm
Fime Period 4	00:00	24:00	Regular	🗆 MD	🗌 Alarm	MD&Alarm
Fime Period 5	00:00	24:00	Regular	🗆 MD	🗌 Alarm	MD&Alarm
Time Period 6	00:00	24:00	Regular	🗆 MD	🗌 Alarm	MD&Alarm
	unday 🗌 Mond	lay 🗌 Tuesday	Wednesday] Thursda	y 🗌 Friday	Saturday
Holiday						
		Save	Cancel			



	×
All	
Channel 1	Channel 2
Channel 3	Channel 4
Save	Cancel
Save	Cancer

Figure 5-83

Parameter	Function
Channel	Please select a channel from the dropdown list.
Pre-record	Please input pre-record time here. The value ranges from 0 to 30.
Redundancy	Check the box here to enable redundancy function. Please note this function is null if there is only one HDD.
Snapshot	Check the box here to enable snapshot function.
Holiday	Check the box here to enable holiday function.
Setup (Sunday to Saturday)	Click the Setup button, you can set record period. See Figure 5-82. There are six periods in one day. If you do not check the date at the bottom of the interface, current setup is for today only. Please click Save button and then exit.
Setup (Holiday)	Click the Setup button, you can set record period. See Figure 5-82. There are six periods in one day. If you check Holiday box, current channel shall record as your holiday setup here.
Сору	Copy function allows you to copy one channel setup to another. After setting in channel, click Copy button, you can go to interface Figure 5-83. You can see current channel name is grey such as channel 1. Now you can select the channel you wan to paste such as channel 5/6/7. If you wan to save current setup of channel 1 to all channels, you can click the first box "ALL". Click the OK button to save current copy setup. Click the OK button in the Encode interface, the copy function succeeded.

5.8.4.1.2 Schedule snapshot

The schedule snapshot interface is shown as below. See Figure 5-84.




Figure 5-84

For detailed operation information, please refer to chapter 5.8.4.1.1. 5.8.4.2 HDD Manage

The interface is shown as in Figure 5-85. Here you can see HDD information. You can also operate the read-only, read-write, redundancy (if there are more than on HDD) and format operation.

Device Name	HDD Operation	Туре	Status	Free Space/Total Space	Start Time/End Time	
SATA-1	Set as read-write HDD	Read-Write	Normal	200.13GB / 232.79GB	2014-07-25 15:24:47 / 2014-08-21 16:39:41	

Figure 5-85

5.8.4.3 Manual Record

The interface is shown as in Figure 5-86.

Record																	
Main Stream	All	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16
Auto	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲
Manual	\odot	$^{\odot}$	\odot	\odot	\odot	\odot	\odot	\odot	\odot								
Stop	\odot	$^{\odot}$	\odot	\odot	\odot	\odot	\odot	\odot	\odot								
Sub Stream																	
Auto	\odot	$^{\odot}$	\odot	\odot	$^{\odot}$	\odot	\odot	\odot	\odot								
Manual	\odot	\odot	\odot	\odot	\odot	\odot	\odot	\odot									
Stop	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲
Snapshot																	
Open	\odot	\odot	\odot	\odot	\odot	\odot	\odot	\odot									
Stop	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲	۲
					_		_										
		-	Sav	e			Re	fresh									

Figure 5-86

Parameter	Function
Channel	Here you can view channel number. The number displayed here is the max channel amount of your device.
Status	There are three statuses: schedule, manual and stop.
Schedule	System enables auto record function as you set in record schedule setup (general, motion detect and alarm).

Manual	It has the highest priority.
	Enable corresponding channel to record no matter what period
	applied in the record setup.
Stop	Stop current channel record no matter what period applied in the
	record setup.
Start all/	Check the corresponding All button, you can enable or disable all
stop all	channels record.

5.8.5 Setting

5.8.5.1 General

The general interface includes general, date/time and holiday setup.

5.8.5.1.1 General

The general interface is shown as in Figure 5-87.

General	Date&Time	Holiday	
Device Name	HCVR		
Device No.	8		
Language	ENGLISH	•	
Video Standard	PAL	•	
HDD Full	Overwrite	•	
Pack Mode	Time Length	▼ 60	min.
Auto Logout	10	min. (0-60)	
Startup Wizard			
Navigation Bar			
IPC Time Sync	24	h	
	Save	Refresh Default	

Figure 5-87

Parameter	Function
Device ID	It is to set device name.
Device No.	It is device channel number.
Language	You can select the language from the dropdown list.
	Please note the device needs to reboot to get the modification activated.
Video Standard	This is to display video standard such as PAL.

HDD full	Here is for you to select working mode when hard disk is full. There are two options: stop recording or rewrite. If current working HDD is overwritten or the current HDD is full while the next HDD is no empty, then system stops recording, If the current HDD is full and then next HDD is not empty, then system overwrites the previous files.
Pack duration	Here is for you to specify record duration. The value ranges from 1 to 120 minutes. Default value is 60 minutes.

5.8.5.1.2 Date and time

The date and time interface is shown as in Figure 5-88.

General	Date&Time Holiday	
Date Format	YYYY MM DD	
Time Format	24-HOUR 💌	
Date Separator	-	
Time Zone	GMT+08:00	
System Time	2016 - 01 - 12 17 : 13 : 50 Sync PC	
DST		
DST Type	O Date O Week	
Begin Time	2000 - 01 - 01 00 : 00	
End Time	2000 - 01 - 01 00 : 00	
NTP		
Server	time.windows.com Manual Update	
Port	123 (1~65535)	
Interval	60 min. (0~65535)	
	Save Refresh Default	

Figure 5-88

Parameter	Function
Date format	Here you can select date format from the dropdown list.
Time Format	There are two options: 24-H and 12-H.
Time zone	The time zone of the device.
System time	It is to set system time. It becomes valid after you set.
Sync PC	You can click this button to save the system time as your PC current time.

DST	Here you can set day night save time begin time and end time. You can set according to the date format or according to the week format.
NTP	You can check the box to enable NTP function.
NTP server	You can set the time server address.
Port	It is to set the time server port.
Interval	It is to set the sync periods between the device and the time server.

5.8.5.1.3 Holiday Setup

Holiday setup interface is shown as in Figure 5-89.

Here you can click Add box to add a new holiday and then click Save button to save.

	General	Date&Time	Holiday					
							Add	
	No.	Status	Holiday Name	Date	Period	Edit	Delete	
	1	Open 💌	national_day	8.21	1 day(s)	2	•	<u>^</u>
								>
[Save	Refresh						

Figure 5-89

5.8.5.2 Display

Display interface includes GUI, TV adjust, Tour and zero-channel encoding.

5.8.5.2.1 Display

Here you can set background color and transparency level. See Figure 5-90.

Display	Tour	Zero-Channel	
Resolution	1280*1024	•	
Transparency	⊡()———		
Image Original Rate			
Time Display			
Channel Display			
Preview Enhancement			
Video Matrix			
	Save	Refresh D	efault

Figure 5-90

Parameter	Function
Resolution	There are four options: $1920 \times 1080, 1280 \times 1024$ (default), $1280 \times 720, 1024 \times 768$. Please note the system needs to reboot to activate current setup.
Transparency	Here is for you to adjust transparency. The value ranges from 128 to 255.
Time title/channel title	Check the box here, you can view system time and channel number on the monitor video.
Image enhance	Check the box; you can optimize the margin of the preview video.

5.8.5.2.2TV Adjust

Note

This function is for some series product only.

It is to set TV output region. See Figure 5-91.

GUI	TV Adjust	Tour	Zero Channel	
		- 		
Top Margin	<u> </u>			
Bottom Margin	۵)	(+ 0		
Left Margin	⊡()	(+ 0		
Right Margin	⊡()			
Brightness	⊡()		
	Save	Refresh	Default	



5.8.5.2.3 Tour

The tour interface is shown as in Figure 5-92. Here you can set tour interval, split mode, motion detect tour and alarm tour mode.

Display	Tour	Zero Channel
Enable Tour		
Interval	5	Second (5-120)
Split	View 1	×
	4 🔽 Channel G	roup 🛆 🛨
	1 🗹 1	
	2 🗹 2	*
	3 🗹 3	*
	4 🗹 4	
	<	
Motion Tour Type	View 1	▼
Alarm Tour Type	View 1	~
	Save	Refresh Default

Figure 5-92

Parameter	Function	
Enable tour	Check the box here to enable tour function.	
Interval	Here is for you to adjust transparency. The value ranges from 5 to 120s. The default setup is 5s.	
Split	Here you can set window mode and channel group. System can support 1/4/8/9/16/25/36-window according to device channel amount.	
Motion tour/Alarm tour	Here you can set motion detect tour/alarm tour window mode. System supports 1/8-window now.	

5.8.5.2.4 Zero-channel Encoding

The interface is shown as in Figure 5-93.

Display	Tour	Zero Channel	
Enable			
Compression	H.264	~	
Resolution	D1	~	
Frame Rate	25	▼	
Bit Rate	1024	Kb/S	
	Save	Refresh Default	

Figure 5-93

Parameter	Function	
Enable	This function is disabled by default. Check the box here to enable	
	this function so that you can control the zero-channel encoding	
	function at the WEB.	
Compression	System default setup is H.264. You can set according to device	
	capability.	
Resolution	The resolution value may vary due to different device capabilities.	
	Please select from the dropdown list.	
Frame rate	The frame rate value may vary due to different device capabilities.	
	Please select from the dropdown list.	
Bit Rate	The default setup is 1024Kb/S. The bit rate value may vary due to	
	different device capabilities and frame rate setups. Please select	
	from the dropdown list.	

5.8.5.3 Video Matrix

The interface is shown as in Figure 5-94.

Here you can set video output channel and interval.

BNC	
Enable	
Interval	5 sec.(5-120)
Resolution	1280*720 💌
Window Split	View 1
	14 🔽 Channel Group 📥 🛨
	1 ☑ 1
	2 🔽 2 👘 😞
	3 🔽 3
	4 🗹 4
	5 🔽 5
	6 🗹 6 🗸
	Save Refresh Default

Figure 5-94

Parameter	Function
Enable	Check the box here to enable this function.
Interval	It is to set the interval from current channel group to the next channel group.
Window split	Support 1-window split only.
Delete	Select a channel group and then click 🔲 to delete it.
Up/Down	Click 🔊 or 💌 to adjust channel tour sequence.

Add channel group

Click ,you can see system pops up the following dialogue box. See Figure 5-95. Please select the channels and then click OK button.

Add Channel Group		×
1 2 3 4 5 6 7 8 9	9 10 11 12 13 14 15 16	
Save	Cancel	

Figure 5-95

Delete channel group

Select a channel group and then click ,you can delete it.

Modify channel group

Select a channel group and then double click, you can see the following interface. See Figure 5-96. You can change the setup and then click OK button.

Mod	dify	Cha	nnel	Gro	up											×
1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	
						4	Sa	ve			Ca	ncel				



Adjust channel group sequence.

Click	*	or	

to change channel sequence.

5.8.5.4 RS232

The RS232 interface is shown as in Figure 5-97.

R\$232			
Function	Console	~	
Baud Rate	115200	~	
Data Bit	8	~	
Stop Bit	1	~	
Parity	None	~	
	Save	Refresh	Default

Figure 5-97

Parameter	Function
Protocol	Select the corresponding dome protocol. Default setup is console.
Baud Rate	Select the baud rate. Default setup is 115200.
Data Bit	The value ranges from 5 to 8.
	Default setup is 8.
Stop bit	There are two options: 1/2. Default setup is 1.
Parity	There are five options: none/odd/even/space/mark.

Parameter	Function
	Default setup is none.

5.8.5.5 PTZ

The PTZ interface is shown as in Figure 5-98 and Figure 5-99.

Before setup, please check the following connections are right:

- PTZ and decoder connection is right. Decoder address setup is right.
- Decoder A (B) line connects with DVR A (B) line.

Click Save button after you complete setup, you can go back to the monitor interface to control speed dome.

PTZ					
Observat					
Channel	1	-			
PTZ Type	Local	Ψ			
Control Mode	HDCVI	▼			
Protocol	HDCVI3.0	-			
Address	1				
Baud Rate	9600	•			
Data Bit	8	•			
Stop Bit	1	•			
Parity	None	•			
	Сору	Save	Refresh	Default	

Figure 5-98

PTZ				
Channel	4	•		
PTZ Type	Remote	~		
	Сору	Save	Refresh	Default

Figure 5-99

Parameter	Function
Channel	Select speed dome connected channel.
PTZ type	There are two types: local/remote. Please select local mode if you are connect RS485 cable to connect to the Speed dome (PTZ). Please select remote mode if you are connecting to the network PTZ camera.

Parameter	Function
Control	You can select control mode from the dropdown list. There are two
mode	options: Serial/HDCVI. For HDCVI series product, please select
	HDCVI. The control signal is sent to the PTZ via the coaxial cable. For
	the serial mode, the control signal is sent to the PTZ via the RS485
	port.
Protocol	Please select protocol from the dropdown list.
	If the control mode is HDCVI, please select HDCVI protocol. The
	default setup is HDCVI3.0.
Address	Set corresponding dome address. Default value is 1. Please note
	your setup here shall comply with your dome address; otherwise
	you can not control the speed dome.
Baud Rate	Select the dome baud rate. Default setup is 9600.
Data Bit	Default setup is 8. Please set according to the speed dome dial switch setup.
Stop bit	Default setup is 1. Please set according to the speed dome dial switch
	setup.
Parity	Default setup is none. Please set according to the speed dome dial switch setup.

5.8.5.6 ATM/POS

The ATM/POS function is for financial areas. It includes Sniffer, information analysis and title overlay function. The Sniffer mode includes COM and network.

5.8.5.6.1 COM Type

The COM interface is shown as below. See Figure 5-100.

- Protocol: Please select from the dropdown list according to your actual situation.
- Overlay channel: Please select the channel you want to overlay the card number.
- Overlay mode: There are two options: preview and encode. Preview means overlay the card number in the local monitor video. Encode means overlay the card number in the record file.
- Overlay Position: Here you can select the proper overlay position from the dropdown list.

СОМ	Net	
Current Sniffer Mod	le is COM	
Protocol	POS	~
Overlay Channel	123	
Overlay Mode	Preview V Encode	
Overlay Position	Top Left	~
Save	Refresh	

Figure 5-100

5.8.5.6.2 Network Type

The network type interface is shown as below. See Figure 5-101.

Here we take the ATM/POS protocol to continue.

There are two types: with or without the protocol according to client's requirements.

With the protocol

For ATM/POS with the protocol, you just need to set the source IP, destination IP (sometimes you need to input corresponding port number).

Current Sniffer Mode is	COM				
Protocol	ATM/POS]			
Overlay Mode	Preview V Encode				
Overlay Position	Top Left 💌]			
Sniffer Group	Sniffer Group1				
Source IP Address	0.0.0.0	Source Port	0		
Destination IP Address	0.0.0.0	Destination Port	0		
Overlay Channel	1 2 3				
	Start Position	Length	Value		
Key Words1	1	0		÷	^
Key Words2	1	0			
Key Words3	1	0		÷	
Key Words4	1	0		÷	
Key Words5	1	0		@	
Key Words6	1	0		0	

Figure 5-101

Without the protocol

For the ATM/POS without the protocol, the interface is shown as in Figure 5-102.

Source IP refers to host IP address that sends out information (usually it is the device host.)

Destination IP refers to other systems that receive information.

Usually you do not need to set source port and target port.

There are total four groups IP. The record channel applies to one group (optional) only. Six frame ID groups verification can guarantee information validity and legal.

COM	Net				
Current Sniffer Mod	le is COM				
Protocol	POS	~			
Overlay Channel	1 2 3				
Overlay Mode	Preview V End	ode			
Overlay Position	Top Left	~			
Source IP Address	0.0.0	. 0 Source	Port	0	
Destination IP Add	ress 0 . 0 . 0	. 0 Destina	ation Port	0	
Save	Refresh				

Figure 5-102

5.8.5.7 Voice

The audio function is to manage audio files and set schedule play function. It is to realize audio broadcast activation function.

5.8.5.7.1 File List

Here you can add audio file, or delete audio file. See Figure 5-103.

File List	Schedule		
File List			
No.	File Name	File Size(Byte)	Delete
1	When You Know.mp3	3953561	ا ا
			×

Figure 5-103

Click Add button, you can add audio file and import the audio file via the local computer. See Figure 5-104.

Upload					? 🔀
🞯 Desktop		~	00	۳ 📁	
My Documen My Network I Adobe Acrob	ts Places lat 7.0 Professional ice Access 2003 fice PowerPoint 2003				
<					
File <u>n</u> ame: Files of tupe:	All Files (* *)			~	<u>O</u> pen Cancel
	My Compute My Compute My Network I Adobe Acrob Microsoft Off Microsoft Off			Image: Computer Image: Computer My Computer My Documents Image: My Network Places Image: Computer Image: Computer Microsoft Office Access 2003 Image: Computer Image: Computer Image: Computer Image: Computer	Image: Second

Figure 5-104

5.8.5.7.2 Schedule

It is to set schedule broadcast function. You can play the different audio files in the specified periods.

From main menu->Setup->System->Voice->.Schedule, you can see the following interface. See Figure 5-105.

Enable	00 : 00]_	24 : 00	None	~	60	min.	0	Mic 💌	
Enable	00 : 00]_	24 : 00	None	~	60	min.	0	Mic	
Enable	00 : 00]-	24 : 00	None	~	60	min.	0	Mic	
Enable	00 : 00]-	24 : 00	None	~	60	min.	0	Mic 💌	
Enable	00 : 00]-	24 : 00	None	~	60	min.	0	Mic 💌	
Enable	00 : 00]-	24 : 00	None	~	60	min.	0	Mic 💌	

Figure 5-105

Parameter	Function
Period	There are six periods. Check the box to enable current setup.
Repeat	It is to set audio file repeat times in the specified period.
Interval	It is the audio file repeated interval in the specified period.

Parameter	Function
Output port	There are two options: MIC (default)/audio. When reuse the MIC port and bidirectional talk port, the bidirectional port has the higher priority. Please note some series product does not support audio function.

Note

- The audio file end time depends on the audio file size and the interval setup.
- Priority: Bidirectional talk>Event trigger alarm>Trial listening>Audio schedule broadcast.

5.8.5.8 Account

Note:

- For the character in the following user name or the user group name, system max supports 6-digits. The space in the front or at the end of the string is null. The valid string includes: character, number, and underline.
- The user amount default setup is 64 and the group amount default setup is 20. The factory default setup includes two levels: user and admin. You can set the corresponding group and then set the rights for the respective user in the specified groups.
- User management adopts group/user modes. The user name and the group name shall be unique. One user shall be included in only one group.
 5.8.5.8.1 User name

In this interface you can add/remove user and modify user name. See Figure 5-106.

SN	User Name	Group Name	User MAC	Memo	Modify	Delete
1	888888	admin		admin(888) 's account	<u>2</u>	•
2	admin	admin		admin 's account	1	•
3	default	user		default account	2	•
uthority						
uthority	Мапиа	al Control	File Backup	Storage	PTZ Control	
	Manua Syster		File Backup Clear Log	Storage Default&Update	PTZ Control System	

Figure 5-106

Add user: It is to add a name to group and set the user rights. See Figure 5-107.

There are three default users: admin (password: admin)/888888(password: 888888) and hidden user "default".

Hidden user "default" is for system interior use only and can not be deleted. When there is no login user, hidden user "default" automatically login. You can set some rights such as monitor for this user so that you can view some channel view without login.

Here you can input the user name and password and then select one group for current user.

Please note the user rights shall not exceed the group right setup.

For convenient setup, please make sure the general user has the lower rights setup than the admin.

dd User				
User Name	1			
Reusable				
Password				
Confirm Pass	word			
Group	admin	~		
User MAC	1	1. 1. 1.		
Memo				
Authority				
System Manag	ger Playb	ack N	Ionitor	
PAII Account PTZ Control Color Setting CAMERA	☑System ☑System Info ☑Storage ☑Clear Log		Default&Update File Backup Network	
	Save	Cancel		8

Figure 5-107

Modify user

It is to modify the user property, belonging group, password and rights. See Figure 5-108. **Modify password**

It is to modify the user password. You need to input the old password and then input the new password twice to confirm the new setup. Please click the OK button to save.

Please note, the password ranges from 1-digit to 6-digit. It shall include the number only. For the user of the account rights, he can modify the password of other users.

/lodify User				×
User Name	uu	~		
User Name	uu			
Reusable				
Memo				
Group	admin	~		
User MAC	1	3 3 3	:	
Modify Passw	ord			
Authority				
System Manag	ger Playb	ack N	Ionitor	
	System	Disconnect	Default&Update	
PTZ Control	System Info	Manual Control	File Backup	
Color Setting	✓Storage	Event	Network	
CAMERA	Clear Log	Shutdown		
				3
	Save	Cancel		

Figure 5-108

5.8.5.8.2 Group

The group management interface can add/remove group, modify group password and etc. The interface is shown as in Figure 5-109.

	·			
Group				
Group Name		Memo	Modify	Delete
admin		administrator group	<u>e</u>	•
user		user group	2	0
		01		
Manual Control	File Backup	Storade		
Manual Control Account	File Backup System Info	Storage Clear Log		
	Group Name admin	Group Name admin	Group Name Memo admin administrator group	Group Name Memo Modify admin administrator group 🖉

Figure 5-109

Add group: It is to add group and set its corresponding rights. See Figure 5-110. Please input the group name and then check the box to select the corresponding rights. It

includes: shutdown/reboot device, live view, record control, PTZ control and etc.

dd Group				1
Group Name Memo Authority				
System Manag	ger Playt	ack N	Ionitor	
☑AII ☑Account ☑PTZ Control ☑Color Setting ☑CAMERA	System System Info Storage Clear Log	Disconnect Manual Control Event Shutdown	 ✓ Default&Update ✓ File Backup ✓ Network 	0
	Save	Cancel		

Figure 5-110

Modify group

Click the modify group button, you can see an interface is shown as in Figure 5-111. Here you can modify group information such as remarks and rights.

odify Group				E
Group Name	user	~		
Group Name	user			
Memo	user group	r in the second s		
Authority				
System Manag	jer Playb	ack	Monitor	
All Account PTZ Control Color Setting CAMERA	System System Info Storage Clear Log	Disconnect Manual Control Event Shutdown	Default&Update	
	Save	Cancel		V

Figure 5-111

5.8.5.9 Auto maintain

The auto maintain interface is shown as in Figure 5-112.

Here you can select auto reboot and auto delete old files interval from the dropdown list. If you want to use the auto delete old files function, you need to set the file period. Click Manual reboot button, you can restart device manually.

Auto Maintain	
Auto Reboot	Sunday 02 : 00
Auto Delete Old Files	Customized 🖌 21 Days ago
	Manual Reboot
	Save Refresh
· · · ·	

Figure 5-112

5.8.5.10 Import/Export

The interface is shown as in Figure 5-113.

Import&Export		
Config Import	Config Export	

Figure 5-113

Please refer to the following sheet for detailed information.

Parameter	Function
Import	It is to import the local setup files to the system.
Export	It is to export the corresponding WEB setup to your local PC.

5.8.5.11 Default

The default setup interface is shown as in Figure 5-114.

Here you can select Channel/Network/Event/Storage/System. Or you can check the All box to select all items.

Default			
Select All			
	✓ NETWORK	V EVENT	
STORAGE	SYSTEM		
Default	Factory Default		

Figure 5-114

5.8.5.12 Upgrade

The upgrade interface is shown as in Figure 5-115.

Please select the upgrade file and then click the update button to begin update. Please note the file name shall be as *.bin. During the upgrade process, do not unplug the power cable, network cable, or shutdown the device.

Important

Improper upgrade program may result in device malfunction!

Upgrade	
Select Firmware File	e Browse Upgrade

Figure 5-115


5.9 Information

5.9.1 Version

The version interface is shown as in Figure 5-116.

Here you can view record channel, alarm input/output information, software version, release date and etc. Please note the following information is for reference only.

Version	
Record Channel:	4
Alarm In:	4
Alarm Out:	3
SN:	YPA4HQ041W00030
System Version:	3.200.0001.8, Build Date: 2014-08-13



5.9.2 Log

Here you can view system log. See Figure 5-117.

Log Start Time	2014 - 08 - 21	00 : 00 : 00 End Time 2014 -	08 - 22 00 : 00 : 00
Type	All		
	lo.	Time	Event
	1	2014-08-21 11:38:36	Shut down
	2	2014-08-21 11:38:36	Boot up
	3	2014-08-21 11:38:36	Video Loss
	4	2014-08-21 11:38:36	Video Loss
	5	2014-08-21 11:38:36	Video Loss
	6	2014-08-21 11:38:36	Video Loss
	7	2014-08-21 11:38:36	HDD
	В	2014-08-21 11:38:56	User logged in
iystem Log Info			
Backup			► ► 1 / 1 ► ► Go To 1 Clear

Figure 5-117

Please refer to the following sheet for log parameter information.

Parameter	Function
Туре	Log types include: system operation, configuration operation, data
	operation, event operation, record operation, user management, log
	clear.
Start time	Set the start time of the requested log.
End time	Set the end time of the requested log.
Search	You can select log type from the drop down list and then click search
	button to view the list.
	You can click the stop button to terminate current search operation.
Detailed information	You can select one item to view the detailed information.
Clear	You can click this button to delete all displayed log files. Please note system does not support clear by type.
Backup	You can click this button to backup log files to current PC.

Note

- If there is no HDD, system max supports 1024 logs.
- If you have connected to the unformatted HDD, system max supports 5000 logs.
- If you have connected to the formatted HDD, system max supports 500,000 logs.
- System operation logs are saved in system memory. Other types of logs are saved in the HDD. If there is no HDD, other types of logs are saved in the system memory too.
- The logs are safe when you format the HDD. But the logs may become loss once you removed the HDD.

5.9.3 Online User

The online user interface is shown as in Figure 5-118.

	User Name	Group Name	IP Address	User Login Time	
1	admin	admin	10.15.9.152	2013-10-24 04:31:33 PM	
2	admin	admin	10.15.9.152	2013-10-24 04:21:12 PM	
3	admin	admin	10.15.6.145	2013-10-24 04:50:01 PM	

Figure 5-118

5.9.4 HDD

The HDD interface is shown as in Figure 5-119. Here you can view HDD information.

Device Name	Status	Free Space/Total Space	S.M.A.R.T
SATA-1	Normal	1.64TB/1.81TB	Normal

Figure 5-119

5.10 Playback

Click Playback button, you can see an interface is shown as in Figure 5-120.

WEB SERVICE PREVIEW PLAYBACK	ALARM SETUP INFO LOGOUT	
	®,œ×	€.cs× < 1 2016 >
((Stun Mon Tue Wed Thu Fri Sat 3 4 5 6 7 8 9 10 11 12 10 14 15 16 17 18 10 20 21 22 23 24 26 20 27 20 29 30 31 11 12 10 10 10 10 10 10 10 11 10 20 10 10 10 10 20 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 10 1
	@.t#×	6,0ix 1 ▼ 2 ▼
6	6	3 • 4 •
		File List
(○▶○◎◎∝ ━•─		
Stop	🖬 Sync 😰 All 😰 Regular 📰 😰 MD 🚽 😰 Alarm 📕 😰 Gard 🖬	(q.)q)

Figure 5-120

5.10.1 Search Record

Please set record type, record date, window display mode and channel name.

Select Date

You can click the date on the right pane to select the date. The green highlighted date is system current date and the blue highlighted date means it has record files.

• Window Split

Select window split mode. Click 🔤 to display in full screen. Click ESC button to exit.

See Figure 5-121.



Figure 5-121

Customized playback

Click , you can see the following interface. See Figure 5-122.




Figure 5-122

Now you can select one or more channel(s) and then click Search to search record(s).

System supports one or more channels. The window split mode can auto adjust according to the channel amount. System max supports 16-split.

Click button to select all channels at the same time.

Click

, system begins playback.

Select Channel

 $1 \sim n(n \text{ depends on your product channel amount})$ means main stream and A1 \sim An ((n depends on your product channel amount)) means sub stream.

• Select Record Type

Check the corresponding box to select record type. See Figure 5-123.



Figure 5-123

5.10.2 File List

Click File list button, you can see the corresponding file(s) in the list. See Figure 5-124.



Figure 5-124

5.10.3 Playback

Select a file you want to play and then click Play button, system can begin playback. You can select to playback in full-screen. Please note for one channel, system can not playback and download at the same time. You can use the playback control bar to implement various operations such as play, pause, stop, slow play, fast play and etc.

5.10.4 Download

Select the file(s) you want to download and then click download button, you can see an interface shown as in Figure 5-125. The Download button becomes Stop button and there is a process bar for your reference. Please go to you default file saved path to view the files.

C		00	:	00	:	00		C	ł
	1		2			3		4	
	Sta	rt Ti	me	•		Туре			
✓	08	:34:	59		ľ	R			
✓	08	:40:	03			R			
M	◀ 1/	1 🕨	Þ	Ju	mp	То	1	₽.	
En	art Ti d Tir e Siz	ne:							
	<u>v</u>	Mor	e			⊻ s ←	top(2 Ba	_)

Figure 5-125

5.10.5 Load more

It is for you to search record or picture. You can select record channel, record type and record time to download. Or you can use watermark function to verify file.

5.10.5.1 Download By File

Select channel, record type, bit stream type and then input start time and end time. Click Search button, the download by file interface is shown as in Figure 5-126.

Download by Fil	e Download by	Time Wate	ermark					
Channel Type Bit Stream Type	All All All Records Main Sub	Start Time End Time	2014 - 02 - 14 2014 - 02 - 17	00 : 00 : 00	Search			
	No.	File Size	Start Time	End Time	File Type	Bit Stream Type	Channel	
	1	2048KB	2014-02-17 08:34:59	2014-02-17 08:39:15	Regular	Main Stream	1	<u>~</u>
	2	8316KB	2014-02-17 08:40:03	2014-02-17 08:59:08	Regular	Main Stream	1	
	3	384KB	2014-02-17 08:34:59	2014-02-17 08:39:15	Regular	Main Stream	2	
	4	8585KB	2014-02-17 08:40:03	2014-02-17 08:59:08	Regular	Main Stream	2	
	5	2048KB	2014-02-17 08:34:59	2014-02-17 08:39:15	Regular	Main Stream	3	
	6	8623KB	2014-02-17 08:40:03	2014-02-17 08:59:08	Regular	Main Stream	3	
	7	384KB	2014-02-17 08:34:59	2014-02-17 08:39:15	Regular	Main Stream	4	
	8	8546KB	2014-02-17 08:40:03	2014-02-17 08:59:08	Regular	Main Stream	4	~
Download to Lo	cal Download to	USB				M 4 1/	1 🕨 🔰 Jump To 🚹 🚺	
Back								

Check the file(s) you want to download and there are two options for you to save the file(s).

• Download to local

Click Download to local, system pops up the following interface for you to set record format and saved path. See Figure 5-127.

Record Format	DAV	~	
Save Path	C:\RecordDownload\		Browse
Saro - Sar	O. Weedrabownioad		0.04/00

Figure 5-127

You can click OK to download and view the download process. After the download operation, you can see corresponding dialog box.

Download to USB

Connect the corresponding p peripheral device, and then click Download to USB button, you can see the following interface. See Figure 5-128.

ype.	All All Records	Start Time End Time	2014 - 02 - 14 2014 - 02 - 17	00 : 00 : 00	Search		
Rt Stream Type	Main Sub 💌						
	No.	File Size	Start Time	End Time	File Type	Bit Stream Type	Channel
	1	2048KB	2014-02-17 08:34:59	2014-02-17 08:39:15	Regular	Main Stream	1
	2	8316KB	2014-02-17 08:40:03	2014-02-17 08:59:08	Regular	Main Stream	1
	3	384KB	2014-02-17 08:34:59	2014-02-17 08:39:15	Regular	Main Stream	2
	4	0585KD	2014-02-17 08:40:03	2014-02-17 08:59:08	Regular	Main Stream	2
	5	2048KB	2014-02-17 08:34:59	2014-02-17 08:39:15	Regular	Main Stream	3
	6	8623KB	2014-02-17 08:40:03	2014-02-17 08:59:08	Regular	Main Stream	з
	7	384KB	2014-02-17 08:34:59	2014-02-17 08:39:15	Regular	Main Stream	4
		THE LOUT	2014-02-17 08:40:03	2014-02-17 08:59:08	Regular	Main Stream	
Download to Lo	8 cal Download to	8545KB	101402-11-0040-03	2014-02-17 00.58.00	regoar		1 🕨 🖬 Jump To 🚺
Download to Lo lackup device so Start Backup	db1(USB DISK) 💌	Search	Backup type DAV	×		H 4 17	
Download to Lo Backup device so Start Backup Nim	db1(USB DISK) 💌	Search Dadwp t pe	Bachup type DAV	V Free Space(KD)	Tetal Space(KB)	i4 4 1/ Dir	edary
Download to Lo Nackup device so Start Backup	db1(USB DISK) 💌	Search	Backup type DAV	×		i4 4 1/ Dir	

Figure 5-128

Select Backup device and backup type first and then click Start backup button.

After the download operation, you can see corresponding dialogue box.

5.10.5.2 Download by Time

Select channel, bit stream type, start time and end time.

Click Download to Local button, you can see download by time interface is shown as in Figure 5-129.

Download by File Download by Time Watermark
Channel 1 M Start Time 2014 - 02 - 14 00 : 00 : 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00 00
Download to Local
Record Format DAV Save Path C:\RecordDownload\ Browse
OK Cancel
Back
Back

Figure 5-129

Set record format and saved path, you can click OK to download and view the download process. After the download operation, you can see corresponding dialog box.

5.10.5.3 Watermark

Watermark interface is shown as In Figure 5-130. Please select a file and then click Verify button to see the file has been tampered with or not

Download by File	Download by Time Watermark		
Local File			
C:\record\root\Centr	e platform	Verify	
Watermark Info			
Watermark Revised In	fo		
No.	Malfunction type Normal	Watermark Time	
Back			

Figure 5-130

5.11 Face Search

On the main interface, click Face search button, you can see an interface shown as below. See Figure 5-131.




Figure 5-131

Please refer to the following sheet for detailed information.

SN	Name	Function
1	Display	• It is to display human face detection file list. The latest file is at the
	pan	top. \
		• Click Export, you can export the selected file to the USB device.
		There are two types: image/record.
		\diamond Image: Export the recognized human face image.
		\diamond Record: Export the record file before and after 10 seconds
		when the DVR recognizes the human face.
2	Playback	Play the searched record file or image. Double click to playback in full
	pane	screen.
3	Search	Set date, start time and end time, click Search button, you can view the
	pane	corresponding file list.

5.12 Alarm

Click alarm function, you can see an interface is shown as Figure 5-132.

Here you can set device alarm type and alarm sound setup (Please make sure you have enabled audio function of corresponding alarm events.).

WEB service	PREVIEW	PLAYBACK	ALARM	SETUP	INFO	LOGOUT	1		V
Alarm Type Motion Detect Tampering Video Loss Intelligentized Detect Operation Message Alarm Sound Play Alarm Sound Sound Path	External Alarm HDD Error HDD Full		No.	SEIUP	Time		Alarm Type	Channel	
									-

Figure 5-132

Please refer to the following sheet for detailed information.

Туре	Parameter	Function		
Alarm	Video loss	System alarms when video loss occurs.		
Туре	Motion detection	System alarms when motion detection alarm		
		occurs.		
	Tampering	System alarms when camera is viciously masking.		
	Disk full	System alarms when disk is full.		
Disk error System alarms when disk error occ		System alarms when disk error occurs.		
	External alarm	Alarm input device sends out alarm.		
Operation	Prompt	Check the box here, system can automatically pops		
		up an alarm icon on the Alarm button in the main		
		interface when there is an alarm.		
Alarm	Play alarm	System sends out alarm sound when an alarm		
Sound	sound	occurs. You can specify as you wish.		
	Sound path	Here you can specify alarm sound file.		

5.13 Log out

Click log out button, system goes back to log in interface. See Figure 5-133. You need to input user name and password to login again.




Figure 5-133

5.14 Un-install Web Control

You can use web un-install tool "uninstall web.bat" to un-install web control.

Please note, before you un-installation, please close all web pages, otherwise the un-installation might result in error.

6 Professional Surveillance System

Besides Web, you can use our Smart PSS to login the device. For detailed information, please refer to *Smart PSS user's manual.*

7 FAQ

1. DVR can not boot up properly.

There are following possibilities:

- Input power is not correct.
- Power connection is not correct.
- Power switch button is damaged.
- Program upgrade is wrong.
- HDD malfunction or something wrong with HDD ribbon.
- Seagate DB35.1, DB35.2, SV35 or Maxtor 17-g has compatibility problem. Please upgrade to the latest version to solve this problem.
- Front panel error.
- Main board is damaged.

2. DVR often automatically shuts down or stops running.

There are following possibilities:

- Input voltage is not stable or it is too low.
- HDD malfunction or something wrong wit the ribbon.
- Button power is not enough.
- Front video signal is not stable.
- Working environment is too harsh, too much dust.
- Hardware malfunction.

3. System can not detect hard disk.

There are following possibilities:

- HDD is broken.
- HDD ribbon is damaged.
- HDD cable connection is loose.
- Main board SATA port is broken.

4. There is no video output whether it is one-channel, multiple-channel or all-channel output.

There are following possibilities:

- Program is not compatible. Please upgrade to the latest version.
- Brightness is 0. Please restore factory default setup.
- There is no video input signal or it is too weak.
- Check privacy mask setup or your screen saver.
- DVR hardware malfunctions.

5. Real-time video color is distorted.

There are following possibilities:

• When using BNC output, NTSC and PAL setup is not correct. The real-time video becomes black and white.

- DVR and monitor resistance is not compatible.
- Video transmission is too long or degrading is too huge.
- DVR color or brightness setup is not correct.

6. Can not search local records.

There are following possibilities:

- HDD ribbon is damaged.
- HDD is broken.
- Upgraded program is not compatible.
- The recorded file has been overwritten.
- Record function has been disabled.

7. Video is distorted when searching local records.

There are following possibilities:

- Video quality setup is too low.
- Program read error, bit data is too small. There is mosaic in the full screen. Please restart the DVR to solve this problem.
- HDD data ribbon error.
- HDD malfunction.
- DVR hardware malfunctions.

8. There is no audio when monitor.

There are following possibilities:

- It is not a power picker.
- It is not a power acoustics.
- Audio cable is damaged.
- DVR hardware malfunctions.

9. There is audio when monitor but there is no audio when system playback.

There are following possibilities:

- Setup is not correct. Please enable audio function
- Corresponding channel has no video input. Playback is not continuous when the screen is blue.

10. Time display is not correct.

There are following possibilities:

- Setup is not correct
- Battery contact is not correct or voltage is too low.
- Crystal is broken.

11. DVR can not control PTZ.

There are following possibilities:

• Front panel PTZ error

- PTZ decoder setup, connection or installation is not correct.
- Cable connection is not correct.
- PTZ setup is not correct.
- PTZ decoder and DVR protocol is not compatible.
- PTZ decoder and DVR address is not compatible.
- When there are several decoders, please add 120 Ohm between the PTZ decoder A/B cables furthest end to delete the reverberation or impedance matching. Otherwise the PTZ control is not stable.
- The distance is too far.

12. Motion detection function does not work.

There are following possibilities:

- Period setup is not correct.
- Motion detection zone setup is not correct.
- Sensitivity is too low.
- For some versions, there is hardware limit.

13. Can not log in client-end or web.

There are following possibilities:

- For Windows 98 or Windows ME user, please update your system to Windows 2000 sp4. Or you can install client-end software of lower version. Please note right now, our DVR is not compatible with Windows VISTA control.
- ActiveX control has been disabled.
- No dx8.1 or higher. Please upgrade display card driver.
- Network connection error.
- Network setup error.
- Password or user name is invalid.
- Client-end is not compatible with DVR program.

14. There is only mosaic no video when preview or playback video file remotely.

There are following possibilities:

- Network fluency is not good.
- Client-end resources are limit.
- There is multiple-cast group setup in DVR. This mode can result in mosaic. Usually we do not recommend this mode.
- There is privacy mask or channel protection setup.
- Current user has no right to monitor.
- DVR local video output quality is not good.

15. Network connection is not stable.

There are following possibilities:

- Network is not stable.
- IP address conflict.

- MAC address conflict.
- PC or DVR network card is not good.

16. Burn error /USB back error.

There are following possibilities:

- Burner and DVR are in the same data cable.
- System uses too much CPU resources. Please stop record first and then begin backup.
- Data amount exceeds backup device capacity. It may result in burner error.
- Backup device is not compatible.
- Backup device is damaged.

17. Keyboard can not control DVR.

There are following possibilities:

- DVR serial port setup is not correct
- Address is not correct
- When there are several switchers, power supply is not enough.
- Transmission distance is too far.

18. Alarm signal can not been disarmed.

There are following possibilities:

- Alarm setup is not correct.
- Alarm output has been open manually.
- Input device error or connection is not correct.
- Some program versions may have this problem. Please upgrade your system.

19. Alarm function is null.

There are following possibilities:

- Alarm setup is not correct.
- Alarm cable connection is not correct.
- Alarm input signal is not correct.
- There are two loops connect to one alarm device.

20. Remote control does not work.

There are following possibilities:

- Remote control address is not correct.
- Distance is too far or control angle is too small.
- Remote control battery power is low.
- Remote control is damaged or DVR front panel is damaged.

21. Record storage period is not enough.

There are following possibilities:

- Camera quality is too low. Lens is dirty. Camera is installed against the light. Camera aperture setup is not correct.
- HDD capacity is not enough.
- HDD is damaged.

22. Can not playback the downloaded file.

There are following possibilities:

- There is no media player.
- No DXB8.1 or higher graphic acceleration software.
- There is no DivX503Bundle.exe control when you play the file transformed to AVI via media player.
- No DivX503Bundle.exe or ffdshow-2004 1012 .exe in Windows XP OS.

23. Forget local menu operation password or network password

Please contact your local service engineer or our sales person for help. We can guide you to solve this problem.

24. When I login via HTTPS, a dialogue says the certificate for this website is for other address.

Please follow chapter 5.8.2.16.1 to create server certificate.

25. When I login via HTTPS, a dialogue says the certificate is not trusted.

Please follow chapter 5.8.2.16.2 to download root certificate.

26. When I login via HTTPS, a dialogue says the certificate has expired or is not valid yet.

Please make sure your PC time is the same as the device time.

27. I connect the general analog camera to the device, there is no video output.

There are following possibilities:

- Check camera power supplying, data cable connection and etc.
- This series device does not support the analog camera of all brands. Please make sure the device supports general standard definition analog camera.

28. I connect the standard definition analog camera or the HDCVI camera to the device, there is no video output.

There are following possibilities:

- Check camera power supplying, or camera data cable connection.
- For the product supports analog standard definition camera/HD camera, you need to go to the main menu->Setting->Camera->Channel type to select corresponding channel type and then restart the DVR.

29. I can not connect to the IP channel.

There are following possibilities:

- Check the camera is online or not.
- Check IP channel setup is right or not (such as IP address, user name, password, connection protocol, port number.).
- The camera has set the whitelist (Only the specified devices can connect to the camera).

30. After I connected to the IP channel, there one-window output is OK, but there is no multiple-window output.

There are following possibilities:

- Check the sub stream of the camera has been enabled or not.
- Check the sub stream type of the camera is H.264 or not.
- Check the device supports camera sub stream resolution or not (such as 960H, D1, HD1 and etc.).

31. After I connected to the IP channel, there multiple-window output is OK, but there is no one-window output.

There are following possibilities:

- Check there is video from the IP channel or not. Please go to the main menu->info->System->BPS to view bit stream real-time information.
- Check the main stream of the camera has been enabled or not.
- Check the main stream type of the camera is H.264 or not.
- Check the device supports camera main stream resolution or not (such as 960H, D1, HD1 and etc.).
- Check camera network transmission has reached the threshold or not. Please check the online user of the camera.

32. After I connected to the IP channel, there is no video output in the one-window or the multiple-window mode. But I can see there is bit stream.

There are following possibilities:

- Check the main stream/sub stream type of the camera is H.264 or not.
- Check the device supports camera main stream/sub stream resolution or not (such as 1080P, 720P, 960H, D1, HD1 and etc.).
- Check the camera setup. Please make sure It supports the products of other manufacturers.

33. DDNS registration failed or can not access the device domain name.

There are following possibilities:

- Check the device is connected to the WAN. Please check the device has got the IP address if the PPPoE can dial. If there is a router, please check the router to make sure the device IP is online.
- Check the corresponding protocol of the DDNS is enabled. Check the DDNS function is OK or not.

• Check DNS setup is right or not. Default Google DNS server is 8.8.8.8, 8.8.5.5. You can use different DNS provided by your ISP.

34. I can not use the P2P function on my cell phone or the WEB.

There are following possibilities:

- Check the device P2P function is enabled or not. (Main menu->Setting->Network->P2P)
- Check the device is in the WAN or not.
- Check cell phone P2P login mode is right or not.
- It is the specified device P2P login port or not when you are using P2P client.
- Check user name or password is right or not.
- Check P2P SN is right or not. You can use the cell phone to scan the QR code on the device P2P interface (Main menu->Setting->Network->P2P), or you can use the version information of the WEB to confirm. (For some previous series products, the device SN is the main board SN, it may result in error.)

35. I connect the standard definition camera to the device, there is no video output.

There are following possibilities:

- Check the DVR supports standard definition signal or not. Only some series product supports analog standard definition signal, HDCVI signal input.
- Check channel type is right or not. For the product supports analog standard definition camera/HD camera, you need to go to the main menu->Setting->Camera->Channel type to select corresponding channel type (such as analog) and then restart the DVR. In this way, the DVR can recognize the analog standard definition.
- Check camera power supplying, or camera data cable connection.

36. I can not connect to the IP camera.

There are following possibilities:

- Check DVR supports IP channel or not. Only some series products support A/D switch function, it can switch analog channel to the IP channel to connect to the IP camera. From Setting->Camera->Channel Type, select the last channel to switch to the IP channel. Some series product products support IP channel extension, it supports N+N mode.
- Check the IPC and the DVR is connected or not. Please go to the main menu->Setting->Camera->Remote to search to view the IP camera is online or not. Or you can go to the main menu->Info->Network->Test, you can input IP camera IP address and then click the Test button to check you can connect to the IP camera or not.
- Check IP channel setup is right or not (such as IP address, manufacturer, port, user name, password, remote channel number and etc.).

Daily Maintenance

- Please use the brush to clean the board, socket connector and the chassis regularly.
- The device shall be soundly earthed in case there is audio/video disturbance. Keep the device away from the static voltage or induced voltage.
- Please unplug the power cable before you remove the audio/video signal cable, RS232 or RS485 cable.
- Do not connect the TV to the local video output port (VOUT). It may result in video output circuit.
- Always shut down the device properly. Please use the shutdown function in the menu, or you can press the power button in the front pane for at least three seconds to shut down the device. Otherwise it may result in HDD malfunction.
- Please make sure the device is away from the direct sunlight or other heating sources. Please keep the sound ventilation.
- Please check and maintain the device regularly.

Appendix A HDD Capacity Calculation

Calculate total capacity needed by each DVR according to video recording (video recording type and video file storage time).

Step 1: According to Formula (1) to calculate storage capacity q_i that is the capacity of each channel needed for each hour, unit Mbyte.

$$q_i = d_i \div 8 \times 3600 \div 1024 \tag{1}$$

In the formula: d_i means the bit rate, unit Kbit/s

Step 2: After video time requirement is confirmed, according to Formula (2) to calculate the storage capacity m_i , which is storage of each channel needed unit Mbyte.

$$m_i = q_i \times h_i \times D_i \tag{2}$$

In the formula:

 h_i means the recording time for each day (hour)

 D_i means number of days for which the video shall be

kept

Step 3: According to Formula (3) to calculate total capacity (accumulation) q_T that is needed for all channels in the DVR during **scheduled video recording**.

$$q_T = \sum_{i=1}^{c} m_i \tag{3}$$

In the formula: c means total number of channels in one DVR

Step 4: According to Formula (4) to calculate total capacity (accumulation) q_T that is needed for all channels in DVR during **alarm video recording (including motion detection)**.

$$q_T = \sum_{i=1}^{c} m_i \times a\% \tag{4}$$

In the formula: a% means alarm occurrence rate

You can refer to the following sheet for the file size in one hour per channel. (All the data listed below are for reference only.)

Bit stream size (max)	File size	Bit stream size (max)	File size
96K	42M	128K	56M
160K	70M	192K	84M
224K	98M	256K	112M
320K	140M	384K	168M

448K	196M	512K	225M
640K	281M	768K	337M
896K	393M	1024K	450M
1280K	562M	1536K	675M
1792K	787M	2048K	900M

Appendix B Compatible backup devices

Manu factor	Model	Capacity
Sandisk	Cruzer Micro	512M
Sandisk	Cruzer Micro	1G
Sandisk	Cruzer Micro	2G
Sandisk	Cruzer Freedom	256M
Sandisk	Cruzer Freedom	512M
Sandisk	Cruzer Freedom	1G
Sandisk	Cruzer Freedom	2G
Kingston	DataTraveler II	1G
Kingston	DataTraveler II	2G
Kingston	DataTraveler	1G
Kingston	DataTraveler	2G
Maxell	USB Flash Stick	128M
Maxell	USB Flash Stick	256M
Maxell	USB Flash Stick	512M
Maxell	USB Flash Stick	1G
Maxell	USB Flash Stick	2G
Kingax	Super Stick	128M
Kingax	Super Stick	256M
Kingax	Super Stick	512M
Kingax	Super Stick	1G
Kingax	Super Stick	2G
Netac	U210	128M
Netac	U210	256M
Netac	U210	512M
Netac	U210	1G
Netac	U210	2G
Netac	U208	4G
Teclast	Ti Cool	128M
Teclast	Ti Cool	256M
Teclast	Ti Cool	512M
Teclast	Ti Cool	1G
SanDisk	cruzer mirco	2G
SanDisk	cruzer mirco	8G
SanDisk	Ti Cool	2G
SanDisk	Hongjiao	4G
Lexar	Lexar	256MB
Kingston	Data Traveler	1G
Kingston	Data Traveler	16GB

Appendix B-1 Compatible USB list

Kingston	Data Traveler	32GB
Aigo	L8315	16GB
Sandisk	250	16GB
Kingston	Data Traveler Locker+	32GB
Netac	U228	8GB

Appendix B-2 Compatible SD Card list

Brand	Standard	Capacity	Card type
Transcend	SDHC6	16GB	Big
Kingston	SDHC4	4GB	Big
Kingston	SD	2GB	Big
Kingston	SD	1GB	Big
Sandisk	SDHC2	8GB	Small
Sandisk	SD	1GB	Small

Appendix B-3 Compatible Portable HDD list

Brand	Model	Capacity
YDStar	YDstar HDD box	40G
Netac	Netac	80G
lomega	lomega RPHD-CG" RNAJ50U287	250GB
WD Elements	WCAVY1205901	1.5TB
Newsmy	Liangjian	320GB
WD Elements	WDBAAR5000ABK-00	500GB
WD Elements	WDBAAU0015HBK-00	1.5TB
Seagate	FreeAgent Go(ST905003F)	500GB
Aigo	H8169	500GB

Appendix B-4 Compatible USB DVD List

Brand	Model
Samsung	SE-S084
BenQ	LD2000-2K4

Appendix B-5 Compatible SATA DVD List

Brand	Model
LG	GH22NS30
Samsung	TS-H653 Ver.A

Samsung	TS-H653 Ver.F
Samsung	SH-224BB/CHXH
SONY	DRU-V200S
SONY	DRU-845S
SONY	AW-G170S
Pioneer	DVR-217CH

Appendix B-6 Compatible SATA HDD List

NOTE: Please upgrade the DVR firmware to latest version to ensure the accuracy of the table below. Here we recommend HDD of 500G to 4T capacity.

Manufacturer	Series	Model	Capacity	Port Mode
Seagate	Seagate SV35.1	ST3250824SV	250G	SATA
Seagate	Seagate SV35.1	ST3500641SV	500G	SATA
Seagate	Seagate SV35.2	ST3250820SV	250G	SATA
Seagate	Seagate SV35.2	ST3320620SV	320G	SATA
Seagate	Seagate SV35.2	ST3500630SV	500G	SATA
Seagate	Seagate SV35.2	ST3750640SV	750G	SATA
Seagate	Seagate SV35.3	ST3250310SV	250G	SATA
Seagate	Seagate SV35.3	ST3500320SV	500G	SATA
Seagate	Seagate SV35.3	ST3750330SV	750G	SATA
Seagate	Seagate SV35.3	ST31000340SV	1T	SATA
Seagate	Seagate SV35.4	ST3320410SV	320G	SATA
Seagate	Seagate SV35.4	ST3250311SV	250G	SATA
Seagate	Seagate SV35.5	ST3500410SV	500G	SATA
Seagate	Seagate SV35.5	ST3500411SV	500G	SATA
Seagate	Seagate SV35.5	ST31000525SV	1T	SATA
Seagate	Seagate SV35.5	ST31000526SV	1T	SATA
Seagate	Seagate SV35.5	ST1000VX000	1T	SATA
Seagate	Seagate SV35.5	ST2000VX003	2T	SATA
Seagate	Seagate SV35.5	ST2000VX002	2T	SATA
Seagate	Seagate SV35.5	ST2000VX000	2T	SATA
Seagate	Seagate SV35.5	ST3000VX000	3T	SATA
Seagate	Seagate Pipeline HD	ST3320410CS	320G	SATA
Seagate	Seagate Pipeline HD	ST3320310CS	320G	SATA
Seagate	Seagate Pipeline HD	ST3500422CS	500G	SATA
Seagate	Seagate Pipeline HD	ST3500321CS	500G	SATA
Seagate	Seagate Pipeline HD2	ST3250412CS	250G	SATA
Seagate	Seagate Pipeline HD2	ST3320311CS	250G	SATA
Seagate	Seagate Pipeline HD2	ST3500414CS	500G	SATA
Seagate	Seagate Pipeline HD2	ST3500312CS	500G	SATA
Seagate	Seagate Pipeline HD2	ST31000424CS	1T	SATA

Seagate	Seagate Pipeline HD2	ST31000322CS	1T	SATA
Seagate	Seagate Pipeline HD2	ST1000VM002	1T	SATA
Seagate	Seagate Pipeline HD2	ST1500VM002	1T	SATA
Seagate	Seagate Pipeline HD2	ST2000VM002	2T	SATA
Seagate	Seagate Pipeline HD2	ST2000VM003	2T	SATA
Seagate	Seagate Constellation	ST3500514NS	500G	SATA
	ES			
Seagate	Seagate Constellation ES	ST31000524NS	1T	SATA
Seagate	Seagate Constellation ES	ST32000644NS	2T	SATA
Seagate	Seagate Constellation ES	ST2000NM0011	2T	SATA
Seagate	Seagate Constellation ES	ST1000NM0011	1T	SATA
Seagate	Seagate Constellation ES	ST500NM0011	500G	SATA
Seagate	Seagate Constellation ES	ST2000NM0031	2T	SATA
Seagate	Seagate Constellation ES	ST1000NM0031	1T	SATA
Seagate	Seagate Constellation ES	ST500NM0031	500G	SATA
Seagate	Seagate Constellation ES	ST2000NM0051	2T	SATA
Seagate	Seagate Constellation ES	ST1000NM0051	1T	SATA
Seagate	Seagate Constellation ES	ST500NM0051	500G	SATA
Seagate	Seagate Constellation ES.2	ST33000650NS	3Т	SATA
Seagate	Seagate Constellation ES.2	ST32000645NS	2T	SATA
Seagate	Seagate Constellation ES.2	ST33000651NS	3Т	SATA
Seagate	Seagate Constellation ES.2	ST32000646NS	2T	SATA
Seagate	Seagate Constellation ES.2	ST33000652NS	3Т	SATA
Seagate	Seagate Constellation ES.2	ST32000647NS	2T	SATA
Westem Digital	Cariar SE	WD3200JD	320G	SATA
Westem Digital	Cariar SE	WD3000JD	300G	SATA

Westem Digital	Cariar SE	WD2500JS	250G	SATA
Westem Digital	Cariar SE16	WD7500KS	750G	SATA
Westem Digital	Cariar SE16	WD5000KS	500G	SATA
Westem Digital	Cariar SE16	WD4000KD	400G	SATA
Westem Digital	Cariar SE16	WD3200KS	320G	SATA
Westem Digital	Cariar SE16	WD2500KS	250G	SATA
Westem Digital	WD Caviar SE16	WD2500YS-01SHB0	250G	SATA
Westem Digital	WD Caviar RE16	WD3200YS-01PGB0	320G	SATA
Westem Digital	WD Caviar RE2	WD5000YS-01MPB0	500G	SATA
Westem Digital	WD AV—AVJS	WD2500AVJS-63WDA0	500G	SATA
Westem Digital	WD AV—AVJS	WD3200AVJS-63WDA0	320G	SATA
Westem Digital	WD AV—AVJS	WD5000AVJS-63YJA0	500G	SATA
Westem Digital	WDAV-GP—AVCS	WD5000AVCS-63H1B1	500G	SATA
Westem Digital	WDAV-GP—AVCS	WD7500AVCS-63ZLB0	750G	SATA
Westem Digital	WDAV-GP—AVCS	WD3200AVCS	320G	SATA
Westem Digital	WDAV-GP—AVCS	WD2500AVCS	250G	SATA
Westem Digital	WDAV-GP-EVCS	WD10EVCS-63ZLB0	1T	SATA
Westem Digital	WDAV-GP-EVCS	WD20EVCS-63ZLB0	2T	SATA
Westem Digital	WDAV-GP—AVVS	WD3200AVVS-63L2B0	320G	SATA
Westem Digital	WDAV-GP—AVVS	WD5000AVVS-63ZWB0	500G	SATA
Westem Digital	WDAV-GP—AVVS	WD7500AVVS-63E1B1	750G	SATA
Westem Digital	WDAV-GP—AVVS	WD7500AVVS-63E1B1	750G	SATA
Westem Digital	WDAV-GP-EVVS	WD10EVVS-63E1B1	1T	SATA
Westem Digital	WDAV-GP-EVDS	WD10EVDS-63N5B1	1T	SATA
Westem Digital	WDAV-GP-EVDS	WD15EVDS-63V9B0	1.5T	SATA
Westem Digital	WDAV-GP-EVDS	WD20EVDS-63T3B0	2T	SATA
Westem Digital	WDAV-GP—AVDS	WD5000AVDS-63U7B0	500G	SATA
Westem Digital	WD AV-GP	WD30EURS	3T	SATA
Westem Digital	WD AV-GP	WD25EURS	2.5T	SATA
Westem Digital	WD AV-GP	WD20EURS	2T	SATA
Westem Digital	WD AV-GP	WD15EURS	1.5T	SATA
Westem Digital	WD AV-GP	WD10EURS	1T	SATA
Westem Digital	WD AV-GP	WD10EURX	1T	SATA
Westem Digital	WD AV-GP	WD7500AURS	750G	SATA
Westem Digital	WD AV-GP	WD7500AVDS	500G	SATA
Westem Digital	WD AV-GP	WD500AVDS	500G	SATA
Westem Digital	WD AV-GP	WD10EUCX	1T	SATA
Samsung	Samsung—HA	HA500LJ/CE	500G	SATA
Samsung	Samsung—HA	HA751LJ	750G	SATA
Samsung	Samsung—HA	HA101UJ/CE	1T	SATA
Samsung	Samsung—HD	HD502HI/CEC	500G	SATA
Samsung	Samsung—HD	HD103SI/CEC	1T	SATA
Samsung	Samsung—HD	HD154UI/CE	1.5T	SATA

Hitachi	HitachiCinemaStar™	HCP725050GLA380	500G	SATA
	5K500			
Hitachi	HitachiCinemaStar™	HCT721050SLA360	500G	SATA
	7K1000.B			
Hitachi	HitachiCinemaStar™	HCT721075SLA360	750G	SATA
	7K1000.B			
Hitachi	HitachiCinemaStar™	HCT721010SLA360	1T	SATA
	7K1000.B			
Maxtor	DiamondMax 20	STM3320820AS	320G	SATA
Maxtor	DiamondMax 20	STM3250820AS	250G	SATA

Appendix C Compatible CD/DVD Burner List

NOTE: Please upgrade the DVR firmware to latest version to ensure the accuracy of the table below. And you can use the USB cable with the model recommended to set USB burner.

Manufacturer	Model	Port Type	Туре
Sony	DRX-S50U	USB	DVD-RW
Sony	DRX-S70U	USB	DVD-RW
Sony	AW-G170S	SATA	DVD-RW
Samsung	TS-H653A	SATA	DVD-RW
Panasonic	SW-9588-C	SATA	DVD-RW
Sony	DRX-S50U	USB	DVD-RW
BenQ	5232WI	USB	DVD-RW

Appendix D Compatible Displayer List

Brand	Model	Dimension (Unit: inch)
BENQ (LCD)	ET-0007-TA	19-inch (wide screen)
DELL (LCD)	E178FPc	17-inch
BENQ (LCD)	Q7T4	17-inch
BENQ (LCD)	Q7T3	17-inch
HFNOVO (LCD)	LXB-L17C	17-inch
SANGSUNG (LCD)	225BW	22 寸(wide screen)
HFNOVO(CRT)	LXB-FD17069HB	17 -inch
HFNOVO(CRT)	LXB-HF769A	17-inch
HFNOVO(CRT)	LX-GJ556D	17-inch
Samsung (LCD)	2494HS	24-inch
Samsung (LCD)	P2350	23-inch
Samsung (LCD)	P2250	22-inch
Samsung (LCD)	P2370G	23-inch
Samsung (LCD)	2043	20-inch
Samsung (LCD)	2243EW	22-inch
Samsung (LCD)	SMT-1922P	19-inch
Samsung (LCD)	T190	19-inch
Samsung (LCD)	T240	24-inch
LG (LCD)	W1942SP	19-inch
LG (LCD)	W2243S	22-inch
LG (LCD)	W2343T	23-inch
BENQ (LCD)	G900HD	18.5-inch
BENQ(LCD)	G2220HD	22-inch
PHILIPS (LCD)	230E	23-inch
PHILIPS (LCD)	220CW9	23-inch
PHILIPS (LCD)	220BW9	24-inch
PHILIPS (LCD)	220EW9	25-inch

Please refer to the following sheet form compatible displayer list.

Brand	Model	network working mode	
D-LinK	DES-1016D	10/100M self-adaptive	
D-LinK	DES-1008D	10/100M self-adaptive	
		Five network modes	
	RG-S1926S	1. AUTO	
Ruijie		2. HALF-10M	
Kujie		3. FULL-10M	
		4 .HALF-100M	
		5. FULL-100M	
НЗС	H3C-S1024	10/100M self-adaptive	
TP-LINK	TL-SF1016	10/100M self-adaptive	
TP-LINK	TL-SF1008+	10/100M self-adaptive	

Appendix F Compatible Wireless Mouse List

Please refer to the following sheet for compatible SD card brand.	
Brand	Model
SINT 讯括 ["]	V80
Rapoo	3500
Logitech	M215
Shuangfeiyan Tianyao G7-630	

Please refer to the following sheet for compatible SD card brand.

Appendix G Earthing

1. What is the surge?

Surge is a short current or voltage change during a very short time. In the circuit, it lasts for microsecond. In a 220V circuit, the 5KV or 10KV voltage change during a very short time (about microseconds) can be called a surge. The surge comes from two ways: external surge and internal surge.

- The external surge: The external surge mainly comes from the thunder lightning. Or it comes from the voltage change during the on/off operation in the electric power cable.
- The internal surge: The research finds 88% of the surge from the low voltage comes from the internal of the building such as the air conditioning, elevator, electric welding, air compressor, water pump, power button, duplicating machine and other device of inductive load.

The lightning surge is far above the load level the PC or the micro devices can support. In most cases, the surge can result in electric device chip damage, PC error code, accelerating the part aging, data loss and etc. Even when a small 20 horsepower inductive engine boots up or stops, the surge can reach 3000V to 50000V, which can adversely affect the electronic devices that use the same distribution box.

To protect the device, you need to evaluate its environment, the lighting affection degree objectively. Because surge has close relationship with the voltage amplitude, frequency, network structure, device voltage-resistance, protection level, ground and etc. The thunder proof work shall be a systematic project, emphasizing the all-round protection (including building, transmission cable, device, ground and etc.). There shall be comprehensive management and the measures shall be scientific, reliable, practical and economic. Considering the high voltage during the inductive thundering, the International Electrotechnical Committee (IEC) standard on the energy absorbing step by step theory and magnitude classification in the protection zone, you need to prepare multiple precaution levels.

You can use the lightning rod, lightning strap or the lightning net to reduce the damage to the building, personal injury or the property,

- The lightning protection device can be divided into three types:
 - Power lightning arrester: There are 220V single-phrase lightning arrester and 380V three-phrase lightening arrester (mainly in parallel connection, sometimes use series connection) You can parallel connect the power lightning arrester in the electric cable to reduce the short-time voltage change and release the surge current. From the BUS to the device, there are usually three levels so that system can reduce the voltage and release the current step by step to remove the thunderstorm energy and guarantee the device safety. You can select the replaceable module type, the terminal connection type and portable socket according to your requirement.


- Signal lightning arrester: This device is mainly used in the PC network, communication system. The connection type is serial connection. Once you connected the signal lightning arrestor with the signal port, it can cut the channel of the thunderstorm to the device, and on the other hand, it can discharge the current to the ground to guarantee the device proper work. The signal lightning arrester has many specifications, and widely used in many devices such as telephone, network, analog communication, digital communication, cable TV and satellite antenna. For all the input port, especially those from the outdoor, you need to install the signal lightning arrester.
- Antenna feed cable lightning arrester: It is suitable for antenna system of the transmitter or the device system to receive the wireless signal. It uses the serial connection too.

Please note, when you select the lighting arrester, please pay attention to the port type and the earthing reliability. In some important environment, you need to use special shielded cable. Do not parallel connect the thunder proof ground cable with the ground cable of the lightning rod. Please make sure they are far enough and grounded respectively.

2. The earthing modes


We all know the earthing is the most complicated technology in the electromagnetism compatibility design since there is no systematic theory or module. The earthing has many modes, but the selection depends on the system structure and performance. The following are some successfully experience from our past work.

One-point ground: In the following figure you can see there is a one-point ground. This connection provides common port to allow signal to be transmitted in many circuits. If there is no common port, the error signal transmission occurred. In the one-point ground mode, each circuit is just grounded only and they are connected at the same port. Since there is only one common port, there is no circuit and so, there is no interference.




Multiple-point ground: In the following figure, you can see the internal circuit uses the chassis as the common point. While at the same time, all devices chassis use the earthing as the common port. In this connection, the ground structure can provide the lower ground resistance because when there are multiple-point grounds; each ground cable is as short as possible. And the parallel cable connection can reduce the total

conductance of the ground conductor. In the high-frequency circuit, you need to use the multiple-point ground mode and each cable needs to connect to the ground. The length shall be less than the 1/20 of the signal wavelength.



Mixed ground: The mix ground consists of the feature of the one-point ground and multiple-point ground. For example, the power in the system needs to use the one-point ground mode while the radio frequency signal requires the multiple-point ground. So, you can use the following figure to earth. For the direct current (DC), the capacitance is open circuit and the circuit is one-point ground. For the radio frequency signal, the capacitance is conducive and the circuit adopts multiple-point ground.



When connecting devices of huge size (the device physical dimension and connection cable is big comparing with the wave path of existed interference), then there are possibility of interference when the current goes through the chassis and cable. In this situation, the interference circuit path usually lies in the system ground circuit.

When considering the earthing, you need to think about two aspects: The first is the system compatibility, and the other is the external interference coupling into the earth circuit, which results in system error. For the external interference is not regular, it is not easy to resolve.


3. Thunder proof ground method in the monitor system

- The monitor system shall have sound thunder proof earthing to guarantee personnel safety and device safety.
- The monitor system working ground resistance shall be less than 1Ω .

- The thunder proof ground shall adopt the special ground cable from the monitor control room to the ground object. The ground cable adopts copper insulation cable or wire and its ground section shall be more than 20mm2.
- The ground cable of the monitor system can not short circuit or mixed connected with the strong alternative current cable.
- For all the ground cables from the control room to the monitor system or ground cable of other monitor devices, please use the copper resistance soft cable and its section shall be more than 4mm2.
- The monitor system usually can adopt the one-point ground.
- Please connect the ground end of 3-pin socket in the monitor system to the ground port of the system (protection ground cable)

4. The shortcut way to check the electric system using the digital multimeter

For 220V AC socket, from the top to the bottom, E (ground cable), N (neutral cable), L(live cable). Please refer to the following figure.




There is a shortcut way to check these thee cables connection are standard or not (not the accurate check).

Importance

In the following operations, the multimeter range shall be at 750V!

For E (earth cable)

Turn the digital multimeter to 750V AC, use your one hand to hold the metal end, and then the other hand insert the pen to the E port of the socket. See the following figure. If the multimeter shows 0, then you can see current earth cable connection is standard. If the value is more than 10, then you can see there is inductive current and the earth cable connection is not proper.




For L (live cable)

Turn the digital multimeter to 750V AC, use your one hand to hold the metal end, and then the other hand insert the pen to the L port of the socket. See the following figure. If the multimeter shows 120, then you can see current live cable connection is standard. If the value is less than 60, then you can see current live cable connection is not proper or it is not the live cable at all.



For N (Neutral cable)

Turn the digital multimeter to 750V AC, use your one hand to hold the metal end, and then the other hand insert the pen to the N port of the socket. See the following figure. If the multimeter shows 0, then you can see current N cable connection is standard. If the value is more than 10, then you can see there is inductive current and the neutral cable connection is not proper. If the value is 120, then you can know misconnected the neutral cable to the live cable.



Note:

- This manual is for reference only. Slight difference may be found in the user interface.
- All the designs and software here are subject to change without prior written notice.
- All trademarks and registered trademarks mentioned are the properties of their respective owners.
- If there is any uncertainty or controversy, please refer to the final explanation of us.
- Please visit our website or contact your local retailer for more information.

DAHUA VISION TECHNOLOGY CO., LTD.

Address: No.1199 Bin'an Road, Binjiang District, Hangzhou, China. Postcode: 310053 Tel: +86-571-87688883 Fax: +86-571-87688815 Email:overseas@dahuasecurity.com Website: www.dahuatech.com